

Statement of Volatility – Dell PowerEdge T560

Dell PowerEdge T560 contains both volatile and non-volatile (NV) components. Volatile components lose their data immediately upon removal of power from the component. Non-volatile components continue to retain their data even after the power has been removed from the component. Components chosen as user-definable configuration options (those not soldered to the motherboard) are not included in the Statement of Volatility. Configuration option information (pertinent to options such as microprocessors, remote access controllers, and storage controllers) is available by component separately. The following NV components are present in the PowerEdge T560 server.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
Planar										
PCH Internal CMOS RAM	Non-Volatile	1	U_PCH1	256 Bytes	Battery-backed CMOS RAM	No	Real-time clock and BIOS configuration settings	BIOS	N/A – BIOS only control	1) Set NVRAM_CLR jumper to clear BIOS configuration settings at boot and reboot system. 2) Power off the system, remove coin cell battery for 30 seconds, replace battery and then power back on. 3) Restore default configuration in F2 system setup menu.
BIOS SPI Flash	Non-Volatile	1	JP45_1	32 MB	SPI Flash	No	Boot code, system configuration information, UEFI	SPI interface via PCH	Software write protected	Not possible with any utilities or applications and system is not functional if corrupted or removed.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
							environment, ME			
BIOS Data SPI Flash	Non-Volatile	1	JP8_1	4 MB	SPI Flash	No	4MB Data SPI ROM storage BIOS setting.	SPI interface via PCH	Software write protected	Not possible with any utilities or applications and the system is not functional if BIOS SPI is corrupted or removed.
iDRAC SPI Flash	Non-Volatile	1	JP46_1	4 MB	SPI Flash	No	iDRAC Uboot (boot loader), server management persistent store (i.e. iDRAC boot variables), and virtual planar FRU	SPI interface via iDRAC	Embedded iDRAC subsystem firmware actively controls sub area based write protection as needed.	The user cannot clear memory completely. However, user data, lifecycle log and archive, SEL, and firmware image repository can be cleared using Delete Configuration and Retire System, which can be accessed through the Lifecycle Controller interface.
BMC EMMC	Non-Volatile	1	U160	8 GB	eMMC NAND Flash	No	Operational iDRAC FW, Lifecycle Controller (LC) USC partition, LC service diags, LC	NAND Flash interface via iDRAC	Embedded FW write protected	The user cannot clear memory completely. However, user data, lifecycle log and archive, SEL, and firmware image repository can be cleared

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
							OS drivers, USC firmware, IDRAC MAC Address, and EPPID, rac log, System Event Log, lifecycle log cache			using Delete Configuration and Retire System, which can be accessed through the Lifecycle Controller interface.
iDRAC DDR4	Volatile	1	U15	8Gb	RAM	Yes	iDRAC RAM	iDRAC firmware	Not write-protected	Remove AC
System CPLD RAM	Volatile	1	U_CPLD1	432 kb	RAM	No	Not utilized	Not utilized	Not accessible	Not accessible
System CPLD Flash	Non-Volatile	1	U_CPLD1	448 kb	FLASH	No	Power on System Firmware	Firmware update	BIOS Security Protocols	Not user clearable
CPLD external EEPROM	Non-volatile	1	U151	2Kb	EEPROM	No	Reserved for OSM using	CPLD	CPLD control	User cannot clear the memory.
System Memory: RDIMM	Volatile	Up to 16	CPU1: A1~A8 CPU2: B1~B8	Up to 256GB per DIMM	RAM	Yes	System OS RAM	System OS	OS Control	Reboot or power down system
CPU VCCIN and	Non-Volatile	2	PU56, PU73	64KB	OTP (one time	No	Operational parameters	Once values are loaded into register	There are passwords for different sections	The user cannot clear memory.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
FIVRA Regulators					programmable)			space a cmd writes to nvm.	of the register space	
CPU INFAON and VCCFA Regulators	Non-Volatile	2	PU68, PU85	64KB	OTP (one time programmable)	No	Operational parameters	Once values are loaded into register space a cmd writes to nvm.	There are passwords for different sections of the register space	The user cannot clear memory.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
12x3.5" SAS/SATA Backplane										
SEP internal flash	Non-Volatile	1	U1	Flash: 512KB	Integrated Flash + Data SRAM + Battery	No	Firmware + FRU	I2C interface via iDRAC	Program write protect bit	Not user clearable

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
				Data SRAM : 256KB Battery Powered Storage SRAM : 64B	Powered Storage SRAM					
8x3.5" SAS/SATA Backplane										
SEP internal flash	Non-Volatile	1	U46	Flash: 512KB Data SRAM : 256KB Battery Powered Storage SRAM : 64B	Integrated Flash + Data SRAM + Battery Powered Storage SRAM	No	Firmware + FRU	I2C interface via iDRAC	Program write protect bit	Not user clearable
8x2.5" NVMe Backplane										

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
SEP internal flash	Non-Volatile	1	U14	Flash: 512KB Data SRAM : 256KB Battery Powered Storage SRAM : 64B	Integrated Flash + Data SRAM + Battery Powered Storage SRAM	No	Firmware + FRU	I2C interface via iDRAC	Program write protect bit	Not user clearable
8x2.5" SAS4/SATA Backplane										
SEP internal flash	Non-Volatile	1	U46	Flash: 512KB Data SRAM : 256KB Battery Powered Storage SRAM : 64B	Integrated Flash + Data SRAM + Battery Powered Storage SRAM	No	Firmware + FRU	I2C interface via iDRAC	Program write protect bit	Not user clearable

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
H965i Front PERC (Internal Controller)										
SPI Flash	Non-Volatile	1	U2	256Mb	SPI Flash	No	Card firmware	Pre-programmed before assembly. Can be updated using Dell/Broadcom tools	Not write protected. Not visible to Host Processor	User cannot clear the memory.
FRU	Non-volatile	1	U1019	2Kb	EEPROM	No	Card manufacturing information	Programmed at ICT during production.	Not write protected	User cannot clear the memory.
CPLD	Non-volatile	1	U1088	64kb	Flash	No	Power sequencing and Cache Offload	Controller may program data during FW update	Not write protected Not visible to host CPU	User cannot clear this memory
MCU	Non-volatile	1	U41	8kb	Flash	No	PCIe Bifurcation information to system iDRAC	BMC may program data if there is an updated version packaged with iDRAC	Not write protected Not visible to host CPU	User cannot clear this memory

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
NVSRAM	Non-volatile	1	U1087	128kB	NVSRAM	No	Configuration data	ROC writes configuration data to NVSRAM	Not write protected Not visible to host CPU	User cannot clear this memory
BMU	Non-Volatile	1	U1126	180KB	Integrated Flash + EEPROM	No	Battery Management control	ROC may program data during FW and during boot	Not write protected	User cannot clear this memory
SPD	Non-volatile	1	U22	256b	EEPROM	No	Memory configuration data	Pre-programmed before assembly	No write protected. Not visible to Host Processor	User cannot clear the memory.
NAND Flash	Non-volatile	1	U1100	512Gb	ONFI Flash	No	Cache offload during unexpected power loss	Programmed by ROC during cache offload	No write protected. Not visible to Host Processor	User cannot clear the memory.
SDRAM	Volatile	9	U1077~U1086	8GB	SDRAM	No	Cache for HDD I/O	ROC writes to this memory - using it as cache for data IO to HDDs	No write protected. Not visible to Host Processor	Cache can be cleared by powering off the card
HBA355i Front (Internal Controller)										
SPI Flash	Non-Volatile	1	U2	128Mb	SPI Flash	No	Card firmware	Pre-programmed before	Not write protected. Not	User cannot clear the memory.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
								assembly. Can be updated using Dell/LSI tools	visible to Host Processor	
FRU	Non-volatile	1	U5	2Kb	EEPROM	No	Card manufacturing information	Programmed at ICT during production.	Not write protected	User cannot clear the memory.
CPLD	Non-volatile	1	U23	24kb	Flash	No	Power sequencing and Cache Offload	Controller may program data during FW update	Not write protected Not visible to host CPU	User cannot clear this memory
MCU	Non-volatile	1	U41	8kb	EEPROM	No	PCIe Bifurcation information to system iDRAC	BMC may program data if there is an updated version packaged with iDRAC	Not write protected Not visible to host CPU	User cannot clear this memory
H755 Front PERC (Internal Controller)										
SDRAM	Volatile	9	U1077~U1085	8GB	SDRAM	No	Cache for HDD I/O	ROC writes to this memory - using it as cache for data IO to HDDs	no write protected. Not visible to Host Processor	Cache can be cleared by powering off the card

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
NV Flash	Non-volatile	1	U1100	512Gb	SPI Flash	No	Card firmware	Pre-programmed before assembly. Can be updated using Dell/LSI tools	no write protected. Not visible to Host Processor	User cannot clear the memory.
BMU	Non-Volatile	1	U1126	180KB	Integrated Flash + EEPROM	No	Battery Management Control	ROC may program data during FW and during boot during battery detection	Not write protected Not visible to host CPU	User cannot clear this memory
SPI Flash	Non-Volatile	1	U1086	128Mb	SPI Flash	No	Holds cache data during power loss	FPGA backs up DDR data to this device in case of a power failure	no write protected. Not visible to Host Processor	Flash can be cleared by powering up the card and allowing the controller to flush the contents to VDs. If the VDs are no longer available, cache can be cleared by going into controller BIOS and selecting Discard Preserved Cache.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
NVSRAM	Non-volatile	1	U1087	128KB	NVSRAM	No	Configuration data	ROC writes configuration data to NVSRAM	no write protected. Not visible to Host Processor	User cannot clear the memory.
FRU	Non-volatile	1	U1019	2Kb	EEPROM	No	Card manufacturing information	Programmed at ICT during production.	no write protected	User cannot clear the memory.
SPD	Non-volatile	1	U22	2Kb	EEPROM	No	Memory configuration data	Pre-programmed before assembly	no write protected. Not visible to Host Processor	User cannot clear the memory.
CPLD	Non-volatile	1	U1088	64kb	Flash	No	Power sequencing and Cache Offload	ROC may program data during FW update	Not write protected Not visible to host CPU	User cannot clear this memory
MCU	Non-volatile	1	U41	8KB	EEPROM	No	PCIe Bifurcation information to system iDRAC	BMC may program data if there is an updated version packaged with iDRAC	Not write protected Not visible to host CPU	User cannot clear this memory

H755N Front PERC (Internal Controller)

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
NVSRAM	Non-volatile	1	U1087	128KB	NVSRAM	No	Configuration data	ROC writes configuration data to NVSRAM	No write protected. Not visible to Host Processor	User cannot clear the memory.
FRU	Non-volatile	1	U1019	2Kb	EEPROM	No	Card manufacturing information	Programmed at ICT during production.	No write protected	User cannot clear the memory.
SPD	Non-volatile	1	U1019	2Kb	EEPROM	No	Memory configuration data	Pre-programmed before assembly	No write protected. Not visible to Host Processor	User cannot clear the memory.
NV Flash	Non-volatile	1	U1100	512Gb	SPI Flash	No	Card firmware	Pre-programmed before assembly. Can be updated using Dell/LSI tools	No write protected. Not visible to Host Processor	User cannot clear the memory.
CPLD	Non-volatile	1	U1088	64kb	Flash	No	Power sequencing and Cache Offload	NA	NA	NA
SPI Flash	Non-Volatile	1	U1086	128Mb	SPI Flash	No	Holds cache data during power loss	FPGA backs up DDR data to this device in case of a power failure	No write protected. Not visible to Host Processor	Flash can be cleared by powering up the card and allowing the controller to flush the contents to VDs. If the VDs are no longer

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
										available, cache can be cleared by going into controller BIOS and selecting Discard Preserved Cache.
SDRAM	Volatile	9	U1077~U1085	8GB	SDRAM	No	Cache for HDD I/O	ROC writes to this memory - using it as cache for data IO to HDDs	No write protected. Not visible to Host Processor	Cache can be cleared by powering off the card
MCU	Non-volatile	1	U41	8KB	EEPROM	No	PCIe Bifurcation information to system iDRAC	NA	NA	NA
BMU	Non-Volatile	1	U1126	180KB	NA	No	Battery Management control	NA	NA	NA
HBA355i Adapter										
SPI Flash	Non-Volatile	1	U2	128Mb	SPI Flash	No	Card firmware	Pre-programmed before assembly. Can be updated using Dell/LSI tools	Not write protected. Not visible to Host Processor	User cannot clear the memory.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
FRU	Non-volatile	1	U5	2Kb	EEPROM	No	Card manufacturing information	Programmed at ICT during production.	Not write protected	User cannot clear the memory.
CPLD	Non-volatile	1	U23	24kb	Flash	No	Power sequencing	Controller may program data during FW update	Not write protected Not visible to host CPU	User cannot clear this memory
H355 Front PERC (Internal Controller)										
SPI Flash	Non-Volatile	1	U2	128Mb	SPI Flash	No	Card firmware	Pre-programmed before assembly. Can be updated using Dell/LSI tools	Not write protected. Not visible to Host Processor	User cannot clear the memory.
FRU	Non-volatile	1	U5	2Kb	EEPROM	No	Card manufacturing information	Programmed at ICT during production.	Not write protected	User cannot clear the memory.
CPLD	Non-volatile	1	U23	24kb	Flash	No	Power sequencing and Cache Offload	Controller may program data during FW update	Not write protected Not visible to host CPU	User cannot clear this memory

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
MCU	Non-volatile	1	U41	8kB	EEPROM	No	PCIe Bifurcation information to system iDRAC	BMC may program data if there is an updated version packaged with iDRAC	Not write protected Not visible to host CPU	User cannot clear this memory
NVSRAM	Non-volatile	1	U3	128kB	NVSRAM	No	Configuration data	ROC writes configuration data to NVSRAM	Not write protected Not visible to host CPU	User cannot clear this memory

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
TPM										
Trusted Platform Module (TPM)	Non-Volatile	1	U2	128 Bytes	EEPROM	Yes	Storage of encryption keys	Using TPM Enabled operating systems	SW write protected	F2 Setup option
BOSS-N1										
RAID controller external SPI FLASH	Non-Volatile	1	U5	128Mb	FLASH EEPROM	No	Boot code, FW	By programming the image via firmware update process	N/A	Use Flash tool, type "go.nsh w y"
MCU	Non-volatile	1	U41	8KB						User cannot clear the memory
FRU	Non-Volatile	1	U4	2Kb	FLASH EEPROM	No	Card manufacturing information	During Manufacturing , by programming the image via firmware update process. During runtime, by I2C	N/A	By writing to Flash

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
								Proprietary Command Protocol		
Base_FIO										
MCU	Non-Volatile	1	U9	8kB	Flash ROM	No	Firmware	I2C interface via iDRAC	Program write protect bit	Not user clearable
Upsell_FIO										
MCU	Non-volatile	1	USAM7	2MB	Flash ROM	No	Driving Health/ Status LED and Wifi-BT communication.	SPI interface via iDRAC	Hardware strapping	User cannot clear the memory.
Gen5 GPU Riser (R1a/R2a)										
MCU	Non-volatile	1	U1	8kB	Flash ROM	No	Riser information	The data is flash via iDRAC auto update	No write protected. Not visible to Host Processor	User cannot clear the memory.

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
PSU										
DELTA PSU (600W, 700W, 800W, 1100W, 1400W, 1800W, 2400W)										
Primary MCU	Non-volatile	1	IC703	64KB	Internal Flash	No	Boot code, FW	The data is flash via Dell Update Package (DUP)	SW write protected	Before firmware update, the memory will be cleared.
Secondary MCU	Non-volatile	1	IC805	64KB	Internal Flash	No	Boot code, FW	The data is flash via Dell Update Package (DUP)	SW write protected	Before firmware update, the memory will be cleared.
FRU	Non-volatile	1	IC704	16KB	EEPROM	No	PSU information	During Manufacturing , by programming the image via firmware update process	SW write protected	User cannot clear the memory.
ARTESYN PSU (800W, 1100W, 1400W, 2400W)										

Item	Non-Volatile or Volatile	Quantity	Reference Designator	Size	Type (e.g. Flash PROM, EEPROM)	Can user programs or operating system write data to it during normal operation?	Purpose? (e.g. boot code)	How is data input to this memory?	How is this memory write protected?	How is the memory cleared?
Primary MCU	Non-volatile	1	U317 (TI)	64K	Internal Flash	No	Boot code, FW	The data is flash via Dell Update Package (DUP)	SW write protected	Before firmware update, the memory will be cleared.
Secondary MCU	Non-volatile	2	U301 (TI) U315 (ST)	32K 128K	Internal Flash	No	Boot code, FW	The data is flash via Dell Update Package (DUP)	SW write protected	Before firmware update, the memory will be cleared.
FRU	Non-volatile	1	U305	2Mb	SERIAL FLASH	No	PSU information	During Manufacturing	SW write protected	User cannot clear the memory.
LiteOn PSU (600W, 700W, 800W, 1100W, 1400W, 1800W)										
Primary MCU	Non-volatile	1	IC050	64K	Internal Flash	No	Boot code, FW	The data is flash via Dell Update Package (DUP)	SW write protected	Before firmware update, the memory will be cleared.
Secondary MCU/FRU	Non-volatile	1	IC900	128K	Internal Flash	No	Boot code, FW	The data is flash via Dell Update Package (DUP)	SW write protected	Before firmware update, the memory will be cleared.



NOTE: For any information that you may need, direct your questions to your Dell Marketing contact.

05 - 2023

© 2023 Dell Inc. or its subsidiaries. All rights reserved. Dell, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.