

SLC TWIN PRO²

On-line double conversion UPS from 4 to 20 kVA

BACKUP CHART : SLC TWIN PRO2 4 – 20 kVA



| PRODUCT | P/N | Stand alone | 2 x | | 2 x | | 2 x | | 2 x | | 2 x | | 2 x | |
|--------------------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|
| | | | 699BX000001 | 699BX000001 | 699BX000002 | 699BX000002 | 699BX000003 | 699BX000003 | 699BX000004 | 699BX000004 | 699BX000005 | 699BX000005 | 699BX000006 | 699BX000006 |
| SLC-4000-TWIN PRO2 | 699CB000001 | 13 | 50 | — | — | — | 165 | — | — | — | — | — | — | — |
| SLC-4000-TWIN PRO2 B1 | 699CB000006 | 0 | 35 | 80 | 45 | 90 | 60 | 120 | — | — | — | — | — | — |
| SLC-5000-TWIN PRO2 | 699CB000002 | 9 | 45 | — | — | — | 75 | — | — | — | — | — | — | — |
| SLC-5000-TWIN PRO2 B1 | 699CB000007 | 0 | 25 | 60 | 30 | 60 | 45 | 90 | — | — | — | — | — | — |
| SLC-6000-TWIN PRO2 | 699CB000003 | 7 | 30 | — | — | — | 50 | — | — | — | — | — | — | — |
| SLC-6000-TWIN PRO2 B1 | 699CB000008 | 0 | 20 | 50 | 25 | 45 | 30 | 75 | — | — | — | — | — | — |
| SLC-8000-TWIN PRO2 | 699CB000004 | 6 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-8000-TWIN PRO2 B1 | 699CB000009 | 0 | 13 | 30 | 17 | 45 | 25 | 50 | 30 | 70 | — | — | — | — |
| SLC-10000-TWIN PRO2 | 699CB000005 | 4 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-10000-TWIN PRO2 B1 | 699CB000010 | 0 | 9 | 25 | 12 | 30 | 16 | 35 | 20 | 55 | — | — | — | — |
| SLC-15000-TWIN PRO2 | 699CD000001 | 7 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-15000-TWIN PRO2 B1 | 699CD000003 | 0 | — | — | — | — | — | — | — | — | 7 | 18 | 12 | 30 |
| SLC-20000-TWIN PRO2 | 699CD000002 | 4 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-20000-TWIN PRO2 B1 | 699CD000004 | 0 | — | — | — | — | — | — | — | — | 4 | 12 | 8 | 20 |
| SLC-8000-TWIN/3 PRO2 | 699CC000001 | 6 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-8000-TWIN/3 PRO2 B1 | 699CC000005 | 0 | 13 | 30 | 17 | 45 | 25 | 50 | 30 | 70 | — | — | — | — |
| SLC-10000-TWIN/3 PRO2 | 699CC000002 | 4 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-10000-TWIN/3 PRO2 B1 | 699CC000006 | 0 | 9 | 25 | 12 | 30 | 16 | 35 | 20 | 55 | — | — | — | — |
| SLC-15000-TWIN/3 PRO2 | 699CC000003 | 7 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-15000-TWIN/3 PRO2 B1 | 699CC000007 | 0 | — | — | — | — | — | — | — | — | 7 | 18 | 12 | 30 |
| SLC-20000-TWIN/3 PRO2 | 699CC000004 | 4 | — | — | — | — | — | — | — | — | — | — | — | — |
| SLC-20000-TWIN/3 PRO2 B1 | 699CC000008 | 0 | — | — | — | — | — | — | — | — | 4 | 12 | 8 | 20 |

Important: B1 Models NO internal batteries (0 min. back-up time). At least 1xBEM (Battery Extension Module) is required.