

## 3600W APS INT Series 36VDC 230V Inverter/Charger with Auto-Transfer Switching, Line-Interactive AVR

MODEL NUMBER: **APSINT3636VR**



### Highlights

- Delivers clean 230V AC power from AC or DC power source
- 3600W continuous output power; 7200W peak power
- Auto-transfer switching option for UPS operation
- Corrects brownouts and overvoltages without using battery power
- Includes APSRM4 remote control module

### Package Includes

- APSINT3636VR 3600W APS INT Series 36V DC 230V AC Inverter/Charger
- APSRM4 remote control module
- Owner's manual

Portable line-interactive power source for any type of equipment from power tools to computers as a vehicle inverter, standalone AC power source or extended-run UPS. Ideal for RVs, commercial and fleet vehicles and emergency vehicles.

### Description

The APSINT3636VR 3600W APS INT Series 36V DC 230V AC Inverter/Charger is a reliable power source for a wide variety of equipment ranging from power tools, pumps and portable lighting to laptop computers and sensitive monitoring equipment. With no fumes, fuel or excess noise, it's an excellent alternative to generator power.

The DC-to-AC inverter features an automatic line-to-battery transfer switch and integrated charging system that allow it to work as a vehicle inverter, standalone AC power source or extended-run UPS. It delivers 3600W of continuous power, 5400W up to one hour or 7200W of peak power up to 10 seconds during equipment startup or cycling. An automatic overload detector, cooling fan and resettable AC circuit breakers protect the unit from damage.

Designed for easy installation in RVs, commercial and fleet vehicles, emergency vehicles and construction equipment, the APSINT3636VR converts stored power from any 36V battery or automotive DC source to safe, stable, computer-grade AC power for unlimited runtime. When hardwired to an external 230V AC source, the unit keeps the user-supplied battery charged via a three-stage 7.5/30A selectable charging system while simultaneously delivering AC power to connected equipment.

When used as a UPS, the APSINT3636VR's automatic voltage regulation feature protects your equipment against blackouts, brownouts, surges and line noise. The APSRM4 module with "traffic light" LEDs is included to provide complete remote monitoring and control of the unit.

### Features

#### Reliable Power for Mobile, Emergency and Remote Sites

- Generates safe, stable, computer-grade 230V AC power from 36V battery bank
- Ideal for powering tools, saws, motors, pumps, portable lighting, appliances and computer equipment in heavy-load conditions
- Designed for easy installation in RVs, commercial and fleet vehicles, emergency vehicles and construction equipment
- Functions as a vehicle inverter, standalone AC power source or extended-run UPS
- Unlimited runtime with variety of user-supplied batteries

### Meets Normal and Peak Power Demands



Powering Business Worldwide



- 3600W of continuous power
- 5400W of reserve power up to 1 hr.
- 7200W of peak power up to 10 sec. to accommodate surge power demands during equipment startup and cycling
- Automatic overload detector, built-in cooling fan and resettable AC circuit breakers protect unit from damage
- High-current DC input terminals for simple hardwired installation

**Automatic Voltage Regulation**

- Corrects brownouts and overvoltages without using battery power during battery charging and UPS standby modes
- Protects against line noise that can damage equipment or cause data loss

**Automatic Transfer Switching**

- Transfer relay switches to inverter power during blackout in 20 ms
- 3-position switch enables Auto, Charge Only or System Off mode
- DIP switches configure high and low voltage auto-transfer

**3-Stage 7.5/30A Selectable Battery Charger**

- Serves as battery charger when external 230V AC power is supplied and powering connected equipment
- Protects battery from overcharging and overdischarging
- Low-battery protection prevents excessive battery depletion
- DIP switches configure wet/gel charging profiles

**Remote Control Capability**

- Included APSRM4 remote control module provides remote monitoring and control of unit

**Front-Panel LEDs**

- Indicate AC/DC operational modes, overload status, DC voltage level, shutdown status and system fault status

**Rugged Polycarbonate Housing**

- Resists moisture, vibration and impact
- Mounts on any rigid horizontal surface

## Specifications

OVERVIEW	
UPC Code	037332095985
INPUT	
Nominal Input Voltage(s) Supported	230V AC
Maximum Input Amps / Watts	DC INPUT: Full continuous load - 114A at 36VDC. AC INPUT: 26 amps at 230VAC with full inverter and charger load (10.4A max charger-only / combined input load to support charger and AC output is automatically controllable to 66%-33%-0% based on AC output loading using the charger limiting set points - see manual for setting instructions)



<b>PHYSICAL</b>	
Material of Construction	Polycarbonate
Cooling Method	Multi-speed fan
Form Factors Supported	Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)
Shipping Dimensions (hwd / in.)	13.40 x 14.50 x 20.90
Shipping Dimensions (hwd / cm)	34.04 x 36.83 x 53.09
Shipping Weight (lbs.)	64.60
Shipping Weight (kg)	29.30
Unit Dimensions (hwd / in.)	7.000 x 8.500 x 14.000
Unit Dimensions (hwd / cm)	17.78 x 21.59 x 35.56
Unit Weight (lbs.)	58
Unit Weight (kg)	26.31
<b>ENVIRONMENTAL</b>	
Relative Humidity	0%-95% Non-Condensing
<b>LINE / BATTERY TRANSFER</b>	
Transfer Time (Line Power to Battery Mode)	20 milliseconds (typical - compatible with many computers, servers and networking equipment - verify transfer time compatibility of loads for UPS applications)
Low Voltage Transfer to Battery Power	In AC "auto" mode, inverter/charger switches to battery mode as line voltage drops to 144V (user adjustable to 163, 182V - see manual)
High Voltage Transfer to Battery Power	In AC "auto" mode, inverter/charger switches to battery mode as line voltage increases to 259V (user adjustable to 264 - see manual)
<b>FEATURES &amp; SPECIFICATIONS</b>	
Load Sensing	Optional load sense function enables automatic inverter shutoff and startup as connected equipment is powered off and on. Front panel load sense potentiometer can be set to shutoff or turn on inverter power in response to loads of any level, up to 150 watts.
<b>STANDARDS &amp; COMPLIANCE</b>	
Product Compliance	RoHS
<b>WARRANTY &amp; SUPPORT</b>	
Product Warranty Period (U.S. & Canada)	1-year limited warranty
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	2-year limited warranty
Product Warranty Period (Puerto Rico)	1-year limited warranty



*Powering Business Worldwide*



1000 Eaton Boulevard  
Cleveland, OH 44122  
United States  
<https://tripplite.eaton.com>

© 2024 Eaton. All Rights Reserved.  
Eaton is a registered trademark. All other trademarks  
are the property of their respective owners.