



## Statement of Volatility – Dell EMC PowerEdge T140

The Statement of Volatility provides you the information related to volatile and non-volatile components of different configurations of Dell EMC PowerEdge servers.

Volatile components lose their data when power cord is removed from the system, whereas, non-volatile components continue to retain their data when the power has been removed from the component.

The following table provides information of different configurations of the PowerEdge T140 servers.

| Item                  | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code)           | How is data written to this memory? | How is memory write-protected? | How is memory cleared?   |
|-----------------------|--------------------------|----------|----------------------|----------------|--|---|---|-------------------------------------|--------------------------------|--|
| <b>Planar</b>         |                          |          |                      |                |  |   |   |                                     |                                |  |
| PCH Internal CMOS RAM | Non-Volatile             | 1        | U_PCH1               | 256 Bytes      | Battery-backed CMOS RAM                  | No  | Real-time clock and BIOS configuration settings | BIOS                                | N/A – BIOS only control        | Perform the following steps:<br><br>1) Set NVRAM_CLR jumper to clear BIOS configuration settings at boot and reboot system;<br><br>2) AC power off system, remove coin cell battery for 30 seconds, replace battery and power on;<br><br>3) Restore default configuration in F2 system setup menu. |

| Item  | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory   | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code) | How is data written to this memory? | How is memory write-protected? | How is memory cleared?   |
|---|--------------------------|----------|----------------------|--|--|---|---------------------------------------|-------------------------------------|--------------------------------|--|
| BIOS Password (part of PCH internal CMOS RAM) | Non-Volatile             | 1        | U_PCH1               | 16 Bytes (out of 256 bytes used for PCH Internal CMOS RAM) | Battery-backed CMOS RAM                  | No  | Password to change BIOS settings      | Keyboard                            | N/A – BIOS only control        | <p>1) Place shunt on CN1001 jumper pins 2 and 4.</p> <p>2) AC power off is required after placing the shunt.</p> <p>3) AC power on with the shunt in place and then can be removed</p> |
| BIOS SPI Flash                                | Non-Volatile             | 1        | U_BIOS_SPI1          | 32 MB  | SPI Flash                                | No  | Boot code                             | SPI interface via PCH               | Software write-protected       | <p>You cannot remove the memory with any utilities or applications.</p> <p><b>Note:</b> When memory is corrupted or removed, System becomes non-functional</p>                         |

| Item                | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code)  | How is data written to this memory? | How is memory write-protected?   | How is memory cleared?   |
|---------------------|--------------------------|----------|----------------------|----------------|--|---|--|-------------------------------------|--|--|
| iDRAC SPI Flash     | Non-Volatile             | 1        | U_BMC_S PI1          | 4 MB           | SPI Flash                                | No  | iDRAC Uboot (bootloader)   | SPI interface via iDRAC             | Embedded iDRAC subsystem firmware actively controls sub area based write protection as needed. | User cannot clear the memory completely. However, user data, lifecycle log and archive, SEL, firmware image repository can be cleared via Delete Configuration and Retire System, accessible in Lifecycle Controller interface |
| BMC EMMC            | Non-Volatile             | 1        | U_EMMC1              | 4 GB           | eMMC NAND Flash                          | No  | Operational iDRAC FW, Lifecycle Controller (LC) USC partition, LC service diags, LC OS drivers, USC firmware | NAND Flash interface via iDRAC      | Embedded FW write protected  | User cannot clear the memory completely. However, user data, lifecycle log and archive, SEL, firmware image repository can be cleared via Delete Configuration and Retire System, accessible in Lifecycle Controller interface |
| CPU Vcore regulator | Non-Volatile             | 2        | PU1                  | 16 KB          | ROM                                      | No  | Operational parameters   | Programmed at factory via I2C       | Not write-protected  | User cannot clear the memory.  |

| Item                 | Non-Volatile or Volatile | Quantity | Reference Designator           | Size of memory                 | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code) | How is data written to this memory?           | How is memory write-protected? | How is memory cleared?           |
|----------------------|--------------------------|----------|--------------------------------|--------------------------------|--|---|---------------------------------------|---|--------------------------------|----------------------------------|
| System CPLD RAM      | Volatile                 | 1        | U_CPLD1                        | 92 Kb                          | RAM                                      | No  | Not utilized                          | Not utilized                                  | Not accessible                 | Not accessible                   |
| System CPLD FLASH    | Non-Volatile             | 1        | U_CPLD1                        | 256 Kb                         | Flash                                    | No  | Power on System Firmware              | Firmware update                               | BIOS Security Protocols        | User cannot clear the memory.    |
| System Memory: UDIMM | Volatile                 | Up to 4  | DIMMA1, DIMMA2, DIMMB1, DIMMB2 | Up to 16 GB per DIMM           | DRAM                                     | Yes   | System OS RAM                         | System OS                                     | OS Control                     | Reboot or power down the system. |
| Internal USB Key     | Non-Volatile             | Up to 1  | INT_USB1                       | Varies (not factory installed) | Flash                                    | Yes   | General purpose USB key drive         | USB interface via PCH. Accessed via system OS | Not write-protected            | Can be cleared in system OS      |
| CPU                  | Volatile                 | 1        | CPU1                           | Various                        | Cache + registers                        | Yes   | Processor cache + registers           | Various                                       | Various                        | Remove A/C                       |
| iDRAC DDR            | Volatile                 | 1        | U_IDRAC9_DRAM1                 | 512 Mb                         | DRAM                                     | No  | iDRAC local memory                    | iDRAC Firmware                                | Not write-protect              | Remove A/C                       |

| Item              | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory                    | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code) | How is data written to this memory?                                    | How is memory write-protected?                     | How is memory cleared?        |
|-------------------|--------------------------|----------|----------------------|-----------------------------------|--|---|---------------------------------------|--|--|-------------------------------|
| iDRAC             | Volatile                 | 1        | U_BMC1               | For CPU:<br>128 KB +<br>Registers | Cache + registers                        | No  | Processor cache + registers           | iDRAC Firmware   | Not write-protected                                | Remove A/C                    |
| PIROM             | Non- Volatile            | 1        | CPU1                 | 256 Bytes                         | EEPROM                                   | No  | Processor info + scratchpad           | SMBus interface to iDRAC   | Out of 256 bytes, 128 bytes are protected by       | User cannot clear the memory. |
| Recovery BIOS SPI | Non- Volatile            | 1        | U_REC_SPI_BIOS1      | 16 MB                             | SPI Flash                                | No  | Recovery image                        | SPI interface via iDRAC  | Not write-protected.                               | User cannot clear the memory. |
| LOM SPI           | Non-Volatile             | 1        | U_LOM_SPI1           | 8 Mb                              | SPI Flash                                | No  | LOM FW                                | Pre-programmed before assembly.<br><br>Can be updated using BRCM tools | Not write-protected.                               | User cannot clear the memory. |
| <b>H730 PERC</b>  |                          |          |                      |                                   |  |   |                                       |  |  |                               |
| NVSRAM            | Non-Volatile             | 1        | U1032                | 128 KB                            | NVSRAM                                   | No  | Configuration data                    | ROC writes configuration data to NVSRAM                                | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| FRU               | Non-Volatile             | 1        | U1019                | 256 B                             | FRU                                      | No  | Card manufacturing information        | Programmed at ICT during production.                                   | Not write-protected.                               | User cannot clear the memory. |

| Item  | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code) | How is data written to this memory?  | How is memory write-protected?                     | How is memory cleared?                        |
|-------|--------------------------|----------|----------------------|----------------|--|---|---------------------------------------|--|--|---|
| SPD   | Non-Volatile             | 1        | U22                  | 256 B          | SPD                                      | No  | Memory configuration data             | Pre-programmed before assembly   | Not write-protected. Not visible to Host Processor | User cannot clear the memory.                 |
| Flash | Non-Volatile             | 1        | U1049                | 16 MB          | Flash                                    | No  | Card firmware                         | Pre-programmed before assembly.<br><br>Can be updated using Dell/LSI tools | Not write-protected. Not visible to Host Processor | User cannot clear the memory.                 |
| SBR   | Non-Volatile             | 1        | U1020                | 8 KB           | Serial Boot ROM                          | No  | Bootloader                            | Pre-programmed before assembly   | Not write-protected. Not visible to Host Processor | User cannot clear the memory.                 |
| SDRAM | Volatile                 | 9        | U1043-U1047          | 4 GB           | SDRAM                                    | No  | Cache for HDD I/O                     | ROC writes to this memory - using it as cache for data IO to HDDs          | Not write-protected. Not visible to Host Processor | Cache can be cleared by powering off the card |

| Item             | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code)        | How is data written to this memory?     | How is memory write-protected?                     | How is memory cleared?        |
|------------------|--------------------------|----------|----------------------|----------------|--|---|--|---|--|-------------------------------|
| 1-Wire EEPROM    | Non-Volatile             | 1        | U1004                | 128 B          | 1-Wire EEPROM                            | No  | Holds default controller properties/settings | ROC writes data to this memory          | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| <b>H330 PERC</b> |                          |          |                      |                |  |   |  |   |  |                               |
| NVSRAM           | Non-Volatile             | 1        | U1033                | 128 KB         | NVSRAM                                   | No  | Configuration data                           | ROC writes configuration data to NVSRAM | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| FRU              | Non-Volatile             | 1        | U1019                | 256 B          | FRU                                      | No  | Card manufacturing information               | Programmed at ICT during production     | Not write-protected.                               | User cannot clear the memory. |
| 1-Wire EEPROM    | Non-Volatile             | 1        | U1004                | 128 B          | 1-Wire EEPROM                            | No  | Holds default controller properties/settings | ROC writes data to this memory          | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| SBR              | Non-Volatile             | 1        | U1020                | 8 KB           | Serial Boot ROM                          | No  | Bootloader                                   | Pre-programmed before assembly          | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |

| Item               | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code) | How is data written to this memory?  | How is memory write-protected?                     | How is memory cleared?        |
|--------------------|--------------------------|----------|----------------------|----------------|--|---|---------------------------------------|--|--|-------------------------------|
| Flash              | Non-Volatile             | 1        | U3                   | 16 MB          | Flash                                    | No  | Card firmware                         | Pre-programmed before assembly.<br><br>Can be updated using Dell/LSI tools | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| <b>HBA330 PERC</b> |                          |          |                      |                |  |   |                                       |  |  |                               |
| NVSRAM             | Non-Volatile             | 1        | U1033                | 128 KB         | NVSRAM                                   | No  | Configuration data                    | ROC writes configuration data to NVSRAM                                    | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| FRU                | Non-Volatile             | 1        | U1019                | 256 B          | FRU                                      | No  | Card manufacturing information        | Programmed at ICT during production  | Not write-protected.                               | User cannot clear the memory. |
| SBR                | Non-Volatile             | 1        | U1020                | 8 KB           | Serial Boot ROM                          | No  | Bootloader                            | Pre-programmed before assembly   | Not write-protected. Not visible to Host Processor | User cannot clear the memory. |
| Flash              | Non-Volatile             | 1        | U3                   | 16 MB          | Flash                                    | No  | Card firmware                         | Pre-programmed   | Not write-protected. Not visible to Host           | User cannot clear the memory. |

| Item                          | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code)   | How is data written to this memory?  | How is memory write-protected?   | How is memory cleared?   |
|-------------------------------|--------------------------|----------|----------------------|----------------|--|---|---|--|--|--|
| <b>TPM</b>                    |                          |          |                      |                |  |   |   |  |  |  |
| Trusted Platform Module (TPM) | Non-Volatile             | 1        | U_TPM                | 128 Bytes      | EEPROM                                   | Yes   | Storage of encryption keys  | Using TPM Enabled operating systems  | Software write-protected   | F2 Setup option  |
| <b>Front IO board</b>         |                          |          |                      |                |  |   |   |  |  |  |
| SPI Flash                     | Non-Volatile             | 1        | U_SPI_FLAS H1        | 32 Mb          | SPI Flash                                | No  | EasyRestore functionality: contains Service Tag, Copy of SEL logs                         | SPI interface from iDRAC to Right Cntl Panel   | Embedded iDRAC subsystem firmware actively controls sub area based write protection as needed. | User cannot clear the memory.  |
| <b>IDSDM - vFlash</b>         |                          |          |                      |                |  |   |   |  |  |  |
| vFlash (uSD)                  | Non-Volatile             | 1        | J3                   | 16 GB          | NAND flash                               | yes   | populate out-of-band or optionally connect to the host as mass storage and boot mechanism | User can provide data to iDRAC (entirely in the iDRAC domain) to be pushed into vFlash | Not write-protected.   | 1. Card may be physically removed and destroyed or cleared via standard means, on a separate computer.<br><br>OR<br>2. User has access to the card in the host |

| Item               | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory      | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation?  | What is the Purpose? (e.g. boot code)                          | How is data written to this memory?  | How is memory write-protected?  | How is memory cleared?   |
|--------------------|--------------------------|----------|----------------------|---------------------|--|--|--|--|---|--|
| iDSDM (uSD1, uSD2) | Non-Volatile             | 2        | J1, J2               | 16 GB, 32 GB, 64 GB | NAND Flash                               | Yes  | Provides mass storage  | device resides in host domain; they are exposed to the user via an internally connected, non-removable USB mass storage device | Physical write-protect switch on ACE card   | <p>1. Card may be physically removed and destroyed or cleared via standard means, on a separate computer.</p> <p>OR</p> <p>2. User has access to the card in the host domain and can clear it manually</p> |
| SPI Flash          | Non-Volatile             | 2        | U2                   | 1 MB                | SPI Flash                                | SPI flash is only indirectly connected to iDRAC. iDRAC can read any address in the SPI flash, but may only write the primary firmware storage area as a part of a firmware update procedure. | Boot firmware storage, configuration and state data for iDSDM. | User can initiate a firmware update of the iDSDM device.   | There is no mechanism provided to iDRAC to write any SPI NOR area outside of the primary iDSDM firmware region. | iDRAC may issue a clear command to erase all contents of the SPI NOR. This action may leave the iDSDM non-functional.  |

| Item   | Non-Volatile or Volatile | Quantity | Reference Designator | Size of memory | Type of memory (e.g. Flash PROM, EEPROM) | Can user programs or operating system write data to it during normal operation? | What is the Purpose? (e.g. boot code)                     | How is data written to this memory?   | How is memory write-protected?                                   | How is memory cleared?                       |
|--|--------------------------|----------|----------------------|----------------|--|---|---|---|--|--|
| <b>LCD Bezel</b>   |                          |          |                      |                |  |   |   |   |  |  |
| Microcontroller  | Non-Volatile             | 1        | IC1                  | 256 KB         | Internal Flash                           | No  | Bootloader and software implementation of LCD command set | Updated as part of secure iDRAC software update. Configuration parameters can change only as part of iDRAC update | Writes are only allowed as part of secure iDRAC update           | User cannot clear the memory.                |
| <b>PSU</b>   |                          |          |                      |                |  |   |   |   |  |  |
| Microcontroller  | Non-Volatile             | Up to 3  | Microchip            | Up to 64 KB    | Flash PROM and EEPROM                    | Yes   | Report PSU information and control firmware               | The data is flash via Dell Update Package (DUP)   | Using signature and manufacture key to write-protect the memory. | The memory is cleared before firmware update |
|  <b>NOTE:</b> For any information that you may need, direct your questions to your Dell Marketing contact. |                          |          |                      |                |  |   |   |   |  |  |

Copyright © 2017 Dell Inc. or its subsidiaries. All Rights Reserved.

Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.