Lenovo V340 V340-17|WL Hardware Maintenance Manual

Note: • Before using this information and the product it supports, be sure to read the general information under "Notices" on page 72.

First Edition (February 2019)

© Copyright Lenovo 2019. All rights reserved.

LIMITED AND RESTRICTED RIGHTS NOTICE: If data or software is delivered pursuant a General Services Administration "GSA" contract, use, reproduction, or disclosure is subject to restrictions set forth in Contract No. GS-35F-05925.

© 2019 Lenovo

Contents

About this manualiv
Safety information1
General safety2
Electrical safety
Safety information3
Safety inspection guide 5
Handling devices that are sensitive to
electrostatic discharge6
Grounding requirements6
Safety notices: multilingual translations 7
Laser compliance statement
Important service information16
Strategy for replacing FRU 16
Strategy for replacing a hard disk drive17
Important notice for replacing a system board 17
Important information about replacing RoHS
compliant FRU
General checkout19
What to do first
Power system checkout21
Checking the AC adapter
Checking operational charging
Chooking the battery pack
Related service information23
Restoring the factory contents by using OneKey
Recovery
Restore of factory default23
Passwords
Hard-disk password24
Administrator password
Power management
Screen blank state
Putting the computer to sleep or shutting it down. 25
Putting your computer to sleep25
Shutting down the computer26
Lenovo V340-17IWL27
Specifications
Status indicators
Hotkeys30
FRU replacement notices
Screw notices31
Removing and replacing an FRU
1010 Optical drive
1020 Base cover

1040 Battery pack41
1050 SSD card43
1060 DIMM45
1070 PCI Express Mini Card for wireless LAN .46
1080 Fan assembly and Heat Sink assembly48
1090 System board52
1100 ODD transfer board and backup battery 54
1110 Speakers56
1120 Touchpad57
1130 Upper case58
1140 LCD unit60
1150 Integrated camera and antenna assembly63
Locations65
Front view and right-side view65
Bottom and Left-side view66
Parts list
Overall68
LCD FRUs70
Notices72
Trademarks

About this manual

This manual contains service and reference information for the following Lenovo product:

Lenovo V340-17IWL

Use this manual to troubleshoot problems.

The manual is divided into the following sections:

- The common sections provide general information, guidelines, and safety information required for servicing computers.
- The product-specific section includes service, reference, and product-specific parts information.

Important:

This manual is intended only for trained servicers who are familiar with Lenovo products. Use this manual to troubleshoot problems effectively.

Before servicing a Lenovo product, make sure to read all the information under "Safety information" on page 1 and "Important service information" on page 16.

Safety information

This chapter presents the following safety information that you need to get familiar with before you service a Lenovo V340-17IWL computer:

- · "General safety" on page 2
- · "Electrical safety" on page 3
- "Safety inspection guide" on page 5
- "Handling devices that are sensitive to electrostatic discharge" on page 6
- · "Grounding requirements" on page 6
- "Safety notices: multilingual translations" on page 7
- · "Laser compliance statement" on page 14

General safety

Follow these rules below to ensure general safety:

- Observe a good housekeeping in the area where the machines are put during and after the maintenance.
- · When lifting any heavy object:
 - 1. Make sure that you can stand safely without slipping.
 - 2. Distribute the weight of the object equally between your feet.
 - Use a slow lifting force. Never move suddenly or twist when you attempt to lift it.
 - Lift it by standing or pushing up with your leg muscles; this action could avoid the strain from the muscles in your back. Do not attempt to lift any object that weighs more than 16 kg (35 lb) or that you think is too heavy for you.
- Do not perform any action that causes hazards to the customer, or that makes the machine unsafe.
- Before you start the machine, make sure that other service representatives and the customer are not in a hazardous position.
- Please remove covers and other parts in a safe place, away from all personnel, while you are servicing the machine.
- Keep your toolcase away from walk areas so that other people will not trip over it.
- Do not wear loose clothing that can be trapped in the moving parts of the machine. Make sure that your sleeves are fastened or rolled up above your elbows. If your hair is long, fasten it.
- Insert the ends of your necktie or scarf inside clothing or fasten it with the nonconductive clip, about 8 centimeters (3 inches) from the end.
- Do not wear jewelry, chains, metal-frame eyeglasses, or metal fasteners for your clothing.

Attention: Metal objects are good electrical conductors.

- Wear safety glasses when you are hammering, drilling, soldering, cutting wire, attaching springs, using solvents, or working in any other conditions that may be hazardous to your eyes.
- After service, reinstall all safety shields, guards, labels, and ground wires.
 Replace any safety device that is worn or defective.
- · Reinstall all covers correctly before returning the machine to the customer.
- Fan louvers on the machine help to prevent the overheating of internal components. Do not obstruct fan louvers or cover them with labels or stickers

Electrical safety

Observe the following rules when working on electrical equipments.

Important:

Use only approved tools and test equipments. Some hand tools have handles covered with a soft material that does not insulate you when working with live electrical currents.

Many customers have rubber floor mats near their machines that contain small conductive fibers to decrease electrostatic discharges. Do not use such kind of mat to protect yourself from electrical shock.

- Find the room emergency power-off (EPO) switch, disconnecting switch or electrical outlet. If an electrical accident occurs, you can then operate the switch or unplug the power cord quickly.
- Do not work alone under hazardous conditions or near the equipment that has hazardous voltages.
- · Disconnect all power before:
 - Performing a mechanical inspection
 - Working near power supplies
 - Removing or installing main units
- Before you start to work on the machine, unplug the power cord. If you
 cannot unplug it, ask the customer to power-off the wall box that supplies
 power to the machine, and to lock the wall box in the off position.
- If you need to work on a machine that has exposed electrical circuits, observe the following precautions:
 - Ensure that another person, familiar with the power-off controls, is near you.
 - **Attention:** Another person must be there to switch off the power, if necessary.
 - Use only one hand when working with powered-on electrical equipment;
 keep the other hand in your pocket or behind your back.
 - **Attention:** An electrical shock can occur only when there is a complete circuit. By observing the above rule, you may prevent a current from passing through your body.
 - When using testers, set the controls correctly and use the approved probe leads and accessories for that tester.
 - Stand on suitable rubber mats (obtained locally, if necessary) to insulate you from grounds such as metal floor strips and machine frames.

Observe the special safety precautions when you work with very high voltages; instructions for these precautions are in the safety sections of maintenance information. Be extremely careful when you measure the high voltages.

- Regularly inspect and maintain your electrical hand tools for safe operational condition.
- · Do not use worn or broken tools and testers.
- Never assume that power has been disconnected from a circuit. First, check it to make sure that it has been powered off.



- · Always look carefully for possible hazards in your work area. Examples of these hazards are moist floors, nongrounded power extension cables, power surges, and missing safety grounds.
- · Do not touch live electrical circuits with the reflective surface of a plastic dental mirror. The surface is conductive; such touching can cause personal injury and machine damage.
- · Do not service the following parts with the power on when they are removed from their normal operating places in a machine:
 - Power supply units
 - Pumps
 - Blowers and fans
 - Motor generators

and similar units. (This practice ensures correct grounding of the units.)

- · If an electrical accident occurs:
 - Caution: do not become a victim yourself.
 - Switch off the power.
 - Send the victim to get medical aid.

Safety inspection guide

The purpose of this inspection guide is to assist you in identifying potential unsafe conditions. As each machine was designed and built, required safety items were installed to protect users and service personnel from injury. This guide addresses only those items. You should use good judgment to identify potential safety hazards according to the attachment of non-Lenovo features or options not covered by this inspection guide.

If any unsafe conditions are present, you must determine how serious the apparent hazard could be and whether you can continue without first correcting the problem.

Consider these conditions and the safety hazards they present:

- Electrical hazards, especially primary power (primary voltage on the frame can cause serious or fatal electrical shock)
- · Explosive hazards, such as a damaged CRT face or a bulging capacitor
- · Mechanical hazards, such as loose or missing hardware

To determine whether there are any potential unsafe conditions, use the following checklist at the beginning of every service task. Begin the checks with the power off, and the power cord disconnected.

Checklist:

- 1. Check exterior covers for damage (loose, broken, or sharp edges).
- 2. Turn off the computer. Disconnect the power cord.
- 3. Check the power cord for:
 - a. A third-wire ground connector in good condition. Use a meter to measure third-wire ground continuity for 0.1 ohm or less between the external ground pin and the frame ground.
 - b. The power cord should be the type specified in the parts list.
 - c. Insulation must not be frayed or worn.
- Check for cracked or bulging batteries.
- 5. Remove the cover.
- Check for any obvious non-Lenovo alterations. Use good judgment as to the safety of any non-Lenovo alterations.
- Check inside the unit for any obvious unsafe conditions, such as metal filings, contamination, water or other liquids, or signs of fire or smoke damage.
- 8. Check for worn, frayed, or pinched cables.
- Check that the power-supply cover fasteners (screws or rivets) have not been removed or tampered with.

Handling devices that are sensitive to electrostatic discharge

Any computer part containing transistors or integrated circuits (ICs) should be considered sensitive to electrostatic discharge (ESD). ESD damage can occur when there is a difference in charge between objects. Protect against ESD damage by equalizing the charge so that the machine, the part, the work mat, and the person handling the part are all at the same charge.

Notes:

- Use product-specific ESD procedures when they exceed the requirements noted here.
- Make sure that the ESD protective devices you use have been certified (ISO 9000) as fully effective.

When handling ESD-sensitive parts:

- · Keep the parts in protective packages until they are inserted into the product.
- · Avoid contact with other people.
- Wear a grounded wrist strap against your skin to eliminate static on your body.
- Prevent the part from touching your clothing. Most clothing is insulative and retains a charge even when you are wearing a wrist strap.
- Use the black side of a grounded work mat to provide a static-free work surface. The mat is especially useful when handling ESD-sensitive devices.
- Select a grounding system, such as those listed below, to provide protection that meets the specific service requirement.

Note:

The use of a grounding system to guard against ESD damage is desirable but not necessary.

- Attach the ESD ground clip to any frame ground, ground braid, or greenwire ground.
- When working on a double-insulated or battery-operated system, use an ESD common ground or reference point. You can use coax or connectoroutside shells on these systems.
- Use the round ground prong of the ac plug on ac-operated computers.

Grounding requirements

Electrical grounding of the computer is required for operator safety and correct system function. Proper grounding of the electrical outlet can be verified by a certified electrician.

Safety notices: multilingual translations

The safety notices in this section are provided in English, French, German, Hebrew, Italian, Japanese, and Spanish.

Safety notice 1

Before the computer is powered on after FRU replacement, make sure all screws, springs, and other small parts are in place and are not left loose inside the computer. Verify this by shaking the computer and listening for rattling sounds. Metallic parts or metal flakes can cause electrical shorts.

Avant de remettre l'ordinateur sous tension après remplacement d'une unité en clientèle, vérifiez que tous les ressorts, vis et autres pièces sont bien en place et bien fixées. Pour ce faire, secouez l'unité et assurez-vous qu'aucun bruit suspect ne se produit. Des pièces métalliques ou des copeaux de métal pourraient causer un court-circuit.

Bevor nach einem FRU-Austausch der Computer wieder angeschlossen wird, muß sichergestellt werden, daß keine Schrauben, Federn oder andere Kleinteile fehlen oder im Gehäuse vergessen wurden. Der Computer muß geschüttelt und auf Klappergeräusche geprüft werden. Metallteile oder-splitter können Kurzschlüsse erzeugen.

לפני הפעלת המחשב לאחר החלפה ERU יש לוודא שכל הברגים, הקפיצים, וחלקים קטנים אחרים נמצאים במקונים ואינים חופשיים לזוז בתוך המחשב. כדי לוודא זאת, יש לטלטל את המחשב ולהקשיב לגילוי קולות שקשוק. חלפי או שבני מתכת עלולים לנודם לקצרים חשמליים. חלפי או שבני מתכת עלולים לנודם לקצרים חשמליים.

Prima di accendere l'elaboratore dopo che é stata effettuata la sostituzione di una FRU, accertarsi che tutte le viti, le molle e tutte le altri parti di piccole dimensioni siano nella corretta posizione e non siano sparse all'interno dell'elaboratore. Verificare ciò scuotendo l'elaboratore e prestando attenzione ad eventuali rumori; eventuali parti o pezzetti metallici possono provocare cortocircuiti pericolosi.

FRU の交換後、コンピュータの電源を入れる前に、ねじ、バネ、その他の小さな部品がすべて正しい位置にあり、またコンピュータの内部で緩んでいないことを確認してください。これを確認するには、コンピュータを振って、カチャカチャと音がしないか確かめます。金属部品や金属破片はショートの原因になることがあります。

Antes de encender el sistema despues de sustituir una FRU, compruebe que todos los tornillos, muelles y demás piezas pequeñas se encuentran en su sitio y no se encuentran sueltas dentro del sistema. Compruébelo agitando el sistema y escuchando los posibles ruidos que provocarían. Las piezas metálicas pueden causar cortocircuitos eléctricos



⚠ DANGER

Some standby batteries contain a small amount of nickel and cadmium. Do not disassemble a standby battery, recharge it, throw it into fire or water, or short-circuit it. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.

Certaines batteries de secours contiennent du nickel et du cadmium. Ne les démontez pas, ne les rechargez pas, ne les exposez ni au feu ni à l'eau. Ne les mettez pas en court-circuit. Pour les mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la pile de sauvegarde ou celle de l'horloge temps réel, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. Une batterie ou une pile inappropriée risque de prendre feu ou d'exploser.

Die Bereitschaftsbatterie, die sich unter dem Diskettenlaufwerk befindet, kann geringe Mengen Nickel und Cadmium enthalten. Sie darf nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Bereitschafts-oder Systembatterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

סוללות המתנה מסוימות מכילות כמות קטנה של ניקל וקימום. אין לפרק סוללת המתנה, לטעון אותה מדש, לאשליון אותה מדש, לאש או אותה מדש, לאשליון אותה מדש, לאש או למיס או לקצר אותה. יש לסלק את הסוללה כבודש על ידי התקנות והחוקים המקומיים. יש כבודש על ידי התקנות והחוקים המקומיים. יש המתאימה, שימוש בסוללה המנוסיעה ברשימות החלקים המתאימה, שימוש בסוללה לא מתאימה עולול.

Alcune batterie di riserva contengono una piccola quantità di nichel e cadmio. Non smontarle, ricaricarle, gettarle nel fuoco o nell'acqua né cortocircuitarle. Smaltirle secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). Quando si sostituisce la batteria dell'RTC (real time clock) o la batteria di supporto, utilizzare soltanto i tipi inseriti nell'appropriato Catalogo parti. L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

予備バッテリーの中には少量のニッケルとカドミウムが含まれているものがあります。したがって、予備バッテリーの分解、再充電、火または水の中への投棄、またはショートさせることは決して行わないでください。バッテリーを廃棄する場合は地方自治体の条例に従ってください。適切なパーツ・リストにあるバッテリーだけを使用してください。関ったパッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。

Algunas baterías de reserva contienen una pequeña cantidad de níquel y cadmio. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.

8

⚠ DANGER

The battery pack contains small amounts of nickel. Do not disassemble it, throw it into fire or water, or short-circuit it. Dispose of the battery pack as required by local ordinances or regulations. Use only the battery in the appropriate parts listing when replacing the battery pack. Use of an incorrect battery can result in ignition or explosion of the battery.

La batterie contient du nickel. Ne la démontez pas, ne l'exposez ni au feu ni à l'eau. Ne la mettez pas en court-circuit. Pour la mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la batterie, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. En effet, une batterie inappropriée risque de prendre feu ou d'exploser.

Akkus enthalten geringe Mengen von Nickel. Sie dürfen nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

מארז הטוללה מכיל כמות קטנה של ניקל
וקדמיום. אין לפרק את מארז הטוללה, להשליך
אותו לאש או למים או לקצר אותו. יש לסלק את
מארז הטוללה הטוללה כנדרש על ידי התקנות
והחוקים המקומיים. יש להשתמש רק בטוללה
המופיעה ברשימת החלקים המתאימה בזמן החלפת
מארז הטוללה. שימוש בטוללה לא מתאימה עלול
לברום להצתה או התפוצוו של הטוללה לא לורום להצתה או התפוצוו של הטוללה.

La batteria contiene piccole quantità di nichel. Non smontarla, gettarla nel fuoco o nell'acqua né cortocircuitarla. Smaltirla secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). Quando si sostituisce la batteria, utilizzare soltanto i tipi inseriti nell'appropriato Catalogo parti. L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

バッテリー・パックには少量のニッケルが含まれています。バッテリー・パックを分解したり、火または水の中に投げ込んだり、ショートさせないでください。バッテリー・パックの廃棄にあたっては、地方自治体の条例または規則に従ってください。バッテリー・パックを交換するときは、適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。

Las baterías contienen pequeñas cantidades de níquel. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas al sustituir la batería. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.



⚠ DANGER

The lithium battery can cause a fire, an explosion, or a severe burn. Do not recharge it, remove its polarized connector, disassemble it, heat it above 100°C (212°F), incinerate it, or expose its cell contents to water. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.

La pile de sauvegarde contient du lithium. Elle présente des risques d'incendie, d'explosion ou de brûlures graves. Ne la rechargez pas, ne retirez pas son connecteur polarisé et ne la démontez pas. Ne l'exposez pas à une temperature supérieure à 100° C, ne la faites pas brûler et n'en exposez pas le contenu à l'eau. Mettez la pile au rebut conformément à la réglementation en vigueur. Une pile inappropriée risque de prendre feu ou d'exploser.

Die Systembatterie ist eine Lithiumbatterie. Sie kann sich entzünden, explodieren oder schwere Verbrennungen hervorrufen. Batterien dieses Typs dürfen nicht aufgeladen, zerlegt, über 100 C erhitzt oder verbrannt werden. Auch darf ihr Inhalt nicht mit Wasser in Verbindung gebracht oder der zur richtigen Polung angebrachte Verbindungsstecker entfernt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

סוללת הליתיום עלולה לגרום לשריפה, להתפוצצות או מולנות קשות. אין לטעון אותה מחדש, לטלק את המחבר המקוטב שלה, לפרק אות א ולחנט אותר לטפנדטורה העולה על 601 מעלות צליוים. אין לשרוף את הסוללה ואין העולה על 601 מעלות צליוים. אין לשרוף את הסוללה ואין לחשוף את תוכן התא למים. יש לטלק את הסוללה כנדרם לחשוף את תוכן התא למים. יש לטלק את הסוללה כנדרם בתקנות ובחוקים המקומיים. יש לשהמש רק בסוללה מבדרש המופיעה ברשימת החלקים המתאימים. שימוש בסוללה אחרת עלו לגרום לסכנת שידיפה או תהמוצצות.

La batteria di supporto e una batteria al litio e puo incendiarsi, esplodere o procurare gravi ustioni. Evitare di ricaricarla, smontame il connettore polarizzato, smontarla, riscaldarla ad una temperatura superiore ai 100 gradi centigradi, incendiarla o gettarla in acqua. Smaltirla secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

リチウム・バッテリーは、火災、爆発、または重症のやけどを引き起こすことがあります。バックアップ・バッテリーの充電、その極性コネクターの取り外し、バッテリー本体の分解、100℃(212°F)以上への加熱、焼却、電池の中身を水に浸すことはしないでください。バッテリーを廃棄する場合は地方自治体の条例に従ってください。適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったパッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。

La batería de repuesto es una batería de litio y puede provocar incendios, explosiones o quemaduras graves. No la recargue, ni quite el conector polarizado, ni la desmonte, ni caliente por encima de los 100°C (212°F), ni la incinere ni exponga el contenido de sus celdas al agua. Deséchela tal como dispone la normativa local.

If the LCD breaks and the fluid from inside the LCD gets into your eyes or on your hands, immediately wash the affected areas with water at least for 15 minutes. Seek medical care if any symptoms caused by the fluid are present after washing.

Si le panneau d'affichage à cristaux liquides se brise et que vous recevez dans les yeux ou sur les mains une partie du fluide, rincez-les abondamment pendant au moins quinze minutes. Consultez un médecin si des symptômes persistent après le lavage.

Die Leuchtstoffröhre im LCD-Bildschirm enthält Quecksilber. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Der LCD-Bildschirm besteht aus Glas und kann zerbrechen, wenn er unsachgemäß behandelt wird oder der Computer auf den Boden fällt. Wenn der Bildschirm beschädigt ist und die darin befindliche Flüssigkeit in Kontakt mit Haut und Augen gerät, sollten die betroffenen Stellen mindestens 15 Minuten mit Wasser abgespült und bei Beschwerden anschließend ein Arzt aufgesucht werden.

אם מסך הגביש הנוזלי (LCD) נשבר והנוזל מתוך המסך בא במגע עם עיניכם או ידיכם, שטפו את האזורים הננועים מיד במים במשך 15 דקות לפחות. פנו לקבלת עזרה רפואית אם תסמינים הנובעים מהמגע עם הנוזל נמשכים לאחר השטיפה.

Nel caso che caso l'LCD si dovesse rompere ed il liquido in esso contenuto entrasse in contatto con gli occhi o le mani, lavare immediatamente le parti interessate con acqua corrente per almeno 15 minuti; poi consultare un medico se i sintomi dovessero permanere.

LCDが破損し、LCDの中の液体が目に入ったり、手に触れたりした場合は、液体が触れた部分を少なくとも15分間洗い流してください。洗い流した後に、液体によって何らかの症状が現れた場合は、医師の治療を受けてください。

Si la LCD se rompe y el fluido de su interior entra en contacto con sus ojos o sus manos, lave inmediatamente las áreas afectadas con agua durante 15 minutos como mínimo. Obtenga atención medica si se presenta algún síntoma del fluido despues de lavarse.



⚠ DANGER

To avoid shock, do not remove the plastic cover that protects the lower part of the inverter card.

Afin d'éviter tout risque de choc électrique, ne retirez pas le cache en plastique protégeant la partie inférieure de la carte d'alimentation.

Aus Sicherheitsgründen die Kunststoffabdeckung, die den unteren Teil der Spannungswandlerplatine umgibt, nicht entfernen.

כדי למנוע התחשמלות, אין להסיר את מכסה הפלסטיק המגן על חלקו התחתון של הכרטיס ההפוך.

Per evitare scosse elettriche, non rimuovere la copertura in plastica che avvolge la parte inferiore della scheda invertitore.

感電を防ぐため、インバーター・カードの下部を保護しているプラスチック・カ バーを外さないでください。

Para evitar descargas, no quite la cubierta de plástico que rodea la parte baja de la tarjeta invertida.

Safety notice 7

⚠ DANGER

Though the main batteries have low voltage, a shorted or grounded battery can produce enough current to burn personnel or combustible materials.

Bien que le voltage des batteries principales soit peu élevé, le court-circuit ou la mise à la masse d'une batterie peut produire suffisamment de courant pour brûler des matériaux combustibles ou causer des brûlures corporelles graves.

Obwohl Hauptbatterien eine niedrige Spannung haben, können sie doch bei Kurzschluß oder Erdung genug Strom abgeben, um brennbare Materialien zu entzünden oder Verletzungen bei Personen hervorzurufen.

אף שהסוללות הראשיות הן בעלות מתח נמוך, סוללה מקוצרת או מוארקת עלולה להפיק זרם מספיק לגרימת כוויות או להצתת חומרים דליקים.

Sebbene le batterie di alimentazione siano a basso voltaggio, una batteria in corto circuito o a massa può fornire corrente sufficiente da bruciare materiali combustibili o provocare ustioni ai tecnici di manutenzione.

メイン・バッテリーの電圧は低くても、ショートしたり、接地したバッテリーが、作業者にやけどを負わせたり、可燃物を燃やすだけの電流を発生させる場合があります。

Aunque las baterías principales tienen un voltaje bajo, una batería cortocircuitada o con contacto a tierra puede producir la corriente suficiente como para quemar material combustible o provocar quemaduras en el personal.

⚠ DANGER

Before removing any FRU, turn off the computer, unplug all power cords from electrical outlets, remove the battery pack, and then disconnect any interconnecting cables

Avant de retirer une unité remplaçable en clientèle, mettez le système hors tension, débranchez tous les cordons d'alimentation des socles de prise de courant, retirez la batterie et déconnectez tous les cordons d'interface.

Die Stromzufuhr muß abgeschaltet, alle Stromkabel aus der Steckdose gezogen, der Akku entfernt und alle Verbindungskabel abgenommen sein, bevor eine FRU entfernt wird.

לפני סילוק FRU כלשהו, יש לכבות את המחשב, לנתק את כל כבלי החשמל משקעי החשמל, להוציא את מארז הסוללה, ואז לנתק כבלי חיבור אחרים אם יש כאלה.

Prima di rimuovere qualsiasi FRU, spegnere il sistema, scollegare dalle prese elettriche tutti i cavi di alimentazione, rimuovere la batteria e poi scollegare i cavi di interconnessione.

FRUを取り外す前に、 ThinkPad の電源を切って、すべての電源コードをコンセントから外してください。次に、バッテリー・パックを外し、相互接続ケーブルを外してください。

Antes de quitar una FRU, apague el sistema, desenchufe todos los cables de las tomas de corriente eléctrica, quite la batería y, a continuación, desconecte cualquier cable de conexión entre dispositivos.

Laser compliance statement

Some models of Lenovo computer are equipped from the factory with an optical storage device such as a CD-ROM drive or a DVD-ROM drive. Such devices are also sold separately as options. If one of these drives is installed, it is certified in the U.S. to conform to the requirements of the Department of Health and Human Services 21 Code of Federal Regulations (DHHS 21 CFR) Subchapter J for Class 1 laser products. Elsewhere, the drive is certified to conform to the requirements of the International Electrotechnical Commission (IEC) 825 and CENELEC EN 60 825 for Class 1 laser products.

If a CD-ROM drive, a DVD-ROM drive, or another laser device is installed, note the following:

⚠ CAUTION

Use of controls or adjustments or performance of procedures other than those specified herein might result in hazardous radiation exposure.

O uso de controles, ajustes ou desempenho de procedimentos diferentes daqueles aqui especificados pode resultar em perigosa exposição à radiação.

凡未在这里指明的任何控制用法、调整、行为,都会导致严重后果。

Pour éviter tout risque d'exposition au rayon laser, respectez les consignes de réglage et d'utilisation des commandes, ainsi que les procédures décrites.

Werden Steuer- und Einstellelemente anders als hier festgesetzt verwendet, kann gefährliche Laserstrahlung auftreten.

Az itt előírt eljárásoktól, beállításoktól és vezérlésektől eltérni a lézersugárzás veszélye miatt kockázatos!

L'utilizzo di controlli, regolazioni o l'esecuzione di procedure diverse da quelle specificate possono provocare l'esposizione a.

Использование элементов настройки и выполнение процедур иных, чем указано здесь, может привести к опасному радиационному облучению.

Použitie kontrôl, úprav alebo iných vykonaní od iných výrobcov, ako je v tomto špecifikované, mohlo by mať za následok nebezpečenstvo vystavenia sa vyžiarovaniu.

本書で指定された内容以外の、お客様による整備、調整、または手順を行った場合、レーザー光の放射の危険があります。

El uso de controles o ajustes o la ejecución de procedimientos distintos de los aquí especificados puede provocar la exposición a radiaciones peligrosas.

Opening the CD-ROM drive, the DVD-ROM drive, or any other optical storage device could result in exposure to hazardous laser radiation. There are no serviceable parts inside those drives. **Do not open**.

A CD-ROM drive, a DVD-ROM drive, or any other storage device installed may contain an embedded Class 3A or Class 3B laser diode. Note the following:

⚠ DANGER

Emits visible and invisible laser radiation when open. Do not stare into the beam, do not view directly with optical instruments, and avoid direct exposure to the beam.

Radiação por raio laser ao abrir. Não olhe fixo no feixe de luz, não olhe diretamente por meio de instrumentos óticos e evite exposição direta com o feixe de luz.

开启时会有激光发射时,请勿盯视激光光束,请勿直接查看 视觉仪器,并且避免直接接触在激光光束之中。

Rayonnement laser si carter ouvert. Évitez de fixer le faisceau, de le regarder directement avec des instruments optiques, ou de vous exposer au rayon.

Laserstrahlung bei geöffnetem Gerät. Nicht direkt oder über optische Instrumente in den Laserstrahl sehen und den Strahlungsbereich meiden.

Kinyitáskor lézersugár! Ne nézzen bele se szabad szemmel, se optikai eszközökkel. Kerülje a sugárnyalábbal való érintkezést!

Aprendo l'unità vengono emesse radiazioni laser. Non fissare il fascio, non guardarlo direttamente con strumenti ottici e evitare l'esposizione diretta al fascio.

Открывая, берегитесь лазерного излучения. Не смотрите на луч, не разглядывайте его с помощью оптических инструментов, а также избегайте прямого воздействия лазерного луча.

Keď je laserová jednotka otvorená. Vyhnite sa priamemu pohľadu a nehľadte priamo s optickými nástrojmi do ľúča a vyhnite sa priamemu vystaveniu ľúčov.

開けるとレーザー光が放射されます。光線を見つめたり、光学機械を使って直接見たりしないでください。

Radiación láser al abrir. No mire fijamente ni examine con instrumental óptico el haz de luz. Evite la exposición directa al haz.

Important service information

This chapter presents the following important service information:

- · "Strategy for replacing FRU" on page 16
 - "Strategy for replacing a hard disk drive" on page 17
 - "Important notice for replacing a system board" on page 17
- "Important information about replacing RoHS compliant FRU" on page 18

Important:

BIOS and device driver fixes are customer-installable. The BIOS and device drivers are posted on the customer support site: http://support.lenovo.com.

Strategy for replacing FRU

Before replacing parts:

Make sure that all software fixes, drivers, and BIOS downloads are installed before replacing any FRU listed in this manual.

After a system board is replaced, ensure that the latest BIOS is loaded to the system board before completing the service action.

To download software fixes, drivers, and BIOS, follow the steps below:

- 1. Go to http://support.lenovo.com.
- Enter the serial number or select a product or use Lenovo smart downloading.
- 3. Select the BIOS/Driver/Applications and download.
- 4. Follow the directions on the screen and install the necessary software.

Use the following strategy to prevent unnecessary expense for replacing and servicing FRU:

- If you are instructed to replace an FRU, but the replacement does not solve the problem, reinstall the original FRU before you continue.
- Some computers have both a processor board and a system board. If you
 are instructed to replace either of them, and replacing one of them does not
 solve the problem, reinstall that board, and then replace the other one.
- If an adapter or a device consists of more than one FRU, any of the FRU
 may be the cause of the error. Before replacing the adapter or device,
 remove the FRU one by one to see if the symptoms change. Replace only
 the FRU that changed the symptoms.

Attention: The setup configuration on the computer you are servicing may have been customized. Running Automatic Configuration may alter the settings. Note the current configuration settings (using the View Configuration option); then, when service has been completed, verify that those settings remain in effect

Strategy for replacing a hard disk drive

Always try to run a low-level format before replacing a hard disk drive. This will cause all customer data on the hard disk to be lost. Make sure that the customer has a current backup of the data before performing this action.

Attention: The drive startup sequence in the computer you are servicing may have been changed. Be extremely careful during write operations such as copying, saving, or formatting. If you select an incorrect drive, data or programs can be overwritten.

Important notice for replacing a system board

Some components mounted on a system board are very sensitive. Improper handling can cause damage to those components, and may cause a system malfunction.

Attention: When handling a system board:

- · Do not drop the system board or apply any excessive force to it.
- · Avoid rough handling of any kind.
- Avoid bending the system board and hard pushing to prevent cracking at each BGA (Ball Grid Array) chipset.

Important information about replacing RoHS compliant FRU

RoHS, The Restriction of Hazardous Substances in Electrical and Electronic Equipment Directive (2002/95/EC) is a European Union legal requirement affecting the global electronics industry. RoHS requirements must be implemented on Lenovo products placed on the market after June 2006. Products on the market before June 2006 are not required to have RoHS compliant parts. If the original FRU parts are non-compliant, replacement parts can also be non-compliant. In all cases if the original FRU parts are RoHS compliant, the replacement part must also be RoHS compliant.

Note: RoHS and non-RoHS FRU part numbers with the same fit and function are identified with unique FRU part numbers.

Lenovo plans to transit to RoHS compliance well before the implementation date and expects its suppliers to be ready to support Lenovo's requirements and schedule in the EU. Products sold in 2005 and 2006 might contain RoHS compliant FRU. The following statement pertains to these products and any product Lenovo produces containing RoHS compliant FRU.

RoHS compliant FRUs have unique FRU part numbers. Before or after the RoHS implementation date, failed RoHS compliant parts must always be replaced with RoHS compliant ones, so only the FRU identified as compliant in the system HMM or direct substitutions for the FRU may be used.

Products marketed before June 2006		Products marketed after June 2006	
Current or original part	Replacement FRU	Current or original part	Replacement FRU
Non-RoHS	Can be Non-RoHS	Must be RoHS Must be Rol	Must be Dell'S
Non-RoHS	Can be RoHS		
Non-RoHS	Can sub to RoHS		Must be Rons
RoHS	Must be RoHS		

Note: A direct substitution is a part with a different FRU part number that is automatically shipped by the distribution center at the time of the order.

General checkout

This chapter presents the following information:

- · "What to do first" on page 20
- · "Power system checkout" on page 21

Before you go to the checkout, make sure to read the following important notes:

Important notes:

- Only certified trained personnel can service the computer.
- Before replacing any FRU, read the entire page on removing and replacing FRU.
- · Carefully remove screws for reuse when replacing FRU.
- Be extremely careful during such write operations as copying, saving, or formatting. Drives in the computer that you are servicing sequence might have been altered. If you select an incorrect drive, data or programs might be overwritten.
- Replace an FRU only with another FRU of the correct model. When you
 replace an FRU, make sure that the machine model and the FRU part number are
 correct by referring to the FRU parts list.
- An FRU should not be replaced just because of a single, unreproducible failure.
 Single failures can occur for a variety of reasons that have nothing to do with a
 hardware defect, such as cosmic radiation, electrostatic discharge, or software
 errors. Consider replacing an FRU only when a problem recurs. If you suspect that
 an FRU is defective, clear the error logs and run the test again. If the error does
 not recur, do not replace the FRU.
- · Be careful not to replace a nondefective FRU.

What to do first

When you do return an FRU, you must include the following information in the parts exchange form or parts return form that you attach to it:

- 1. Name and phone number of servicer
- 2. Date of service
- 3. Date on which the machine failed
- 4. Date of purchase
- 5. Procedure index and page number in which the failing FRU was detected
- 6. Failing FRU name and part number
- 7. Machine type, model number, and serial number
- 8. Customer's name and address

Note for warranty: During the warranty period, the customer may be responsible for repair costs if the computer damage was caused by misuse, accident, modification, unsuitable physical or operating environment, or improper maintenance by the customer.

The following is a list of some common items that are not covered under warranty and some symptoms that might indicate that the system was subjected to stress beyond normal use.

Before checking problems with the computer, determine whether the damage is covered under the warranty by referring to the following list:

The following are not covered under warranty:

- LCD panel cracked from the application of excessive force or from being dropped
- · Scratched (cosmetic) parts
- · Distortion, deformation, or discoloration of the cosmetic parts
- Plastic parts, latches, pins, or connectors that have been cracked or broken by excessive force
- · Damage caused by liquid spilled into the system
- Damage caused by the improper insertion of a PC Card or the installation of an incompatible card
- · Improper disk insertion or use of an optical drive
- Diskette drive damage caused by pressure on the diskette drive cover, foreign material in the drive, or the insertion of a diskette with multiple labels
- · Damaged or bent diskette eject button
- · Fuses blown by attachment of a nonsupported device
- Forgotten computer password (making the computer unusable)
- · Sticky keys caused by spilling a liquid onto the keyboard
- · Use of an incorrect AC adapter on laptop products

The following symptoms might indicate damage caused by nonwarranted activities:

- Missing parts might be a symptom of unauthorized service or modification.
- If the spindle of a hard disk drive becomes noisy, it may have been subjected to excessive force, or dropped.

Power system checkout

To verify a symptom, follow the steps below:

- 1. Turn off the computer.
- 2. Remove the battery pack.
- 3. Connect the AC adapter.
- 4. Make sure that power is supplied when you turn on the computer.
- 5. Turn off the computer.
- 6. Disconnect the AC adapter and install the charged battery pack.
- Make sure that the battery pack supplies power when you turn on the computer.

If you suspect a power problem, see the appropriate one of the following power supply checkouts:

- · "Checking the AC adapter" on page 21
- · "Checking operational charging" on page 21
- · "Checking the battery pack" on page 22


Checking the AC adapter

You are here because the computer fails only when the AC adapter is used.

- If the power-on indicator does not turn on, check the power cord of the AC adapter for correct continuity and installation.
- If the computer does not charge during operation, go to "Checking operational charging".

To check the AC adapter, follow the steps below:

- 1. Unplug the AC adapter cable from the computer.
- Measure the output voltage at the plug of the AC adapter cable. See the following figure:



Pin	Voltage (V DC)
1	+20
2	0
	`

Note: Output voltage for the AC adapter pin No. 2 may differ from the one you are servicing.

- 3. If the voltage is not correct, replace the AC adapter.
- 4. If the voltage is acceptable, do the following:
- Replace the system board.
- If the problem persists, go to "Lenovo V340-17IWL" on page 27.

Note: Noise from the AC adapter does not always indicate a defect.



Checking operational charging

To check whether the battery charges properly during operation, use a discharged battery pack or a battery pack that has less than 50% of the total power remaining when installed in the computer.

Perform operational charging. If the battery status indicator or icon does not light on, remove the battery pack and let it return to room temperature. Reinstall the battery pack. If the charge indicator or icon is still off, replace the battery pack.

If the charge indicator still does not light on, replace the system board. Then reinstall the battery pack. If it is still not charged, go to the next section.

Checking the battery pack

Battery charging does not start until the Power Meter shows that less than 95% of the total power remains; under this condition the battery pack can charge to 100% of its capacity. This protects the battery pack from being overcharged or from having a shortened life.

To check your battery, move your cursor to the Power Meter icon in the icon tray of the Windows® taskbar and wait for a moment (but do not click it), and the percentage of battery power remaining is displayed. To get detailed information about the battery, double-click the Power Meter icon.

Note: If the battery pack becomes hot, it may not be able to be charged. Remove it from the computer and leave it at room temperature for a while. After it cools down, reinstall and recharge it.

Related service information

This chapter presents the following information:

- "Restoring the factory contents by using OneKey Recovery" on page 23
- · "Passwords" on page 24
- · "Power management" on page 25

Restoring the factory contents by using OneKey Recovery

Restore of factory default

The Lenovo V340-17IWL computers come with pre-installed OneKey Recovery System. In order to save application files and the initial backed up files of the system, the hard disk in a Lenovo computer includes a hidden partition when it is shipped. If you need to restore the system to the point of your first boot up, just enter Lenovo OneKey Recovery System and run **System Recovery**. For details of OneKey Recovery System, see the User Guide for Lenovo OneKey Recovery system.

Note: This will delete all the new data on the system partition (C drive), which is not recoverable. Make sure to back up your critical data before you perform this action.

When you use the recovery discs to boot your computer, the system will enter the user interface for system recovery automatically. Please follow the prompt to insert the backup discs to complete the whole recovery process.

Note: The recovery process might take up to 2 hours.

Passwords

As many as three passwords may be needed for any Lenovo computer: the power-on password (POP), the hard disk password (HDP), and the administrator password.

If any of these passwords has been set, a prompt for it appears on the screen whenever the computer is turned on. The computer does not start until the password is entered.

Power-on password

A power-on password (POP) protects the system from being powered on by an unauthorized person. The password must be entered before an operating system can be booted.

Hard-disk password

There are two hard-disk passwords (HDPs):

- + User HDP for the user
- + Master HDP for the system administrator, who can use it to get access to the hard disk drive even if the user has changed the user HDP

Attention: If the user HDP has been forgotten, check whether a master HDP has been set. If it has, it can be used for access to the hard disk drive. If no master HDP is available, neither Lenovo nor Lenovo authorized service technicians provide any services to reset either the user or the master HDP, or to recover data from the hard disk drive. The hard disk drive can be replaced for a scheduled fee

Administrator password

Administrator password controls the access of the whole setup utility. Only after the Administrator password has been set can the User password be set. If Administrator password was cleared, the User password was cleared too.

Power management

Note: Power management modes are not supported for APM operating system.

To reduce power consumption, the computer has three power management modes: screen blank, sleep (standby), and hibernation.

Screen blank state

If the time set on the "Turn off monitor" timer in the operating system expires, the LCD backlight turns off. You can also turn off the LCD backlight by pressing [[ax_n]].

To end screen blank state and resume normal operation, press any key on the keyboard.

Putting the computer to sleep or shutting it down

When you have finished working with your computer, you can put it to sleep or shut it down.

Putting your computer to sleep

If you will be away from your computer for only a short time, put the computer to sleep.

When the computer is in sleep mode, you can quickly wake it to resume use, bypassing the startup process.

To put the computer to sleep, do one of the following:

- · Close the display lid.
- · Press and hold the Power key for about 1 to 5 seconds.
- Move the cursor to the lower-left corner, and then select the Start button.
 Select Power → Sleep.

Note: Put your computer to sleep before you move it. Moving your computer while the hard disk drive is spinning can damage the hard disk, causing loss of data

To wake up the computer, perform the following:

· Press any key on the keyboard.



Shutting down the computer

If you are not going to use your computer for a long time, shut it down. To shut down your computer, do one of the following:

· Move the cursor to the lower-left corner, and then select the Start button. Select Power \bigcirc \rightarrow Shut down.



· Right-click or press the Start button in the lower-left corner and select Shut down or sign out \rightarrow Shut down.



Lenovo V340-17IWL

This chapter presents the following product-specific service references and product-specific parts information:

- "Specifications" on page 27
- · "Status indicators" on page 29
- "Hotkeys" on page 30
- "FRU replacement notices" on page 31
- · "Removing and replacing an FRU" on page 32
- · "Locations" on page 65
- · "Parts list" on page 67

Specifications

The following table lists the specifications of the V340-17IWL:

Table 1. Specifications

Form Factor	
Dimensions	Approximately 413 mm × 284.6 mm × 24.3 mm
Weight	Approximately 2.8 kg with battery
LCD size	17.3-inch
Processor	
Click Control Pane	perties of your computer, you can do this as follows: I, then click Hardware and Sound, click Device Manager Printers and double click Processors.
Memory	
Type and speed	On board x 1 + DIMM x 1, 2133MHz
Maximum supported capacity	16 GB
SSD	
Interface	M.2 SATA/PCIe
Hard disk drive	
Form factor	2.5-inch, 7 mm
Capacity	SSD + HDD
Interface	2.5-inch SATA



Table 1. Specifications (continued)

Optical Drive			
Form factor	9.0 mm		
Туре	Writer		
Display			
Display resolution (LCD)	1400 × 900 pixels HD+/1920 × 1080 pixels FHD		
LCD backlight	LED		
I/O Ports			
USB	USB 3.0 × 2, Type-C (Support USB 3.1 Gen 1, Output 5V DC, 1.5A DC) × 1		
Audio	Combo audio jack × 1		
Video/Audio	HDMI slot × 1		
Ethernet	RJ-45 × 1		
Battery pack			
Туре	Polymer		
Cells/Capacity	3 Cell, 36 Wh		
Note: The capacity given here is the typical or average capacity as measured in a specific test environment. Capacities measured in other environments may differ but are no lower than the rated capacity (see product label).			
AC power adapter			
Input	100-240 V, 50-60 Hz		
Output voltage	20 V DC		
Power	45/65 W		
Miscellaneous			
Camera	0.3 M/HD		
Security	Kensington slot × 1		

Status indicators

The system status indicators below show the computer status:




Table 2. Status indicators

AC power adapter status	Indicator status	Meaning	
Disconnected	Off	The computer is not connected to ac power.	
Commented	Amber	The battery has between 1% and 90% charge and still charging.	
Connected	White	The battery has between 91% and 100% charge.	

Indicator	Indicator status	Meaning
Power status indicator	On (solid white)	The computer is on (battery power 21%-100%).
	Fast blinking white	The computer is on (battery power 1%-20%).
	Slow blinking white	The computer is in sleep mode.
	Off	The computer is off or in hibernation mode



Hotkeys

You can access certain system settings quickly by pressing the appropriate hotkeys.

Table 3. Hotkeys

(N) :	Mute/unmute sound.	- :	Turn on/off airplane mode.
□ :	Decrease system volume.		Enable/Disable the integrated camera.
(4+) :	Increase system volume.	△ :	Lock/Unlock the LCD screen.
× _{FF} :	Enable/Disable the integrated microphone.	FIO :	Enable the external projector or dangle the external display.
C (5)	Refresh page.		Decrease display brightness.
. :	Enable/Disable the touchpad.	(; + ; ; ; ; ; ; ; ; ; ; ; ; ; ; ; ; ;	Increase display brightness.

FRU replacement notices

This section presents notices related to removing and replacing parts. Read this section carefully before replacing any FRU.

Screw notices

Loose screws can cause a reliability problem. In the Lenovo computer, this problem is addressed with special nylon-coated screws that have the following characteristics:

- · They maintain tight connections.
- · They do not easily come loose, even with shock or vibration.
- · They are harder to tighten.
- · Each one should be used only once.

Do the following when you service this machine:

- Keep the screw kit in your tool bag.
- · Carefully remove screws for reuse when replacing FRU.
- · Use a torque screwdriver if you have one.

Tighten screws as follows:

· Plastic to plastic

Turn an additional 90° after the screw head touches the surface of the plastic part:



· Logic card to plastic

Turn an additional 180° after the screw head touches the surface of the logic card:



Torque driver

If you have a torque screwdriver, refer to the "Torque" column for each step.

- Make sure that you use the correct screws. If you have a torque screwdriver, tighten all screws firmly to the torque shown in the table. Carefully remove screws for reuse when replacing FRU. Make sure that all screws are tightened firmly.
- Ensure torque screwdrivers are calibrated correctly following country specifications.

Removing and replacing an FRU

This section presents exploded figures with the instructions to indicate how to remove and replace the FRU. Make sure to observe the following general rules:

- 1. Do not attempt to service any computer unless you have been trained and certified. An untrained person runs the risk of damaging parts.
- 2. Before replacing any FRU, review "FRU replacement notices" on page 31.
- Begin by removing any FRUs that have to be removed before the failing FRU. Any of such FRU are listed at the top of the page. Remove them in the order in which they are listed.
- 4. Follow the correct sequence in the steps to remove the FRU, as given in the figures by the numbers in square callouts.
- When turning a screw to replace an FRU, turn it in the direction as given by the arrow in the figure.
- When removing the FRU, move it in the direction as given by the arrow in the figure.
- To put the new FRU in place, reverse the removal procedures and follow any of the notes that pertain to replacement. For information about connecting and arranging internal cables, see "Locations" on page 65.
- 8. When replacing an FRU, use the correct screw as shown in the procedures.

⚠ DANGER

Before removing any FRU, turn off the computer, unplug all power cords from electrical outlets, remove the battery pack, and then disconnect any of the interconnecting cables.

Attention: After replacing an FRU, do not turn on the computer until you have made sure that all screws, springs, and other small parts are in place and none are loose inside the computer. Verify this by shaking the computer gently and listening for rattling sounds. Metallic parts or metal flakes can cause electrical short circuits.

Attention: The system board is sensitive to, and can be damaged by, electrostatic discharge. Before touching it, establish personal grounding by touching a ground point with one hand or using an electrostatic discharge (ESD) strap (P/N 6405959) to remove potential shock reasons.

1010 Optical drive

Step 1: Remove the screw 1.

Step 2: Pull the optical drive out in the direction shown by arrow 2.



Figure 1. Remove the optical drive

Step	Screw (quantity)	Color	Torque
1	M2.5 × 7 mm, Phillips head, nylok-coated (1)	Black/ Silver	3.0+/-0.3 kgf/cm



Step 3: Remove the screw 3.

Step 4: Carefully remove the optical drive bracket and bezel in the directions shown by arrows 4 and 5.




Figure 2. Remove the optical drive bracket and bezel

Step	Screw (quantity)	Color	Torque
3	M2 × 3 mm, Phillips head, nylok-coated (1)	Black	1.85+/-0.15 kgf/cm

1020 Base cover

For access, remove this FRU:

• "1010 Optical drive" on page 33

Step 1: Remove the screws 1.




Figure 3. Remove the screws

Step	Screw (quantity)	Color	Torque
1	M2.5 × 7 mm, Phillips-head, nylok-coated (12)	Black/ Silver	3.0+/-0.3 kgf/cm






Figure 4. Remove the base cover

Note: Applying labels to the base cover

The new base cover FRU is shipped with a kit containing labels of several kinds. When you replace the base cover, you need to apply the following labels:

The following labels need to be peeled off from the old base cover and put on the new base cover.


- QR label
- b Intel label/AMD label
- c VGA label
- d ES label
- e Palmrest label 65 × 20mm
- f Rating label 66 × 24mm
- g Rating label for Print 43 × 24mm
- h Country label
- Adapter label 65 x 20mm
- WL/BT label 35 × 15mm
- k OS label 16 × 22.5mm

For some models, you also need to apply one or two FCC labels. Check the old base cover; if it has one or two FCC labels, find duplicates of them in the label kit and apply them to the new base cover.

For the location of each label, refer to the following figures:







1030 Hard disk drive

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35

Attention:

- Do not drop the hard disk drive or apply any physical shock to it. The hard disk drive is sensitive to physical shock. Improper handling can cause damage and permanent loss of data.
- Before removing the drive, suggest the customer to backup all the information on it if possible.
- Never remove the drive while the system is operating or in suspend mode.

Step 1: Remove the screws 1.

Step 2: Detach the HDD board connector in the direction shown by arrow 2.




Figure 5. Remove the screws and detach the HDD board connector

Step	Screw (quantity)	Color	Torque
1	M2 × 6 mm, Phillips-head, nylok-coated (4)	Black	1.85+/-0.15 kgf/cm



Remove the hard disk drive from the slot in the direction shown by Step 4: arrow 3.



Figure 6. Remove the hard disk drive

Step 5: Remove the screws 4.

Step 6: Detach the bracket from the hard disk drive in the direction shown

by arrow 5.



Figure 7. Remove the screws and dtach the HDD bracket

1040 Battery pack

⚠ DANGER

Only use the battery specified in the parts list for your computer. Any other battery could ignite or explode.

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35

Step 1: Detach the battery pack connector in the direction shown by arrow 1.

Step 2: Remove the screws 2.




Figure 8. Detach the battery pack connector and remove the screws

Step	Screw (quantity)	Color	Torque
2	M2 × 6 mm, Phillips-head, nylok-coated (5)	Black	1.85+/-0.15 kgf/cm





Figure 9. Remove the battery pack

1050 SSD card

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1040 Battery pack" on page 41

Attention:

- Do not drop the SSD card or apply any physical shock to it. The SSD card is sensitive to physical shock. Improper handling can cause damage and permanent loss of data
- Before removing the SSD card, suggest the customer to backup all the information on it if possible.
- Never remove the SSD card while the system is operating or in suspend mode.

Step 1: Remove the screw 1.



Figure 10. Remove the screw

Step	Screw (quantity)	Color	Torque
1	M2 × 6 mm, Phillips-head, nylok-coated (1)	Black	1.85+/-0.15 kgf/cm






Figure 11. Remove the SSD card

1060 **DIMM**

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1040 Battery pack" on page 41
- Step 1: Release the two latches on both edges of the socket at the same time in the directions shown by arrows 1.
- Step 2: Unplug the DIMM in the direction shown by arrow 2.




Figure 12. Release the latches and unplug the DIMM



1070 PCI Express Mini Card for wireless LAN

For access, remove the FRU in following order::

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1040 Battery pack" on page 41

Important:

The preinstalled WLAN module may only be replaced with a Lenovo approved module in order to comply with FCC and IC regulations. Refer to Table 4 "Parts list—Overall" on page 68 for Lenovo part numbers for the approved modules.

Step 1: Disconnect the two wireless LAN cables (black, gray) 1.

Step 2: Remove the screw 2.



Figure 13. Disconnect the two wireless LAN cables and remove the screw

In step 1, unplug the jacks by using the removal tool antenna RF connector (P/N: 08K7159), or pick up the connectors with your fingers and gently unplug them in the direction shown by the arrows.

Notes: The wireless LAN card has 2 cables in step 1.

The wireless LAN card in some models might have 3 cables in step 1.

Step	Screw (quantity)	Color	Torque
2	M2 × 3 mm, Phillips-head, nylok-coated (1)	Black	1.85+/-0.15 kgf/cm

46



Step 3: Remove the card in the direction shown by arrow 3.

Figure 14. Remove the PCI Express mini card

When installing:

- In models with a wireless LAN card that has two antenna connectors, plug
 the black cable (1st) (MAIN) into the jack labeled MAIN, and the grey cable
 (2nd) (AUX) into the jack labeled AUX on the card.
- In models with a wireless LAN card that has three antenna connectors, plug
 the black cable (1st) (MAIN) into the jack labeled 1, the grey cable (3rd) into
 the jack labeled 3, and the white cable (2nd) (AUX) into the jack labeled 2 on
 the card.

1080 Fan assembly and Heat Sink assembly

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1040 Battery pack" on page 41
- "1070 PCI Express Mini Card for wireless LAN" on page 46

Step 1: Release the cables from the cable guides in the direction shown by arrows 1.



Figure 15. Release the antenna cables

When installing: Route the antenna cables along the cable guides. As you route the cables, make sure that they are not subjected to any tension. Tension could cause the cables to be damaged by the cable guides, or a wire to be broken.

- Step 2: Unplug the fan connector in the direction shown by arrow 2.
- Step 3: Remove the screw 3.




Figure 16. Unplug the fan connector and remove the screw

Step	Screw (quantity)	Color	Torque
3	M2 × 6 mm, Phillips head, nylok-coated (1)	Black	1.85+/-0.15 kgf/cm

Step 4: Remove the fan in the direction shown by arrow 4. Be careful not to damage the connector.



Figure 17. Remove the fan



Step 5: Remove the screws 5.



Figure 18. Remove the screws

Step 6: Lift the heat sink in the direction shown by arrows 6.



Figure 19. Remove the heat sink




Figure 20. Heat sink

When installing: Before you attach the fan assembly to the computer, apply thermal grease, at an amount of 0.2 grams, to the a part shown in the figure above. Either too much or too little grease application can cause a thermal problem due to imperfect contact with a component.



1090 System board

Important notices for handling the system board:

When handling the system board, bear the following in mind.

- · Be careful not to drop the system board on a bench top that has a hard surface, such as metal, wood, or composite.
- · Avoid rough handling of any kind.
- During the whole process, make sure not to drop or stack the system board.
- If you put a system board down, make sure to put it only on a padded surface such as an ESD mat or conductive corrugated material.

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1030 Hard disk drive" on page 39
- · "1040 Battery pack" on page 41
- "1050 SSD card" on page 43
- "1060 DIMM" on page 45
- "1070 PCI Express Mini Card for wireless LAN" on page 46
- "1080 Fan assembly and Heat Sink assembly" on page 48

Step 1: Disconnect the connectors in the directions shown by arrows 1.




Figure 21. Disconnect the connectors

- Step 2: Remove the screws 2.
- Step 3: Remove the system board in the direction shown by arrow 3.




Figure 22. Remove the screws and system board

Step	Screw (quantity)	Color	Torque
2	M2 × 3 mm, Phillips-head, nylok-coated (2)	Black	1.85+/-0.15 kgf/cm



1100 ODD transfer board and backup battery

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1030 Hard disk drive" on page 39
- "1040 Battery pack" on page 41
- "1050 SSD card" on page 43
- "1060 DIMM" on page 45
- "1070 PCI Express Mini Card for wireless LAN" on page 46
- "1080 Fan assembly and Heat Sink assembly" on page 48
- "1090 System board" on page 52
- Step 1: Remove the screw 1.
- Step 2: Remove the ODD transfer board in the direction shown by arrow 2.



Figure 23. Remove the ODD transfer board

Step	Screw (quantity)	Color	Torque
1	M2 × 3 mm, Phillips-head, nylok-coated (1)	Black	1.85+/-0.15 kgf/cm

Step 3: Unplug the backup battery connector in the direction shown by arrow 3.




Figure 24. Remove the backup battery

1110 Speakers

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1040 Battery pack" on page 41

Step 1: Unplug the speaker connector and then remove the speakers 1.




Figure 25. Remove the speakers

1120 Touchpad

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1030 Hard disk drive" on page 39
- "1040 Battery pack" on page 41
- "1050 SSD card" on page 43
- "1060 DIMM" on page 45
- "1070 PCI Express Mini Card for wireless LAN" on page 46
- "1080 Fan assembly and Heat Sink assembly" on page 48
- "1090 System board" on page 52
- "1100 ODD transfer board and backup battery" on page 54

Step 1: Remove the screws 1.

Step 2: Detach the touchpad in the direction shown by arrow 2.




Figure 26. Remove the screws and detach the touchpad



1130 Upper case

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1030 Hard disk drive" on page 39
- "1040 Battery pack" on page 41
- "1060 DIMM" on page 45
- "1070 PCI Express Mini Card for wireless LAN" on page 46
- "1080 Fan assembly and Heat Sink assembly" on page 48
- "1090 System board" on page 52
- "1100 ODD transfer board and backup battery" on page 54
- "1110 Speakers" on page 56
- "1120 Touchpad" on page 57

Step 1: Remove the screws 1.






Figure 27. Remove the screws

Step	Screw (quantity)	Color	Torque
1	M2.5 × 5 mm, Phillips-head, nylok-coated (4)	Silver	3 +/-0.3 kgf/cm



Step 2: Open the hinge in the direction shown by arrows 2.

Figure 28. Open the hinge






Figure 29. Remove the upper case



1140 LCD unit


For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- · "1030 Hard disk drive" on page 39
- "1040 Battery pack" on page 41
- "1050 SSD card" on page 43
- "1060 DIMM" on page 45
- "1070 PCI Express Mini Card for wireless LAN" on page 46
- "1080 Fan assembly and Heat Sink assembly" on page 48
- "1090 System board" on page 52
- "1100 ODD transfer board and backup battery" on page 54
- "1110 Speakers" on page 56
- "1120 Touchpad" on page 57
- "1130 Upper case" on page 58

Step 1: Pull the hinge cap in the direction shown by arrow 1 to release the hooks.



Figure 30. Remove the hinge cap



Step 2: Remove the LCD front bezel in the direction shown by arrows 2.

Figure 31. Remove the LCD front bezel

- Step 3: Remove the screws 3.
- Step 4: Lift the LCD module slightly 4.
- Step 5: Disconnect the connector in the direction shown by arrow 5.
- Step 6: Remove the LCD module.




Figure 32. Remove the screws and LCD module connector

Step	Screw (quantity)	Color	Torque
3	M2 × 3 mm, Phillips-head, nylok-coated (4)	Black	1.85+/-0.15 kgf/cm



Step 7: Remove the screws 6.




Figure 33. Remove the screws

Step	Screw (quantity)	Color	Torque
7	M2.5 × 2.5 mm, Phillips-head, nylok-coated (4)	Black	3+/-0.3 kgf/cm

Step 8: Remove the LCD hinges in the direction shown by arrows 7.




Figure 34. Remove the LCD hinges

When installing: Make sure that the connector is attached firmly and that you do not pinch the antenna cables when you attach the LCD assembly. Route the LCD cable along the cable guides.

1150 Integrated camera and antenna assembly

For access, remove the FRU in following order:

- "1010 Optical drive" on page 33
- "1020 Base cover" on page 35
- "1030 Hard disk drive" on page 39
- "1040 Battery pack" on page 41
- "1050 SSD card" on page 43
- "1060 DIMM" on page 45
- "1070 PCI Express Mini Card for wireless LAN" on page 46
- "1080 Fan assembly and Heat Sink assembly" on page 48
- "1090 System board" on page 52
- "1100 ODD transfer board and backup battery" on page 54
- "1110 Speakers" on page 56
- "1120 Touchpad" on page 57
- "1130 Upper case" on page 58
- "1140 LCD unit" on page 60

Step 1: Detach the camera connector in the direction shown by arrow 1.



Figure 35. Detach the camera connector



Note: The integrated camera is stuck on the top center of the LCD cover.

Step 2: Remove the integrated camera in the direction shown by arrow 2.



Figure 36. Remove the integrated camera

When installing: Stick the integrated camera to the top center of the LCD cover and adjust its placement to make sure the connector is attached firmly.

- Step 3: Peel off the adhesive tape securing the antenna boards.
- Step 4: Release the cables from the cable guide.
- Remove the antenna assembly in the direction shown by arrows 3. Step 5:





Figure 37. Remove the antenna assembly

Locations

Front view and right-side view


- 1 Camera
- 2 Shutter
- 3 Camera indicator
- 4 Wireless LAN/Bluetooth antennas
- 5 Microphones
- 6 Screen
- 7 Ventilation slots
- 8 Mini-security slot
- 9 CD/DVD drive
- 10 Touchpad





Bottom and Left-side view

- 1 Ventilation slots
- 2 Power connector
- 3 Battery/Charging status indicator
- 4 Ethernet connector
- 5 HDMI[™] connector
- 6 USB 3.0 connectors
- 7 Audio connector
- 8 USB-C[™] connector
- 9 Novo button
- 10 Power LED
- 11 Speakers



Parts list

This section presents the following service parts:

- · "Overall" on page 68
- · "LCD FRUs" on page 70

Note:


Each FRU is available for all types or models, unless specific types or models are specified.

Attention:

Do not attempt to replace an FRU on your own. If an FRU is damaged, contact a Lenovo authorized servicer or a marketing representative for replacement or repair. Only qualified technicians can inspect or repair this product.



Overall



Lenovo V340-17IWL

Table 4. FRU (CRU) category


No.	FRU (CRU) category	Self-service CRU	Optional-service CRU
1	LCD unit (see "LCD FRUs" on page 75).	No	No
2	Uppercase	No	No
3	Hinge cap	No	No
4	Wi-Fi card	No	No
5	Fan and heat sink	No	No
6	System board	No	No
7	CMOS battery	No	No
8	SSD	No	No
9	Memory module cover	No	No
10	Memory module	No	No
11	Speakers	No	No
12	Lowercase	No	No
13	Battery	No	No
14	Touchpad	No	No
15	ODD	Yes	No
16	ODD transfer board	No	No
17	HDD bracket	No	No
18	HDD	No	No



LCD FRUs

In Lenovo V340-17IWL, there is following type of LCD.

• "17.3-in. HD LED"



Lenovo V340-17IWL

Table 5. FRU (CRU) categories for LCD module

No.	FRU (CRU) category	Self-service CRU	Optional-service CRU
1	LCD bezel	No	No
2	Hinge cap	No	No
3	Integrated camera	No	No
4	LCD panel	No	No
5	LCD Hinges	No	No
6	Wi-Fi antennas	No	No
7	LCD cover	No	No
8	LCD cable	No	No



Notices

Lenovo may not offer the products, services, or features discussed in this document in all countries. Consult your local Lenovo representative for information on the products and services currently available in your area. Any reference to a Lenovo product, program, or service is not intended to state or imply that only that Lenovo product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any Lenovo intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any other product, program, or service.

Lenovo may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents.

LENOVO GROUP LTD. PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some jurisdictions do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. Lenovo may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

The products described in this document are not intended for use in implantation or other life support applications where malfunction may result in injury or death to persons. The information contained in this document does not affect or change Lenovo product specifications or warranties. Nothing in this document shall operate as an express or implied license or indemnity under the intellectual property rights of Lenovo or third parties. All information contained in this document was obtained in specific environments and is presented as an illustration. The result obtained in other operating environments may vary.

Lenovo may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Any references in this publication to non-Lenovo Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this Lenovo product, and use of those Web sites is at your own risk.

Any performance data contained herein was determined in a controlled environment. Therefore, the result obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Trademarks

The following terms are trademarks or registered trademarks of Lenovo in the United States, other countries, or both.

Lenovo

OneKey

Microsoft and Windows are trademarks of Microsoft Corporation in the United States, other countries, or both.

Other company, products, or service names may be trademarks or service marks of others.