

Inspiron 7391

Setup and Specifications



Notes, cautions, and warnings

 **NOTE:** A NOTE indicates important information that helps you make better use of your product.

 **CAUTION:** A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.


© 2019-2020 Dell Inc. or its subsidiaries. All rights reserved. Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

1 Set up your Inspiron 7391.....	4
2 Views of Inspiron 7391.....	6
Left.....	6
Right.....	6
Base.....	7
Display.....	7
Bottom.....	8
3 Specifications of Inspiron 7391.....	9
Dimensions and weight.....	9
Processors.....	9
Chipset.....	9
Operating system.....	10
Memory.....	10
Ports and connectors.....	10
Communications.....	11
Audio.....	11
Storage.....	12
Intel Optane Memory H10 with solid-state storage (optional).....	12
Media-card reader.....	13
Keyboard.....	13
Camera.....	13
Touchpad.....	14
Touchpad gestures.....	14
Power adapter.....	14
Battery.....	14
Display.....	15
Fingerprint reader (optional).....	16
Video.....	16
Computer environment.....	16
4 Keyboard shortcuts.....	18
5 Getting help and contacting Dell.....	20

Set up your Inspiron 7391

NOTE: The images in this document may differ from your computer depending on the configuration you ordered.

1. Connect the power adapter and press the power button.



NOTE: To conserve battery power, the battery might enter power saving mode. Connect the power adapter and press the power button to turn on the computer.

2. Finish operating system setup.

For Ubuntu:

Follow the on-screen instructions to complete the setup. For more information about installing and configuring Ubuntu, see the knowledge base articles [SLN151664](#) and [SLN151748](#) at www.dell.com/support.

For Windows:

Follow the on-screen instructions to complete the setup. When setting up, Dell recommends that you:

- Connect to a network for Windows updates.

NOTE: If connecting to a secured wireless network, enter the password for the wireless network access when prompted.

- If connected to the internet, sign-in with or create a Microsoft account. If not connected to the internet, create an offline account.
- On the **Support and Protection** screen, enter your contact details.

3. Locate and use Dell apps from the Windows Start menu—Recommended

Table 1. Locate Dell apps

Resources	Description
	<p>My Dell</p> <p>Centralized location for key Dell applications, help articles, and other important information about your computer. It also notifies you about the warranty status, recommended accessories, and software updates if available.</p>
	<p>SupportAssist</p> <p>Pro-actively checks the health of your computer's hardware and software. The SupportAssist OS Recovery tool troubleshoots issues with the operating system. For more information, see the SupportAssist documentation at www.dell.com/support.</p>

Resources

Description

 **NOTE:** In SupportAssist, click the warranty expiry date to renew or upgrade your warranty.



Dell Update

Updates your computer with critical fixes and latest device drivers as they become available. For more information about using Dell Update, see the knowledge base article [SLN305843](#) at www.dell.com/support.




Dell Digital Delivery

Download software applications, which are purchased but not pre-installed on your computer. For more information about using Dell Digital Delivery, see the knowledge base article [153764](#) at www.dell.com/support.

Views of Inspiron 7391

Left



1. Power-adapter port

Connect a power adapter to provide power to your computer.

2. Battery-status light

Indicates the battery-charge status.

Solid white—Power adapter is connected and the battery has more than 5% charge.

Amber—Computer is running on battery and the battery has less than 5% charge.

Off—Power adapter is disconnected or the battery is fully charged.

3. HDMI port

Connect to a TV or another HDMI-in enabled device. Provides video and audio output.

4. USB 3.2 Gen 1 (Type-C) port with Power Delivery/DisplayPort

Connect peripherals such as external storage devices, printers, and external displays.

Supports Power Delivery that enables two-way power supply between devices. Provides up to 15 W power output that enables faster charging.

NOTE: A USB Type-C to DisplayPort adapter (sold separately) is required to connect a DisplayPort device.

5. microSD-card slot

Reads from and writes to the microSD-card.

Right




1. Headset port

Connect headphones or a headset (headphone and microphone combo).

2. USB 3.2 Gen 1 port

Connect peripherals such as external storage devices and printers. Provides data transfer speeds up to 5 Gbps.

Base



1. Touchpad

Move your finger on the touchpad to move the mouse pointer. Tap to left-click and two finger tap to right-click.

2. Left-click area

Press to left-click.

3. Right-click area

Press to right-click.

4. Power button with fingerprint reader

Press to turn on the computer if it is turned off, in sleep state, or in hibernate state.

When the computer is turned on, press the power button to put the computer into sleep state; press and hold the power button for 10 seconds to force shut-down the computer.

Place your finger on the power button to log-in with the fingerprint reader.

NOTE: You can customize power-button behavior in Windows. For more information, see *Me and My Dell* at www.dell.com/support/manuals.

Display



1. Left microphone

Provides digital sound input for audio recording and voice calls.

2. Camera

Enables you to video chat, capture photos, and record videos.


3. Camera-status light

Turns on when the camera is in use.

4. **Right microphone**

Provides digital sound input for audio recording and voice calls.

Bottom



1. **Left speaker**

Provides audio output.

2. **Service Tag label**

The Service Tag is a unique alphanumeric identifier that enables Dell service technicians to identify the hardware components in your computer and access warranty information.

3. **Right speaker**

Provides audio output.

Specifications of Inspiron 7391

Dimensions and weight

Table 2. Dimensions and weight

Description	Values
Height:	
Front	14.90 mm (0.59 in.)
Rear	16.50 mm (0.65 in.)
Width	307.60 mm (12.11 in.)
Depth	204.70 mm (8.06 in.)
Weight (maximum)	<ul style="list-style-type: none"> Integrated graphics: 0.95 kg (2.09 lb) Discrete graphics: 0.97 kg (2.13 lb)
	<p>NOTE: The weight of your computer depends on the configuration ordered and the manufacturing variability.</p>

Processors

Table 3. Processors

Description	Values		
Processors	10th Generation Intel Core i3	10th Generation Intel Core i5	10th Generation Intel Core i7
Wattage	15 W	15 W	15 W
Core count	2	4	4
Thread count	4	8	8
Speed	Up to 3.5 GHz	Up to 3.9 GHz	Up to 4.6 GHz
Cache	4 MB	6 MB	8 MB
Integrated graphics	Intel UHD Graphics	Intel UHD Graphics	Intel UHD Graphics

Chipset

Table 4. Chipset

Description	Values
Chipset	Integrated in the processor
Processor	10th Generation Intel Core i3/i5/i7
DRAM bus width	64-bit

Description	Values
Flash EPROM	32 MB
PCIe bus	Up to Gen3

Operating system

- Windows 10 Home (64-bit)
- Windows 10 Professional (64-bit)

Memory

Table 5. Memory specifications

Description	Values
Slots	Onboard memory  NOTE: The memory is integrated on the system board from the factory and it cannot be upgraded later.
Type	LPDDR3
Speed	2133 MHz
Maximum memory	8 GB
Minimum memory	4 GB
Memory size per slot	Onboard memory GB
Configurations supported	Not supported

Ports and connectors

Table 6. External ports and connectors

External:	
USB	<ul style="list-style-type: none"> • One USB 3.2 Gen 1 (Type-C) port with Power Delivery/DisplayPort • One USB 3.2 Gen 1 port
Audio	One headset (headphone and microphone combo) port
Video	One HDMI 1.4b port
Media card reader	One microSD card slot
Docking port	Not supported
Power adapter port	One 4.5 mm x 2.9 mm DC-in E4
Security	Not supported

Table 7. Internal ports and connectors**Internal:**

M.2	<ul style="list-style-type: none"> One M.2 2280/2230 slot for solid-state drive/Intel Optane One M.2 2230 slot for Wi-Fi and Bluetooth combo card One M.2 2230 slot for solid-state drive
-----	--

NOTE: To learn more about the features of different types of M.2 cards, see the knowledge base article [SLN301626](#).

Communications

Wireless module

Table 8. Wireless module specifications

Description	Values	
Model number	Intel 9560	Intel 9462
Transfer rate	Up to 1730 Mbps	Up to 433 Mbps
Frequency bands supported	5 GHz	5 GHz
Wireless standards	<ul style="list-style-type: none"> WiFi 802.11a/b/g Wi-Fi 4 (WiFi 802.11n) Wi-Fi 5 (WiFi 802.11ac) 	<ul style="list-style-type: none"> WiFi 802.11a/b/g Wi-Fi 4 (WiFi 802.11n) Wi-Fi 5 (WiFi 802.11ac)
Encryption	<ul style="list-style-type: none"> 64-bit/128-bit WEP AES-CCMP TKIP 	<ul style="list-style-type: none"> 64-bit/128-bit WEP AES-CCMP TKIP
Bluetooth	Bluetooth 5	Bluetooth 5

Audio

Table 9. Audio specifications

Description	Values
Controller	Realtek ALC3204
Stereo conversion	Supported
Internal interface	Intel High Definition Audio
External interface	Headset combo connector
Speakers	Two
Internal speaker amplifier	Supported
External volume controls	Keyboard shortcut controls
Speaker output:	
Average	2 W

Description	Values
Peak	2.5 W
Subwoofer output	Not supported
Microphone	Dual-array microphones

Storage

Your computer supports one of the following configurations:

- One M.2 2230/2280 solid-state drive/Intel Optane
- One M.2 2230/2280 solid-state drive and one M.2 2230 solid-state drive

The primary drive of your computer varies with the storage configuration. For computers with a M.2 drive, the M.2 drive is the primary drive

Table 10. Storage specifications

Storage type	Interface type	Capacity
One M.2 2230/2280 solid-state drive	PCIe Gen3.0x4 NVMe, up to 32 Gbps	Up to 512 GB
One M.2 2230 solid-state drive	PCIe Gen3.0x2 NVMe, up to 16 Gbps	Up to 512 GB

Intel Optane Memory H10 with solid-state storage (optional)

Intel Optane technology utilizes 3D XPoint memory technology and functions as a non-volatile storage cache/accelerator and/or storage device depending on the Intel Optane memory installed in your computer.

Intel Optane Memory H10 with solid-state storage functions as both a non-volatile storage cache/accelerator (enabling enhanced read/write speeds for hard-drive storage) and a solid-state storage solution. It neither replaces nor adds to the memory (RAM) installed on your computer.

Table 11. Intel Optane Memory H10 with solid-state storage specifications

Description	Values
Interface	PCIe 3.0 x4 NVMe <ul style="list-style-type: none"> • One PCIe 3.0 x4 for Optane memory • One PCIe 3.0 x2 for solid-state storage
Connector	M.2
Form factor	2230/2280
Capacity (Optane memory)	Up to 32 GB
Capacity (solid-state storage)	Up to 512 GB

NOTE: Intel Optane Memory H10 with solid-state storage is supported on computers that meet the following requirements:

- **9th Generation or higher Intel Core i3/i5/i7 processors**
- **Windows 10 64-bit version or higher (Anniversary Update)**
- **Intel Rapid Storage Technology driver version 15.9.1.1018 or higher**

Media-card reader

Table 12. Media-card reader specifications

Description	Values
Type	One microSD card slot
Cards supported	<ul style="list-style-type: none">• Micro Secure Digital (mSD)• Micro Secure Digital High Capacity (mSDHC)• Micro Secure Digital Extended Capacity (mSDXC)

Keyboard

Table 13. Keyboard specifications

Description	Values
Type	<ul style="list-style-type: none">• Standard non-backlit keyboard• Backlit keyboard
Layout	QWERTY
Number of keys	<ul style="list-style-type: none">• United States and Canada: 81 keys• United Kingdom: 82 keys• Japan: 85 keys
Size	X=18.7 mm key pitch Y=18.05 mm key pitch
Shortcut keys	<p>Some keys on your keyboard have two symbols on them. These keys can be used to type alternate characters or to perform secondary functions. To type the alternate character, press Shift and the desired key. To perform secondary functions, press Fn and the desired key.</p> <p>NOTE: You can define the primary behavior of the function keys (F1–F12) changing Function Key Behavior in BIOS setup program.</p>

[Keyboard shortcuts](#)

Camera

Table 14. Camera specifications

Description	Values
Number of cameras	One
Type	HD RGB camera
Location	Front camera
Sensor type	CMOS sensor technology
Resolution:	
Still image	0.92 megapixel
Video	1280 x 720 (HD) at 30 fps

Description	Values
Diagonal viewing angle	74.9 degrees

Touchpad

Table 15. Touchpad specifications

Description	Values
Resolution:	
Horizontal	1920
Vertical	1080
Dimensions:	
Horizontal	105 mm (4.13 in.)
Vertical	65 mm (2.56 in.)

Touchpad gestures

For more information about touchpad gestures for Windows 10, see the Microsoft knowledge base article [4027871](https://support.microsoft.com/4027871) at support.microsoft.com.

Power adapter

Table 16. Power adapter specifications

Description	Values
Type	65 W
Diameter (connector)	4.5 mm x 2.9 mm
Input voltage	100 VAC–240 VAC
Input frequency	50 Hz–60 Hz
Input current (maximum)	1.60 A
Output current (continuous)	3.34 A
Rated output voltage	19.50 VDC
Temperature range:	
Operating	0°C to 40°C (32°F to 104°F)
Storage	-40°C to 70°C (-40°F to 158°F)

Battery

Table 17. Battery specifications

Description	Values
Type	4-cell "smart" lithium-ion

Description	Values
Voltage	7.60 VDC
Weight (maximum)	0.22 kg (0.49 lb)
Dimensions:	
Height	257.85 mm (10.15 in.)
Width	98.80 mm (3.89 in.)
Depth	4.30 mm (0.17 in.)
Temperature range:	
Operating	0°C to 35°C (32°F to 95°F)
Storage	-40°C to 65°C (-40°F to 149°F)
Operating time	Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.
Charging time (approximate)	3 hours (when the computer is off) <i>i</i> NOTE: Control the charging time, duration, start and end time, and so on using the Dell Power Manager application. For more information on the Dell Power Manager see, <i>Me and My Dell</i> on www.dell.com/
Life span (approximate)	300 discharge/charge cycles
Coin-cell battery	CR2032
Operating time	Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.

Display

Table 18. Display specifications

Description	Values
Type	13.3 FHD WLED
Panel technology	Wide Viewing Angle (WVA)
Luminance (typical)	300 nits
Dimensions (active area):	
Height	165.24 mm (6.51 in.)
Width	293.76 mm (11.57 in.)
Diagonal	337.04 mm (13.27 in.)
Native resolution	1920 x 1080
Megapixels	2.07
Pixels Per Inch (PPI)	166
Contrast ratio (min)	600
Response time (max)	35 ms

Description	Values
Refresh rate	60 Hz
Horizontal view angle	80
Vertical view angle	80
Pixel pitch	0.15 mm
Power consumption (maximum)	4.60 W
Anti-glare vs glossy finish	Glossy Finish
Touch options	No

Fingerprint reader (optional)

Table 19. Fingerprint reader specifications

Description	Values
Sensor technology	Capacitive
Sensor resolution	500 dpi
Sensor area	4.06mm x 3.25 mm
Sensor pixel size	80 x 64

Video

Table 20. Discrete graphics specifications

Discrete graphics			
Controller	External display support	Memory size	Memory type
NVIDIA N17S-G2 (MX250)	Not supported	2 GB	GDDR5

Table 21. Integrated graphics specifications

Integrated graphics			
Controller	External display support	Memory size	Processor
Intel UHD Graphics	One HDMI 1.4b port	Shared system memory	10th Generation Intel Core i3/i5/i7

Computer environment

Airborne contaminant level: G1 as defined by ISA-S71.04-1985

Table 22. Computer environment

Description	Operating	Storage
Temperature range	0°C to 35°C (32°F to 95°F)	-40°C to 65°C (-40°F to 149°F)
Relative humidity (maximum)	10% to 90% (non-condensing)	0% to 95% (non-condensing)
Vibration (maximum)*	0.66 GRMS	1.30 GRMS

Description	Operating	Storage
Shock (maximum)	110 G†	160 G†
Altitude (maximum)	-15.2 m to 3048 m (-49.87 ft to 10000 ft)	-15.2 m to 10668 m (-49.87 ft to 35000 ft)

* Measured using a random vibration spectrum that simulates user environment.

† Measured using a 2 ms half-sine pulse when the hard drive is in use.

Keyboard shortcuts

NOTE: Keyboard characters may differ depending on the keyboard language configuration. Keys used for shortcuts remain the same across all language configurations.





Some keys on your keyboard have two symbols on them. These keys can be used to type alternate characters or to perform secondary functions. The symbol shown on the lower part of the key refers to the character that is typed out when the key is pressed. If you press shift and the key, the symbol shown on the upper part of the key is typed out. For example, if you press **2**, 2 is typed out; if you press **Shift + 2**, @ is typed out.



The keys F1-F12 at the top row of the keyboard are function keys for multi-media control, as indicated by the icon at the bottom of the key. Press the function key to invoke the task represented by the icon. For example, pressing F1 mutes the audio (refer to the table below).

However, if the function keys F1-F12 are needed for specific software applications, multi-media functionality can be disabled by pressing **Fn + Esc**. Subsequently, multi-media control can be invoked by pressing **Fn** and the respective function key. For example, mute audio by pressing **Fn + F1**.

NOTE: You can also define the primary behavior of the function keys (F1–F12) by changing Function Key Behavior in BIOS setup program.



Table 23. List of keyboard shortcuts

Function key	Redefined key (for multimedia control)	Behavior
	 + 	Mute audio
	 + 	Decrease volume
	 + 	Increase volume
	 + 	Play/Pause
	 + 	Toggle keyboard backlight (optional) NOTE: Non-backlight keyboards have F10 function key without the backlight icon and does not support toggle keyboard backlight function.
	 + 	Decrease brightness
	 + 	Increase brightness

Function key	Redefined key (for multimedia control)	Behavior
	 + 	Switch to external display
	 + 	Print Screen
	 + 	Home
	 + 	End

The **Fn** key is also used with selected keys on the keyboard to invoke other secondary functions.

Table 24. List of keyboard shortcuts

Function key	Behavior
 + 	Pause/Break
 + 	Toggle scroll lock
 + 	System request
 + 	Toggle between power and battery-status light/hard-drive activity light
 + 	Open application menu
 + 	Toggle Fn-key lock

Getting help and contacting Dell

Self-help resources

You can get information and help on Dell products and services using these self-help resources:

Table 25. Self-help resources

Self-help resources	Resource location
Information about Dell products and services	www.dell.com
My Dell	
Tips	
Contact Support	In Windows search, type <code>Contact Support</code> , and press Enter.
Online help for operating system	www.dell.com/support/windows www.dell.com/support/linux
Troubleshooting information, user manuals, setup instructions, product specifications, technical help blogs, drivers, software updates, and so on.	www.dell.com/support
Dell knowledge base articles for a variety of computer concerns.	<ol style="list-style-type: none"> 1. Go to www.dell.com/support. 2. Type the subject or keyword in the Search box. 3. Click Search to retrieve the related articles.
Learn and know the following information about your product:	See <i>Me and My Dell</i> at www.dell.com/support/manuals .
<ul style="list-style-type: none"> • Product specifications • Operating system • Setting up and using your product • Data backup • Troubleshooting and diagnostics • Factory and system restore • BIOS information 	<p>To locate the <i>Me and My Dell</i> relevant to your product, identify your product through one of the following:</p> <ul style="list-style-type: none"> • Select Detect Product. • Locate your product through the drop-down menu under View Products. • Enter the Service Tag number or Product ID in the search bar.

Contacting Dell

To contact Dell for sales, technical support, or customer service issues, see www.dell.com/contactdell.

 **NOTE: Availability varies by country/region and product, and some services may not be available in your country/region.**

 **NOTE: If you do not have an active internet connection, you can find contact information on your purchase invoice, packing slip, bill, or Dell product catalog.**