
Quick Start

Thank you for purchasing the MSI® **MEG B550 UNIFY-X** motherboard. This Quick Start section provides demonstration diagrams about how to install your computer. Some of the installations also provide video demonstrations. Please link to the URL to watch it with the web browser on your phone or tablet. You may have even link to the URL by scanning the QR code.


Preparing Tools and Components



Safety Information


- The components included in this package are prone to damage from electrostatic discharge (ESD). Please adhere to the following instructions to ensure successful computer assembly.
- Ensure that all components are securely connected. Loose connections may cause the computer to not recognize a component or fail to start.
- Hold the motherboard by the edges to avoid touching sensitive components.
- It is recommended to wear an electrostatic discharge (ESD) wrist strap when handling the motherboard to prevent electrostatic damage. If an ESD wrist strap is not available, discharge yourself of static electricity by touching another metal object before handling the motherboard.
- Store the motherboard in an electrostatic shielding container or on an anti-static pad whenever the motherboard is not installed.
- Before turning on the computer, ensure that there are no loose screws or metal components on the motherboard or anywhere within the computer case.
- Do not boot the computer before installation is completed. This could cause permanent damage to the components as well as injury to the user.
- If you need help during any installation step, please consult a certified computer technician.
- Always turn off the power supply and unplug the power cord from the power outlet before installing or removing any computer component.
- Keep this user guide for future reference.
- Keep this motherboard away from humidity.
- Make sure that your electrical outlet provides the same voltage as is indicated on the PSU, before connecting the PSU to the electrical outlet.
- Place the power cord such a way that people can not step on it. Do not place anything over the power cord.
- All cautions and warnings on the motherboard should be noted.
- If any of the following situations arises, get the motherboard checked by service personnel:
 - Liquid has penetrated into the computer.
 - The motherboard has been exposed to moisture.
 - The motherboard does not work well or you can not get it work according to user quide.
 - The motherboard has been dropped and damaged.
 - The motherboard has obvious sign of breakage.
- Do not leave this motherboard in an environment above 60°C (140°F), it may damage the motherboard.

Installing a Processor





If you are installing the screw-type CPU heatsink, please follow the figure below to remove the retention module first and then install the heatsink.




Installing DDR4 memory






http://youtu.be/T03aDrJPyQs




Connecting the Front Panel Header








Installing the Motherboard







https://youtu.be/wWI6Qt51Wnc




Connecting the Power Connectors







Installing a Graphics Card



Connecting Peripheral Devices



Power On



Contents

Quick Start	1
Preparing Tools and Components	1
Safety Information	2
Installing a Processor	3
Installing DDR4 memory	5
Connecting the Front Panel Header	6
Installing the Motherboard	7
Connecting the Power Connectors	8
Installing SATA Drives	9
Installing a Graphics Card	10
Connecting Peripheral Devices	11
Power On	12
Specifications	15
Package contents	22
Block Diagram	23
Rear I/O Panel	24
LAN Port LED Status Table	24
Audio Ports Configuration	24
Realtek Audio Console	25
Installing Antennas	27
Overview of Components	28
Processor Socket	30
DIMM Slots	31
PCI_E1~4: PCIe Expansion Slots	32
M2_1~4: M.2 Slots (Key M)	36
SATA1~6: SATA 6Gb/s Connectors	38
JFP1, JFP2: Front Panel Connectors	39
JAUD1: Front Audio Connector	39
CPU_PWR1~2, ATX_PWR1, PCIE_PWR1: Power Connectors	40
JUSB3~4: USB 2.0 Connectors	41
JUSB1: USB 3.2 Gen 2 10Gbps Type-C Connector	41
JUSB2: USB 3.2 Gen 1 5Gbps Connector	
JTPM1: TPM Module Connector	42
CPU_FAN1, PUMP_FAN1, SYS_FAN1~6: Fan Connectors	43
JCI1: Chassis Intrusion Connector	44
JBAT1: Clear CMOS (Reset BIOS) Jumper	45

	POWER1, RESET1: Power Button, Reset Button	. 45
	JRGB1: RGB LED connector	46
	JRAINBOW1~2: Addressable RGB LED connectors	47
	JCORSAIR1: CORSAIR Connector	. 48
Onbo	pard LEDs	49
	EZ Debug LED	
	LED_SW1: EZ LED Control	49
	Debug Code LED	49
	Hexadecimal Character Table	. 50
	Boot Phases	. 50
	Debug Code LED Table	. 50
	ACPI States Codes	. 54
Insta	alling OS, Drivers & Utilities	55
	Installing Windows® 10	
	Installing Drivers	
	Installing Utilities	. 55
UEFI	I BIOS	
	BIOS Setup	
	Entering BIOS Setup	
	Resetting BIOS	
	Updating BIOS	
	EZ Mode	. 60
	Advanced Mode	. 63
	SETTINGS Menu	64
	OC Menu	. 66
	M-FLASH Menu	. 69
	OC PROFILE Menu	. 70
	HARDWARE MONITOR Menu	. 71
AMD	RAID Configuration	73
	Enabling RAIDXpert2 Configuration Utility	
	Initializing Disks	. 74
	Creating Arrays	. 75
	Deleting Arrays	. 76
	Installing RAID Driver	. 77
Trou	ıbleshooting	78

Specifications

CPU	Supports AMD Ryzen [™] 5000 & 3000 Series desktop processors (not compatible with AMD Ryzen [™] 5 3400G & Ryzen [™] 3 3200G) and AMD Ryzen [™] 4000 G-Series desktop		
	processors for AM4 socket		
Chipset	AMD B550 Chipset		
	• 2x DDR4 memory slots, support up to 64GB*		
	 Supports DDR4 1866/ 2133/ 2400/ 2667/ 2800/ 2933/ 3000/ 3066/ 3200 MHz by JEDEC 		
	 AMD Ryzen™ 4000 G-Series processors support DDR4 2667/ 2800/ 2933/ 3000/ 3066/ 3200/ 3466/ 3600/ 3733/ 3866/ 4000/ 4133/ 4266/ 4400/ 4533/ 4600/ 4733/ 4800/ 5000/ 5100/ 5300+ [Max. 5800] MHz by A-XMP OC MODE 		
	 AMD Ryzen™ 5000 & 3000 Series processors (not compatible with Ryzen™ 5 3400G & Ryzen™ 3 3200G) support DDR4 2667/ 2800/ 2933/ 3000/ 3066/ 3200/ 3466/ 3600/ 3733/ 3866/ 4000/ 4133/ 4266/ 4400/ 4533/ 4600/ 4733/ 4800/ 4866/ 5000/ 5100+ MHz by A-XMP OC MODE 		
	 AMD Ryzen[™] 4000 G-Series processors 		
Memory	 1DPC 1R max speed 5300 MHz (QVL), Max. 5800 MHz 		
	□ 1DPC 2R max speed 4266 MHz, Max. 4600 MHz		
	■ AMD Ryzen [™] 5000 & 3000 Series processors (not compatible with AMD Ryzen [™] 5 3400G & Ryzen [™] 3 3200G)		
	 1DPC 1R max speed 5100 MHz (QVL), Max. 5300 MHz 		
	 1DPC 2R max speed 4266 MHz (QVL) 		
	Dual channel memory architecture		
	Supports non-ECC UDIMM memory		
	Supports ECC UDIMM memory (non-ECC mode)		
	Supports un-buffered memory		
	* Please refer www.msi.com for more information on compatible memory.		
	• 1 x HDMI 2.1 port, supporting a maximum resolution of 4096x2160 @120 Hz*/**		
Onboard Graphics	Maximum shared memory of 16GB		
	* Available for the processor with integrated graphics. ** Graphics specifications may vary depending on the CPU installed.		
Multi-GPU	• Supports 2-Way AMD CrossFire ™ Technology		

	• 6x SATA 6Gb/s ports*/** (from Chipset)
	• 4x M.2 slots (Key M)
	M2_1 slot (from CPU)
	 Supports PCIe 4.0/ 3.0 x4***
	 Supports SATA 6Gb/s
	 Supports 2280/ 22110 storage devices
	■ M2_2 slot
	 Chipset support mode (default, from Chipset) - supports PCIe 3.0 x2
	• CPU support mode (From CPU) - supports PCIe 4.0/ 3.0 x4 ***/ ****
	 Supports 2280 storage devices
Storage	■ M2_3 slot
Storage	 Chipset support mode (default, from Chipset) - supports PCIe 3.0 x2**
	$^{\circ}$ CPU support mode (From CPU) - supports PCIe 4.0/ 3.0 x4**/****
	 Supports SATA 6Gb/s*
	 Supports 2280/ 22110 storage devices
	M2_4 slot (from Chipset)
	 Supports PCIe 3.0 x4
	 Supports 2280 storage devices
	* The SATA5 port will be unavailable when installing M.2 SATA SSD into M2_3. ** The SATA5 and SATA6 ports will be unavailable when installing M.2 PCIe SSD into M2_3.
	*** M.2 specifications may vary depending on the CPU installed. **** Please refer to PCIe bandwidth configuration table for PCIe & M.2 slots (page 33) for details.
	• Supports RAID 0, RAID 1 and RAID 10 for SATA storage devices
RAID	• Supports RAID 0, RAID 1 and RAID 10 for M.2 NVMe storage devices

	AMD Processor		
	• 1x PCIe 4.0/ 3.0 x16 slot (PCI_E1)*		
F	Supports x16 or x8 mode**		
	AMD B550 Chipset		
	• 1x PCIe 3.0 x16 slot , support x4 mode (PCI_E4)***		
Expansion Slot	• 2x PCIe 3.0 x1 slots (PCI_E2 & PCI_E3)****		
	* PCIe specifications may vary depending on the CPU installed.		
	** Please refer to PCIe bandwidth configuration table for PCIe & M.2 slots (page 33) for details.		
	*** The PCI_E4 slot will be unavailable, when installing M.2 SSD into M2_4.		
	**** The both PCIe x1 slots will be unavailable after you install the M.2 SSD into M2_2 slot in Chipset support mode (default mode).		
	AMD Processor		
	 4x USB 3.2 Gen 2 10Gbps ports(3 Type-A ports and 1 Type-C port) on the back panel 		
	AMD B550 chipset		
	1x USB 3.2 Gen 2 10Gbps Type-C internal connector		
USB	 2x USB 3.2 Gen 1 5Gbps ports are available through the internal USB 3.2 Gen 1 5Gbps connector 		
	 4x USB 2.0 ports on the back panel 		
	AMD B550 chipset + USB 2.0 Hubs		
	 4x USB 2.0 ports are available through the internal USB 2.0 connectors 		
LAN	1x Realtek® RTL8125B 2.5Gbps LAN controller		
	Intel® Wi-Fi 6 AX200		
	• The Wireless module is pre-installed in the M2_WIFI1 (Key-E) slot		
Wireless LAN & Bluetooth®	• Supports MU-MIMO TX/RX, 2.4GHz/ 5GHz (160MHz) up to 2.4Gbps		
	• Supports 802.11 a/ b/ g/ n/ ac/ ax		
	• Supports Bluetooth® 5.1		
	Realtek® ALC1220P Codec		
Audio	7.1-Channel High Definition Audio		
	 Supports Optical S/PDIF output 		

	• 1x 24-pin ATX main power connector
	• 2x 8-pin ATX 12V power connector
	• 1x 6-pin PCIE power connector
	• 6x SATA 6Gb/s connectors
	• 4x M.2 slots (M-Key)
	• 1x USB 3.2 Gen 2 10Gbps Type-C port
	• 1x USB 3.2 Gen 1 5Gbps connector (supports additional 2 USB 3.2 Gen 1 5Gbps ports)
	• 2x USB 2.0 connectors (supports additional 4 USB 2.0 ports)
	• 1x 4-pin CPU fan connector
Internal Connectors	• 1x 4-pin water-pump fan connector
internat connectors	• 6x 4-pin system fan connectors
	1x Front panel audio connector
	• 2x System panel connectors
	• 1x Chassis Intrusion connector
	• 1x 4-pin RGB LED connectors
	• 2x 3-pin RAINBOW LED connectors
	• 1x 3-pin CORSAIR LED connector
	• 1x TPM module connector
	• 1x Clear CMOS jumper
	• 1x Power button
	• 1x Reset button

	• 1x Clear CMOS Button		
	• 1x Flash BIOS Button		
	• 1x PS/2 keyboard/ mouse combo port		
	• 4x USB 2.0 Type-A ports		
	• 1x HDMI port		
Back Panel	• 2x USB 3.2 Gen 2 10Gbps Type-A ports		
Connectors	• 1x 2.5 Gbps LAN (RJ45) port		
	• 1x USB 3.2 Gen 2 10Gbps Type-A port		
	• 1x USB 3.2 Gen 2 10Gbps Type-C port		
	• 2x Wi-Fi Antenna connectors		
	• 5x audio jacks		
	• 1x Optical S/PDIF Out connector		
	1x EZ LED Control switch		
LED Features	• 1x 2-Digit Debug Code LED		
	• 4x EZ Debug LED		
I/O Controller	NUVOTON NCT6687D-R Controller Chip		
	CPU/ System/ Chipset temperature detection		
Hardware Monitor	CPU/ System/ Pump fan speed detection		
	CPU/ System/ Pump fan speed control		
	ATX Form Factor		
Form Factor	• 12 in. x 9.6 in. (30.4 cm x 24.4 cm)		
	• 1x 256 Mb flash		
	• UEFI AMI BIOS		
BIOS Features	• ACPI 6.1 , SMBIOS 2.8		
	Multi-language		

Software	 Drivers DRAGON CENTER MSI APP Player (BlueStacks) CPU-Z MSI GAMING Nahimic Audio Google Chrome ™, Google Toolbar, Google Drive Norton ™ Internet Security Solution 		
Dragon Center Features	 Gaming Mode Gaming Hotkey LAN Manager Mystic Light Ambient Link User Scenario Hardware Monitor True Color Duet Display Live Update Speed Up Smart Tool Super Charger Voice Boost 	Please refer to http://download.msi.com/manual/mb/DRAGONCENTER2.pdf for more details.	
Special Features	 Audio Audio Boost4 Nahimic 3 Voice Boost Network 2.5G LAN LAN Manaer Intel WiFi 6 		

- Cooling
 - All Aluminum Design
 - Extended Heatsink Design
 - Mosfet Baseplate
 - 4x M.2 Shield Frozr
 - Pump Fan
 - Smart Fan Control
- LED
 - Mystic Light Extension (RGB/RAINBOW/CORSAIR)
 - Mystic light SYNC
 - Ambient Link
 - EZ LED Control
 - EZ DEBUG LED
- Performance
 - Lightning Gen 4 PCI-E Slot
 - Lightning Gen 4 M.2
 - Multi GPU-CrossFire Technology
 - DDR4 Boost
 - GAME Boost
 - Core Boost
 - USB with Type A+C
 - USB 3.2 Gen 2 10G
 - Front USB Type-C
 - Dual CPU Power (8+8 pin)
- Protection
 - PCI-F Steel Armor
 - Pre-installed I/O Shield
- Experience
 - Dragon Center
 - Click BIOS 5
 - Flash BIOS Button

Special Features

JCORSAIR1 Connector Specification

Supporting CORSAIR RGB Products	Maximum connection
	20*
Lighting Node PRO LED Strip	* 20% brightness is recommended when the number of
	LED strips exceeds 8.
HD120 RGB Fan	6
SP120 RGB Fan	6
LL120 RGB Fan	6

Package contents


Please check the contents of your motherboard package. It should contain:

Motherboard	MEG B550 UNIFY-X	
	SATA 6G cables (2 cables/pack)	
	LED JRAINBOW cable	
Cable	LED JRGB Y cable	
	LED JCORSAIR cable	1
	Wi-Fi Antenna	1
	M.2 screws (3 pcs./pack)	
Accessories	DIY Stands Set	
	Case Badge	
	Product registration card	1
Application Driver DVD		1
	User manual	1
	Quick installation guide	1
Documentation	DIY Stands Set Quick Guide	1
	MSI components compatibility & reward program card	1




If any of the above items are damaged or missing, please contact your retailer.

Block Diagram




Rear I/O Panel




- Flash BIOS Port/ Button Please refer to page 59 for Updating BIOS with Flash BIOS Button.
- Clear CMOS Button Power off your computer. Press and hold the Clear CMOS button for about 5-10 seconds to reset BIOS to default values.

LAN Port LED Status Table




Audio Ports Configuration



Realtek Audio Console


After Realtek Audio Console is installed. You can use it to change sound settings to get better sound experience.



- Connector Settings Jack Status
- Device Selection allows you to select a audio output source to change the related options. The **check** sign indicates the devices as default.
- Application Enhancement the array of options will provide you a complete guidance of anticipated sound effect for both output and input device.
- Main Volume controls the volume or balance the right/left side of the speakers that you plugged in front or rear panel by adjust the bar.
- Jack Status depicts all render and capture devices currently connected with your computer.
- Connector Settings configures the connection settings.

Auto popup dialog

When you plug into a device at an audio jack, a dialogue window will pop up asking you which device is current connected.




Each jack corresponds to its default setting as shown on the next page.




Important

The pictures above for reference only and may vary from the product you purchased.


Audio jacks to headphone and microphone diagram



Audio jacks to stereo speakers diagram




Audio jacks to 7.1-channel speakers diagram




Installing Antennas


- 1. Combine the antenna with the base.
- 2. Screw two antenna cables tight to the WiFi antenna connectors as shown.



3. Place the antenna as high as possible.




Overview of Components



Component Contents


Port Name	Port Type	
CPU_FAN1, PUMP_FAN1, SYS_FAN1~6	Fan Connectors	43
CPU_PWR1~2, ATX_PWR1, PCIE_PWR1	Power Connectors	40
DIMMA1/B1	DIMM Slots	31
JAUD1	Front Audio Connector	39
JBAT1	Clear CMOS Jumper	45
JCI1	Chassis Intrusion Connector	44
JCORSAIR1	CORSAIR Connector	48
JFP1, JFP2	Front Panel Connectors	39
JRAINBOW1~2	Addressable RGB LED connectors	
JRGB1	RGB LED connector	
JTPM1	TPM Module Connector	
JUSB1	USB 3.2 Gen 2 10Gbps Type-C Connector	
JUSB2	USB 3.2 Gen 1 5Gbps Connector	42
JUSB3~4	USB 2.0 Connectors	41
LED_SW1	EZ LED Control	49
M2_1~4	M.2 Slots (Key M)	36
PCI_E1~4	PCIe Expansion Slots	
POWER1, RESET1	Power Button, Reset Button	
Processor Socket	Socket AM4	30
SATA1~6	SATA 6Gb/s Connectors	38

Processor Socket



Introduction to the AM4 CPU


The surface of the AM4 CPU has a yellow triangle to assist in correctly lining up the CPU for motherboard placement. The yellow triangle is the Pin 1 indicator.




Important

- When changing the processor, the system configuration could be cleared and reset BIOS to default values, due to the AM4 processor's architecture.
- Always unplug the power cord from the power outlet before installing or removing the CPU.
- When installing a CPU, always remember to install a CPU heatsink. A CPU heatsink is necessary to prevent overheating and maintain system stability.
- Confirm that the CPU heatsink has formed a tight seal with the CPU before booting your system.
- Overheating can seriously damage the CPU and motherboard. Always make sure the cooling fans work properly to protect the CPU from overheating. Be sure to apply an even layer of thermal paste (or thermal tape) between the CPU and the heatsink to enhance heat dissipation.
- If you purchased a separate CPU and heatsink/ cooler, Please refer to the documentation in the heatsink/ cooler package for more details about installation.
- This motherboard is designed to support overclocking. Before attempting to overclock, please make sure that all other system components can tolerate overclocking. Any attempt to operate beyond product specifications is not recommended. MSI® does not quarantee the damages or risks caused by inadequate operation beyond product specifications.

DIMM Slots








- Always insert memory modules in the DIMMA1 slot first.
- Due to chipset resource usage, the available capacity of memory will be a little less than the amount of installed.
- Based on CPU specification, the Memory DIMM voltage below 1.35V is suggested to protect the CPU.
- To ensure system stability for Dual channel mode, memory modules must be of the same type, number and density.
- Some memory modules may operate at a lower frequency than the marked value when overclocking due to the memory frequency operates dependent on its Serial Presence Detect (SPD). Go to BIOS and find the **DRAM Frequency** to set the memory frequency if you want to operate the memory at the marked or at a higher frequency.
- It is recommended to use a more efficient memory cooling system for full DIMMs installation or overclocking.
- The stability and compatibility of installed memory module depend on installed CPU and devices when overclocking.
- Please refer www.msi.com for more information on compatible memory.

PCI E1~4: PCIe Expansion Slots





Important

- If you install a large and heavy graphics card, you need to use a tool such as MSI Gaming Series Graphics Card Bolster to support its weight to prevent deformation of the slot.
- When adding or removing expansion cards, always turn off the power supply and unplug the power supply power cable from the power outlet. Read the expansion card's documentation to check for any necessary additional hardware or software changes.
- The PCI E4 slot will be unavailable, when installing M.2 SSD into M2 4.
- The both PCIe x1 slots will be unavailable after you install the M.2 SSD into M2 2 slot in Chipset support mode (default mode).
- Please refer to the following PCIe bandwidth configuration table for PCIe & M.2 slots for details.

PCIe bandwidth configuration table for PCIe & M.2 slots

The M2 2 and M2 3 slots can be used under two PCIe bandwidth modes: Chipset mode (default) and CPU mode (by BIOS selection). In these two modes, they provide different PCIe bandwidth for M2_2 and M2_3 slots, please refer the table below for details

Slot	Chipset Mode CPU Mode		Mode		
PCI_E1	@ 4.0/ 3.0 x16*		@ 4.0/ 3.0 x8*		
PCI_E2	_	3.0 x1	3.0 x1		
PCI_E3	_	3.0 x1	3.0 x1		
PCI_E4	_	@ 3.0 x4	_	@ 3.0 x4	
M2_1	4.0/ 3.0 x4*		4.0/ 3.0 x4*		
M2_2	3.0 x2	Empty	4.0/ 3.0 x4*		
M2_3	3.0	3.0 x2**		4.0/ 3.0 x4*/**	
M2_4	3.0 x4	Empty	3.0 x4	Empty	

(—: unavailable, @: graphics card)

^{**} The SATA5 and SATA6 ports will be unavailable when installing M.2 PCIe SSD into M2 3. The SATA5 port will be unavailable when installing M.2 SATA SSD into M2 3.




Important

- Enabling CPU mode, please go to BIOS > SETTINGS > Advanced > PCI sub-system Settings > PCI_E1 Lanes Configuration and configure the PCIe Lanes to x8/x4/x4 for PCI E1, M2 2 and M2 3 slots first. In **CPU mode**, the PCI E1, M2 2 and M2 3 slots share the same PCIe bandwidth.
- In CPU mode with AMD Ryzen™ 5000 & 3000 series processors (not compatible with AMD RyzenTM 5 3400G & RyzenTM 3 3200G), if you install the MSI M.2 Xpander series add-in card into PCI E1 slot, only two M.2 slots of the add-in card are available.
- In **CPU mode** with **AMD Ryzen™ 4000-G** series processors, if you install the MSI M.2 Xpander series add-in card into PCI E1 slot, only one M.2 slot of the add-in card is available.


^{*} PCIe/ M.2 specifications may vary depending on the CPU installed.

M.2 slots with examples of various combination possibilities


1xM.2 PCIe SSD + 6xSATA HDDs



2xM.2 PCIe SSDs + 6xSATA HDDs




3xM.2 PCIe SSDs + 4xSATA HDDs




For CPU mode these two PCIe x1 slots are available.


1xM.2 SATA SSD + 6xSATA HDDs



1xM.2 SATA SSD + 1xM.2 PCIe SSD + 6xSATA HDDs



1xM.2 SATA SSD + 2xM.2 PCIe SSD + 6xSATA HDDs




PCIe x1 slots are un-available. (Default)

For CPU mode these two PCIe x1 slots are available.


(Default)

4xM.2 PCIe SSDs + 4xSATA HDDs



For CPU mode these two PCIe x1 slots are available.


2xM.2 SATA SSD + 2xM.2 PCIe SSD + 5xSATA HDDs



For Chipset mode these two PCIe x1 slots are un-available. (Default)

For CPU mode these two PCIe x1 slots are available.

M2 1~4: M.2 Slots (Key M)








Watch the video to learn how to Install M.2 module.

http://youtu.be/JCTFABytrYA

Installing M.2 module


- 1. Loosen the screws of M.2 SHIELD FROZR heatsink.
- Remove the M.2 SHIELD FROZR and remove the protective films from the thermal pads.




- 3. M2_1 and M2_3 slots are equipped with one standoff. To avoid damage to the M.2 SSD. If you want to install 22110 M.2 SSD, please remove the standoff.
- 4. There are two thermal pads on each M.2 slot base plate. The thermal pad-2 is fixed on the M.2 Plate and should not be removed. For double-side M.2 SSD, completely remove the thermal pad-1 and protection
 - For single-side M.2 SSD, remove the protection film from pad-1.

Important


- Pictures shown in this section are for illustration purpose only and may differ from the actual plates and thermal pads.
- If your M.2 SSD equips its own heathink, please remove the thermal pad-1 and thermal pad-2, and install the M.2 SSD into the M.2 slot.



- 5. Insert your M.2 SSD into the M.2 slot at a 30-degree angle.
- 6. If the M.2 SSD is shorter than the M.2 SHIELD FROZR heatsink, place the M.2 screw in the notch on the trailing edge of the M.2 module and tighten it into the standoff.



7. Put the M.2 SHIELD FROZR heatsink back in place and secure it.






If your M.2 SSD equips its own heatsink, please do not re-install the M.2 SHIELD FROZR heatsink.

SATA1~6: SATA 6Gb/s Connectors

These connectors are SATA 6Gb/s interface ports. Each connector can connect to one SATA device.








- Please do not fold the SATA cable at a 90-degree angle. Data loss may result during transmission otherwise.
- SATA cables have identical plugs on either sides of the cable. However, it is recommended that the flat connector be connected to the motherboard for space saving purposes.
- The SATA5 port will be unavailable, when installing M.2 SATA SSD into M2_3.
- The SATA5 and SATA6 ports will be unavailable when installing M.2 **PCIe** SSD into M2 3.

JFP1, JFP2: Front Panel Connectors

These connectors connect to the switches and LEDs on the front panel.








JAUD1: Front Audio Connector


This connector allows you to connect audio jacks on the front panel.



	2	:	10
1	MIC L	2	Ground
3	MIC R	4	NC
5	Head Phone R	6	MIC Detection
7	SENSE_SEND	8	No Pin
9	Head Phone L	10	Head Phone Detection

CPU_PWR1~2, ATX_PWR1, PCIE_PWR1: Power Connectors

These connectors allow you to connect an ATX power supply.



	8 DDD 5 CPU_PWR1-2								
1	Ground	5	+12V						
2	Ground	6	+12V						
3	Ground	7	+12V						
4	Ground	8	+12V						

		1	+3.3V	13	+3.3V		
		2	+3.3V	14	-12V		
		3	Ground	15	Ground		
12 🔲 24		4	+5V	16	PS-0N#		
		5	Ground	17	Ground		
	ATX_PWR1	6	+5V	18	Ground		
	AIX_I WICI	7	Ground	19	Ground		
	1 00 13	8	PWR 0K	20	Res		
1 66 13			9	5VSB	21	+5V	
						10	+12V
		11	+12V	23	+5V		
		12	+3.3V	24	Ground		

1 3	1	+12V	4	Ground		
	2	+12V	5	Ground		
4 6	3	+12V	6	Ground		




Important

Make sure that all the power cables are securely connected to a proper ATX power supply to ensure stable operation of the motherboard.

JUSB3~4: USB 2.0 Connectors

These connectors allow you to connect USB 2.0 ports on the front panel.



	2	::	9
1	VCC	2	VCC
3	USB0-	4	USB1-
5	USB0+	6	USB1+
7	Ground	8	Ground
9	No Pin	10	NC





\ Important

- Note that the VCC and Ground pins must be connected correctly to avoid possible
- In order to recharge your iPad,iPhone and iPod through USB ports, please install MSI® DRAGON CENTER utility.

JUSB1: USB 3.2 Gen 2 10Gbps Type-C Connector


This connector allows you to connect USB 3.2 Gen 2 10Gbps Type-C connector on the front panel. The connector possesses a foolproof design. When you connect the cable, be sure to connect it with the corresponding orientation.





JUSB2: USB 3.2 Gen 1 5Gbps Connector

This connector allows you to connect USB 3.2 Gen 1 5Gbps ports on the front panel.



	20		10
1	Power	11	USB2.0+
2	USB3_RX_DN	12	USB2.0-
3	USB3_RX_DP	13	Ground
4	Ground	14	USB3_TX_C_DP
5	USB3_TX_C_DN	15	USB3_TX_C_DN
6	USB3_TX_C_DP	16	Ground
7	Ground	17	USB3_RX_DP
8	USB2.0-	18	USB3_RX_DN
9	USB2.0+	19	Power
10	Ground	20	No Pin




Important

Note that the Power and Ground pins must be connected correctly to avoid possible damage.

JTPM1: TPM Module Connector


This connector is for TPM (Trusted Platform Module). Please refer to the TPM security platform manual for more details and usages.



12 • • 11							
1	SPI Power	2	SPI Chip Select				
3	Master In Slave Out (SPI Data)	4	Master In Slave In (SPI Data)				
5	Reserved	6	SPI Clock				
7	Ground	8	SPI Reset				
9	Reserved	10	No Pin				
11	Reserved	12	Interrupt Request				

CPU FAN1, PUMP FAN1, SYS FAN1~6: Fan Connectors

Fan connectors can be classified as PWM (Pulse Width Modulation) Mode or DC Mode. PWM Mode fan connectors provide constant 12V output and adjust fan speed with speed control signal. DC Mode fan connectors control fan speed by changing voltage. The auto mode fan connectors can automatically detect PWM and DC mode. However, you can follow the instruction below to adjust the fan connector to PWM or DC Mode manually.



Switching fan mode and adjusting fan speed

You can switch between PWM mode and DC mode and adjust fan speed in BIOS > HARDWARE MONITOR.

Select PWM mode or DC mode



There are gradient points of the fan speed that allow you to adjust fan speed in relation to CPU temperature.



Make sure fans are working properly after switching the PWM/ DC mode.


Pin definition of fan connectors

	1	PWN	4 Mode pin definition
1	Ground	2	+12V
3	Sense	4	Speed Control Signal

	DC Mode pin definition									
1	Ground	2	Voltage Control							
3	Sense	4	NC							

JCI1: Chassis Intrusion Connector

This connector allows you to connect the chassis intrusion switch cable.



Using chassis intrusion detector


- 1. Connect the JCI1 connector to the chassis intrusion switch/ sensor on the chassis.
- 2. Close the chassis cover.
- 3. Go to BIOS > SETTINGS > Security > Chassis Intrusion Configuration.
- 4. Set Chassis Intrusion to Enabled
- 5. Press F10 to save and exit and then press the Enter key to select Yes.
- 6. Once the chassis cover is opened again, a warning message will be displayed on screen when the computer is turned on.

Resetting the chassis intrusion warning

- 1. Go to BIOS > SETTINGS > Security > Chassis Intrusion Configuration.
- 2. Set Chassis Intrusion to Reset.
- 3. Press F10 to save and exit and then press the Enter key to select Yes.

JBAT1: Clear CMOS (Reset BIOS) Jumper

There is CMOS memory onboard that is external powered from a battery located on the motherboard to save system configuration data. If you want to clear the system configuration, set the jumpers to clear the CMOS memory.




Resetting BIOS to default values

- 1. Power off the computer and unplug the power cord.
- 2. Use a jumper cap to short **JBAT1** for about 5-10 seconds.
- 3. Remove the jumper cap from JBAT1.
- 4. Plug the power cord and Power on the computer.


POWER1, RESET1: Power Button, Reset Button


The Power / Reset button allows you to power on / reset the computer.




JRGB1: RGB LED connector

The JRGB connector allows you to connect the 5050 RGB LED strips 12V.






RGB LED Strip Connection



RGB LED Fan Connection







- The JRGB connector supports up to 2 meters continuous 5050 RGB LED strips (12V/G/R/B) with the maximum power rating of 3A (12V).
- Always turn off the power supply and unplug the power cord from the power outlet before installing or removing the RGB LED strip.
- Please use MSI's software to control the extended LED strip.


JRAINBOW1~2: Addressable RGB LED connectors

The JRAINBOW connectors allow you to connect the WS2812B Individually Addressable RGB LED strips 5V.






Addressable RGB LED Strip Connection



Addressable RGB LED Fan Connection







- The JRAINBOW connector supports up to 75 LEDs WS2812B Individually Addressable RGB LED strips (5V/Data/Ground) with the maximum power rating of 3A (5V). In the case of 20% brightness, the connector supports up to 200 LEDs.
- Always turn off the power supply and unplug the power cord from the power outlet before installing or removing the RGB LED strip.
- Please use MSI's software to control the extended LED strip.

JCORSAIR1: CORSAIR Connector

The JCORSAIR1 connector allows you to connect the CORSAIR Individually Addressable Lighting PRO RGB LED strips 5V or CORSAIR RGB fans with the CORSAIR fan hub. Once all items are connected properly, you can control the CORSAIR RGB LED strips and fans with MSI's software.



CORSAIR Lighting Node PRO Connection




- Fans must start at 1 and continue in series. 1 > 2 > 3 > 4 > 5 > 6. Any fan not connected in series will break communication and the RGB LED lighting function will not work.
- Quantity of RGB LED Fans or RGB LED Lighting PRO strips supported may differ between models. Please refer to the motherboard specification.
- CORSAIR RGB LED Fan and CORSAIR Lighting Node PRO can't be used at the same time.

Onboard LEDs

EZ Debug LED


These LEDs indicate the debug status of the motherboard.




- **CPU** indicates CPU is not detected or fail.
- DRAM indicates DRAM is not detected or fail.
- □ VGA indicates GPU/ PCIE/ M.2 device is not detected
- **BOOT** indicates the booting device is not detected

LED SW1: EZ LED Control


This switch is used to switch on/ off all the LEDs of motherboard.





Debug Code LED

The Debug Code LED displays progress and error codes during and after POST. Refer to the Debug Code LED table for details.



Hexadecimal Character Table

Hexadecimal	0	1	2	3	4	5	6	7	8	9	А	В	С	D	Е	F
Debug Code LED display		1	8	3	7	5	6	7	8	9	A	Ь		덢	E	F

Boot Phases

Security (SEC) - initial low-level initialization

Pre-EFI Initialization (PEI) - memory initialization

Driver Execution Environment (DXE) - main hardware initialization

Boot Device Selection (BDS) - system setup, pre-OS user interface & selecting a bootable device (CD/DVD, HDD, USB, Network, Shell, ...)

Debug Code LED Table

SEC Progress Codes

01	Power on. Reset type detection (soft/hard)				
02	AP initialization before microcode loading				
03	System Agent initialization before microcode loading				
04	PCH initialization before microcode loading				
06	Microcode loading				
07	AP initialization after microcode loading				
08	System Agent initialization after microcode loading				
09	PCH initialization after microcode loading				
0B	Cache initialization				

SEC Error Codes

0C - 0D	Reserved for future AMI SEC error codes
0E	Microcode not found
0F	Microcode not loaded

PEI Progress Codes

10	PEI Core is started
11	Pre-memory CPU initialization is started
12 - 14	Pre-memory CPU initialization (CPU module specific)
15	Pre-memory System Agent initialization is started
16 - 18	Pre-Memory System Agent initialization (System Agent module specific)
19	Pre-memory PCH initialization is started
1A - 1C	Pre-memory PCH initialization (PCH module specific)
2B	Memory initialization. Serial Presence Detect (SPD) data reading
2C	Memory initialization. Memory presence detection
2D	Memory initialization. Programming memory timing information

2E	Memory initialization. Configuring memory
2F	Memory initialization (other)
31	Memory Installed
32	CPU post-memory initialization is started
33	CPU post-memory initialization. Cache initialization
34	CPU post-memory initialization. Application Processor(s) (AP) initialization
35	CPU post-memory initialization. Boot Strap Processor (BSP) selection
36	CPU post-memory initialization. System Management Mode (SMM) initialization
37	Post-Memory System Agent initialization is started
38 - 3A	Post-Memory System Agent initialization (System Agent module specific)
3B	Post-Memory PCH initialization is started
3C - 3E	Post-Memory PCH initialization (PCH module specific)
4F	DXE IPL is started

PEI Error Codes

4B	Memory not installed (For Summit CPU)
E0	Memory not installed (For Bristol CPU)

DXE Progress Codes

60	DXE Core is started
61	NVRAM initialization
62	Installation of the PCH Runtime Services
63	CPU DXE initialization is started
64 - 67	CPU DXE initialization (CPU module specific)
68	PCI host bridge initialization
69	System Agent DXE initialization is started
6A	System Agent DXE SMM initialization is started
6B - 6F	System Agent DXE initialization (System Agent module specific)
70	PCH DXE initialization is started
71	PCH DXE SMM initialization is started
72	PCH devices initialization
73 - 77	PCH DXE Initialization (PCH module specific)
78	ACPI module initialization
79	CSM initialization
7A - 7F	Reserved for future AMI DXE codes
90	Boot Device Selection (BDS) phase is started
91	Driver connecting is started
92	PCI Bus initialization is started
93	PCI Bus Hot Plug Controller Initialization
94	PCI Bus Enumeration 32
95	PCI Bus Request Resources

96	PCI Bus Assign Resources
97	Console Output devices connect
98	Console input devices connect
99	Super IO Initialization
9A	USB initialization is started
9B	USB Reset
9C	USB Detect
9D	USB Enable
9E -9F	Reserved for future AMI codes
Α0	IDE initialization is started
A1	IDE Reset
A2	IDE Detect
А3	IDE Enable
A4	SCSI initialization is started
A5	SCSI Reset
A6	SCSI Detect
A7	SCSI Enable
A8	Setup Verifying Password
A9	Start of Setup
AB	Setup Input Wait
AD	Ready To Boot event
AE	Legacy Boot event
AF	Exit Boot Services event
В0	Runtime Set Virtual Address MAP Begin
B1	Runtime Set Virtual Address MAP End
B2	Legacy Option ROM Initialization
В3	System Reset
В4	USB hot plug
B5	PCI bus hot plug
B6	Clean-up of NVRAM
В7	Configuration Reset (reset of NVRAM settings)
B8 - BF	Reserved for future AMI codes

DXE Error Codes

D0	CPU initialization error
D1	System Agent initialization error
D2	PCH initialization error
D3	Some of the Architectural Protocols are not available
D4	PCI resource allocation error. Out of Resources
D5	No Space for Legacy Option ROM
D6	No Console Output Devices are found

D7	No Console Input Devices are found
D8	Invalid password
D9	Error loading Boot Option (LoadImage returned error)
DA	Boot Option is failed (StartImage returned error)
DB	Flash update is failed
DC	Reset protocol is not available

S3 Resume Progress Codes

E0	S3 Resume is stared (S3 Resume PPI is called by the DXE IPL)
E1	S3 Boot Script execution
E2	Video repost
E3	OS S3 wake vector call
E4 - E7	Reserved for future AMI progress codes

S3 Resume Error Codes

E8	S3 Resume Failed
E9	S3 Resume PPI not Found
EA	S3 Resume Boot Script Error
EB	S3 OS Wake Error
EC - EF	Reserved for future AMI error codes

Recovery Progress Codes

F0	Recovery condition triggered by firmware (Auto recovery)
F1	Recovery condition triggered by user (Forced recovery)
F2	Recovery process started
F3	Recovery firmware image is found
F4	Recovery firmware image is loaded
F5 - F7	Reserved for future AMI progress codes

Recovery Error Codes

F8	Recovery PPI is not available
F9	Recovery capsule is not found
FA	Invalid recovery capsule
FB - FF	Reserved for future AMI error codes

ACPI States Codes

The following codes appear after booting and the operating system into ACPI modes.

01	System is entering S1 sleep state
02	System is entering S2 sleep state
03	System is entering S3 sleep state
04	System is entering S4 sleep state
05	System is entering S5 sleep state
10	System is waking up from the S1 sleep state
20	System is waking up from the S2 sleep state
30	System is waking up from the S3 sleep state
40	System is waking up from the S4 sleep state
AC	System has transitioned into ACPI mode. Interrupt controller is in PIC mode.
AA	System has transitioned into ACPI mode. Interrupt controller is in APIC mode.

Installing OS, Drivers & Utilities

Please download and update the latest utilities and drivers at www.msi.com

Installing Windows® 10

- 1. Power on the computer.
- 2. Insert the Windows® 10 installation disc/USB into your computer.
- 3. Press the **Restart** button on the computer case.
- 4. Press F11 key during the computer POST (Power-On Self Test) to get into Boot Menu
- 5. Select the Windows® 10 installation disc/USB from the Boot Menu.
- 6. Press any key when screen shows Press any key to boot from CD or DVD... message.
- 7. Follow the instructions on the screen to install Windows[®] 10

Installing Drivers

- 1. Start up your computer in Windows® 10.
- 2. Insert MSI® Drive Disc into your optical drive.
- 3. Click the Select to choose what happens with this disc pop-up notification, then select Run DVDSetup.exe to open the installer. If you turn off the AutoPlay feature from the Windows Control Panel, you can still manually execute the **DVDSetup.exe** from the root path of the MSI Drive Disc.
- 4. The installer will find and list all necessary drivers in the **Drivers/Software** tab.
- 5. Click the **Install** button in the lower-right corner of the window.
- 6. The drivers installation will then be in progress, after it has finished it will prompt you to restart.
- 7. Click OK button to finish.
- 8. Restart your computer.

Installing Utilities

Before you install utilities, you must complete drivers installation.

- 1. Open the installer as described above.
- 2. Click the Utilities tab.
- 3. Select the utilities you want to install.
- 4. Click the Install button in the lower-right corner of the window.
- 5. The utilities installation will then be in progress, after it has finished it will prompt you to restart.
- 6. Click OK button to finish.
- 7. Restart your computer.

UEFI BIOS

MSI UEFI BIOS is compatible with UEFI (Unified Extensible Firmware Interface) architecture. UEFI has many new functions and advantages that traditional BIOS cannot achieve, and it will completely replace BIOS in the future. The MSI UEFI BIOS uses UEFI as the default boot mode to take full advantage of the new chipset's capabilities. However, it still has a CSM (Compatibility Support Module) mode to be compatible with older devices. That allows you to replace legacy devices with UEFI compatible devices during the transition.



Important

The term BIOS in this user guide refers to UEFI BIOS unless otherwise noted.

UEFI advantages

- Fast booting UEFI can directly boot the operating system and save the BIOS selftest process. And also eliminates the time to switch to CSM mode during POST.
- Supports for hard drive partitions larger than 2 TB.
- Supports more than 4 primary partitions with a GUID Partition Table (GPT).
- Supports unlimited number of partitions.
- Supports full capabilities of new devices new devices may not provide backward compatibility.
- Supports secure startup UEFI can check the validity of the operating system to ensure that no malware tampers with the startup process.

Incompatible UEFI cases

- 32-bit Windows operating system this motherboard supports only Windows 10 64-bit operating system.
- Older graphics card the system will detect your graphics card. When display a warning message There is no GOP (Graphics Output protocol) support detected in this graphics card.



Important

We recommend that you to use a GOP/ UEFI compatible graphics card.

How to check the BIOS mode?

After entering the BIOS, find the BIOS Mode at the top of the screen.



LIFFI hoot mode



CSM hoot mode

BIOS Setup

The default settings offer the optimal performance for system stability in normal conditions. You should always keep the default settings to avoid possible system damage or failure booting unless you are familiar with BIOS.



Important

- BIOS items are continuously update for better system performance. Therefore, the description may be slightly different from the latest BIOS and should be for reference only. You could also refer to the **HELP** information panel for BIOS item description.
- The pictures in this chapter are for reference only and may vary from the product you purchased.
- The BIOS items will vary with the processor.

Entering BIOS Setup

Press Delete key, when the Press DEL key to enter Setup Menu, F11 to enter Boot **Menu** message appears on the screen during the boot process.

Function key

F1: General Help list

F2: Add/ Remove a favorite item

F3: Enter Favorites menu

F4. Enter CPU Specifications menu

F5: Enter Memory-Z menu

F6. Load optimized defaults

Switch between Advanced mode and EZ mode F7.

F8 Load Overclocking Profile

F9: Save Overclocking Profile

F10: Save Change and Reset*

F12: Take a screenshot and save it to USB flash drive (FAT/ FAT32 format only).

Ctrl+F: Enter Search page

^{*} When you press F10, a confirmation window appears and it provides the modification information. Select between Yes or No to confirm your choice.

Resetting BIOS

You might need to restore the default BIOS setting to solve certain problems. There are several ways to reset BIOS:

- Go to BIOS and press F6 to load optimized defaults.
- Short the Clear CMOS jumper on the motherboard.



Be sure the computer is off before clearing CMOS data. Please refer to the Clear CMOS jumper section for resetting BIOS.

Updating BIOS

Updating BIOS with M-FLASH

Before updating:

Please download the latest BIOS file that matches your motherboard model from MSI website. And then save the BIOS file into the USB flash drive.

Updating BIOS:

- 1. Insert the USB flash drive that contains the update file into the USB port.
- 2. Please refer the following methods to enter flash mode.
 - Reboot and press Ctrl + F5 key during POST and click on Yes to reboot the system.

Press <Ctrl+F5> to activate M-Flash for BIOS update.

• Reboot and press **Del** key during POST to enter BIOS. Click the **M-FLASH** button and click on Yes to reboot the system.



- 3. Select a BIOS file to perform the BIOS update process.
- 4. When prompted click on Yes to start recovering BIOS.
- **5.** After the flashing process is 100% completed, the system will reboot automatically.

Updating the BIOS with MSI DRAGON CENTER

Before updating:

Make sure the LAN driver is already installed and the internet connection is set properly.

Updating BIOS:

- 1. Install and launch MSI DRAGON CENTER and go to **Support** page.
- 2. Select Live Update and click on Advance button.



- 3. Click on Scan button to search the latest BIOS file.
- 4. Select the BIOS file and click on **Download** icon to download and install the latest BIOS file.
- 5. Click Next and choose In Windows mode. And then click Next and Start to start updating BIOS.
- **6.** After the flashing process is 100% completed, the system will restart automatically.

Updating BIOS with Flash BIOS Button

- Please download the latest BIOS file that matches your motherboard model from the MSI® website.
- 2. Rename the BIOS file to MSI.ROM, and save it to the root of your USB flash drive.
- 3. Connect the power supply to CPU PWR1 and ATX PWR1. (No need to install CPU and memory.)
- 4. Plug the USB flash drive that contains the MSI.ROM file into the Flash BIOS Port on the rear I/O panel.
- 5. Press the Flash BIOS Button to flash BIOS, and the LED starts flashing.
- **6.** The LED will be turned off when the process is completed.

EZ Mode

At EZ mode, it provides the basic system information and allows you to configure the basic setting. To configure the advanced BIOS settings, please enter the Advanced Mode by pressing the **Setup Mode switch** or **F7** function key.



• GAME BOOST - click on it to togale the GAME BOOST for overclocking. This function is only available when both of the motherboard and CPU are supporting this function.



Important

We don't recommend you to adjust any BIOS item after activating the GAME BOOST function for keeping the optimal performance and system stability.

- A-XMP Profile allows you to select the A-XMP profile for memory to overclock. This function is only available when the system, memory and CPU are supporting this function.
- Setup Mode switch press this tab or the F7 key to switch between Advanced mode and F7 mode
- Screenshot click on this tab or the F12 key to take a screenshot and save it to USB flash drive (FAT/ FAT32 format only).
- Search click on this tab or the Ctrl+F keys to enter the search page. It allows you to search by BIOS item name. Move the mouse over a blank space and right click the mouse to exit the search page.



Important

In search page, only the F6, F10 and F12 function keys are available.

• Language - allows you to select language of BIOS setup.

- System information shows the CPU/ DDR speed, CPU/ MB temperature, MB/ CPU type, memory size, CPU/ DDR voltage, BIOS version and build date.
- Boot device priority bar you can move the device icons to change the boot priority. The boot priority from high to low is left to right.
- Component Information click on the CPU, Memory, Storage, Fan Info and Help buttons to show the information of connected component.
- Function buttons enable or disable these functions by clicking on these buttons. The function is enabled when the button shows **ON**.



Important

The function buttons will vary with the motherboard you purchased.

- M-Flash click on this button to enter the M-Flash menu that provides the way to update BIOS with a USB flash drive.
- Hardware Monitor click on this button to enter the Hardware Monitor menu that allows you to manually control the fan speed by percentage.
- Favorites click on this button or press the F3 key to show the Favorites window. It provides 5 menus for you to create personal BIOS menu where you can save and access favorite/ frequently-used BIOS setting items.



To add a BIOS item to a favorite menu

- 1. Select a BIOS item not only on BIOS menu but also on search page.
- Right-click or press **F2** key.
- 3. Choose a favorite page and click on OK.



To delete a BIOS item from favorite menu

- 1. Select a BIOS item on favorite menu.
- 2. Right-click or press F2 key.
- 3. Choose Delete and click on OK.



Advanced Mode

Press Setup Mode switch or F7 function key can switch between EZ Mode and Advanced Mode in BIOS setup.



- BIOS menu selection the following options are available:
 - **SETTINGS** allows you to specify the parameters for chipset and boot devices.
 - **OC** allows you to adjust the frequency and voltage. Increasing the frequency may get better performance.
 - M-FLASH provides the way to update BIOS with a USB flash drive.
 - OC PROFILE allows you to manage overclocking profiles.
 - HARDWARE MONITOR allows you to set the speeds of fans and monitor voltages of system.
 - **BOARD EXPLORER** provides the information of installed devices on this motherboard.
- Menu display provides BIOS setting items and information to be configured.

SETTINGS Menu

This menu allows you to specify the parameters for system, chipset and boot devices.

► System Status sub-menu

The System Status sub-menu allows you to set the system clock and view system information

System Date

Sets the system date. Use tab key to switch between date elements.

The format is <day> <month> <date> <year>.

Day of the week, from Sun to Sat, determined by BIOS. Read-only. <day>

<month> The month from Jan. through Dec.

<date> The date from 1 to 31 can be keyed by numeric function keys.

<vear> The year can be adjusted by users.

System Time

Sets the system time. Use tab key to switch between time elements.

The time format is <hour> <minute> <second>.

► SATA PortX/M2 X

Shows the information of connected SATA/ M.2 device.



Important

If the connected SATA/ M.2 device is not displayed, turn off computer and re-check SATA/ M.2 cable and power cable connections of the device and motherboard.

System Information

Shows detailed system information, including CPU type, BIOS version, and Memory (read only).

▶ DMI Information

Shows system information, desktop board information and chassis information.

Advanced sub-menu

The Advanced sub-menu allows you to adjust and set the parameters and behaviors of PCIe, ACPI, integrated peripherals, integrated graphics, USB, power management and Windows.

▶ PCI Subsystem Settings

Sets PCI, PCI express interface protocol and latency timer. Press Enter to enter the sub-menu.

► ACPI Settings

Sets ACPI parameters of onboard power LED behaviors.

Integrated Peripherals sub-menu

Sets integrated peripherals' parameters, such as LAN, Wi-Fi, HDD, SSD, USB and audio.

Integrated Graphics Configuration sub-menu (optional)

Adjusts integrated graphics settings for optimum system. This sub-menu is only available when using the CPU which integrate with IGP.

▶ USB Configuration sub-menu

Sets the onboard USB controller and device function. Press Enter to enter the sub-menu.

► Power Management Setup sub-menu

Sets system Power Management of ErP and AC Power Loss behaviors. You can optimize the system power consumption in this menu.

▶ Windows OS Configuration

Sets Windows detailed configuration and behaviors. You also can set the secure boot and control key management to prevent the unauthorized accessing for system.

► Wake Up Event Setup sub-menu

Sets system wake up behaviors for different sleep modes.

Secure Frase+

Enables or disables Secure Erase+ function. Secure Erase+ is the best way to effectively wipe all data from a SSD. Please note that data of SSD will be erased after enabling Secure Erase+.

► NVMe SSD Self-Tests

Enables or disables the NVMe SSD self-test function to ensure it is functioning properly. Only the NVMe 1.3 or above SSD can support this function.

► Realtek PCIe GbE Family Controller (MAC sub-menu

This sub-menu shows driver information and configuration of the Ethernet controller parameter.

▶ Boot sub-menu

Use this menu to set the system boot states and the sequence of system boot devices.

► Security sub-menu

Use this menu to set the administrator password and the user password for system security. This menu also allows you to set the TPM (Trusted Platform Module) function



Important

When selecting the Administrator / User Password items, a password box will appear on the screen. Type the password then press **Enter**. The password typed now will replace any previous set password from CMOS memory. You will be prompted to confirm the password. You may also press **Esc** key to abort the selection.

To clear a set password, press **Enter** when you are prompted to enter a new password. A message will confirm the password is being disabled. Once the password is disabled, you can enter the setup and OS without authorization.

► Save & Exit

This menu allows you to load the BIOS default values or factory default settings into the BIOS and exit the BIOS setup utility with or without changes.

OC Menu

This menu allows you to configure the frequencies and voltages for overclocking. Please note that, higher frequency and voltage may benefit overclocking capability but cause system un-stability.



Important

- Overclocking your PC manually is only recommended for advanced users.
- Overclocking is not guaranteed, and if done improperly, it could void your warranty or severely damage your hardware.
- If you are unfamiliar with overclocking, we advise you to use GAME BOOST function for easy overclocking.
- The BIOS items in OC menu will vary with the processor.

OC Explore Mode [Normal]

Enables or disables to show the normal or expert version of OC settings.

[Normal] Provides the regular OC settings in BIOS setup.

[Expert] Provides the advanced OC settings for OC expert to configure in BIOS

setup.

Note: We use * as the symbol for the OC settings of Expert mode.

► CPU Ratio Apply Mode [All Core]*

Sets applied mode for CPU ratio. This item only appears when a CPU that supports Turbo Boost is installed.

► CPU Ratio [Auto]

Sets the CPU ratio that is used to determine CPU clock speed. This item can only be changed if the processor supports this function.

▶ Advanced CPU Configuration

Press Enter to enter the sub-menu. User can set the parameters about CPU power/ current. The system may become unstable or unbootable after changing the parameters. If it occurs, please clear the CMOS data and restore the default settings.

► FCH Base Clock (MHz) [Auto]

Sets the CPU Base clock. You may overclock the CPU by adjusting this value. Please note that overclocking behavior and stability is not quaranteed. This item appears when a CPU that support this function is installed.

► A-XMP [Disabled]

Please enable A-XMP or select a profile of memory module for overclocking the memory. This item will be available when the installed processor, memory modules and motherboard support this function.

► DRAM Frequency [Auto]

Sets the DRAM frequency. Please note the overclocking behavior is not guaranteed.

► Adjusted DRAM Frequency

Shows the adjusted DRAM frequency. Read-only.

► FCLK Frequency [Auto]

Sets the FCLK frequency (Internal Data Fabric clock of DRAM). Please note the overclocking behavior is not guaranteed.

► UCLK DIV1 Mode [Auto]

Sets UCLK (Internal memory controller clock) mode.

► Memory Try It ! [Disabled]

It can improve memory compatibility or performance by choosing optimized memory preset. This item will be available when the installed processor supports this function.

► Memory Failure Retry [Enabled]

Enables or disables the system reboot function when the memory OC retry fails.

▶ Memory Fast Boot [Enabled] *

Enables or disables the initiation and training for memory every booting.

[Auto] The setting will be configured automatically by BIOS.

[Enabled] System will completely keep the archives of first intiation and training

for memory. So the memory will not be initialed and trained when

booting to accelerate the system booting time.

[Disabled] The memory will be initialed and trained every booting.

► Advanced DRAM Configuration

Press Enter to enter the sub-menu. User can set the memory timing for each/all memory channel. The system may become unstable or unbootable after changing memory timing. If it occurs, please clear the CMOS data and restore the default settings. (Refer to the Clear CMOS jumper section to clear the CMOS data, and enter the BIOS to load the default settings.)

▶ DigitALL Power sub-menu

Press Enter to enter the sub-menu. In the sub-menu, you can setup some protecting conditions about voltage/ current/ temputure for CPU.

► CPU Voltages control [Auto]

These options allows you to set the voltages related to CPU. If set to Auto, BIOS will set these voltages automatically or you can set it manually.

► DRAM Voltages control [Auto]

These options allows you to set the voltages related to memory. If set to Auto, BIOS will set these voltages automatically or you can set it manually.

► CPU Specifications sub-menu

Press Enter to enter the sub-menu. This sub-menu displays the information of installed CPU. You can also access this information menu at any time by pressing [F4]. Read only.

► MEMORY-Z sub-menu

Press Enter to enter the sub-menu. This sub-menu displays all the settings and timings of installed memory. You can also access this information menu at any time by pressing [F5].


M-FLASH Menu

M-FLASH provides the way to update BIOS with a USB flash drive. Please download the latest BIOS file that matches your motherboard model from MSI website, save the BIOS file into your USB flash drive. And then follow the steps below to update BIOS.

- 1. Insert the USB flash drive that contains the update file into the computer.
- 2. Click on M-FLASH tab, a demand message will be prompted. Click on Yes to reboot and enter the flash mode.



3. The system will enter the flash mode and a file selection menu will appear after rebooting.



- 4. Select a BIOS file to perform the BIOS update process.
- 5. After the flashing process is 100% completed, the system will reboot automatically.

OC PROFILE Menu



► Overclocking Profile 1/2/3/4/5/6

Overclocking Profile 1/2/3/4/5/6 management. Press **Enter** to enter the sub-menu.

► Set Name for Overclocking Profile 1/2/3/4/5/6

Name the current overclocking profile.

► Save Overclocking Profile 1/2/3/4/5/6

Save the current overclocking profile.

► Load Overclocking Profile 1/2/3/4/5/6

Load the current overclocking profile.

► Clear Overclocking Profile 1/2/3/4/5/6

Clear the current overclocking profile.

▶ 0C Profile Load from ROM

Load OC profile from BIOS ROM.

▶ OC Profile Save to USB

Save OC profile to the USB flash drive. The USB flash drive should be FAT/ FAT32 format only.

▶ OC Profile Load from USB

Load OC profile from the USB flash drive. The USB flash drive should be FAT/ FAT32 format only.

HARDWARE MONITOR Menu

This menu allows you to adjust the fan speed manually and monitor CPU/ system voltage.

> Select a temperature curve line (white) to be showed in Fan operating window



• Smart Fan - This setting enables/disables the Smart Fan function. Smart Fan is an excellent feature which will adjust the CPU/system fan speed automatically depending on the current CPU/system temperature, avoiding the overheating to damage your system.

► Settings Buttons

- All Full Speed configures all fans to run at full operating speed.
- All Set Default configures all fans' speeds return the BIOS default values.
- All Set Cancel discards current changes and restores previous settings for all fan.



Important

Make sure fans are working properly after adjusting the fan speed and switching the fan mode

Adjusting fans

- 1. Selects a fan that you want to adjust and to display the fan duty curve line (yellow) in fan operating windows.
- Click and drag the duty points to adjust the fan speed.





\ Important

The pictures in this section are for reference only and may vary from the motherboard you purchased.

AMD RAID Configuration

The following are the RAID levels supported by RAIDXpert2.

- **RAID 0** (Striping) breaks the data into blocks which are written to separate hard drives. Spreading the hard drive I/O load across independent channels greatly improves I/O performance.
- **RAID 1** (Mirroring) provides data redundancy by mirroring data between the hard drives and provides enhanced read performance.
- **RAID 10** (Striped RAID1 Sets) uses four hard drives to create a combination of RAID 0 and 1 by forming a RAID 0 array from two RAID 1 arrays.
- **Volume** (JBOD) provides the ability to link-together storage from one or several disks, regardless of the size of the space on those disks. Useful in scavenging space on disks unused by other disks in the array. Does not provide performance benefits or data redundancy.
- **RAIDABLE** (also known as RAID Ready) allows the user to add more storage space or create a redundant array after a system is installed.

RAID level comparison

	RAID 0	RAID 1	RAID 10
Minimum # drives	2	2	4
Data protection	None	Excellent	Excellent
Read performance	Excellent	OK	OK
Write performance	Excellent	Good	Good
Capacity utilization	100%	50%	50%



Important

All the information/volumes/pictures listed in your system might differ from the illustrations in this appendix.

Enabling RAIDXpert2 Configuration Utility

To enter the RAIDXpert2 Configuration Utility menu

- 1. Power on and press **Delete** key to enter BIOS Setup menu.
- 2. Press F7 to switch to Advanced mode from EZ mode.
- Go to BIOS > SETTINGS > Advanced > Integrated Peripherals > SATA Mode and change setting to RAID Mode.
- Go to BIOS > SETTINGS > Advanced > Windows OS Configuration > BIOS UEFI/ CSM Mode and change setting to UEFI.
- 5. Press **F10** to save configuration and exit, and then reboot and press **Delete** key to enter BIOS Setup menu.
- Go to BIOS > SETTINGS > Advanced > RAIDXpert2 Configuration Utility submenu.

Initializing Disks

New disks and legacy disks must be initialized before they can be used to create an AMD-RAID array. Initialization writes AMD-RAID configuration information (metadata) to a disk.




Important

- If a disk is part of an AMD-RAID array, the disk cannot be selected for initialization. To initial the disk anyway, delete the AMD-RAID array. Data on the disk is deleted during initialization so ensure the correct disks are chosen to initialize.
- A legacy disk can contain valid data. When a legacy disk is initialized, all data on the disk is lost

To initialize disks

- 1. As previously mentioned, enable RAIDXpert2 Configuration Utility.
- 2. Go to BIOS > SETTINGS > Advanced > RAIDXpert2 Configuration Utility > Physical Disk Management > Select Physical Disk Operations > Initialize Disk sub-menu.



- 3. Select desired disks by changing the Physical Disk setting to **Enabled**.
- 4. Select **OK**, then press Enter.



- 5. Review the warning message, if you want to proceed, select YES, then press Enter.
- 6. Initialization takes 10 to 15 seconds per disk. During initialization, a complete rescan of all channels is done automatically.

Creating Arrays

Arrays can be created after the disks are initialized.



Important

- For redundant arrays, the Create process is not started until after the operating system and AMD-RAID OS drivers have been installed and the system has booted to the operating system. However, the arrays are immediately available to use for either a bootable array or a data array.
- Array numbers are valid only for a given boot and might be different in the RAIDXpert2 Configuration Utility and RAIDXpert2. If a permanent label is required, use the RAIDXpert2 Web GUI Array Naming feature.
- At any point in the procedure, return to a prior window by pressing ESC.
- If the system is booted from an AMD-RAID bootable array, the first array in the Arrays section must be the bootable array. The system boots only from the first array in the Arrays section.

To create an array

- 1. As previously mentioned, enable RAIDXpert2 Configuration Utility.
- Go to BIOS > SETTINGS > Advanced > RAIDXpert2 Configuration Utility > Array Management > Create Array sub-menu.



- 3. Select the RAID level from the **Select RAID Level** drop down menu.
- Enter Select Physical Disks sub-menu, select member disks by changing the Physical Disk setting to Enabled.



- Select Apply Changes, then press Enter to apply and go back to previous submenu.
- Change the Select CacheTagSize, Read Cache Policy and Write Cache Policy settings according to your needs.
- 7. Select Create Array, then press Enter.

Deleting Arrays



Important


- Deleting an array permanently destroys all data that is on the array. This action cannot be undone and it is very unlikely that the data can be recovered.
- Do not delete the first array listed in the Arrays section, if it is the AMD-RAID bootable array. Doing this deletes the operating system and AMD-RAID files.

To delete an array

- 1. As previously mentioned, enable RAIDXpert2 Configuration Utility.
- 2. Go to BIOS > SETTINGS > Advanced > RAIDXpert2 Configuration Utility > Array Management > Delete Array sub-menu.



- 3. Select the desired array and change the setting to **Enabled**.
- 4. Enter Delete Array(s) sub-menu.



- 5. Review the warning message, if you want to proceed, Select Confirm and change the setting to Enabled.
- 6. Select YES then press Enter.

Installing RAID Driver

New Operating System Installation

The following details the installation of the drivers while installing operating system.

- 1. During the operating system installation, after selecting the location to install Windows click on **Load driver** button to install a third party RAID driver.
- 2. When prompted, insert the USB flash drive with AMD RAID Drivers and then click Browse
 - To make an AMD RAID Drivers USB flash drive. Insert the MSI Driver Disc into the optical drive. Copy all the contents in \Storage\AMD\
- 3. Navigate to the **rcbottom** folder, then click **OK**.
- 4. Select the (rcbottom.inf) driver, click Next.
- 5. Click **Browse** and navigate to the rcraid folder, then click **OK**.
- 6. Select the (rcraid.inf) driver, click Next.
- 7. You have successfully installed the RAID driver, and Windows setup should continue
- 8. Leave the disk/ USB drive in the computer until the system reboots itself. Windows setup will need to copy the files after the RAID volume is formatted, and Windows setup starts copying files.

AMD RAIDXpert2 Management Suite Installation

- 1. Set the SATA Mode to RAID Mode in BIOS
- 2. Insert the MSI Driver Disc into the optical drive.
- 3. Click the Select to choose what happens with this disc pop-up notification, then select Run DVDSetup.exe to open the installer. If you turn off the AutoPlay feature from the Windows Control Panel, you can still manually execute the DVDSetup. exe from the root path of the MSI Driver Disc.
- 4. Under the **Drivers/Software** tab. check the **AMD RAID Drivers** check-box.
- 5. Click the Install button.
- 6. When prompt you to restart, click **OK** button to finish.
- 7. Restart your computer and enter the Windows operating system.
- 8. Double-click the RAIDXpert2 icon to open the RAIDXpert2 Web GUI.
 - Default credentials are:
 - Username admin
 - Password admin
- 9. Change the credentials:
 - Create new username and password
- 10. Re-log into the RAIDXpert2 Web GUI with the new credentials.

Troubleshooting

Before sending the motherboard for RMA repair, try to go over troubleshooting guide first to see if your got similar symptoms as mentioned below.

The power is not on.

- Connect the AC power cord to an electrical outlet securely.
- Check if all ATX power connectors like ATX PWR1. CPU PWR1 are connected from the power supply to the motherboard?
- Some power supply units have a power button on the rear side, make sure the button is turned on
- Check if the power switch cable is connected to JFP1 pin header properly.
- Verify the Clear CMOS jumper JBAT1 is set to Keep DATA.
- Test with another known working power supply of equal or greater wattage.

The power is on, but no signal to monitor

- Connect the monitor power cord to a electrical outlet securely.
- Make sure the monitor is turned on.
- Select different inputs on the monitor.
- If 3 long beeps are heard, remove all memory modules and try to install only one memory module in the **DIMMA1** slot first and then restart the computer.
- If 1 long 2 short beeps are heard, remove and reinstall the graphics card and then restart the computer.
- Test with another known working graphics card.

The computer does not boot after updating the BIOS

- · Clear the CMOS.
- Use the secondary BIOS to bootup the system (Only for motherboard with Dual BIOS)

Lost BIOS password

· Clear the CMOS, but that will cause you to lose all customized settings in the BIOS.

There is no audio

- · Adjust the volume.
- · Connect the speakers/headphones to audio ports on the motherboard rear IO panel.
- Remove secondary speakers/ headphones, HDMI cables, USB audio devices
- Test with another known working speaker or headphone.

There is no network

- Make sure the network chipset driver has been installed.
- Verify if the network cable is properly connected and make sure the LAN port LEDs are properly illuminated.
- Verify your TCP/IP settings.
- · Restart or reset your router.
- Test with another known working LAN cable.

The USB device is not working

- Make sure your USB drive driver has been installed.
- · Verify if USB device is listed in Windows® Device Manager.
- Connect the USB device to other USB. port on the motherboard rear IO panel.

Regulatory Notices

FCC Compliance Statement

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- · Reorient or relocate the receiving antenna
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.



Tested to comply with FCC standards FOR HOME OR OFFICE USE

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

[1] This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CE Conformity



Products bearing the CE marking comply with one or more of the following EU Directives as may be applicable:

RED 2014/53/EU; Low Voltage Directive 2014/35/EU; EMC Directive 2014/30/EU; RoHS Directive 2011/65/EU. Compliance with these directives is assessed using applicable European Harmonized Standards. The point of contact for regulatory matters is MSI, MSI-NL Eindhoven 5706 5692 ER Son.

KC인증서



상호: (주)엠에스아이코리아 제품명: 메인보드 모델명: 20-7D13 제조년월: 2020년

제조단철: 2020년 R-R-MSI-20-7D13 제조자 및 제조국가: MSI/중국

クラスB情報技術装置



この装置は、クラスB情報技術装置です。この 装置は、家庭環境で使用することを目的として いますが、この装置がラジオやテレビジョン受 信機に近接して使用されると、受信障害を引き

起こすことがあります。取扱説明書に従って

正しい取り扱いをして下さい

C-Tick Compliance



Battery Information

European Union:



Batteries, battery packs, and accumulators should not be disposed of as unsorted household waste. Please use the public collection system to return, recycle, or treat them in compliance with the local regulations.

Taiwan:



廢電池請回收

For better environmental protection, waste batteries should be collected separately for recycling or special disposal.

California, USA:



The button cell battery may contain perchlorate material and requires special handling when recycled or disposed of in California.

For further information please visit: http://www.dtsc.ca.gov/hazardouswaste/perchlorate/

CAUTION: There is a risk of explosion, if battery is incorrectly replaced.

Replace only with the same or equivalent type recommended by the manufacturer.

Chemical Substances Information

In compliance with chemical substances regulations, such as the EU REACH Regulation (Regulation EC No. 1907/2006 of the European Parliament and the Council), MSI provides the information of chemical substances in products at:

https://storage-asset.msi.com/html/popup/csr/evmtprtt_pcm.html

Environmental Policy

 The product has been designed to enable proper reuse of parts and recycling and should not be thrown away at its end of life.



- Users should contact the local authorized point of collection for recycling and disposing of their end-of-life products.
- Visit the MSI website and locate a nearby distributor for further recycling information.
- Users may also reach us at gpcontdev@msi.com for information regarding proper Disposal, Take-back, Recycling, and Disassembly of MSI products.

WEEE (Waste Electrical and Electronic Equipment) Statement

FNGLISH

To protect the global environment and as an environmentalist, MSI must remind you that

Under the European Union ("EU") Directive on Waste Electrical and Electronic Equipment, Directive 2002/96/EC, which takes effect on August 13, 2005, products of "electrical and electronic equipment" cannot be discarded as

municipal wastes anymore, and manufacturers of covered electronic equipment will be obligated to take back such products at the end of their useful life. MSI will comply with the product take back requirements at the end of life of MSI-branded products that are sold into the EU. You can return these products to local collection points.

DEUTSCH

Hinweis von MSI zur Erhaltung und Schutz unserer

Gemäß der Richtlinie 2002/96/EG über Elektro- und Elektronik-Altgeräte dürfen Elektro- und Elektronik-Altgeräte nicht mehr als kommunale Abfälle entsorgt werden. MSI hat europaweit verschiedene Sammelund Recyclingunternehmen beauftragt, die in die Europäische Union in Verkehr gebrachten Produkte, am Ende seines Lebenszyklus zurückzunehmen. Bitte entsorgen Sie dieses Produkt zum gegebenen Zeitpunkt ausschliesslich an einer lokalen Altgerätesammelstelle in Ihrer Nähe.

En tant qu'écologiste et afin de protéger l'environnement, MSI tient à rappeler ceci...

Au sujet de la directive européenne (EU) relative aux déchets des équipement électriques et électroniques, directive 2002/96/EC, prenant effet le 13 août 2005, que les produits électriques et électroniques ne peuvent être déposés dans les décharges ou tout simplement mis à la poubelle. Les fabricants de ces équipements seront obligés de récupérer certains produits en fin de vie. MSI prendra en compte cette exigence relative au retour des produits en fin de vie au sein de la communauté européenne. Par conséquent vous pouvez retourner localement ces matériels dans les points de collecte.

РУССКИЙ

Компания MSI предпринимает активные действия по защите окружающей среды, поэтому напоминаем

В соответствии с директивой Европейского Союза (ЕС) по предотвращению загрязнения окружающей среды использованным электрическим и электронным оборудованием (директива WEEE 2002/96/EC), вступающей в силу 13 августа 2005 года, изделия, относящиеся к электрическому и электронному оборудованию, не могут рассматриваться как бытовой мусор, поэтому производители вышеперечисленного электронного оборудования обязаны принимать его для переработки по окончании срока службы. MSI обязуется соблюдать требования по приему продукции, проданной под маркой MSI на территории ЕС, в переработку по окончании срока службы. Вы можете вернуть эти изделия в специализированные пункты приема.

MSI como empresa comprometida con la protección del medio ambiente, recomienda:

Bajo la directiva 2002/96/EC de la Unión Europea en materia de desechos y/o equipos electrónicos, con fecha de rigor desde el 13 de agosto de 2005, los productos clasificados como "eléctricos y equipos electrónicos" no pueden ser depositados en los contenedores habituales de su municipio, los fabricantes de equipos electrónicos, están obligados a hacerse cargo de dichos productos al termino de

su período de vida. MSI estará comprometido con los términos de recogida de sus productos vendidos en la Unión Europea al final de su periodo de vida. Usted debe depositar estos productos en el punto limpio establecido por el ayuntamiento de su localidad o entregar a una empresa autorizada para la recogida de estos residuos

NEDERI ANDS

Om het milieu te beschermen, wil MSI u eraan herinneren dat

De richtlijn van de Europese Unie (EU) met betrekking tot Vervuiling van Electrische en Electronische producten (2002/96/EC), die op 13 Augustus 2005 in zal gaan kunnen niet meer beschouwd worden als vervuiling. Fabrikanten van dit soort producten worden verplicht om producten retour te nemen aan het eind van hun levenscyclus. MSI zal overeenkomstig de richtlijn handelen voor de producten die de merknaam MSI dragen en verkocht zijn in de EU. Deze goederen kunnen geretourneerd worden op lokale inzamelingspunten.

SRPSKI

Da bi zaštitili prirodnu sredinu, i kao preduzeće koje vodi računa o okolini i prirodnoj sredini, MSI mora da vas podesti da...

Po Direktivi Evropske unije ("EU") o odbačenoj ekektronskoj i električnoj opremi, Direktiva 2002/96/ EC, koja stupa na snagu od 13. Avgusta 2005, proizvodi koji spadaju pod "elektronsku i električnu opremu" ne mogu više biti odbačeni kao običan otpad i proizvođači ove opreme biće prinuđeni da uzmu natrag ove proizvode na kraju njihovog uobičajenog veka trajanja. MSI će poštovati zahtev o preuzimanju ovakvih proizvoda kojima je istekao vek trajanja, koji imaju MSI oznaku i koji su prodati u EU. Ove proizvode možete vratiti na lokalnim mestima za prikupljanje.

Aby chronić nasze środowisko naturalne oraz jako firma dbająca o ekologię, MSI przypomina, że...

Zgodnie z Dyrektywa Unii Europejskiej ("UE") dotyczaca odpadów produktów elektrycznych i elektronicznych (Dyrektywa 2002/96/EC), która wchodzi w życie 13 sierpnia 2005, tzw. "produkty oraz wyposażenie elektryczne i elektroniczne " nie mogą być traktowane jako śmieci komunalne, tak więc producenci tych produktów beda zobowiazani do odbierania ich w momencie gdy produkt jest wycofywany z użycia. MSI wypełni wymagania UE, przyjmując produkty (sprzedawane na terenie Unii Europejskiej) wycofywane z użycia. Produkty MSI będzie można zwracać w wyznaczonych punktach zbiorczych.

TÜRKCE

Çevreci özelliğiyle bilinen MSI dünyada çevreyi korumak icin hatırlatır:

Avrupa Birliği (AB) Kararnamesi Elektrik ve Elektronik Malzeme Atığı, 2002/96/EC Kararnamesi altında 13 Ağustos 2005 tarihinden itibaren gecerli olmak üzere, elektrikli ve elektronik malzemeler diğer atıklar gibi çöpe atılamayacak ve bu elektonik cihazların üreticileri, cihazların kullanım süreleri bittikten sonra ürünleri geri toplamakla yükümlü olacaktır. Avrupa Birliği'ne satılan MSI markalı ürünlerin kullanım süreleri bittiğinde MSI ürünlerin geri alınması isteği ile isbirliği icerisinde olacaktır. Ürünlerinizi yerel toplama noktalarına bırakabilirsiniz.

ČESKY

Záleží nám na ochraně životního prostředí - společnost MSI upozorňuje...

Podle směrnice Evropské unie ("EU") o likvidaci elektrických a elektronických výrobků 2002/96/ EC platné od 13. srpna 2005 je zakázáno likvidovat "elektrické a elektronické výrobky" v běžném komunálním odpadu a výrobci elektronických výrobků, na které se tato směrnice vztahuje, budou povinní odebírat takové výrobky zpět po skončení jejich životnosti. Společnost MSI splní požadavky na odebírání výrobků značky MSI, prodávaných v zemích EU, po skončení jejich životnosti. Tyto výrobky můžete odevzdat v místních sběrnách.

Annak érdekében, hogy környezetünket megvédjük, illetve környezetvédőként fellépve az MSI emlékezteti Önt. hogy .

Az Európai Unió ("EU") 2005. augusztus 13-án hatályba lépő, az elektromos és elektronikus berendezések hulladékairól szóló 2002/96/EK irányelve szerint az elektromos és elektronikus berendezések többé nem kezelhetőek lakossági hulladékként, és az ilyen elektronikus berendezések gyártói kötelessé válnak az ilyen termékek visszavételére azok hasznos élettartama végén. Az MSI betartja a termékvisszavétellel kapcsolatos követelményeket az MSI márkanév alatt az EU-n belül értékesített termékek esetében, azok élettartamának végén. Az ilyen termékeket a legközelebbi gyűjtőhelyre viheti.

Per proteggere l'ambiente, MSI, da sempre amica della natura, ti ricorda che...

In base alla Direttiva dell'Unione Europea (EU) sullo Smaltimento dei Materiali Elettrici ed Elettronici, Direttiva 2002/96/EC in vigore dal 13 Agosto 2005, prodotti appartenenti alla categoria dei Materiali Elettrici ed Elettronici non possono più essere eliminati come rifiuti municipali: i produttori di detti materiali saranno obbligati a ritirare ogni prodotto alla fine del suo ciclo di vita. MSI si adeguerà a tale Direttiva ritirando tutti i prodotti marchiati MSI che sono stati venduti all'interno dell'Unione Europea alla fine del loro ciclo di vita. È possibile portare i prodotti nel più vicino punto di raccolta

日本JIS C 0950材質宣言

日本工業規格JIS C 0950により、2006年7月1日以降に販 売される特定分野の電気および電子機器について、製造 者による含有物質の表示が義務付けられます。

https://storage-asset.msi.com/html/popup/csr/ cemm jp.html

India RoHS

This product complies with the "India E-waste (Management and Handling) Rule 2011" and prohibits use of lead, mercury, hexavalent chromium, polybrominated biphenyls or polybrominated diphenyl ethers in concentrations exceeding 0.1 weight % and 0.01 weight % for cadmium, except for the exemptions set in Schedule 2 of the Rule.

Türkiye EEE yönetmeliği

Türkiye Cumhuriyeti: EEE Yönetmeliğine Uygundur

Україна обмеження на наявність небезпечних речовин

Обладнання відповідає вимогам Технічного регламенту щодо обмеження використання деяких небезпечних речовин в електричному та електронному обладнані, затвердженого постановою Кабінету Міністрів України від 3 грудня 2008 № 1057.

Viêt Nam RoHS

Kể từ ngày 01/12/2012, tất cả các sản phẩm do công ty MSI sản xuất tuân thủ Thông tư số 30/2011/TT-BCT quy định tạm thời về giới hạn hàm lượng cho phép của một số hóa chất độc hai có trong các sản phẩm điện, điển tử"

Wireless Radio Use

This device is restricted to indoor use when operating in the 2.4GHz, 5GHz frequency band.

Cet appareil doit être utilisé à l'intérieur.

당해 무선설비는 운용중 전파혼신 가능성이 있음.

この製品は、周波数帯域 2.4GHz, 5GHz で動作していると きは、屋内においてのみ使用可能です。

NCC無線設備警告聲明

工作頻率2.4GHz, 5GHz該頻段限於室內使用。

經型式認證合格之低功率射頻電機,非經許可,公司、商 號或使用者均不得擅自變更頻率、加大功率或變更原設 計之特性及功能。

低功率射頻電機之使用不得影響飛航安全及干擾合法通 信;經發現有干擾現象時,應立即停用,並改善至無干擾時 方得繼續使用。前項合法通信,指依電信法規定作業之無 線電通信。低功率射頻電機須忍受合法通信或工業、科學 及醫療用電波輻射性電機設備之干擾。

Products with radio functionality (EMF)

This product incorporates a radio transmitting and receiving device. For computers in normal use, a separation distance of 20 cm ensures that radio frequency exposure levels comply with EU requirements. Products designed to be operated at closer proximities, such as tablet computers, comply with applicable EU requirements in typical operating positions. Products can be operated without maintaining a separation distance unless otherwise indicated in instructions specific to the product.

Restrictions for products with radio functionality



CAUTION: IEEE 802.11x wireless LAN with 5.15-5.35 GHz frequency band is restricted for indoor use only in all European Union member states, EFTA (Iceland, Norway,

Liechtenstein), and most other European countries (e.g., Switzerland, Turkey, Republic of Serbia). Using this WLAN application outdoors might lead to interference issues with existing radio services.

Radio frequency bands and maximum power levels

Features :802.11 a/b/g/n/ac/ax, BT

:2.4GHz, 5GHz Frequency Range Modulation :FHSS, DSSS, OFDM

Power Output :10, 20, 23

Channel Band Width :1, 5, 20, 40, 80, 160 MHz

MS-7D13主板产品中有害物质的名称及含量

	有害物质					
部件名称	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
 印刷电路板组件*	×	(rig)	(00)	(01(11))	(1 00)	(1 882)
以则电路恢组计·		0	0	0	0	0
电池**	×	0	0	0	0	0
外部信号连接头	×	0	0	0	0	0
线材	×	0	0	0	0	0

本表格依据 SJ/T 11364 的规定编制。

- ○:表示该有害物质在该部件所有均质材料中的含量均在 GB/T 26572 规定的限量要求以下。
- <: 表示该有害物质至少在该部件的某一均质材料中的含量超出 GB/T 26572 规定的限量要求,但所有部件都符合 欧盟RoHS要求。
- * 印刷电路板组件: 包括印刷电路板及其构成的零部件。
- ** 电池本体上如有环保使用期限标识,以本体标识为主。
- 上述有毒有害物质或元素清单会依型号之部件差异而有所增减。
- 產品部件本体上如有环保使用期限标识,以本体标识为主。

限用物質含有情況標示聲明書

設備名稱:電腦主機板			型號(型式):MS-7D13					
	限用物質及其化學符號							
單元	鉛 (Pb)	汞 (Hg)	鎘 (Cd)	六價鉻 (Cr ⁺⁶)	多溴聯苯 (PBB)	多溴二苯醚 (PBDE)		
電路板	0	0	0	0	0	0		
電子元件	_	0	0	0	0	0		
金屬機構件	_	0	0	0	0	0		
塑膠機構件	0	0	0	0	0	0		

備考1. "超出0.1 wt %" 及 "超出0.01 wt %" 係指限用物質之百分比含量超出百分比含量基準值。

備考2. "○" 係指該項限用物質之百分比含量未超出百分比含量基準值。

備考3. "一" 係指該項限用物質為排除項目。

Copyright

msi Micro-Star Int'l Co.,Ltd.

Copyright © 2020 All rights reserved.

The MSI logo used is a registered trademark of Micro-Star Int'l Co., Ltd. All other marks and names mentioned may be trademarks of their respective owners. No warranty as to accuracy or completeness is expressed or implied. MSI reserves the right to make changes to this document without prior notice.

Revision History

Version 2.0. 2020/09. First release. Version 2.1, 2020/11, updated release.

Technical Support

If a problem arises with your system and no solution can be obtained from the user quide, please contact your place of purchase or local distributor. Alternatively, please try the following help resources for further guidance.

- · Visit the MSI website for technical guide, BIOS updates, driver updates, and other information: http://www.msi.com
- · Register your product at: http://register.msi.com

