## Product Line CISRACK

Type RM-CI-T6-MC

#### Supported Models MERAKI MX68 MERAKI MX68W MERAKI MX68CW

DIMENSIONS 1U COLOR Metallic Blue PACKING DIMENSIONS 80 x 520 x 270 mm 3.14 x 20.47 x 10.63 in PRODUCT DIMENSIONS 44 x 482 x 217 mm (height x width x depth) 1.73 x 18.98 x 8.54 in

# MOUNTING INSTRUCTIONS

- 1. Remove the screw from the right bottom of the media converter and use it to fix the media converter on the rack.
- 2. Remove the four rubber feet from your Cisco appliance.
- 3. Remove the two bolts (situated on the front side of the appliance) from the bottom of the Cisco appliance.
- 4. Place your Cisco appliance backwards through the FRONT opening of the rack.
- 5. Turn over the rack with the Cisco appliance and use the original bolts to fix the appliance on the rack and turn it back over.
- 6. Plug in the power cord of the media converter, plug the USB cable into the appliance and tie the excess length of the power cable down with a zip tie.
- 7. Place the power supply on the add-on, tie it down with the two zip ties and slide it into the rack. Fix with a bolt and nut.
- 8. Lead the low voltage power cable through the large square hole towards the front of the rack and connect it to the power inlet. Use a zip tie to secure the power cable on the rack and tie the excess length of the cable down with a zip tie.
- 9. Place the light pipe through the opening of the rack. See picture above.
- 10. Place your CisRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

## PACKAGE CONTENTS

#### Qty Description

- 1 CisRack + light pipe
- 1 Media converter
- 4 Zip ties
- 1 Torx T8 key
- 1 USB/DC cable
- 1 Bolt M3x6mm
- 1 Nut M3

EMEA Office Nonnenveld 27 4811 HN Breda The Netherlands T +31 76 200 37 40 E sales@rackmount.it WWW.RACKMOUNT.IT US Office 9201 Metric Blvd - Unit A Austin - TX 78758 United States T +1 512 521 03 33 E sales-us@rackmount.it



## Consider the environment, recycle where applicable.

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 1 - 30-09-2021

