

HyperX ProCast Microphone

PROFESSIONAL-GRADE CONDENSER MIC.

The HyperX ProCast is a professional-grade condenser microphone with an XLR connection¹ built for people who make a living with their voices. Capture more details in your recordings thanks to the cardioid gold-sputtered large diaphragm condenser capsule. The ProCast's included anti-vibration shock mount and snap on HyperX Shield pop filter work together to help reduce unwanted rumbles and pops in your recordings. It also features a switchable 80Hz high-pass filter and -10dB PAD, further ensuring that you're only recording exactly what you want in a variety of scenarios. With support for 3/8" and 5/8" threads, the stylish ProCast is compatible with most arms and stands, making it an easy way to take your streaming or recording setup to the next level.



Key features

Large condenser for excellent noise performance

ProCast's design enables better high-frequency details compared to electret and dynamic mics and improved low-frequency performance over smaller diaphragm condensers.

Professional-grade XLR Connection

The ProCast requires 48V of phantom power, so connect it via XLR cable to professional interfaces or preamps to start your recording.²

Built-in anti-vibration shock mount

Isolate the mic and suppress the sound of unintentional rumbles and bumps with the elastic rope suspension.

Compatible with most boom arms and mic stands

The versatile mic and adapter fit 3/8-inch and 5/8-inch threaded setups, so it's compatible with most mic stands or boom arms.

Cardioid polar pattern for solo recording

The cardioid polar pattern emphasizes sounds in front of the mic, making it perfect for voiceovers, streaming, vocals, podcasts, or other single-source audio recording.

Detachable HyperX Shield metal pop filter included

Simply snap the HyperX Shield to the ProCast's included anti-shock mount to filter out those plosive puffs of air that result from p sounds.

Fine-tune your audio recordings

ProCast's switchable 80Hz filter helps reduce unwanted low-end frequencies like rumbles and vibrations. The passive attenuation allows the mic to handle high sound pressure level sources of audio.

Stunning professional design

The sleek, unique HyperX design blends form and function, making the ProCast as elegant as it is practical.



Product Names

Product name: HyperX ProCast Microphone

Product Numbers

Product number: 699Z0AA

Warranty

Manufacturer Warranty: 2 year

Appearance

Product Primary Color: Black

Battery and Power

Impedance: Output Impedance: 16 Ω

Box contents

What's in the box: Condenser Mic, HyperX Shield Pop Filter, Mount Adapter, Quick Start Guide

Compatibility

Compatibility statement: XLR

Connectivity and communications

USB specification: Balanced 3-pin XLR male

Dimensions

Height (metric): 209mm
Width (metric): 102mm
Length (metric): 134mm

Multimedia and input devices

Connection type: Balanced 3-pin XLR male
Polar pattern: Cardioid
Signal-to-noise ratio: 75dB
Frequency response (microphone): 20Hz–20kHz
Sensitivity (microphone): -38 ± 3 dBV (1V/Pa at 1kHz)
Noise (RMS) (microphone): -118 dBV (A-weighting) B65
Boom mic element: Gold-sputtered externally-polarized condenser

Weights

Weight (metric): 376g
Weight note (metric): Weight (Shock mount and pop filter): 127g - Total Weight: 503g

MESSAGING FOOTNOTES

¹ Interface, preamp, XLR cable, and boom arm/mic stand are not included.

² We recommend an interface with at least 60dB of gain.