

Technical Specifications

APC Netshelter Rack Automatic Transfer Switch, 1U, 20A, 120V, 2 L5-20 IN, 10 5-20R OUT, 50/60 Hz | AP4452A | Downloaded on 11/02/2022 (EST)



APC Netshelter Rack Automatic Transfer Switch, 1U, 20A, 120V, 2 L5-20 IN, 10 5-20R OUT, 50/60 Hz

AP4452A

Call for More Information 0800 2799254

- Includes: Mounting hardware, Rack mounting brackets, Serial configuration cable

Output

Overload Protection	No
Cord Length	2.4meters
Maximum Total Current Draw	20

Input

Input frequency	50/60 Hz
Input Connections	NEMA L5-20P 16 A 2P + E
Cord Length	2.4meters
Acceptable Input Voltage	108 - 132VAC
Number of Power Cords	2
Load Capacity	1920VA
Maximum Input Current	20A
Maximum Line Current	20A
Regulatory Derated Input Current (North America)	20A

Physical

Maximum Height	44MM, 4.4CM
Maximum Width	432MM, 43.2CM
Maximum Depth	236MM, 23.6CM
Rack Height	1U
Net Weight	4.4KG

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.

Technical Specifications

APC Netshelter Rack Automatic Transfer Switch, 1U, 20A, 120V, 2 L5-20 IN, 10 5-20R OUT, 50/60 Hz | AP4452A | Downloaded on 11/02/2022 (EST)

Physical

Color	Black
-------	-------

Environmental

Operating Temperature	-5 - 45 °C
-----------------------	------------

Operating Relative Humidity	5 - 95 %
-----------------------------	----------

Operating Elevation	0 - 3048meters
---------------------	----------------

Storage Temperature	-25 - 65 °C
---------------------	-------------

Storage Relative Humidity	5 - 95 %
---------------------------	----------

Storage Elevation	0 - 15240meters
-------------------	-----------------

Conformance

Approvals	EN 55022 class A, FCC part 15 class A
-----------	---------------------------------------

Standard warranty	2 years repair or replace
-------------------	---------------------------

Sustainable Offer Status

RoHS	Compliant
------	-----------

Other Environmental Compliance	China RoHS
--------------------------------	------------

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.