

Hermes RGB Memory

To push the limits, Predator Hermes RGB DDR5 offers high speeds up to 8000 MHz, striking design, impressive RGB lighting, and spectacular performance, empowering overclockers, enthusiasts, and gamers to stand out amid the competition. Available in three color schemes, Hermes is compatible with a variety of motherboards, graphics cards, and heat sinks.











RGB

Mesmerizing

RGB lighting











PMIC





Product Features

Impressive Speed Performance

Available with impressive speeds up to 8000 MHz, Hermes DDR5 provides different speed options. It offers the ultimate edge over any competition.

Low Latency

Tested rigorously for overclocking potential, Hermes drops the latency to CL36 and the voltage to 1.45 V, drastically improving performance for both gaming and business.

New Look, New Style

Available in White / Silver / Black to suit your own style, Hermes DDR5 showcases superior product design and technical advantages.

Quality Components for Enhanced Performance

With its programmable PMIC, Hermes achieves more efficient power load management, and improves system stability .It also adopts 10-layer PCB to bring enhanced data integrity and overclocking performance.

No More Heat Issues

Hermes comes with an optional complimentary customized fan in 40 × 40 mm (max. air flow: 4.72 CFM), which is easy to install on mainstream DDR5 motherboards in the market. It also has a metallic heat sink to enhance heat dissipation.

Proven quality

Hermes DDR5 modules undergo a barrage of strict testing throughout the production process—including tests for compatibility, reliability, and other parameters of quality. Hermes comes with a limited lifetime warranty to bring you peace of mind.


Predator Advantage

Predator is a high-end gaming brand owned by the world-renowned PC manufacturer Acer. With a respected series of premium products for hardcore gamers and enthusiasts, Predator brand is recognized as a leader in the gaming community by experts and influencers. Under an official license, Predator storage and memory products are designed, built, and marketed by a specialist maker of SSDs. Meeting strict licensing conditions ensures each product lives up to the brand name.













Hermes RGB Memory

| SPECIFICATION | | | | | | | | | | | |
|---------------------|--------------------------------------|----------|----------|----------|----------|----------|----------|--|--|--|--|
| DIMM Type | DDR5 RGB UDIMM | | | | | | | | | | |
| Capacity | 32 GB: 16 GB x 2 64 GB: 32 GB x 2 | | | | | | | | | | |
| Frequency | 6400 MHz | 6600 MHz | 6800 MHz | 7200 MHz | 7600 MHz | 7800 MHz | 8000 MHz | | | | |
| Timing | CL32 | CL34 | CL32 | CL34 | CL36 | CL36 | CL36 | | | | |
| Working Voltage | 1.4 V | 1.4 V | 1.4 V | 1.4 V | 1.4 V | 1.45 V | 1.45 V | | | | |
| Working Temperature | 0 °C to 85 °C | | | | | | | | | | |
| Storage Temperature | -55 °C to 100 °C | | | | | | | | | | |
| Certifications | CE, FCC, RoHS, VCCI, RCM, BSMI | | | | | | | | | | |
| Warranty | Limited Lifetime | | | | | | | | | | |

Hermes Line-up

| Density | Speed | Rank | Timing | Voltage | Package (single capacity X number) | Model Number | Part Number | Color |
|---------|-------|------|----------------|---------|---------------------------------------|-------------------------|--------------|--------|
| 32 GB | 6400 | 1R*8 | CL32-39-39-102 | 1.4V | 16GBX2pcs | HERMES-32GB-6400-1R8-V1 | BL.9BWWR.390 | White |
| | 6400 | 1R*8 | CL32-39-39-102 | 1.4V | 16GBX2pcs | HERMES-32GB-6400-1R8-V2 | BL.9BWWR.391 | Black |
| | 6400 | 1R*8 | CL32-39-39-102 | 1.4V | 16GBX2pcs | HERMES-32GB-6400-1R8-V3 | BL.9BWWR.392 | Silver |
| | 6600 | 1R*8 | CL34-40-40-105 | 1.4V | 16GBX2pcs | HERMES-32GB-6600-1R8-V1 | BL.9BWWR.393 | White |
| | 6600 | 1R*8 | CL34-40-40-105 | 1.4V | 16GBX2pcs | HERMES-32GB-6600-1R8-V2 | BL.9BWWR.394 | Black |
| | 6600 | 1R*8 | CL34-40-40-105 | 1.4V | 16GBX2pcs | HERMES-32GB-6600-1R8-V3 | BL.9BWWR.395 | Silver |
| | 6800 | 1R*8 | CL32-45-45-108 | 1.4V | 16GBX2pcs | HERMES-32GB-6800-1R8-V4 | BL.9BWWR.399 | White |
| | 6800 | 1R*8 | CL32-45-45-108 | 1.4V | 16GBX2pcs | HERMES-32GB-6800-1R8-V5 | BL.9BWWR.400 | Black |
| | 6800 | 1R*8 | CL32-45-45-108 | 1.4V | 16GBX2pcs | HERMES-32GB-6800-1R8-V6 | BL.9BWWR.401 | Silver |
| | 7200 | 1R*8 | CL34-45-45-115 | 1.4V | 16GBX2pcs | HERMES-32GB-7200-1R8-V1 | BL.9BWWR.405 | White |
| | 7200 | 1R*8 | CL34-45-45-115 | 1.4V | 16GBX2pcs | HERMES-32GB-7200-1R8-V2 | BL.9BWWR.406 | Black |
| | 7200 | 1R*8 | CL34-45-45-115 | 1.4V | 16GBX2pcs | HERMES-32GB-7200-1R8-V3 | BL.9BWWR.407 | Silver |
| | 7600 | 1R*8 | CL36-46-46-121 | 1.4V | 16GBX2pcs | HERMES-32GB-7600-1R8-V1 | BL.9BWWR.408 | White |
| | 7600 | 1R*8 | CL36-46-46-121 | 1.4V | 16GBX2pcs | HERMES-32GB-7600-1R8-V2 | BL.9BWWR.409 | Black |
| | 7600 | 1R*8 | CL36-46-46-121 | 1.4V | 16GBX2pcs | HERMES-32GB-7600-1R8-V3 | BL.9BWWR.410 | Silver |
| | 7800 | 1R*8 | CL36-46-46-125 | 1.45 | 16GBX2pcs | HERMES-32GB-7800-1R8-V1 | BL.9BWWR.411 | White |
| | 7800 | 1R*8 | CL36-46-46-125 | 1.45 | 16GBX2pcs | HERMES-32GB-7800-1R8-V2 | BL.9BWWR.412 | Black |
| | 7800 | 1R*8 | CL36-46-46-125 | 1.45 | 16GBX2pcs | HERMES-32GB-7800-1R8-V3 | BL.9BWWR.413 | Silver |
| | 8000 | 1R*8 | CL36-48-48-126 | 1.45 | 16GBX2pcs | HERMES-32GB-8000-1R8-V1 | BL.9BWWR.414 | White |
| | 8000 | 1R*8 | CL36-48-48-126 | 1.45 | 16GBX2pcs | HERMES-32GB-8000-1R8-V2 | BL.9BWWR.415 | Black |
| | 8000 | 1R*8 | CL36-48-48-126 | 1.45 | 16GBX2pcs | HERMES-32GB-8000-1R8-V3 | BL.9BWWR.416 | Silver |
| 64 GB | 6400 | 2R*8 | CL32-39-39-102 | 1.4V | 32GBX2pcs | HERMES-64GB-6400-2R8-V1 | BL.9BWWR.423 | White |
| | 6400 | 2R*8 | CL32-39-39-102 | 1.4V | 32GBX2pcs | HERMES-64GB-6400-2R8-V2 | BL.9BWWR.424 | Black |
| | 6400 | 2R*8 | CL32-39-39-102 | 1.4V | 32GBX2pcs | HERMES-64GB-6400-2R8-V3 | BL.9BWWR.425 | Silver |

- 1. Maintenance and future updates are required throughout product life cycle. Specifications are subject to change without notice.
- 2. The pictures are for illustration only. Actual product may vary due to product enhancements or changes.
- 3. Not all products are sold in all regions of the world.
- 4. Instructions for purchasing high-frequency memory: high-overclocking memory needs to be equipped with a matching motherboard and processor to exert its overclocking performance. Please verify prior to purchase whether your motherboard and CPU support the specifications of Predator DRAM. Activate XMP after installation to enjoy the overclocking speed.
- 5. Please visit www.predatorstorage.com for more details.

















Acer Storage Customer Service Hotline in US: 1-866-351-8791

Acer Storage After-sales Service in US: Email: Storage.SupportUS@acer.com Chat: Go.Acer.com/US.Storage.Chat

Other Countries:

Email: CS@predatorstorage.com

