

Product Line
PA-RACK

Type
RM-PA-T12

Supported Models **PALO ALTO NETWORKS
ION 1200-S**

DIMENSIONS 1U

COLOR RAL 9005 Black

PRODUCT DIMENSIONS 44 x 482 x 217 mm
(height x width x depth) 1.73 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Remove the 3 bolts situated on the bottom of your Palo Alto.
2. Place your Palo Alto on the rack with the connectors facing the front, do this by slightly tilting the appliance and pushing first on the right and next on the left.
3. Fix the appliance with the 3 provided bolts from the bottom of the rack.
4. To install the power supply, put the zip ties through the designated holes, place the power supply on the rack between the zip ties and tighten firmly.
5. Guide the power cable true the designated hole and connect it to your Palo Alto device.
6. Secure the cable with the zip tie on the rack next to the power supply and tie the excess length of the power cable down with a zip tie.
7. Repeat step 4 to 6 in case a redundant power supply is used.
8. Place your PA-Rack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	PA-Rack
1	PA-Rack extension plate
9	Zip ties
3	Bolts UNC6-32



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

18-06-2024

EMEA Office
Nonnenveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
559 S Interstate 35, Suite 350
Round Rock - TX 78664
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT