

# Statement of Volatility-Dell Pro P 27 USB-C Hub Monitor

## P2726HE

**△ CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.**

The Dell P2726HE monitor contains both volatile and non-volatile (NV) components. Volatile components lose their data immediately after power is removed from the component. Non-volatile (NV) components continue to retain their data even after power is removed from the component. The following NV components are present on the P2726HE system board.

**Table 1. List of Non-Volatile Components on System Board**

**\*P2726HEt**

**\*\*P2726HEf**

Description	Reference Designator	Volatility Description	User Accessible for external data	Remedial Action (Action necessary to prevent loss of data)
*Serial Flash ROM W25Q32JVSSJQ	U302	Non-volatile Flash memory, 32M bit. To store scaler firmware.	No	Part placed on main interface board which is hardware/software write protected.
*Serial Flash ROM W25Q40RVSNJQ	U1909, U1910	Non-volatile Flash memory, 4M bit. To store intel HUB IC firmware.	No	Part placed on main interface board which is hardware/software write protected.
*Serial Flash ROM MX25V80066M1I02	U1303	Non-volatile Flash memory, 8M bit. To PD controller firmware.	No	Part placed on main interface board which is hardware/software write protected.
*EEPROM M24128-BRMN6TP	U303	Non-volatile memory, 128K bit. To store scaler data.	No	Part placed on main interface board which is hardware/software write protected.
**System EEPROM	U14	Non-volatile memory, 32 Kbit. For storage system setting.	No	Part placed on main interface board which is hardware/software write protected.
**System Flash ROM	U24	Non-volatile memory, 32 Mbit. For storage system firmware.	No	Part placed on main interface board which is hardware/software write protected.
**HUB Flash ROM	U1203	Non-volatile memory, 2 Mbit. For storage HUB firmware.	No	Part placed on main interface board which is hardware/software write protected.
**HUB Flash ROM	U1302	Non-volatile memory, 2 Mbit. For storage HUB firmware.	No	Part placed on main interface board which is hardware/software write protected.
**PD Flash ROM	U404	Non-volatile memory, 8 Mbit. For storage PD firmware.	No	Part placed on main interface board which is hardware/software write protected.

**△ CAUTION: All other components on the system board erase data if power is removed from the system.**

**Original Publish Date: March 2026 | A00**

Copyright © 2026 Dell Inc. or its subsidiaries. All Rights Reserved. Dell Technologies, Dell, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.