

Product Line
WG-RACK

Type
RM-WG-T5

Supported Models **WATCHGUARD
FIREBOX T35
FIREBOX T55**

DIMENSIONS 1.3/2U
COLOR WatchGuard Red
PACKING DIMENSIONS 80 x 520 x 270 mm
3.14 x 20.47 x 10.63 in
PRODUCT DIMENSIONS 57 x 482 x 217 mm
(height x width x depth) 2.24 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Place the power supply on the rack and tie it down with 2 zip ties.
2. Remove the bolt from the side of your WatchGuard Firebox T35/55 with the Torx Key.
3. Place your WatchGuard on the rack, fix the WatchGuard with the provided bolt and allen key on the side of the appliance.
4. Tie the excess length of the power cable down with the 3rd zip tie.
5. Remove the label from its carrier and place it above the connectors on the front.
6. Connect the cables from your WatchGuard to the connectors.
7. Place your WG-Rack in your 19 inch rack.
8. Place the Rackmount.IT front plate **BELOW** the WG-Rack in your 19 inch rack. Together they are 2U high.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	WG-Rack + RJ45 couplers + front plate
3	Zip ties
1	Adhesive label
7	Cables - 0.5 meter
1	Allen Key + Torx Key
1	Bolt M3x6mm

Industrial version is supplied with shielded couplers and cables



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 3 - 26-10-2018

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT