

Product Line
FORTIRACK

Type
RM-FR-T11
RM-FR-T11i

Supported Models **FORTIGATE 80E/81E**
FORTIGATE 70D
FORTIGATE 90D / 92D
FORTIGATE 90E / 91E

DIMENSIONS 1U
COLOR RAL 9003 White
PACKING DIMENSIONS 80 x 520 x 270 mm
3.14 x 20.47 x 10.63 in
PRODUCT DIMENSIONS 44 x 482 x 217 mm
(height x width x depth) 1.73 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Place the power supply on the rack and tie it down with the 2 zip ties.
2. Remove the 4 rubber feet from the bottom of the FortiGate.
3. Place your FortiGate on the rack & fix the FortiGate with the 2 bolts from the bottom and tighten it lightly.
4. Tie the excess length of the power cable down with the 3rd zip tie.
5. Connect the cables from your FortiGate to the connectors.
6. Optional: use two zip ties to hold the cables together.
7. Place your FortiRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	FortiRack + RJ45 couplers
5	Zip ties
2	Bolts M3x6mm
16	Cables - 0.5 meter

Industrial version is supplied with shielded couplers and cables



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 10 - 11-05-2021

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT