

SPECIFICATION

| | |
|---------------------------|--|
| Model Name | MEG X299 CREATION |
| CPU Support | Supports Intel® X-series Processors Family |
| CPU Socket | LGA 2066 |
| Chipset | Intel® X299 Chipset |
| Graphics Interface | 4 x PCI-E 3.0 x16 slots Support 4-way NVIDIA® SLI™ / 4-way AMD® CrossFire™ |
| Memory Support | 8 DIMMs, Quad Channel Max Frequency DDR4-4200+(OC) |
| Expansion Slots | 1 x PCI-E x1 slot |
| Storage | 3 x Turbo M.2 slots, 1 x Turbo U.2 8 x SATA 6Gb/s |
| USB Ports | 3 x USB 3.1 Gen 2 (Type A+C) 10 x USB 3.1 Gen 1 6 x USB 2.0 |
| LAN | Realtek RTL8125-CG 2.5G LAN + Intel® I219v Gigabit LAN |
| Wireless / BT | Intel® WIFI AC 9260 |
| Audio | 8-Channel (7.1) HD Audio with Audio Boost 4 |
| Form Factor | E-ATX |

FEATURE

Core Boost

With premium layout and fully digital power design to support more cores and provide better performance.

Triple 8 Pin Power Supply

By providing triple 8 pin connectors to ensure adequate power supply to unleash ultimate multi-core CPU performance.

M.2 SHIELD FROZR

Onboard M.2 thermal solution to keep M.2 SSDs safe while preventing throttling, making them run cooler & faster.

DDR4 Boost with Steel Armor

Fully isolated and shielded DIMM slots to deliver pure data signals for the best gaming performance and stability.

MULTI-GPU

Supports 4-way NVIDIA SLI™ and 4-way AMD CrossFire™ with optimal slot placement for the best airflow.

Triple Turbo M.2

Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.


BIOS Flashback+

Simply use a USB key to flash any BIOS within seconds, without installing a CPU, memory or graphics card.

Mystic Light RGB LED

Personalize your PC with 16.8 million colors / 29 effects, controlled in one click!

CONNECTIONS



1. Clear CMOS Button
2. PS/2 Port
3. USB 3.1 Gen1 Ports
4. 2.5G LAN Port
5. Intel® LAN Ports
6. Intel® WiFi/ Bluetooth Module
7. HD Audio Connectors
8. BIOS FLASHBACK+
9. USB 2.0 Ports
10. USB 3.1 Gen1 Ports
11. Lightning USB 3.1 Gen 2 Type A + C
12. Optical S/PDIF-Out