

Inspiron 3505

Setup and Specifications



Notes, cautions, and warnings

 **NOTE:** A NOTE indicates important information that helps you make better use of your product.

 **CAUTION:** A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.

Contents

Chapter 1: Set up your Inspiron 3505.....	4
Chapter 2: Views of Inspiron 3505.....	6
Right.....	6
Left.....	6
Top.....	7
Front.....	8
Bottom.....	9
Chapter 3: Specifications of Inspiron 3505.....	10
Dimensions and weight.....	10
Processor.....	10
Chipset.....	11
Operating system.....	11
Memory.....	11
External ports.....	12
Internal slots.....	12
Ethernet.....	12
Wireless module.....	13
Audio.....	13
Storage.....	14
Media-card reader.....	14
Keyboard.....	14
Camera.....	15
Touchpad.....	15
Power adapter.....	16
Battery.....	16
Display.....	17
Fingerprint reader (optional).....	18
GPU—Integrated.....	18
Operating and storage environment.....	18
Chapter 4: Keyboard shortcuts.....	20
Chapter 5: Getting help and contacting Dell.....	23

Set up your Inspiron 3505

i **NOTE:** The images in this document may differ from your computer depending on the configuration you ordered.

1. Connect the power adapter and press the power button.



i **NOTE:** The battery may go into power-saving mode during shipment to conserve charge on the battery. Ensure that the power adapter is connected to your computer when it is turned on for the first time.

2. Finish Windows setup.

Follow the on-screen instructions to complete the setup. When setting up, Dell recommends that you:

- Connect to a network for Windows updates.
- **i** **NOTE:** If connecting to a secured wireless network, enter the password for the wireless network access when prompted.
- If connected to the Internet, sign in with or create a Microsoft account. If not connected to the Internet, create an offline account.
- On the **Support and Protection** screen, enter your contact details.

3. Locate and use Dell apps from the Windows Start menu—Recommended.

Table 1. Locate Dell apps

Resources	Description
	My Dell Centralized location for key Dell applications, help articles, and other important information about your computer. It also notifies you about the warranty status, recommended accessories, and software updates if available.
	SupportAssist SupportAssist proactively and predictively identifies hardware and software issues on your computer and automates the engagement process with Dell Technical support. It addresses performance and stabilization issues, prevents security threats, monitors and detects hardware failures. For more information, see SupportAssist for Home PCs User's Guide on www.dell.com/

Table 1. Locate Dell apps (continued)

Resources	Description
	<p>serviceabilitytools. To navigate to SupportAssist for Home PCs User's Guide, click SupportAssist and then, click SupportAssist for Home PCs User's Guide.</p> <p>(i) NOTE: In SupportAssist, click the warranty expiry date to renew or upgrade your warranty.</p>
	<p>Dell Update</p> <p>Updates your computer with critical fixes and latest device drivers as they become available. For more information about using Dell Update, see the knowledge base article SLN305843 at www.dell.com/support.</p>
	<p>Dell Digital Delivery</p> <p>Download software applications, which are purchased but not pre-installed on your computer. For more information about using Dell Digital Delivery, see the knowledge base article 153764 at www.dell.com/support.</p>

Views of Inspiron 3505

Right



1. SD-card slot

Reads from and writes to the SD card. The computer supports the following card types:

- Secure Digital (SD)
- Secure Digital High Capacity (SDHC)
- Secure Digital Extended Capacity (SDXC)


2. USB 2.0 port

Connect devices such as external storage devices and printers. Provides data transfer speeds up to 480 Mbps.

3. Security-cable slot (wedge-shaped)

Connect a security cable to prevent unauthorized movement of your computer.

Left



1. Power-adapter port

Connect a power adapter to provide power to your computer and charge the battery.

2. Power and battery-status light/hard-drive activity light

Indicates the battery-charge status or the hard-drive activity.

i **NOTE:** Press Fn+H to switch between the power and battery-status light, and hard-drive activity light.

Hard-drive activity light

Turns on when the computer reads from or writes to the hard drive.

Power and battery-status light

Indicates the power and battery-charge status.

Solid white—Power adapter is connected and the battery has more than 5% charge.

Amber—Computer is running on battery and the battery has less than 5% charge.

Off

- Power adapter is connected, and the battery is fully charged.
- Computer is running on battery, and the battery has more than 5% charge.
- Computer is in sleep state, hibernation, or turned off.

3. HDMI port

Connect to a TV, external display or another HDMI-in enabled device. Provides video and audio output.

(i) NOTE: The maximum resolution supported by the HDMI port is 1920 x 1080 at 60 Hz (24-bit).

4. Network port

Connect an Ethernet (RJ45) cable from a router or a broadband modem for network or Internet access.

5. USB 3.2 Gen 1 ports (2)

Connect devices such as external storage devices and printers. Provides data transfer speeds up to 5 Gbps.

6. Headset jack

Connect headphones or a headset (headphone and microphone combo).

Top



1. Touchpad

Move your finger on the touchpad to move the mouse pointer. Tap to left-click and two fingers tap to right-click.

2. Left-click area

Press to left-click.

3. Right-click area

Press to right-click.

4. Power button with optional fingerprint reader

Press to turn on the computer if it is turned off, in sleep state, or in hibernate state.

When the computer is turned on, press the power button to put the computer into sleep state; press and hold the power button for 10 seconds to force shut-down the computer.

If the power button has a fingerprint reader, place your finger on the power button to log in.

(i) NOTE: You can customize power-button behavior in Windows. For more information, see *Me and My Dell* at www.dell.com/support/manuals.

(i) NOTE: The power-status light on the power button is available only on computers without the fingerprint reader. Computers that are shipped with the fingerprint reader that is integrated on the power button will not have the power-status light on the power button.

(i) NOTE: To reset the battery, press and hold the power button for 25 seconds.

Front



1. Camera

Enables you to video chat, capture photos, and record videos.

2. Camera-status light

Turns on when the camera is in use.

3. Microphone

Provides digital sound input for audio recording, voice calls, and so on.

Bottom



1. Left speaker

Provides audio output.

2. Service Tag label

The Service Tag is a unique alphanumeric identifier that enables Dell service technicians to identify the hardware components in your computer and access warranty information.

3. Right speaker

Provides audio output.

Specifications of Inspiron 3505

Dimensions and weight

The following table lists the height, width, depth, and weight of your Inspiron 3505.

Table 2. Dimensions and weight

Description	Values
Height:	
Front height	18 mm (0.71 in.)
Rear height	19.89 mm (0.78 in.)
Width	363.96 mm (14.33 in.)
Depth	249 mm (9.80 in.)
Weight (maximum)	<ul style="list-style-type: none"> Touchscreen: 1.98 kg (4.36 lb) Non-touchscreen: 1.96 kg (4.32 lb) <p>i NOTE: The weight of your computer depends on the configuration ordered and manufacturing variability.</p>

Processor

The following table lists the details of the processors supported by your Inspiron 3505.

Table 3. Processor

Description	Option one	Option two	Option three	Option Four	Option Five	Option Six
Processor type	AMD Ryzen 3 3250U	AMD Ryzen 5 3450U	AMD Ryzen 5 3500U	AMD Ryzen 7 3700U	AMD Athlon Silver 3050U	AMD Athlon Gold 3150U
Processor wattage	15 W	15 W	15 W	15 W	15 W	15 W
Processor core count	2	4	4	4	2	2
Processor thread count	4	8	8	8	2	4
Processor speed	Up to 3.5 GHz	Up to 3.5 GHz	Up to 3.7 GHz	Up to 4 GHz	Up to 3.2 GHz	Up to 3.3 GHz
Processor cache	4 MB	4 MB	4 MB	4 MB	4 MB	4 MB
Integrated graphics	AMD Radeon Graphics	AMD Radeon Vega 8 Graphics	AMD Radeon Vega 8 Graphics	AMD Radeon RX Vega 10 Graphics	AMD Radeon Graphics	AMD Radeon Graphics

Chipset

The following table lists the details of the chipset supported by your Inspiron 3505.

Table 4. Chipset

Description	Values
Chipset	Integrated
Processor	<ul style="list-style-type: none">• AMD Ryzen 3/5/7• AMD Athlon Gold/Silver
DRAM bus width	64-bit
Flash EPROM	16 MB
PCIe bus	Up to Gen3.0

Operating system

Your Inspiron 3505 supports the following operating systems:

- Windows 10 Home, 64-bit
- Windows 10 Pro, 64-bit
- Windows 10 S-mode, 64-bit

Memory

The following table lists the memory specifications of your Inspiron 3505.

Table 5. Memory specifications

Description	Values
Memory slots	Two-SODIMM slots
Memory type	DDR4
Memory speed	2400 MHz
Maximum memory configuration	16 GB
Minimum memory configuration	4 GB
Memory size per slot	4 GB, 8 GB, 12 GB, 16 GB
Memory configurations supported	<ul style="list-style-type: none">• 4 GB, 1 x 4 GB, DDR4, 2400 MHz• 8 GB, 1 x 8 GB, DDR4, 2400 MHz• 16 GB, 1 x 16 GB, DDR4, 2400 MHz• 8 GB, 2 x 4 GB, DDR4, 2400 MHz• 12 GB, 1 x 8 GB + 1 x 4 GB, DDR4, 2400 MHz• 16 GB, 2 x 8 GB, DDR4, 2400 MHz

External ports

The following table lists the external ports of your Inspiron 3505.

Table 6. External ports

Description	Values
Network port	One RJ-45 port
USB ports	<ul style="list-style-type: none">One USB 2.0 portTwo USB 3.2 Gen 1 ports
Audio port	One headset jack NOTE: The 3.5 mm headset jack functionality varies by model configuration. For best results, use Dell recommended audio accessories.
Video port	One HDMI 1.4 port NOTE: The maximum resolution supported by the HDMI port is 1920 x 1080 at 60 Hz (24-bit).
Media-card reader	One SD-card slot
Power-adapter port	One 4.5 mm x 2.9 mm DC-in
Security-cable slot	One security-cable slot (wedge-shaped)

Internal slots

The following table lists the internal slots of your Inspiron 3505.

Table 7. Internal slots

Description	Values
M.2	<ul style="list-style-type: none">One M.2 2230 slot for WiFi and Bluetooth combo cardOne M.2 2230/2280 slot for solid-state drive NOTE: To learn more about the features of different types of M.2 cards, see the knowledge base article 000144170 at www.dell.com/support .

Ethernet

The following table lists the wired Ethernet Local Area Network (LAN) specifications of your Inspiron 3505.

Table 8. Ethernet specifications

Description	Values
Model number	Realtek RTL 8106E, PCI-e ethernet controller
Transfer rate	10/100 Mbps

Wireless module

The following table lists the Wireless Local Area Network (WLAN) modules supported on your Inspiron 3505.

Table 9. Wireless module specifications

Description	Option one	Option two
Model number	Realtek RTL8723DE	Qualcomm QCA9377 (DW1810)
Transfer rate	Up to 150 Mbps	Up to 433 Mbps
Frequency bands supported	2.4 GHz	2.4 GHz/5 GHz
Wireless standards	<ul style="list-style-type: none">Wi-Fi 802.11 a/b/gWi-Fi 4 (WiFi 802.11n)	<ul style="list-style-type: none">Wi-Fi 802.11 a/b/gWi-Fi 4 (WiFi 802.11n)Wi-Fi 5 (WiFi 802.11ac)
Encryption	<ul style="list-style-type: none">64-bit/128-bit WEPAES-CCMPTKIP	<ul style="list-style-type: none">64-bit/128-bit WEPAES-CCMPTKIP
Bluetooth	Bluetooth 4.2	Bluetooth 5.0

Audio

The following table lists the audio specifications of your Inspiron 3505.

Table 10. Audio specifications

Description	Values
Audio controller	<ul style="list-style-type: none">Realtek ALC3204Cirrus Logic CS8409 (CS42L42+SN005825)
Stereo conversion	Supported
Internal audio interface	High definition audio
External audio interface	Headset jack NOTE: The 3.5 mm headset jack functionality varies by model configuration. For best results, use Dell recommended audio accessories.
Number of speakers	Two
Internal-speaker amplifier	Supported
External volume controls	Keyboard shortcut controls
Speaker output:	
	Average speaker output
	2 W
	Peak speaker output
	2.5 W
Subwoofer output	Not supported
Microphone	Single digital microphone

Storage

This section lists the storage options on your Inspiron 3505.

Your Inspiron 3505 supports one of the following storage configurations:

- One 2.5-inch hard-drive
- One M.2 2230/2280 solid-state drive
- One 2.5-inch hard-drive and one M.2 2230/2280 solid-state drive

The primary drive of your Inspiron 3505 varies with the storage configuration. For computers:

- with a M.2 drive, the M.2 drive is the primary drive
- without a M.2 drive, the 2.5-inch hard drive is the primary drive

Table 11. Storage specifications

Storage type	Interface type	Capacity
2.5-inch hard-disk drive	SATA AHCI, up to 6 Gbps	Up to 2 TB
M.2 2230 solid-state drive	PCIe Gen3.0x4 NVMe, up to 32 Gbps	Up to 512 GB
M.2 2280 solid-state drive	PCIe Gen3.0x4 NVMe, up to 32 Gbps	Up to 1 TB

Media-card reader

The following table lists the media cards supported by your Inspiron 3505.

Table 12. Media-card reader specifications

Description	Values
Media-card type	One SD card slot
Media-cards supported	<ul style="list-style-type: none">• Secure Digital (SD)• Secure Digital High Capacity (SDHC)• Secure Digital Extended Capacity (SDXC)
(i) NOTE: The maximum capacity supported by the media-card reader varies depending on the standard of the media card installed in your computer.	

Keyboard

The following table lists the keyboard specifications of your Inspiron 3505.

Table 13. Keyboard specifications

Description	Values
Keyboard type	<ul style="list-style-type: none">• Standard keyboard• Standard backlit keyboard
Keyboard layout	QWERTY
Number of keys	<ul style="list-style-type: none">• United States and Canada: 101 keys• United Kingdom: 102 keys• Japan: 105 keys
Keyboard size	X=18.7 mm key pitch

Table 13. Keyboard specifications (continued)

Description	Values
	Y=18.05 mm key pitch
Keyboard shortcuts	<p>Some keys on your keyboard have two symbols on them. These keys can be used to type alternate characters or to perform secondary functions. To type the alternate character, press Shift and the desired key. To perform secondary functions, press Fn and the desired key.</p> <p>NOTE: You can define the primary behavior of the function keys (F1–F12) changing Function Key Behavior in BIOS setup program.</p> <p>For more information, see Keyboard shortcuts.</p>

Camera

The following table lists the camera specifications of your Inspiron 3505.

Table 14. Camera specifications

Description	Values
Number of cameras	One
Camera type	HD RGB camera
Camera location	Front camera
Camera sensor type	CMOS sensor technology
Camera resolution:	
Still image	0.92 megapixel
Video	1280 x 720 (HD) at 30 fps
Diagonal viewing angle:	78.6 degrees

Touchpad

The following table lists the touchpad specifications of your Inspiron 3505.

Table 15. Touchpad specifications

Description	Values
Touchpad resolution:	
Horizontal	1230
Vertical	750
Touchpad dimensions:	
Horizontal	104.40 mm
Vertical	64.40 mm

Table 15. Touchpad specifications (continued)

Description	Values
Touchpad gestures	For more information about touchpad gestures available on Windows 10, see the Microsoft knowledge base article 4027871 at support.microsoft.com .

Power adapter

The following table lists the power adapter specifications of your Inspiron 3505.

Table 16. Power adapter specifications

Description	Values
Type	45 W
Connector dimensions:	
External diameter	4.50 mm
Internal diameter	2.90 mm
Input voltage	100 VAC–240 VAC
Input frequency	50 Hz–60 Hz
Input current (maximum)	1.30 A
Output current (continuous)	2.31 A
Rated output voltage	19.50 VDC
Temperature range:	
Operating	0°C to 40°C (32°F to 104°F)
Storage	-40°C to 70°C (-40°F to 158°F)

 **CAUTION:** Operating and storage temperature ranges may differ among components, so operating or storing the device outside these ranges may impact the performance of specific components.

Battery

The following table lists the battery specifications of your Inspiron 3505.

Table 17. Battery specifications

Description	Values
Battery type	3-cell polymer, 42 Whr
Battery voltage	11.40 VDC
Battery weight (maximum)	0.20 kg (0.44 lb)
Battery dimensions:	
Height	184.15 mm (7.25 in.)

Table 17. Battery specifications (continued)

Description		Values
	Width	97.15 mm (3.82 in.)
	Depth	5.90 mm (0.23 in.)
Temperature range:		
	Operating	0°C to 35°C (32°F to 95°F)
	Storage	-40°C to 65°C (-40°F to 149°F)
Battery operating time		Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.
Battery charging time (approximate) NOTE: Control the charging time, duration, start and end time, and so on using the Dell Power Manager application. For more information on the Dell Power Manager see, <i>Me and My Dell</i> on www.dell.com .		3 hours (when the computer is off) NOTE: Control the charging time, duration, start and end time, and so on using the Dell Power Manager application. For more information on the Dell Power Manager see, <i>Me and My Dell</i> on www.dell.com /
Coin-cell battery		CR2032
CAUTION: Operating and storage temperature ranges may differ among components, so operating or storing the device outside these ranges may impact the performance of specific components.		

Display

The following table lists the display specifications of your Inspiron 3505.

Table 18. Display specifications

Description	Option one	Option two	Option three
Display type	High Definition (HD)	Full High Definition (FHD)	Full High Definition (FHD)
Display-panel technology	Twisted Nematic (TN)	Wide-Viewing Angle (WVA)	Wide-Viewing Angle (WVA)
Display-panel dimensions (active area):			
Height	193.54 mm (7.62 in.)	193.54 mm (7.62 in.)	193.54 mm (7.62 in.)
Width	344.23 mm (13.55 in.)	344.23 mm (13.55 in.)	344.23 mm (13.55 in.)
Diagonal	394.90 mm (15.55 in.)	394.90 mm (15.55 in.)	394.90 mm (15.55 in.)
Display-panel native resolution	1366 x 768	1920 x 1080	1920 x 1080
Luminance (typical)	220 nits	220 nits	220 nits
Megapixels	1.05	2.07	2.07
Color gamut	45% (NTSC)	45% (NTSC)	45% (NTSC)
Pixels Per Inch (PPI)	100	141	141
Contrast ratio (typ)	400:1	400:1	600:1

Table 18. Display specifications (continued)

Description	Option one	Option two	Option three
Response time (max)	25 ms	35 ms	35 ms
Refresh rate	60 Hz	60 Hz	60 Hz
Horizontal view angle	40 +/- degrees	80 +/- degrees	80 +/- degrees
Vertical view angle	+10/-30 degrees	80 +/- degrees	80 +/- degrees
Pixel pitch	0.25 mm	0.18 mm	0.18 mm
Power consumption (maximum)	4.20 W	4.2 W	4.6 W
Anti-glare vs glossy finish	Anti-glare	Anti-glare	Anti-glare
Touch options	No	No	Yes

Fingerprint reader (optional)

The following table lists the specifications of the optional fingerprint-reader of your Inspiron 3505.

Table 19. Fingerprint reader specifications

Description	Values
Fingerprint-reader sensor technology	Capacitive
Fingerprint-reader sensor resolution	500 dpi
Fingerprint-reader sensor pixel size	64 x 80

GPU—Integrated

The following table lists the specifications of the integrated Graphics Processing Unit (GPU) supported by your Inspiron 3505.

Table 20. GPU—Integrated

Controller	External display support	Memory size	Processor
AMD Radeon Vega 8 Graphics	One HDMI 1.4 port	Shared system memory	AMD Ryzen 5
AMD Radeon RX Vega 10 Graphics	One HDMI 1.4 port	Shared system memory	AMD Ryzen 7
AMD Radeon Graphics	One HDMI 1.4 port	Shared system memory	<ul style="list-style-type: none"> • AMD Ryzen 3 • AMD Athlon Gold/Silver

Operating and storage environment

This table lists the operating and storage specifications of your Inspiron 3505.

Airborne contaminant level: G1 as defined by ISA-S71.04-1985

Table 21. Computer environment

Description	Operating	Storage
Temperature range	0°C to 35°C (32°F to 95°F)	-40°C to 65°C (-40°F to 149°F)
Relative humidity (maximum)	10% to 90% (non-condensing)	0% to 95% (non-condensing)
Vibration (maximum)*	0.66 GRMS	1.30 GRMS
Shock (maximum)	110 G†	160 G†
Altitude range	-15.2 m to 3048 m (-49.87 ft to 10000 ft)	-15.2 m to 10668 m (-49.87 ft to 35000 ft)

 **CAUTION:** Operating and storage temperature ranges may differ among components, so operating or storing the device outside these ranges may impact the performance of specific components.

* Measured using a random vibration spectrum that simulates user environment.

† Measured using a 2 ms half-sine pulse when the hard drive is in use.

Keyboard shortcuts

i **NOTE:** Keyboard characters may differ depending on the keyboard language configuration. Keys used for shortcuts remain the same across all language configurations.

Some keys on your keyboard have two symbols on them. These keys can be used to type alternate characters or to perform secondary functions. The symbol shown on the lower part of the key refers to the character that is typed out when the key is pressed. If you press shift and the key, the symbol shown on the upper part of the key is typed out. For example, if you press **2**, **2** is typed out; if you press **Shift + 2**, **@** is typed out.

The keys F1-F12 at the top row of the keyboard are function keys for multi-media control, as indicated by the icon at the bottom of the key. Press the function key to invoke the task represented by the icon. For example, pressing F1 mutes the audio (refer to the table below).





However, if the function keys F1-F12 are needed for specific software applications, multi-media functionality can be disabled by pressing **fn + Esc**. Subsequently, multi-media control can be invoked by pressing **fn** and the respective function key. For example, mute audio by pressing **fn + F1**.

i **NOTE:** You can also define the primary behavior of the function keys (F1-F12) by changing **Function Key Behavior** in BIOS setup program.

Table 22. List of keyboard shortcuts

Function key	Redefined key (for multimedia control)	Behavior
 F1	fn +  F1	Mute audio
 F2	fn +  F2	Decrease volume
 F3	fn +  F3	Increase volume
 F4	fn +  F4	Play/Pause
 F5	fn +  F5	Toggle keyboard backlight (optional) NOTE: Non-backlight keyboards have F5 function key without the backlight icon and does not support toggle keyboard backlight function.
 F6	fn +  F6	Decrease brightness

Table 22. List of keyboard shortcuts (continued)

Function key	Redefined key (for multimedia control)	Behavior
 F7	fn + 	Increase brightness
 F8	fn + 	Switch to external display
 F10	fn + 	Print screen
 F11	fn + 	Home
 F12	fn + 	End

The **fn** key is also used with selected keys on the keyboard to invoke other secondary functions.

Table 23. List of keyboard shortcuts



Function key	Behavior
fn + 	Pause/Break
fn + 	Toggle scroll lock
fn + 	System request
fn + 	Open application menu
fn + 	Toggle fn-key lock
fn + 	Emoji
fn + 	Page up

Table 23. List of keyboard shortcuts (continued)

Function key	Behavior
 + 	Page down

Getting help and contacting Dell

Self-help resources

You can get information and help on Dell products and services using these self-help resources:

Table 24. Self-help resources

Self-help resources	Resource location
Information about Dell products and services	www.dell.com
My Dell app	
Tips	
Contact Support	In Windows search, type Contact Support , and press Enter.
Online help for operating system	www.dell.com/support/windows
Access top solutions, diagnostics, drivers and downloads, and learn more about your computer through videos, manuals and documents.	<p>Your Dell computer is uniquely identified by a Service Tag or Express Service Code. To view relevant support resources for your Dell computer, enter the Service Tag or Express Service Code at www.dell.com/support.</p> <p>For more information on how to find the Service Tag for your computer, see Locate the Service Tag on your computer.</p>
Dell knowledge base articles for a variety of computer concerns	<ol style="list-style-type: none"> 1. Go to www.dell.com/support. 2. On the menu bar at the top of the Support page, select Support > Knowledge Base. 3. In the Search field on the Knowledge Base page, type the keyword, topic, or model number, and then click or tap the search icon to view the related articles.

Contacting Dell

To contact Dell for sales, technical support, or customer service issues, see www.dell.com/contactdell.

 **NOTE:** Availability varies by country/region and product, and some services may not be available in your country/region.

 **NOTE:** If you do not have an active Internet connection, you can find contact information about your purchase invoice, packing slip, bill, or Dell product catalog.