

Inversor de 150W 12V para 230V com porta USB de 2.1A

Alimente e carregue os seus dispositivos enquanto viaja



EW3990 8054392611414

OVERVIEW

- Inversor de 12 Volts DC para 230 Volts AC
- · Ligue à tomada de isqueiro do seu veículo
- · Porta USB de 2,1A incorporada para carregar/alimentar o seu smartphone, tablet e outros dispositivos alimentados por USB
- Potência de saída 150 Watts
- Encaixa no suporte para copos do seu veículo
- · Com proteção contra sub e sobretensão, sobrecarga, sobreaquecimento e curto circuito

SPECIFICATIONS

• 2 YEAR WARRANTY

- Continuous Power: 150W
- Peak Power: 300W
- Input Voltage: DC 11-15V (Max 15A)
- Output Voltage: AC 230V +/-10%
- USB: DC 5V (Max 2100mA)
- Sine wave: Modified
- Frequency: 50+/-3Hz
- Under voltage shutdown: 10.8V or lower
- Over voltage shutdown: 15V or higher
- · Child protection: Yes
- Under/over voltage protection: Yes
- Over temperature protection: Yes
- Short circuit protection: Yes
- · Overload protection: Yes
- Max. amperage: 15A when using 150W powered device
- No load current: 0.45A

SYSTEM REQUIREMENTS

Converter: No Power Strip: No Power supplies: No UPS: No

QUALITY · VALUE · DESIGN · ③ HELPDESK · 5 YEARS WARRANTY

www.ewent-online.com



Inversor de 150W 12V para 230V com porta USB de 2.1A Alimente e carregue os seus dispositivos enquanto viaja

DESCRIPTION

QUALITY · VALUE · DESIGN · ③ HELPDESK · 5 YEARS WARRANTY

www.ewent-online.com



Inversor de 150W 12V para 230V com porta USB de 2.1A

Alimente e carregue os seus dispositivos enquanto viaja

IMAGES













QUALITY · VALUE · DESIGN · **()** HELPDESK · 5 YEARS WARRANTY

www.ewent-online.com



QUALITY · VALUE · DESIGN · O HELPDESK · 5 YEARS WARRANTY

www.ewent-online.com

All data and pictures in this data sheet have been created and their accuracy verified. No rights may be derived from in accurately presented content





QUALITY · VALUE · DESIGN · O HELPDESK · 5 YEARS WARRANTY

www.ewent-online.com

All data and pictures in this data sheet have been created and their accuracy verified. No rights may be derived from in accurately presented content