

MOTHERBOARD X299 XPOWER GAMING AC

X FOR XTREME





SPECIFICATIONS

Model Name X299 XPOWER GAMING AC Segment **Enthusiast GAMING**

CPU support Supports New Intel® Core™ X-series Processor Family

CPU socket LGA 2066

Chipset Intel® X299 Chipset 4 x PCI-E 3.0 x16 slots Graphics Interface 4-way SLI / CrossFire

8 DIMMs, Quad Channel DDR4-4133+(OC)MHz, Dual Channel Memory support

DDR4-4500+(OC)MHz Expansion slots 1 x PCI-E 3.0 x1 slot

10x SATA 6Gb.s ports, 3x Turbo M.2 slots, 1x Turbo U.2 SATA / M.2 / U.2

connector

Intel® Optane™ Intel® Optane™ Memory Ready USB 3.1 Gen2 3 x USB 3.1 Gen2 (Type A+C)

USB 3.1 Gen1 10 x USB 3.1 Gen1 USB 2.0 6 x USB 2.0

IAN Intel® I219-V Gigabit LAN, Intel® I211-AT Gigabit LAN Audio 7.1 Channel High Definition Audio with S/PDIF

Form Factor E-ATX

FEATURES

- 1. 12+1+1 PHASE DIGITAL POWER DESIGN WITH DrMOS; premium power phases ensure a clean, stable and optimized power delivery for the high-end processor.
- 2. MYSTIC LIGHT and MYSTIC LIGHT SYNC; personalize your PC with 16.8 million colors / 17 effects controlled in one click with the Mystic Light APP or a mobile device.
- 3. M.2 SHIELD FROZR: strengthened built-in M.2 thermal solution. Keeps M.2 SSDs safe while preventing throttling, making them run faster.
- 4. 3D PRINTING Support: modify and customize your system with 3D printed materials using the special 3D print screws.
- 5. DUAL GAMING LAN with Wireless support, powered by Intel®; the best solution for both Intranet, Internet and wireless demands by offering the lowest latency.
- 6. VROC WITH M.2 XPENDER-Z: build the prompt OS disk with 2X fast M.2 devices in RAID 0 from processors directly.
- 7. TURBO SOCKET with GAME BOOST; allows for additional tuning of Ring voltages for no limits overclocking and one second automated overclocking, GAME BOOST.
- 8. Lightning Fast Game experience: speed up when loading with 3X TURBO M.2, Turbo U.2 and LIGHTNING USB 3.1 GEN2

REAR CONNECTORS

1. Clear CMOS Button 8. BIOS Flashback Button

2. Keyboard / Mouse 9. USB 2.0 / BIOS Flashback+

This datasheet was generated on Jule 18 July 1

7. Golden Audio Connectors

