

## Replacement Universal AC/DC Power Adapter with NA Power Cord for Docking Stations DK30C2DPEP, DK30C2DPPD and DK31C3HDPD - 150W (19.5V/2.5A)

**Product ID:** 158-DOCKPOWERADAPTER



This 150W AC/DC power supply can provide a power source for any electronic device that has an N-type barrel and requires 19.5 volts and up to 2.5 amps of power.

The power supply is a perfect replacement for the lost or damaged 19.5-volt 2.5-amp power adapter you've used to power your existing electronics.

When downtime isn't an option, keeping spare power adapters on hand ensures that you won't be left waiting for a replacement to arrive or have to replace your devices just for the sake of a compatible power source.

This 19.5V 2.5A DC power supply is a direct replacement for the power adapters included with the following StarTech.com products:

DK30C2DPEP Laptop Docking Station

DK30C2DPPD Laptop Docking Station

DK31C3HDPD Laptop Docking Station

This product is backed for 3-years by StarTech.com, including free lifetime 24/5 multi-lingual technical assistance.

### Certifications, Reports and Compatibility



### Applications

- Replace a lost or broken 19.5V DC power supply
- Keep an extra power adapter on hand for your mission-critical devices

## Features

- **REPLACEMENT POWER ADAPTER:** Replaces the power adapter included with models of StarTech.com docking stations
- **WORKS WITH:** DK30C2DPEP, DK30C2DPPD and DK31C3HDPD laptop docking stations
- **TECHNICAL SPECIFICATIONS:** 150W Power Adapter - 100 - 240 AC Input Voltage - 19.5V Output Voltage - 2.5A Output Current - NEMA 1-15P - N-Barrel Connector (5.5 mm outside diameter / 2.5 mm inside diameter)
- **THE IT PRO'S CHOICE:** Designed and built for IT Professionals, this power adapter is backed for 3-years including free lifetime 24/5 multi-lingual technical assistance

---

### Power

Warranty	3 Years
Power Source	AC Adapter Included
Input Voltage Frequency	50 - 60Hz
Max Inrush Current	29% margin of the I <sup>2</sup> T (Ampere Squared Seconds) rating of the input fuse and bridge rectifier
Input Voltage	100 - 240 AC
Input Current	2.5
Output Voltage	19.5V DC
Output Current	7.7A
Center Tip Polarity	Positive
Plug Type	N
Power Consumption (In Watts)	150

---

### Physical Characteristics

Product Length	0.0 in [0.0 mm]
Product Width	0.0 in [0.0 mm]

Product Height	0.0 in [0.0 mm]
Weight of Product	0.0 oz [0.0 g]

---

#### Packaging Information

Package Length	4.1 in [10.4 cm]
Package Width	3.5 in [8.9 cm]
Package Height	2.4 in [6.0 cm]
Shipping (Package) Weight	7.4 oz [210.0 g]

---

#### What's in the Box

Included in Package	1 - universal power adapter (NA)
---------------------	----------------------------------

---

***\*Product appearance and specifications are subject to change without notice.***

