## reelink

| Picture            | resirk                 |  |
|--------------------|------------------------|--|
| Model              | Go Series G330         |  |
| Video & Audio      | Image Sensor           | 1/2.7" CMOS sensor   |
|                    | Resolution             | 2560 x 1440 (4MP) @15FPS   |
|                    | Video Compres-<br>sion | H.265  |
|                    | Field of View          | Horizontal: 105°   |
|                    |                        | Vertical: 55°  |
|                    |                        | Diagonal: 125°   |
|                    | Infrared Night Vision  | Up to 10 meters (33ft); LED:<br>6pcs/14mil/850nm<br>(Auto-switching with IR-cut filter)  |
|                    |                        | (Adto-switching with IR-cut filter)  |
|                    | Frame Rate             | Main stream: 10fps - 15fps (default: 15fps)  |
|                    |                        | Sub stream: 10fps - 15fps (default: 15fps)   |
|                    | Code Rate              | Main stream: 1024Kbps - 4096Kbps<br>(default: 3072Kbps)                                  |
|                    |                        | Sub stream: 64Kbps - 672Kbps (default: 672Kbps)  |
|                    | Audio                  | Two-way audio  |
| Power Requirements | Battery                | 28Wh rechargeable battery (Battery life varies based on settings, usage & temper-ature.) |
|                    | Solar                  | Reolink Solar Panel 2 (6W)   |
| Interface          | Power Port             | USB Type-C port  |
|                    | SD Card Slot           | Supports Max. 128GB microSD card   |
|                    | SIM Card Slot          | Nano   |
|                    | Reset Button           | YES  |
|                    | Audio In/Out           | Built-in microphone and speaker  |
| 3G/4G              | Frequency Bands        | • <b>Europe:</b><br>LTE FDD: B1/B3/B7/B8/B20/B28A<br>WCDMA: B1/B8                        |

## reelink

| Picture                  | resirk                       |  |
|--------------------------|------------------------------|--|
| Model                    | Go Series G330               |  |
| Software                 | OS Supported                 | PC: Windows, Mac OS; Smartphone: iOS,<br>Android                                   |
|                          | Protocols & Stand-<br>ards   | SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P   |
|                          | User Access                  | Max. 12 simultaneous streams (2 main & 10 sub streams)                             |
| Other Fea-<br>tures      | Smart Alarm                  | PIR detection; person detection; vehicle detection; animal detection               |
|                          | PIR Detecting Dis-<br>tance  | Adjustable up to 10m (33ft)  |
|                          | PIR Detecting Angle          | 120° horizontal  |
|                          | Recording Modes              | Triggered recording  |
|                          | Time Lapse                   | YES  |
|                          | Smart Home<br>Compatibility  | Google Assistant; Alxea  |
|                          | Cloud Storage                | Supports Reolink Cloud (available in selected countries)                           |
| Working En-<br>vironment | Operating Tem-<br>perature   | -10°C~+55°C (14°F~131°F)   |
|                          | Operating Hu-<br>midity      | 20% ~ 85%  |
|                          | Weatherproof                 | IP65   |
| Mechanical               | Dimensions                   | Φ 194*75 mm  |
|                          | Weight (Battery<br>Included) | 450g   |
| Warranty                 | Limited Warranty             | 2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/. |