

Product Line
TP-RACK

Type
RM-OM-T2

Supported Models **ER706**
ER706W-4G
WITH OPTIONAL OC200

DIMENSIONS 1U

COLOR RAL 9005 Black

PRODUCT DIMENSIONS 44 x 482 x 217 mm
(height x width x depth) 1.73 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Slide your appliance from behind through the brackets on the left side and push up the small plate behind to secure it.
2. Plug the power cable in and secure the cable with 1 zip tie. The zip tie goes through the 2 small holes behind the appliance.
3. Optional: Remove the metal circles on the front of the rack with a screwdriver and a hammer and connect the pigtails from the back of the FortiRack to the round holes. Pigtails not provided.
4. If no OC200 is used, place your TP-Rack in your 19-inch cabinet. Otherwise continue.
5. Remove the front plate located on the right side, by applying force on it until the upperside comes loose. Now move the plate in both directions in quick succession until the front plate breaks loose.
6. Slide the OC200 from behind through the brackets and push up the small plate behind to secure it.
7. Plug the power cable in and secure the cable with 1 zip tie. The zip tie goes through the 2 small holes behind the appliance.
8. Place your TP-Rack in your 19-inch cabinet.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	TP-Rack
2	Zip ties



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

19-06-2024

EMEA Office
Nonnenveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
559 S Interstate 35, Suite 350
Round Rock - TX 78664
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT