# HP LaserJet MFP M234d Printer



## Fast, reliable performance. Exceptional value

Increase productivity with this high-performance black-and-white printer in an award-winning compact design.<sup>2</sup> Experience the fastest two-sided printing in class<sup>8</sup> with copying and scanning, plus simplified setup and time-saving features with the HP app.<sup>3</sup>





This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: http://www.hp.com/learn/ds

## Built for fast and reliable printing

- Deliver multipage documents in a flash with the fastest two-sided printing in class.<sup>8</sup>
- Rely on consistent, high-quality prints page after page. Get the quality you expect from an industry leader.
- Easily handle high-volume print jobs and reload paper less often with a 150-sheet capacity paper tray.
- Get a lot from one device. Easily handle task with multifunction performance print, scan, copy.

## Award-winning design for your workspace<sup>2</sup>

- $\bullet\ \ \ \mbox{Save space}$  and reduce clutter with an award-winning compact design.  $^2$
- You can fit this LaserJet almost anywhere. Get projects done quickly with a printer that fits your workspace.

### Easy to set up, easy to use

- Get started fast with easy setup guidance from the HP app. 1 Quickly setup and get back to business.
- Help protect the information that matters most. Get security essentials to help maintain privacy and control.
- Easily connect your printer to your computer with the provided USB cable and built-in USB port.
- $\bullet \quad \text{Easily manage tasks with smart guided buttons buttons illuminate only when needed.} \\$

## Compact and energy efficient design

- Optimise printer energy usage with HP Auto-On/Auto-Off technology.<sup>4</sup>
- Easily recycle your used Original HP Toner Cartridges for free through the HP Planet Partners program.<sup>5</sup>
- This HP LaserJet meets ecolabel requirements, including Blue Angel.

## Product walkaround

## HP LaserJet MFP M234d Printer

- 1. USB Connection
- 2. Automatic two-sided printing: 18 ipm A4
- 3. Smart, contextual UI
- 4. Easy ID copy
- 5. 100 sheet output tray
- 6. 150 sheet enclosed input tray



# Accessories, Supplies and Support

Supplies	W1350A HP 135A Black Original LaserJet Toner Cartridge (~1,100 pages) W1350X HP 135X High Yield Black Original LaserJet Toner Cartridge (~2,400 pages)
Service and Support	UH761E HP 3 year Standard Exchange (available in all EMEA countries except Middle East, Adriatic, Africa, Russia, South Africa, Israel, Slovenia, Turkey) UH757E HP 3 year Next Business Day Exchange (available in Austria, Belgium, Czech Republic, Denmark, Finland, Greece, Ireland, Italy, Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Sweden, Switzerland, UK) UH764E HP 3 year Return to Depot (available in Adriatic, Africa, CIS, EEM, Israel, Middle East, Romania, Russia, South Africa, Turkey)

# Technical specifications

Model	HP LaserJet MFP M234d Printer
Product number	8)9K4F
Functions	Print, copy, scan
Control panel	Icon LCD; 3 lights (Media, Toner, Lid open); 10 buttons (Wi-Fi, Minus, Menu, Plus, Copy, ID copy, Info, Resume, Cancel, Power)
Print	
Print technology	Laser
Print speed <sup>9</sup>	Black (A4, normal): Up to 29 ppm; Black (A4, duplex): Up to 18 ipm Colour (A4, duplex): Up to 18 ipm
First page out <sup>11</sup>	Black (A4, ready): As fast as 7 sec; Black (A4, sleep): As fast as 7.6 sec
Print resolution	Black (best): Up to 600 x 600 dpi
Monthly duty cycle <sup>12</sup>	Up to 20,000 pages A4; Recommended monthly page volume: 200 to 2,000
Printer smart software features <sup>1,2</sup>	Automatic duplex printing, HP Auto-On/Auto-Off, HP App
Standard print languages	PCLmS; URF; PWG
Print area	Print margins Top: 6 mm, Bottom: 6 mm, Left: 5 mm, Right: 5 mm; Maximum print area: 216 x 354 mm
Duplex printing	Auto-duplex
Сору	
Copy speed <sup>7</sup>	Black (A4): Up to 14 cpm
Copier specifications	Auto-enlarge; Lighter/Darker; Number of Copies; Optimize; Paper Size; Paper type; Reduce to Fit; Maximum number of copies. Up to 99 copies; Reduce/Enlarge: 25 to 400%
Scan	
Scan file format	JPEG, TIF, PDF, BMP, PNG
Scanner specifications	Scan input modes: HP App; and user applications via Twain version: Version 2.1; Duplex ADF scanning: No;
Recommended monthly scan volume	150 to 1500
Scannable area	Maximum media size (flatbed): 297 x 216 mm
Bit depth/ Grey scale levels	24-bit/256
Processor speed	500 MHz
Connectivity	
Standard	1 Hi-Speed USB 2.0 (device)
Supported network protocols	TCP/IP: IP-v4; IP-v6; LPD; SLP; Bonjour; WS-Discovery; BOOTP/DHCP/AutoIP; SNMP v 1/2/3;HTTP/HTTPS; UDP; IPP
Memory	Standard: 64 MB; Maximum: 64 MB
Media handling	•
Number of paper trays	Standard: 1: Maximum: 1
Media types	Paper (läser, plain, rough, vellum), Erwelopes, Labels, Cardstock, Postcard
Media size	Custom (metric): 101.6 x 152.4 to 216 x 356 mm Supported (metric): A4; A5; A6; B5 (IIS) ADF: A4, B4, B5, C7; 76 x 216 mm to 127 x 356 mm
Media handling	Standard input: 150-sheet input tray Standard output: 100-sheet output tray
Media weight	60 to 163 g/m²
Input capacity	Tray 1: Sheets: 150; Envelopes: 10 Maximum: Up to 150 sheets
Output capacity	Standard: Up to 100 sheets Envelopes: Up to 10 envelopes Maximum: Up to 100 sheets
Compatible operating systems <sup>15</sup>	Windows 11; Windows 10; Windows 8; Windows 8.1; Windows 7; macOS 10.14 Mojave; macOS 10.15 Catalina; macOS 11 Big Sur; macOS 12 Monterey; Linux
Compatible network operating systems	Windows 11; Windows Server; Linux
Minimum system requirements	
	Windows: Microsoft® Windows® 11, 10: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, Microsoft® Internet Explorer; USB Port  Mac mac(DS v14 Sonoma; mac(DS v13 Ventura; mac(DS v12 Monterey; 2 GB HD; Internet required; USB
Software included	Windows: Microsoft® Windows® 11, 1:0.12-bit or 64-bit, 2:GB available hard disk space, Internet connection, Microsoft® Internet Explorer; USB Port Mac: macOS v14 Sonoma; macOS v13 Ventura; macOS v12 Monterey; 2:GB HD; Internet required; USB No CD; Downloadable Software from http://www.hp.com or http://www.123.hp.com
Software included	Mac: macOS v14 Sonoma; macOS v13 Ventura; macOS v12 Monterey; 2 GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://www.123.hp.com
Software included Security management	Mac maxOS v14 Sonoms; maxOS v12 Wentura; maxOS v12 Monterey; 2 GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www.hp.com.http://www
Software included Security management Printer management	Mac: macOS v14 Sonoma; macOS v13 Ventura; macOS v12 Monterey; 2 GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://www.123.hp.com
Software included Security management Printer management Dimensions and weight	Mac maxOS v14 Sonoms; maxOS v12 Monterey; Z GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http:
Software included Security management Printer management Dimensions and weight Printer dimensions (WxDxH)	Mac maxOS v14 Sonoms; maxOS v12 Monterey; 2 GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://www.123.hp.com  Secure Boot, Secure Firmware Integrity, Runtime Code Integrity, password protected EWS, secure browsing via SSL/TLS 1.0, TLS 1.1, TLS 1.2; TLS 1.0/1.1 disabled by default; Update to OpenSSL version 1.1.1; Enable/disable Network ports; SNMPv1, SnMPv2, and SNMPv3, community password change; Secure defaults, Encrypted data at rest, Active FW update, Admin password by default, Cipher & TLS selection; Account lockout; Secure Wi-Fi setup  HP Printer Assistant (UDC); HP Device Toolbox  Minimum 368 x 298.6 x 241.9 mm; Maximum: 368 x 419.6 x 436.3 mm
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight	Mac macOS v14 Sononas; macOS v12 Wentura; was with was v12 Wentura; was v14 Sononas; w14 Sononas; w1
Software included Security management Printer management Dimensions and weight Printer dimensions (WxDxH)	Mac macOS v14 Sononas; macOS v12 Wentura; was v14 Sonona; v15 V
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight	Mac macOS v14 Sononas; macOS v12 Wentura; was with was v12 Wentura; was v14 Sononas; w14 Sononas; w1
Software included Security management Printer management Dimensions and weight Printer dimensions (W x D x H) Printer weight Operating environment	Mac macOS v14 Sonoms; macOS v12 Monterey; 2 GB HD; Internet required; USB  No CD; Downloadable Software from http://www.htz.no.no.no.no.no.no.no.no.no.no.no.no.no.
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight  Operating environment  Storage conditions	Mac macOS v14 Sonoms; macOS v12 Mentura; macOS v12 Monterey; 2 G8 HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://www.123 HD; Internet required; USB  Secure Boot, Secure Firmware Intergrib, Runtime Code Integrity, password protected EWS, secure browsing via SSL/TLS 1.0, TLS 1.1, TLS 1.2; TLS 1.0/1.1 disabled by default; Update to OpenSSL version 1.1.1; Enable/disable Network ports; SMMPv1, SMMPv2, and SMMPv3, community password change; Secure defaults, Encrypted data at rest, Active FW update, Admin password by default, Cipher & TLS selection; Account lockout; Secure Wi-Fi setup  HP Printer Assistant (UDC); HP Device Toolbox  Minimum 368 x 298.6 x 241.9 mm; Maximum 368 x 419.6 x 436.3 mm  7.6 kg  Temperature: 15 to 32.5% Humidity: 30 to 70% RH  Temperature: 20 to 60°C Humidity: 10 to 90% RH
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (Wx D x H)  Printer weight  Operating environment  Storage conditions  Acoustics <sup>8</sup>	Mac macOS v14 Sonones; macOS v12 Wentura; macOS v12 Monterey; Z GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://www.123.hp.com  Secure Boot, Secure Firmware Integrity, Runtime Code Integrity, password protected EWS, secure browsing via SSL/TLS 1.0, TLS 1.1, TLS 1.2; TLS 1.0/1.1 disabled by default; Update to OpenSSL version 1.1.1; Enable/disable Network ports; SMMPv12, SMMPv2, and SMMPv3, community password change; Secure defaults, Encrypted data at rest, Active FW update, Admin password by default, Uphare & TLS selection, Account lockout; Secure Wi-Fi setup HP Printer Assistant (UDC); HP Device Toolbox  Minimum 368 x 298.6 x 241.9 mm; Maximum: 368 x 419.6 x 436.3 mm  7.6 kg  Temperature: 15 to 32.5°C Humidity: 30 to 70% RH  Temperature: 20 to 60°C Humidity: 10 to 90% RH  Acoustic power emissions: 6.6 B(A) Acoustic pressure emissions: 51 dB(A)  Requirements: 220 to 240 VAC (*f-10%), 60 Hz/50 Hz, 2.8 A; Consumption: 453 wasts factive printing), 3.3 wasts (ready), 0.6 wasts (sleep), 0.6 wasts (Auto Off/Wake on USB, enabled at shipment), 0.04 wasts (Auto-off/Manual-on), 0.04 (Manual Off); Typical Electricity Consumption: (TEC)**-0.25 F AW/Weyles (Blue Annel);
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight  Operating environment  Storage conditions  Acoustics <sup>8</sup> Power <sup>3</sup>	Mac macOS v14 Sononas; macOS v12 Wentura; macOS v12 Wonterey; Z GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://www.h23.hp.com  Secure Boot, Secure Firmware Integrity, Runtime Code Integrity, password protected FWS, secure browsing via SSL/TLS 1.0, TLS 1.1, TLS 1.2; TLS 1.0/1.1 disabled by default; Update to OpenSSL version 1.1.1; Enable/disable Network ports; SMMPv1, SNMPv2, and SNMPv3, community password change; Secure defaults, Encrypted data at rest, Active FW update, Admin password by default, Cipher & TLS selection; Account lockout; Secure Wi-Fi setup  HP Printer Assistant (UDC); HP Device Toolbox  Minimum 368 x 298.6 x 241.9 mm; Maximum: 368 x 419.6 x 436.3 mm  7.6 kg  Temperature 15 to 32.5% Humidity: 30 to 70% RH  Temperature -20 to 60°C  Humidity: 10 s 90% RH  Acoustic power emissions: 6.6 B(A) Acoustic pressure emissions: 51 dB(A)  Requirements: 220 to 240 VAC (+7-10%), 60 Hz/S0 Hz, 28 A; Consumption: 453 watts Cactive printing), 3.3 watts (ready), 0.6 watts (Auto Off/Wake on USB, enabled at shipment), 0.04 watts (Auto-off/Manual-on), 0.04 (Manual Off); Typical Electricity Consumption: ITEO 12-0.257 kWin/Week (Blue Angel); Power supply byte Bullit-11 1010 or 2007 Power Supply
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight  Operating environment  Storage conditions  Acoustics <sup>8</sup> Power <sup>3</sup> Energy savings feature technology	Mac macOS v14 Sonona; macOS v13 Ventura; macOS v12 Monterey; Z.G. HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight  Operating environment  Storage conditions  Acoustics <sup>8</sup> Power <sup>3</sup> Energy savings feature technology  Certifications	Mac macOS v14 Sonona; macOS v13 Ventura; macOS v12 Monterey; Z GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http://
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight  Operating environment  Storage conditions  Acoustics <sup>®</sup> Power <sup>®</sup> Energy savings feature technology  Certifications  Sustainable impact specifications	Mac macOS v14 Sononas; macOS v13 Ventura; macOS v12 Monterey; Z GB HD; Internet required; USB  No CD; Downloadable Software from http://www.hp.com or http:/
Software included  Security management  Printer management  Dimensions and weight  Printer dimensions (W x D x H)  Printer weight  Operating environment  Storage conditions  Acoustics <sup>8</sup> Power <sup>3</sup> Energy savings feature technology  Certifications  Sustainable impact specifications  Country of origin	Mac macOS v14 Sononas; macOS v12 Wentura; v12 Wentura; v12 Wentura; v13 Wentura; v13 Wentura; v14 Wentura; v15 Wen

#### **Footnotes**

- 1 Requires HP app download available at https://www.hp.com/go/mobileprinting . Certain features are available in English language only, and may vary by printer model/country, and between desktop/mobile applications. HP reserves the right to introduce charges for use of functionality facilitated by the HP app. Internet access required and may not be available in all countries. HP account required for full functionality. Fax capabilities are for sending a  $fax only. \ List of supported operating \ systems \ available \ in \ app \ stores. \ See \ details \ at \ https://www.hpsmart.com$
- https://www.red-dot.org/project/hp-laserjet-printer-series-52406
- <sup>3</sup> Based on internal HP testing. Average timing estimate based on: 1) downloaded HP app on mobile or desktop device, 2) setting up Shortcut, 3) scanning jobs which have more than 2-3 tasks associated with them (scan to email, save and rename, store to cloud, etc.). Average timing savings comparison based on using printer and desktop scan software to complete similar scanning tasks. Requires the HP app download and supported HP printer. For details on local printing requirements see https://www.hp.com/go/mobileprinting
- <sup>4</sup> HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade.
- <sup>5</sup> Program availability varies. Original HP cartridge return and recycling is currently available in more than 60 countries, territories and regions in Asia, Africa, Europe, and North and South America through the HP Planet Partners
- program. For details, see https://www.hp.com/recycle

  7 This HP printing system is awarded the Blue Angel according to DE-UZ 219 in commercial use for the following 33 countries: Germany, Austria, Switzerland, France, United Kingdom, Ireland, Sweden, Denmark, Finland, Norway, Belgium, Netherlands, Luxembourg, Italy, Spain, Portugal, Poland, Czech Republic, Slovakia, Slovenia, Hungary, Croatia, Romania, Bulgaria, Greece, Estonia, Latvia, Lithuania, Serbia, Turkey, Israel, Morocco, South Africa.

  8 Compared to in-class monochrome duplex laser printers less than £119 and duplex laser MFPs less than £179. Exact HP printer speeds vary depending on the system configuration, software application, driver, and document complexity. Keypoint Intelligence March 2024 study commissioned by HP, based on research of OEM-published specifications and publicly available information as of March 2024. Market share as reported by IDC for Q4 2023 for  $North\ America\ and\ Europe.\ For\ details:\ keypoint intelligence.com/HPF as test Duplex M200$

### Technical specifications disclaimers

- <sup>1</sup> HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade.
- <sup>2</sup> Requires HP app download available at www.hp.com/go/mobileprinting. Certain features are available in English language only, and may vary by printer model/country, and between desktop/mobile applications. HP reserves the right to introduce charges for use of functionality facilitated by the HP app. Internet access required and may not be available in all countries. HP account required for full functionality. Fax capabilities are for sending a fax only. List of supported operating systems available in app stores. See details at www.hpsmart.com.
- <sup>3</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115V device.
- 4 For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on
- <sup>5</sup> Declared yields based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/toneryield
- . Approximate vield. Actual vield depends on printer and specific use. See http://www.hp.com/go/pagevield for more information
- First Copy Out from Ready and Simplex Copy Speed measured using ISO/IEC 29183, Duplex Copy Speed measured using ISO/IEC 24735, excludes first set of test documents. For more information see https://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application and document complexity.
- B Configuration tested: simplex printing, A4 paper at an average of 29 ppm
- 9 Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

  10 Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see https://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration,
- software application, driver, and document complexity.
- 11 Measured using ISO/IEC 17629. For more information see https://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- 12 Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.

  13 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.
- 15 Not supporting Windows® XP (64-bit) and Windows Vista® (64-bit) Full solution software available only for Windows 10 and newer; For Windows Server 2016 64-bit only print driver is installed; Linux systems use in-05 HPLIP




www.blauer-engel.de/uz219











gb-en August 2024

