



ECMA/TC38-TG3/2015/026 (Rev. 1 – 15 April 2017)

## Annex B2 - Product environmental attributes Desktop/All-in-One Computers

The declaration may be published only when all rows and/or fields marked with \* are filled-in (n.a. for not applicable). Additional information regarding each item may be found under P15.

Brand *	Lenovo	Logo	)
Company name *	Lenovo	]	
Contact information *	Lenovo Global Environmental Affairs		Lenovo
e-mail address	Alvin L Carter		LCIIOVO
	alcarter@lenovo.com		
Internet site *	https://www.lenovo.com/us/en/sustainability-resources/		
Additional information	The latest version of this document can be found at:		
	http://www.lenovo.com/ecodeclaration		

	based on product specification or test results based obtained from sample testing), that the product nts given in this declaration.
Type of product *	Desktop
Commercial name *	ThinkCentre M70t Gen 4
Model number *	12DK,12DL,12DU,12DV,12FH,12KG, 12DK,12DL,12DU,12DV,12FH,12KG
Issue date *	2023/3/23, updated 2023.07.28
Intended market *	☐ Global ☐ Europe ☐ Asia, Pacific & Japan ☐ Americas ☐ Other
Additional information	ES8.0 (12DK,12DL,12DU,12FH,12KG), TCO9.0

This is an uncontrolled copy when in printed form. Please refer to the contact information for the latest version.

#### About Annex B2

Annex B2 reflects Product environmental attributes relevant for Computers and Computer Monitors. The following items from the ECMA-370 Main body are not shown in the template:

P4.1 – P4.3 Consumable materials

P9.1 TEC and Print speed

P10.2 - P10.3 Chemical emissions from printing products

P11.1 - P11.3 Consumable materials for printing products

Model nu	mber *	12DK,12DL,12DU,12DV,12FH,12KG, 12DK,12DL,12DU,12DV,12FH,12KG Logo	Lon		
Issue date	e *	2023/3/23	Lend	DVC	<b>)</b>
Product	environ	mental attributes - Legal requirements	Require	ment	met
Item		• .	Yes	No	n.a.
P1		ous substances and preparations			
P1.1*	Products	s do comply with current European RoHS Directive. (See legal reference and NOTE B1)	$\boxtimes$		
P1.2*	Commer	s do not contain Asbestos (see legal reference). nt: Legal reference has no maximum concentration value.			
P1.3*	hydrobro trichloroe	s do not contain Ozone Depleting Substances: Chlorofluorocarbons (CFC), omofluorocarbons (HBFC), hydrochlorofluorcarbons (HCFC), Halons, carbontetrachloride, 1,1,1-ethane, methyl bromide (see legal reference). Comment: Legal reference has no maximum ration values.			
P1.4*	terpheny	s do not contain more than; 0,005% polychlorinated biphenyl (PCB), 0,005% polychlorinated /l (PCT) in preparations (see legal reference).			
P1.5*	Products	s do not contain more than 0,1% short chain chloroparaffins (SCCP) with 10-13 carbon atoms in the notaining at least 48% per mass of chlorine in the SCCP (see legal reference).	ne 🔀		
P1.6*	(see lega	th direct and prolonged skin contact do not release nickel in concentrations above 0,5 μg/cm²/wee al reference). nt: Max limit in legal reference when tested according to EN1811:2011-5.	ek 🔀		
P1.7*	REACH	Article 33 information about substances in articles is available at (add URL or mail contact): www.lenovo.com/us/en/Lenovo-REACH-SVHC-Disclosure			
P2	Batterie				
P2.1*		oduct contains a battery or an accumulator, the battery/accumulator is labeled with the disposal Information on proper disposal is provided in user manual. (See legal reference)			
P2.2*	Batteries reference	s or accumulators do not contain more than 0,0005% of mercury or 0,002% of cadmium. (See lega e)	al 🔀		
P2.3*	Batteries	s and accumulators are readily removable. (See legal reference)	$\boxtimes$		
P3	Conform	nity verification & Eco design (ErP)			
P3.1*	The Dec	duct is CE-marked to show conformance with applicable legal requirements (see legal reference). elaration of Conformity can be requested at:  www.lenovo.com/us/en/compliance/eu-doc for us/  ps://www.lenovo.com/us/en/compliance/uk-doc for UK			
P3.2*		duct complies with the Eco design requirements for energy-related products, al reference).			
	, ,	d information is;			
	declarat				
P5		packaging			
P5.1*	hexavale	ng and packaging components do not contain more than 0,01% lead, mercury, cadmium an ent chromium by weight of these together.			
P5.2*	The pac	kaging materials are marked with abbreviations and numbers indicating the nature of the material(	(s) 🔀		

The product packaging material is free from ozone depleting substances as specified in the Montreal Protocol (see legal reference).

Comment: Legal reference has no maximum concentration values.

Information for recyclers/treatment facilities is available (see legal reference).

used (see legal reference).

Treatment information

P5.3\*

P6

P6.1\*

NOTE B1 Restriction applies to the homogeneous material, unless other specified and expressed in weight %. Stating "Yes" means that the product is compliant with the mandatory requirements.

Model nu	ımber *	12DK,12DL,12DU,12DV,12FH,12KG, 12DK,12DL,12DU,12DV,12FH,12KG	Logo	on		
Issue dat	te *	2023/3/23		_en	OVC	) <sub>th</sub>
Product		mental attributes - Market requirements (See General NOTE GN l Inmental conscious design		equire	mont	met
Item		tory to fill in. Additional information regarding each item may be found under P14.	IX	Yes	No	n.a.
P7		Disassembly, recycling		103	140	n.a.
P7.1*		t have to be treated separately are easily separable		$\square$		
P7.2*	Plastic m	naterials in covers/housing have no surface coating.				
P7.3*	Plastic p	arts > 100 g consist of one material or of easily separable materials.		$\boxtimes$		
P7.4*	Plastic p	arts > 25 g have material codes according to ISO 11469 referring ISO 1043-4.		$\boxtimes$		
P7.5	Plastic p	arts are free from metal inlays or have inlays that can be removed with commonly a	vailable tools.	$\boxtimes$		
P7.6*	Labels a	re easily separable. (This requirement does not apply to safety/regulatory labels).			Ī	
	Product	lifetime				
P7.7*	Upgradir	g can be done e.g. with processor, memory, cards or drives		$\boxtimes$		
P7.8*	Upgradir	g can be done using commonly available tools		$\boxtimes$		
P7.9	Spare pa	rts are available after end of production for: 5 years				
P7.10	Service i	s available after end of production for: 5 years				
		and substance requirements				
P7.11*		cover/housing material type (e.g. plastics, metal, aluminum):				
D7 40			I type: Metal			
P7.12		n materials of external electrical cables are PVC free.		<u> </u>		<del>-  -  -  -  -  -  -  -  -  -  -  -  -  -</del>
P7.13		n materials of internal electrical cables are PVC free.			<u> </u>	Щ.
P7.14	weight (* polyvinyl	plastic casing/cover parts > 25 g contain no more than 0,1% weight (1000 ppm) br 1000 ppm) chlorine attributable to brominated flame retardants, chlorinated flame chloride or 0,3% weight (3000 ppm) bromine and 0,3% weight (3000 ppm) chlorine in 25% post-consumer recycled content.	retardants, and			
P7.15	Printed of	ircuit boards, PCBs (without components) are low halogen: all  PCBs > 25 g  in IEC 61249-2-21. (See 1NOTE B2)	are low halogen			
P7.16		tarded plastic parts > 25 g in covers / housings are marked according ISO 1043-4:				
P7.17		nemical specifications of flame retardants in printed circuit boards > 25 g (without co	mponents):			
	<b>⊠</b> TBBF	'A (additive), TBBPA (reactive) (See NOTE B3), Other: , CAS #:				
		nemical specifications of flame retardants in printed circuit boards (without compone g ISO 1043-4:	nts) > 25 g			
P7.18	concentr 1. Chem 2. Chem	ame retarded plastic parts > 25 g contain the following flame retardant substance: ations above 0,1%: ical name: , CAS #: (See NOTE B4) ical name: , CAS #: " ical name: , CAS #: " ical name: , CAS #: "	s/preparations in			$\boxtimes$
	Alt. 2: Ch	nemical specifications of flame retardants in plastic parts > 25 g according ISO 1043	3-4:			
P7.19	In plastic	parts > 25 g, flame retardant substances/preparations above 0,1% are used which the following Risk phrases; and Hazard statements:				
P7.20*		sumer recycled plastic material content is used in the product (See Note B6):	.5.5 50)	$\boxtimes$		
	a) Of t	t least one of the two alternatives below shall be answered; otal plastic parts' weight > 25 g, the postconsumer recycled plastic material content centage of total plastic by weight) is 50.19 %.	(calculated as a			

b) The weight of recycled material is 194.2 g.

GENERAL NOTE Standard references should direct to the latest version of a standard. If an older version of a standard is used, section P15 shall be used for explanation.

NOTE B2 IEC 61249-2-21 defines maximum limits of 900 ppm for each of the substances chlorine and bromine and a maximum limit of 1500ppm of these substances combined. The standard does not address fluorine, iodine and astatine which are included in the group of halogens.

NOTE B3 and B4 A Guidance document on Chemical substances is available; see <a href="http://www.ecma-international.org/publications/standards/Ecma-370.htm">http://www.ecma-international.org/publications/standards/Ecma-370.htm</a>

NOTE B5 If a certain substance has been assigned a certain risk phrases / hazard statement in the referenced source, this does not necessarily mean the substance has been tested for all of the hazards referred to by a certain customer.

NOTE B6 Applies to a product containing plastic parts whose combined weight exceeds 100 g with the exception of printed circuit boards, cables, connectors and electronic components and bio-based plastic material.

Model number *	12DK,12DL,12DU,12DV,12FH,12KG, 12DK,12DL,12DU,12DV,12FH,12KG	Logo	Len	01/6	
Issue date *	2023/3/23		Len		714
Product environr	nental attributes - Market requirements (continued)		Requi	remen	t met
Item			Yes	No	n.a.

P7.21*		stance requirements	(continued) d in the product (See N	IOTE R7):	
F1.Z1	•			,	
			es below shall be answ the biobased plastic n		ated as a percentage of
	total plastic b	y weight) is %.	·	•	· -
	or b) The weight of	f the biobased plastic	material is g.		
P7.22*	Light sources are f	free from mercury, i.e.	less than 0,1 mg/lamp		
Do		specify: Number of lar	mps: and maxim	num mercury content po	er lamp: mg
<b>P8</b> P8.1*	Batteries Battery chemical c	composition: Lithium	Manganese Dioxide		
P9	<u>.</u>	tion (See NOTE B8)	manganese bloxide		
P9.1	For the product the	e following power leve	ls or energy consumpti	ions are reported:	
Energy mo		Power level at	Power level at	Power level at	Reference/Standard for energy
		100 V AC	115 V AC	230 V AC	modes and test method *
Peak (On-	max)	W	W	W	Full load
Categor	y -l2-				
	State - WOL	13.9W	14.6W	13.9W	ENERGY STAR Computers V8
Enabled					(P <sub>idle</sub> )
	State - WOL	9.9W	11.9W	12W	ENERGY STAR Computers V8
Enabled					(P <sub>idle</sub> )
Sleep (S3)	- WOL Enabled	1.9W	1.9W	1.9W	ENERGY STAR Computers V8
					(P <sub>sleep</sub> )
Off (S5) -	WOL Enabled	0.7W	0.7W	<b>0.7</b> W	ENERGY STAR Computers V8
					(P <sub>off</sub> )
Categor	y -D2-				
Short Idle	State - WOL	25.5W	21 W	<b>25.5</b> W	ENERGY STAR Computers V8
Enabled					(P <sub>idle</sub> )
Long Idle	State - WOL	<b>21</b> W	17.3 W	<b>20.7</b> W	ENERGY STAR Computers V8
Enabled					(P <sub>idle</sub> )
Sleep (S3)	- WOL Enabled	1.3W	1.3 W	1.3W	ENERGY STAR Computers V8
, ,					(P <sub>idle</sub> )
Sleep (S3)	- WOL Disabled	0.7W	0.7W	0.7W	ENERGY STAR Computers
, ,					V8(P <sub>off</sub> )
ETEC *		12 55.4 kWh/year	12 57 kWh/year	/2 53.5kWh/year	$E_{TEC} = (8760/1000) \times (P_{off} \times 0.45)$
Annual En	ergy Consumption				+ P <sub>sleep</sub> x 0.05 + P <sub>long_Idle</sub> x 0.15+
		D2 91.6 kWh/year	D2 76.6 kWh/year	D2 91.3kWh/year	P <sub>short Idle</sub> x 0.35)
External P	ower Supply Efficien		I Efficiency Marking Pr		Enabled; P <sub>idle</sub> : Idle State - WOL Enabled
Display res		egapixels	, 9	,	
		ave mode: 25 minutes			
P9.2*			on is provided with the	product.	
P9.3	Energy efficiency	class (monitors only):	N/A		

NOTE B8 A Guidance document on Energy Efficiency is available;

 $\underline{\text{http://www.ecma-international.org/publications/standards/Ecma-370.htm}}$ 

NOTE B9 A Guidance document on Acoustic Noise is available; see <a href="http://www.ecma-international.org/publications/standards/Ecma-370.htm">http://www.ecma-international.org/publications/standards/Ecma-370.htm</a>

NOTE B7 The following is to be excluded from the calculation of percentage: printed circuit boards, labels, cables, connectors and electronic components and postconsumer recycled plastic

P10	Emissions		
	Noise emission	on – Declared according to ISO 9296 (See NOTE	B9)
P10.1	Mode	Mode description	Statistical upper limit A-weighted sound power level, L <sub>WA,c</sub> (B)
Ì	Idle	* HDD:Idle	* 3.2
ĺ	Operation	* HDD: Operating	* 3.6
	Other mode	Declared A-weighted sound pressure level (dB) $L_{p  m Am}$	
	Other mode	Declared A-weighted sound pressure level (dB) $L_{p  m Am}$	25.6 (operator position desktop – operating)
	Measured acco	ording to: SO 7779 ECMA-74	
		Other (only if not covered by E	ECMA-74)

Model nur	nber *	12DK,	12DL,12DU,1	12DV,12FF	1,12KG, 12D	K,12DL,	12DU,12DV,1	12FH,12KG	Logo	Leno	VO	
Issue date	*	2023/3	/23							Leilo	VO.	
Product	environr	mental	attributes -	Market ı	requireme	nts (con	tinued)			Require	ment	met
Item						(000)				Yes	No	n.a.
	Electron	magneti	c emissions									
P10.4	Compute		y meets the r	equiremer	nt for low free	quency el	ectromagneti	c fields of the foll	owing voluntary			
P12			computing									
P12.1*		•						display technolo	gies.			$\boxtimes$
P12.2*	The phy	sical inp	ut device me	ets the req	uirements of	f ISO 999	5 and ISO 92	241-410.				
P13			documentat									
P13.1*	Product Product Product	packagi packagi packagi	ng material ty ng material ty ng material ty ng material ty	/pe(s): LD/ /pe(s): Co/ / pe(s): LD	PE rrugated sin PPE Bag	igle wall	wei	ight (kg): <b>0.98</b> ight (kg): <b>0.265</b> ight (kg): <b>0.047</b> <b>51</b>				
P13.2*	Product	plastic p	rimary packa	iging is fre	e from PVC.					$\boxtimes$		
P13.3*			nary corruga ered fiber cor			ing, spec	cify the conta	ined percentage	of minimum po	ost-		
P13.4*			r user and pr Paper,	oduct doc	umentation (	tick box):						
P13.5		d produc	nplete this ite t documenta ecify:									
	Totally of Element Process	al chlori	ne-free									
D4.4												
<b>P14</b> P14.1	The prov			ements of	the following	voluntar	y program(s):					
	ENERG Eco-labe Eco-labe	Y STAR el: el:	R	Criteria ve Criteria ve Criteria ve	ersion: <b>8.0</b> ersion: ersion:		Date: 2023. Date: Date:	3.2 Product of Product	category: <b>Deskto</b> category: category:	ор		
P15								V,12FH,12KG)				
P9								of the tested pro				
	_	Categor /	СРО	Memory	HDD	SSD	Graphics	power supply	Sleep	mode		
			I5-13500	128GB	2TB 3.5"HDD 1TB 2.5 HDD		GTX3050	260W	S3			
	the info supplied information	rmation r's know tion. Th t Repres	contained in vledge availa e information sentative foi	n this doc able at the n provide more info	ument. All i time of con d here is ap ormation.	nformati npletion, proxima	on provided , and supplie te and provi	or warranties wh by supplier in to er shall have no ded for informat	his document is obligation to up	s provided odate such	based	on
P9								est information: owProductGroup	o&pgw_code=C	0		

NOTE B10 Additional lines may be inserted to declare further items, by positioning the cursor at the far right of the row and hitting the <Enter> key.

## Legal references Europe Annex B2

Reference	Declaration item
Directive 2011/65/EU (RoHS Directive) * * Specific exemptions apply for certain products and applications.	P1.1
Regulation (EC) 1907/2006(REACH, Annex XVII	P1.2, P1.4, P1.6, P1.7
Regulation (EC) 2037/2000, 2038/2000, 2039/2000 (Marketing and use of Ozone layer depleting substances)	P1.3, P5.3
Norwegian regulation relating to restrictions on the use of certain dangerous chemicals 20.12.2002	P1.5
Directive 2013/56/EC (Battery and accumulators Directive) *  * These provisions shall not apply where, for safety, performance, medical or data integrity reasons, continuity of power supply is necessary and requires a permanent connection between the appliance and the battery or accumulator.	P2.1, P2.2, P2,3, P8.1
Directive 2006/95/EC (Low Voltage Directive)	P3.1
Directive 2004/108/EC (EMC Directive)	P3.1
Directive 1999/5/EC (R&TTE Directive)	P3.1
Regulation (EC) 801/2013 amending Regulation (EC) No 1275/2008 with regard to ecodesign requirements for standby, off mode electric power consumption of electrical and electronic household and office equipment, and amending Regulation (EC) No 642/2009 with regard to ecodesign requirements for televisions	P3.1, P3.2
Regulation (EC) No 1272/2008 (CLP Regulation)	P7.19
Directive 2004/12/EC (Packaging Directive)	P5.1
Decision 97/129/EC (Secondary packaging legislation)	P5.2
Directive 2012/19/EU (WEEE directive)	P6.1

# Lenovo ErP Lot3 Information Sheet - PC / Notebook -

As required by COMMISSION REGULATION (EU) No 617/2013 of 26 June 2013 implementing Directive 2009/125/EC of the European Parliament and of the Council with regard to ecodesign requirements for computers and computer servers (ErP Lot3).

### **Products scope of this sheet:**

Desktop computer, integrated desktop computer, and notebook computer

This document is only valid in connection with the IT Eco Declaration of the specific Product.

Commercial name	ThinkCentre M70t Gen 4	Logo
Model Number	12DK,12DL,12DU,12DV,12FH,12KG, 12DK,12DL,12DU,12DV,12F H,12KG	Lenovo
Issue Date	2023/3/23	
Additional information	ES8.0 (12DK,12DL,12DU,12DV,12FH,12KG), TCO9.0	

(d)	year of manufacture:				2021
(e)	Etec value (kWh) per ErP Lot 3 Categor disabled and if the system is tested with				cards (dGfx) are
(f)	Etec value (kWh) per ErP Lot 3 Categorenable	ry and capability adjust	ments applied when <b>a</b>	III discrete graphics	cards (dGfx) are
		Category A (according to ErP Lot 3)	Category B (according to ErP Lot 3)	Category C (according to ErP Lot 3)	Category D (according to ErP Lot 3
	Memory over base [GB]				128
ents	Additional internal storage	(Yes / No)	(Yes / No)	(Yes / No)	Yes (Yes / No)
capability adjustments applied during testing	Discrete television tuner	(Yes / No)	(Yes / No)	(Yes / No)	No (Yes / No)
ability a lied du	Discrete Audio Card	(Yes / No)	(Yes / No)	(Yes / No)	No (Yes / No)
cap	Discrete graphics Card(s) [number / #]	#: (Yes / No)	#: (Yes / No)	#: (Yes / No)	Yes #: (Yes / No)
	Category of discrete graphics Card(s)				G3
sults	Etec Value (kWh) - dGfx disabled all discrete graphics cards (dGfx) are disabled/ UMA is active for switchable graphics/ product has no graphics cards (dGfx)				
Test results	Etec Value (kWh) - dGfx enabled all discrete graphics cards (dGfx) are enabled				95.16
(g)	Idle state power demand (Watts);	l .		l	D:26.08
(h)	Sleep mode power demand (Watts);				D:1.38
(i)	Sleep mode with WOL enabled power do	emand (Watts) (where	enabled);		D:1.35
j)	Off mode power demand (Watts);				D:0.66
(k)	Off mode with WOL enabled power dem	and (Watts) (where en	abled);		D:0.66
(1)	Internal power supply efficiency at 10 %,	, 20 %, 50 % and 100 9	% of rated output pow	er (if applicable):	
	D:10% 89.74% 20% <b>92.24%</b> 50% <b>9</b>	<b>1.45%</b> 100% <b>87.99%</b>	Average 90.64%		
(m)	External power supply efficiency (if appli	cable)*:			
	Average active efficiency:				
	*internal note: show values for all available external p				
(o)	Minimum number of loading cycles that Measurement methodology used to dete	the batteries can withst	tand (applies only to n	otebook computers):	. NA
(p-1)	weasurement methodology used to dete	ermine information men 80 plus program		nemai Pou emciency:	
p-2)	Measurement methodology used to dete				

	Measurement methodology used to determine information mentioned in points (o) – loading cycles batteries:	
( A)		
(p-4)	Measurement methodology used to determine information mentioned in maximum, idle, sleep, off mode power as defined in Point P9.1 in the Product IT Eco Declaration:	
	refer to IEC62623:2013-Desktop and notebook computers-Measurement of energy consumption	
(q)	Sequence of steps for achieving a stable condition with respect to power demand:	
	Based on user manual/Power on->Wait 5 minutes->Stable condition	
(r)	Description of how sleep and/or off mode was selected or programmed:	
	Based on user manual-Set power button behaviors	
	Set power button behaviors	
	You can define what the power button does according to your preference. For example, by pressing the power button, you can turn off the computer or put the computer to sleep or hibernation mode.	
	To change what the power button does:	
	1. Go to Control Panel and view by large icons or small icons.	
	<ol><li>Click Power Options → Choose what the power buttons do.</li></ol>	
	3. Change the settings as you prefer.	
s)	Sequence of events required to reach the mode where the equipment automatically changes to sleep and/or off mode:	
(t)	Based on user manual/Control Panel->Power Options-> Change Settings-> Restore default settings for this plan  Duration of idle state condition before the computer automatically reaches sleep mode, or another	25
(u)	condition which does not exceed the applicable power demand requirements for sleep mode (in minutes):	
u,		
	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):	NA NA
v)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):	
v)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA	NA
(v) (w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:	NA
(v) (w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan  Set the power plan  For ENERGY STAR® compliant computers, the following power plan takes effect when your computers have	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan  Set the power plan  For ENERGY STAR® compliant computers, the following power plan takes effect when your computers have been idle for a specified duration:  Table 1. Default power plan (when plugged into ac power)	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan  Set the power plan  For ENERGY STAR® compliant computers, the following power plan takes effect when your computers have been idle for a specified duration:	NA
v) w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan  Set the power plan  For ENERGY STAR® compliant computers, the following power plan takes effect when your computers have been idle for a specified duration:  Table 1. Default power plan (when plugged into ac power)  Turn off the display: After 10 minutes	NA
(v) (w)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan  Set the power plan  For ENERGY STAR® compliant computers, the following power plan takes effect when your computers have been idle for a specified duration:  Table 1. Default power plan (when plugged into ac power)  • Turn off the display: After 10 minutes • Put the computer to sleep: After 25 minutes	NA
(v) (w) (x)	Length of time after a period of user inactivity in which the computer automatically reaches a power mode that has a lower power demand requirement than sleep mode (in minutes):  Length of time before the display sleep mode is set to activate after user inactivity (in minutes):  Information on the energy-saving potential of power management functionality:  NA  User information on how to enable the power management functionality:  Based on user manual-Set the power plan  For ENERGY STAR® compliant computers, the following power plan takes effect when your computers have been idle for a specified duration:  Table 1. Default power plan (when plugged into ac power)  Turn off the display: After 10 minutes Put the computer to sleep: After 25 minutes  To awaken the computer from Sleep mode, press any key on your keyboard.	NA

the		system, — inform			Hz, — total harmonic distortion of strumentation, set-up and circuits	
		Test volta	age in V and frequen	ncy in Hz: 23	0V/50Hz	
		Total harmonic	distortion of the elec	tricity supp	ly system: <u>≤</u> 2%	
Instrument		Instrument Range Used		Make and Model **		
	B63	Digital Watch	Full range	CASIO; HS-70W; SN:301Q02R		
	B100	power Meter	0~600V;0~20A	YOKOGAWA;WT310;SN:C2RD07008 V		
	C18	Ambient Monitor	-10~60 °C /0~100%RH	Testo;622;SN:39504298/305		
Additional No	tebook Batte	ry Information:				•
		Battery[ies] <u>not</u> user replaceable		ole	Battery[ies] user replaceable	n/a
		The battery[ies] in this product cannot be easil replaced by users themselves. 1)		ot be easily		
Internal/built-in Battery						
External/detachable Battery						
Bios Backup Battery						
Other:						
Additional info	rmation					
кумулаторната[ите] as baterías de este p yměnu baterías de este p yměnu baterías de este p yměnu batería/bateril rugeren kan ikke ude er Akku/die Akkus dia asutajad ei saa selle μπαταρία[-ες] στο π a/les batterie (s prése orisnik ne može lako a batteria/le batterie i etotāji paši nevar nor io gaminio baterijos [l termék akkumulátors-batterija/batterija f'dar atteriet [ene] i dette p e batterij(en) in dit pr izytkownik nie može s ou as baterias deste ateria (bateriile) din a atériu(-ie) v tomto výr aterij/baterije v tem iz ämän tuotteen akku [et är inte enkelt för ku	батерия[и] в този г roducto no риеden з roducto no pueden з roducto no pueden з roducto no pueden sees Produkts kann. toote akut/akusid is poïóv αυτό δεν μπορ nte(s) dans ce producto producto ne mainīt šā ražojuma a baterijų] pats vartoto atvakumulátorait a f ni i-prodott ma tistax oroduktet kan ikke le oduct is (zijn) door csam w łatwy sposób produto não poder acest produs nu poai robku nemôže vymiedelku uporabniki sa rakut] ei[vāt] ole help unden att själv byta	ser sustituídas fácilmer neměli provádět sami tteriet/batterierne i dett /können nicht ohne wei e hőlpsasti asendada. σούν να αντικατασταθο uit ne peuvent être faci am u ovom proizvodu. on può/possono essere akumulatoru(-us). ojas negali lengvai pake ielhasználó nem tudja et/jistghux tiġi/jigu sostih tt erstattes av brukerne de gebruiker niet gemal wymienić baterii w tyrn a ser facilmente substit te (pot) fi uşor înlocuită te (pot) fi uşor înlocuită	a amenµ[ят] лесно от сам te por los propios usuarios uzivatelé. e produkt. titeres vom Benutzer selbst τύν εύκολα από τους ίδιους lement remplacée(s) par le e facilmente sostituita/e dal eisti. egyedül egyszerűen kicsen wita/i mill-utenti stess. e selv. kkelijk vervangbaar. n produkcie. uídas pelos próprios utiliza (nlocuite) de utilizatorii în amenjati. avissa.	ausgetauscht w τους χρήστες se utilisateurs eu l'utente. élni.	verden.	