

Trasmettitore KVM HDMI su rete IP per la serie di prodotti IH2006, 4K 60Hz, senza driver, AVoIP, include kit di montaggio, solo trasmettitore

ID prodotto: IH2006-KVM-TX



The AVoIP KVM Transmitter enables remote access to computers over a TCP/IP network using a keyboard, mouse, and 4K 60Hz HDMI monitor when paired with a compatible receiver. Designed as a replacement unit, it ensures continued performance, security, and uptime by protecting systems from unauthorized access and physical damage.

The plug-and-play design requires no drivers or software, making setup quick and hassle-free. It is compatible with all major operating systems, including Windows, macOS, and Linux, as well as hardware platforms like Intel, AMD, Snapdragon/ARM, and Apple Silicon.

Designed to seamlessly integrate with existing IH2006 Series Receivers, this transmitter offers a hassle-free replacement option, keeping your AV infrastructure running smoothly and maximizing uptime.

The transmitter features a durable metal housing with mounting kit for wall or under-desk installation, along with rubber feet for desktop stability. A local HDMI output allows direct connection to a nearby display, while RS232 and 3.5mm audio passthrough ports enable seamless serial and audio extension.

Certificazioni, report e compatibilità





Applicazioni

- Reduce the need for physical access to a computer or server, improving security and efficiency
- Enables secure, high-performance connections between workstations and studio equipment
- Allows operators to manage critical systems from a safe or more convenient location

Caratteristiche

- **AVoIP KVM TRANSMITTER:** When paired with an IH2006 receiver (sold separately), extend 4K 60Hz HDMI and USB over a TCP/IP network to a remote display; Ideal as a direct replacement for an existing transmitter, ensuring performance, compatibility, and uptime
- **REPLACEMENT-READY SOLUTION:** Designed to seamlessly integrate with existing IH2006 Series Receivers, this transmitter offers a hassle-free replacement option, keeping your AV infrastructure running smoothly
- **NO DRIVERS OR SOFTWARE:** Requires no configuration to get it working; Compatible with any operating system including Windows, macOS and Linux, as well as all hardware platforms such as Intel, AMD, Snapdragon/ARM and Apple Silicon
- **LOCAL HDMI OUTPUT:** IP KVM Transmitter features an HDMI output to connect a local display, allowing you to view the content without being at the receiver's location; Three-wire RS232 port and a 3.5mm audio passthrough port offer serial and audio extension
- **SECURE & FLEXIBLE INSTALLATION:** Durable metal housing with included mounting kit for wall or under-desk installation; Rubber feet prevent slipping for desktop use; Ideal for industrial and professional environments

Hardware

Norme di garanzia	2 Years
Audio	Sì
Porte KVM	1
Interfaccia PC	USB
Tipo video PC	HDMI

Montaggio a rack	No
Cavi inclusi	No

Prestazioni

Supporto OSD e tasti di scelta rapida	No
Video Revision	HDMI 2.0
Controllo IP	Sì
Hot-Key Selection	No
Risoluzioni digitali massime	3840 x 2160 @ 60Hz
Specifiche audio	HDMI - 2 Channel Audio
Supporto selezione porte	Non applicabile

Connettore/i

Interfacce console	1 - RJ-45
	1 - HDMI
Connettori host	1 - Blocco terminale (3 fili)
	1 - USB 2.0 Type-C
	1 - HDMI
	1 - 3.5mm Stereo Female 3 pos
Altre Interfacce	1 - USB micro-B (5 pin)

Software

Compatibilità con sistemi operativi	Non è necessario alcun driver o software
-------------------------------------	--

Indicatori

Indicatori LED	1 - Power LED:
	Solid Blue: Indicates the unit is receiving Power
	1 - Sync LED:

Off: Transmitter and Receiver have no established a connection

Slow Orange Flash: Transmitter and Receiver are connected via Gigabit Ethernet but no Video is transmitting

Quick Orange Flash: Transmitter and Receiver are connected via 100Mbps Ethernet but no Video is transmitting

Solid Orange: Video is transmitting

1 - KVM LED:

Flashing: KVM data is transmitting

Solid: Computer and USB Port are connected

Alimentazione

Fonte di Alimentazione	Adattatore CA incluso
Tensione ingresso	100 - 240 AC
Corrente ingresso	0.3A
Tensione di uscita	5 DC
Corrente di uscita	2A
Tipo punta centrale	Positivo
Tipo presa	M
Consumo energetico	10W

Ambientale

Temperatura d'esercizio	-20°C to 60°C (-4°F to 140°F)
Temperatura di conservazione	-30°C to 70°C (-22°F to 158°F)
Umidità	0% ~ 90% RH (senza condensa)

Caratteristiche fisiche

Colore	Nero
--------	------

Tipo enclosure	Acciaio
Lunghezza prodotto	0.0 in [0.0 mm]
Larghezza prodotto	0.0 in [0.0 mm]
Altezza prodotto	0.0 in [0.0 mm]
Peso prodotto	0.0 oz [0.0 g]

Informazioni confezione

Lunghezza Confezione	5.9 in [14.9 cm]
Package Width	7.8 in [19.9 cm]
Package Height	3.1 in [8.0 cm]
Peso spedizione (confezione)	1.1 lb [0.5 kg]

Contenuto della confezione

Incluso nella confezione	1 - IP KVM Transmitter
	1 - Confezione di piedini in gomma
	1 - RS-232 Terminal Header
	1 - Kit di montaggio
	1 - Adattatore di alimentazione universale (NA/UK/UE/ANZ)

* L'aspetto e le specifiche dell'articolo sono soggetti a modifiche senza preavviso.