



Auxiliary switch, 1NO+1NC 20-150ms leading, for four-hole front mounting, for floor mounting and encapsulated switches, accessory for main and emergency off switch 3LD2 for 160 - 250A and for molded case switch 3LD5 UL for 100A-150A

Model	
product brand name	SENTRON
design of the product	accessories for 3LD2 main and EMERGENCY-STOP switches, 3LD2 maintenance and repair switches with EMC shield plate
operational current	- at AC-15 / at 48 V / rated value 10 A - at AC-15 / at 110 V / rated value 6 A - at AC-15 / at 230 V / rated value 3 A - at AC-15 / at 400 V / rated value 1.7 A - at AC-15 / at 500 V / rated value 1.5 A - at DC-13 / at 110 V / rated value 0.25 A - at DC-13 / at 48 V / rated value 0.5 A - at DC-13 / at 24 V / rated value 1 A
lead time / relating to main contacts	20 ms
type of connectable conductor cross-sections / for auxiliary contacts	- solid 1x (0.75 ... 2.5 mm²) - finely stranded / with core end processing 1x (0.75 ... 2.5 mm²) - stranded 1x (0.75 ... 2.5 mm²)
General Product Approval	
Declaration of Conformity	



[Confirmation](#)



[UK Declaration of Conformity](#)

Test Certificates other

[Special Test Certificate](#)

[Miscellaneous](#)

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3LD9240-5D>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3LD9240-5D>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3LD9240-5D

CAX-Online-Generator

<http://www.siemens.com/cax>

Tender specifications

<http://www.siemens.com/specifications>



