Data Sheet

# Predator Galea 570



## Galea 570 Gaming Headset

**Level up with 50mm drivers, dual ENC mics, and tri-mode connection. Customize audio and mic settings via the QuarterMaster App for tailored performance.**

### HEAR TO WIN

50mm drivers deliver deep bass and crisp highs. With the QuarterMaster app, users can tailor sound and mic settings for any game—immersive audio or clear voice, all precisely tuned.

### DUAL-MIC ENC, CLEAR COMMS

Whether using the detachable omnidirectional boom mic or the onboard mic, ENC technology continuously suppresses ambient noise to highlight your voice.

### INLINE CONTROLS, TOTAL COMMAND

Switch between 2.4GHz (via USB-A/C dongle), Bluetooth 5.4, and wired modes. Enjoy up to 30 hours of lag-free play—stay connected and in the fight, no matter your setup.

## Specifications



# Predator Galea 570

| | | |
|---|---|---|
| Dimension | Headset: 213 x 94 x 166 mm<br>Dongle: 61 x 21 x 10 mm | |
| Weight | 310.5 g ± 5 g | |
| Compatibility | Windows10/ Windows11/ iOS/ Mac OS<br>Android OS/ PS4/ PS5/ Switch<br>Devices with USB | |
| Features | Battery | 1000mAh |
| | Color | Black |
| | Headphone Drivers | Φ50mm |
| | Frequency Response | Speaker: 20~20KHz<br>Microphone: 100~10KHz |
| | Frame material | ABS |
| | Ear pad material | PU |
| | Type | Ear pad: Over ear<br>Microphone: Omnidirectional |
| | ENC | Yes |
| | Maximum Input Power | 40mW |
| | Sensitivity | Speaker: 120 dB ± 3 dB<br>Microphone: -38 dB ± 3 dB |
| | Impedance | 32Ω ± 15% |
| | Software | Predator QuarterMaster app |

© Copyright 2026 Acer Inc.