

PHILIPS



Wired on/off switch (2-channel)

Hue

Add non-smart lights to Hue

App & voice control

No battery required

Unlock more with a Bridge

8721103111753



Easy smart lighting

Add your non-smart lights to your Philips Hue ecosystem – so you can control them like your Hue lights. The wired on/off switch works with most traditional lights and fittings, alongside your existing Hue lights. This 2-channel version lets you control two separate groups of lights independently from the same switch. No need to replace your antique chandeliers or designer fittings. Make the lights you already love – smart! Once installed, you can manage your lights from the Hue app, with voice assistants, or directly from your wall switch. Set timers and schedules that fit your daily routine. Powered by your home's wiring – no need to replace batteries. Install it behind your wall switch, or in the ceiling above your light fixture, where a neutral wire is available. Enjoy reliable, responsive control with a Hue Bridge, even if Wi-Fi is down. For more information: <https://www.philips-hue.com/support/wall-switch-modules>

Specifications

Design and finishing

- Colour: White
- Material: Synthetic

Durability

- Ambient temperature range: -5 to +40 °C
- Nominal lifetime: 25,000

Environmental

- Operational humidity: 20% <H<70% (non-condensing)
- Operational temperature: -5 °C - 45 °C

Extra feature/accessory incl.

- Hue Switch Included: Yes
- Centrepiece: Yes

Guarantee

- 2 years: Yes

Miscellaneous

- Especially designed for: Functional, Bedroom, Dining Room, Living Room, Home Office, Hallway, Study

Packaging information

- EAN: 8721103111753

Power consumption

- Power: 0.6

Product dimensions and weight

- Overall height: 16.8 mm
- Overall length: 41 mm
- Overall width: 37.3 mm

Service

- Warranty: 2 year(s)

Technical specifications

- Mains power: 220–240 V
- IP code: IP20
- Class of protection: Class III – Safe Extra Low Voltage
- UL wet/damp/dry location: Dry location
- Radio frequency sensing: Not applicable
- Zigbee repeater functionality: Yes
- Mounting options: Ceiling, Wall

The bulb

- Software upgradable: Yes

The switch

- Configurable buttons: 2
- Lifetime: 25,000 clicks
- Mounting options: wall
- Supported wiring: Neutral wired
- Output channel: 2 channels
- Supported switch type: Push, Rocker
- Bulb load: 6A (shared)
- Dimmer load: Not applicable

What's in the box

- Wall switch module: 1

What's supported

- Compatible with Effects feature: Yes
- Philips Hue App: Android 12.0 and above, iOS 17 or later
- WiFi: Works without Wi-Fi
- Defined support period: Minimum 60 months from date of purchase from an authorised reseller
- Max. number of accessories: 12 (with Hue Bridge)
- Compatible operating systems: iOS, Android
- Communication protocol: Bluetooth, Zigbee
- Compatibility with third-party systems: Alexa, Google Home, Apple HomeKit, IFTTT, Klikaanklikuit, Matter, Samsung SmartThings, Sonos
- Matter functionality: Via Hue Bridge or third-party hubs (thread border routers)

Box specifications

Packaging dimensions and weight

- EAN/UPC - product: 8721103111753
- Net weight: 0.02 kg
- Gross weight: 0.06 kg
- Height: 140 mm
- Length: 88 mm
- Width: 45 mm





© 2026 Signify Holding. All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.