

PHILIPS



Wired dimmer switch (1-channel)

Hue

Add dimmable non-smart lights to Hue

App & voice control

No battery required

Unlock more with a Hue Bridge

8721103111876



Easy smart lighting

Add your dimmable non-smart lights to your Philips Hue ecosystem for effortless control and convenience. The wired dimmer switch lets you control most traditional lights and fixtures alongside your existing Hue lights, all in one seamless experience. No need to replace your antique chandeliers or designer fittings. Make the lights you already love – smart! Control them in the Hue app, with voice assistants, or directly from your wall switch. Set automations that fit your daily routine, and include lights in scenes. The compact module installs behind the switch and it is mains powered, no battery required. If you are replacing a dimmer switch, a push switch is required to operate this product. As part of the Hue ecosystem, based on a reliable Zigbee network, you stay in control of your lights, even when Wi-Fi is down. For more information: <https://www.philips-hue.com/support/wall-switch-modules>

Specifications

Design and finishing

- Colour: White
- Material: Synthetic

Durability

- Nominal lifetime: 25,000

Environmental

- Operational humidity: 20% <H<70% (non-condensing)
- Operational temperature: -5 °C - 45 °C

Extra feature/accessory incl.

- Hue Switch Included: Yes
- Centrepiece: Yes

Guarantee

- 2 years: Yes

Miscellaneous

- Especially designed for: Functional, Bedroom, Dining Room, Living Room, Home Office, Hallway, Study

Packaging information

- EAN: 8721103111876

Power consumption

- Power: 0.4

Product dimensions and weight

- Overall height: 16.8 mm
- Overall length: 41 mm
- Overall width: 37.3 mm

Service

- Warranty: 2 year(s)

Technical specifications

- Mains power: 220–240 V
- IP code: IP20
- Class of protection: Class III – Safe Extra Low Voltage
- UL wet/damp/dry location: Dry location
- Radio frequency sensing: MotionAware™
- Zigbee repeater functionality: Yes
- Mounting options: Ceiling, Wall

The bulb

- Software upgradable: Yes

The switch

- Configurable buttons: 1
- Lifetime: 25,000 clicks
- Mounting options: wall
- Supported wiring: Neutral wired, Non-neutral wired
- Output channel: 1 channel
- Supported switch type: Push, Rocker
- Bulb load: 20-150W Halogen, Incandescent – leading edge, 20-200W Halogen, Incandescent – trailing edge, 5-200W LED-trailing edge (including dimmable LED ballasts), 5-20W LED-leading edge
- Dimmer load: Leading edge, Trailing edge

What's in the box

- Wall switch module: 1

What's supported

- Compatible with Effects feature: Yes
- Philips Hue App: Android 12.0 and above, iOS 17 or later
- WiFi: Works without Wi-Fi
- Defined support period: Minimum of 48 months after introduction date
- Max. number of accessories: 12 (with Hue Bridge)
- Compatible operating systems: iOS, Android
- Communication protocol: Bluetooth, Zigbee
- Compatibility with third-party systems: Alexa, Google Home, Apple HomeKit, IFTTT, Klikaanklikuit, Matter, Samsung SmartThings, Sonos
- Matter functionality: Via Hue Bridge or third-party hubs (thread border routers)

Box specifications

Packaging dimensions and weight

- EAN/UPC - product: 8721103111876
- Net weight: 0.02 kg
- Gross weight: 0.06 kg
- Height: 140 mm
- Length: 88 mm
- Width: 45 mm



© 2026 Signify Holding. All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.