

Philips Wireless TV link

SBCVL1200

Share your satellite & subscription TV channels

without wires

Watch your TV programmes wirelessly on your 2nd TV. You can choose between 2 devices at the press of a button and do not have to swap cables.

Watch and listen anywhere!

- Watch any video device on a 2nd TV
- · Connect 2 devices simultanously
- \bullet Works with DVD+RW/ DVD/ VCR / set-top box, and many more
- Compatible with most video devices and brands

Operate your TV entertainment anywhere!

- Device can be operated in a closed cabinet
- · Access to 2 devices at the press of a button

Simple set-up and easy to use

- · Less clutter, less fuss and no cable laying or drilling
- Wireless signal passes through walls and ceilings



SBCVL1200/85

Specifications

Tuner/Reception/Transmission

- Antenna location: Picture & sound: Internal, RC extender: External
- Frequency range: picture & sound: 2.4 GHz RC extender: 433 MHz MHz
- TV system: PAL, SECAM
- Typical range indoor: 15-30 m
- Typical range outdoor: 100 m
- Remote control extender
- Supported IR carrier frequency: 32-40 KHz

Accessories

- AC/DC Adaptor: 2x 9VDC, 300mA
- SCART duplicator: 2 pcs on transmitter

Dimensions

• Receiver dimensions (W x H x D):



204 x 65 x 168 mm

- Temperature (operation): $+5^{\circ}$ C to $+35^{\circ}$ C
- Transmitter dimensions (W \times H \times D): 204 \times 65 \times 168 mm

Power

- Power consumption: 7 W
- Power supply: AC/DC Adapter, 220-240V

Transmitter

- SCART 1: CVBS in, Audio L+R in
- SCART 2: CVBS in, Audio L+R in

Receiver

· SCART out: CVBS out, Audio L+R out

Highlights

Watch any device on a 2nd TV

The wireless link uses standard SCART and cinch plugs that are used by almost every brand of audio/video devices. If you device has one of these standard connectors it works with the wireless link

Connect 2 devices

The easy way to switch between any two devices without having to reconfigure your entire home cinema set-up. The wireless TV link has two separate inputs, each with its own SCART connector, enabling you to connect two A/V source devices at the same time.

Works with DVD and many more

Extend your possibilities for viewing movies, sports events, live performances and a range of TV channels anywhere in your home. The wireless TV link is suitable for transmission of AV content of all brands of PayTV and Pay-per-View decoders, satellite receivers, set-top boxes, DVD players, VCRs and camcorders.

Works on almost all brands

The wireless link uses standard SCART and cinch plugs that are used by almost every brand of audio/video devices.

Operates in closed cabinet

If you store your audio/video devices in a cabinet, you cannot operate these devices with a normal IR remote control. The Philips wireless remote control link allows you to operate these devices with the cabinet doors closed thanks to an RF-based link that picks up the infrared signals of a remote control and translates them into RF. The receiver unit then translates them back to IR.

One touch access to 2 devices

There's no need to swap cables at the transmitter to view any video device on the second TV. Simple press the input selection button to switch from input device

Wireles means no drilling

A 2.4 GHz wireless link between the receiver and transmitter means you don't have to lay cables or drill holes through walls.

Wireless goes through walls

There's no need to buy or rent duplicate A/V equipment. The wireless RF system extends your possibilities for viewing DVD movies and your favorite Satellite or TV channels anywhere in your home. With a range of up to 30 meters inside the house, it delivers high-quality video and stereo audio no matter where your second TV is located.



Issue date 2014-02-10

© 2014 Koninklijke Philips N.V. All Rights reserved.

Version: 4.0.5

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V. or their respective owners.

12 NC: 9082 100 00246 EAN: 87 10101 65629 8

www.philips.com