

Dimmer switch

046677458157



Control your lights

anywhere in your house

Enrich your system with the Philips Hue dimmer switch and enjoy smooth wireless dimming. The switch works as a normal wall switch and dimmer. Place it anywhere you want, using screws or the adhesive tape on the back plate of the switch.

Benefits


Easy control

- Dim your Philips Hue lights
- Place it where it matters
- Use as a remote control
- No wires - battery powered
- Switch between scenes
- Requires a Philips Hue bridge

PHILIPS

Features

Dim your Philips Hue lights



Using the Philips Hue dimmer switch, you can smoothly dim your favorite light setting up and down

Place it anywhere




The Philips Hue dimmer switch works as a normal wall switch and dimmer. You can place it anywhere you want, using screws or the adhesive tape on the back plate of the switch

Use as a remote control



Pick up the remote and use it wherever you want for your comfort. The control unit of the switch is magnetic and can be removed from the base plate.

No wires - battery powered



The Philips Hue dimmer switch is battery-powered, so there is no installation required

Switch between scenes



When using your dimmer switch with Philips Hue white ambiance or Philips Hue white and color ambiance products, you can use the on-button to switch between 4 light recipes, or use the Philips Hue app to configure your favorite 4 scenes. It's all up to you

Requires a Philips Hue bridge



This product requires a connection to the Philips Hue bridge

Specifications

Please note that this is a pre-sales leaflet. The contents of this leaflet reflect the best of our knowledge per date and country mentioned above. The contents of this leaflet are subject to change without notice. Philips does not accept any liability as to the contents of this leaflet.

The switch

Batteries included	1 x CR2450
Frequency band	2400 – 2483.5 MHz
Lifetime	50000 clicks
Max. lights per switch	10 if not linked to Hue bridge
Minimal battery life-time	3 year(s)
Minimal range indoor	500 inch
Software upgradeable	when connected to Hue bridge
Switch depth	0.43 inch
Switch height	3.6 inch
Switch width	1.38 inch
Weight of switch	37 g
Wall plate depth	0.55 inch
Wall plate height	2.76 inch
Wall plate width	4.5 inch
Weight including wall plate	67 g

Zigbee Light link protocol IEEE 802.15.4

What's in the box

Hue dimmer switch 1

Environmental

Operational humidity 5% < H < 95% (non condensing)
Operational temperature -10°C – 45°C

Guarantee

2 years Yes



data subject to change
2018, July 26

Version: 4.0.1
UPC: 046677458157

© 2018 Koninklijke Philips N.V.
All rights reserved.

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V. or their respective owners.

www.philips.com