## ThinkCentre M800z Platform Specifications

Product Specifications Reference (PSREF)

Processor	Intel <sup>®</sup> Celeron <sup>®</sup> , Intel Pentium <sup>®</sup> , or 6th Generation Intel Core™ i3 / i5 / i7 Processor						Keyboard	Some: Preferred Pro USB Keyboard (USB connector), Lenovo logo						
	Processor Cores / Frequency Cache Memory Types Integrated						litoybourd	Some: Lenovo Slim USB Keyboard (USB connector), black						
			Base/Max(GHz)			Graphics	Mouse		Some: Ultraslim Plus Wireless Keyboard (2.4GHz via USB receiver), black Some: Enhanced Optical USB Mouse, black, Lenovo logo					
	Celeron G3900	2/2	2.8 G	2 MB	DDR4-2133	HD 510					Mouse (2.4GHz via USB receiver), black			
	Pentium G4400 Pentium G4500		3.3 G 3.5 G	3 MB	DDR4-2133 DDR4-2133	HD 510 HD 530	Mechanical	Business black color						
	Core i3-6100	2/2 2/4	3.7 G	3 MB 3 MB	DDR4-2133	HD 530		Toolle						
	Core i3-6300	2/4	3.8 G	4 MB	DDR4-2133	HD 530		• Suppo	ort VES	A mount (100mm)				
	Core i5-6400	4/4	2.7 G / 3.3 G	6 MB	DDR4-2133	HD 530				Dimensions (WxDxH)	Max weight (lb / kg)	Adjustments		
	Core i5-6500	4/4	3.2 G / 3.6 G	6 MB	DDR4-2133	HD 530		Withou	ut stand:	21.1 X 1.8 X 14.3 (inch); 535 X 45 X 363 (mm)	(Touch) 14.6 / 6.6 (Non-touch) 12.8 / 5.8	N/A		
	Core i5-6600	4/4	3.3 G / 3.9 G	6 MB	DDR4-2133	HD 530		With	Basic	21.1 X 9.6 X 17.0 (inch);	/	Tilt: 45° back,		
	Core i7-6700	4/8	3.4 G / 4.0 G	8 MB	DDR4-2133	HD 530		Monito	or stand:		(Non-touch) 17.0 / 7.7	-5° forward		
Memory	32GB max, DDR	4 2133 t	wo 260-nin SO-[	DIMM sor	kets dual-chann	el canable	-	Mith LI	IltroElov	$(21.1 \times 10.0 \times 10.2 \text{ (in ab)})$	(Touch) 20.2 / 0.2	Tilt: 61° back,		
Disk			•		-	ci capabic	-		tand:	21.1X 10.0 X 19.3 (inch); 535 X 253 X 489 (mm)	(Touch) 20.3 / 9.2 (Non-touch) 18.3 / 8.3	-5° forward; Lift: 160mm;		
DISK	Some: SATA 6.0Gb/s, 2.5" Wide, 5400 rpm or 7200 rpm Some: Solid State Hybrid Drive (SSHD) / with 8GB MLC NAND flash memory, SATA 6.0Gb/s, 2.5" Wide, 5400 rpm Some: Solid State Drive (SSD) / SATA 6.0Gb/s, 2.5" Wide Some: DVD, SATA 1.5Gb/s, 9.5mm high										Swivel: +/-45°			
							Power supply	150 watts, autosensing, 85% PSU						
Optical							Limited warranty <sup>3</sup>							
Optical	Some: DVD, SA			n high				Some:	1-year	or 3-year, limited onsite	service			
Media reader	Optional 9-in-1 m		0						service, OID (Onsite International Delivery) /					
Graphics	Intel HD Graphics 510/530 in processor, uses main memory, DirectX <sup>®</sup> 12, external monitor support via DisplayPort™; <i>Max resolution:</i> 4096x2304 (DP)@60Hz 21.5" (546.1mm) Full HD 1080p (1920x1080) TFT color, MVA panel, wide viewing							For Lenovo service upgrade options, please go to S-TC sheet						
							Preload		Preloaded operating system Preloaded applications (only so Some: Windows® 7 Professional 64 listed)					
Display								Some.	preinstalled through downgrade • Desktop Power Manager					
	angle (+/- 89°), LED backlight, 250 nits, 16:9 aspect ratio, 1000:1 contrast ratio, anti-glare for both touch models and non-touch models							rights in Windows 10 Pro 64-bit • Lenovo Solution Center						
Light sensor	anti-glare for bot	h touch m	nodels and non-t	ouch mo	dels			Some: Some:	Windo	ws 7 Professional 64 ws 10 Pro 64-bit	<ul> <li>Lenovo REACHit</li> <li>Lenovo SHAREit</li> </ul>			
Multi-touch	Optional Projecte	) technol	ogy, supports 10-	point touch		Some: Windows 10 Home 64-bit • Lenovo Bluetooth Lock								
Camera	Optional 1.0-megapixel camera, fixed focus, supports 720p, with digital microphone, LED indicator, physical switch on/off							(for models with Wi-Fi/BT card)						
Controls			nower button						<ul> <li>McAfee<sup>®</sup> LiveSafe<sup>™</sup> (3</li> <li>Microsoft Office preloa</li> </ul>					
Chipset	Microphone mute, brightness up/down buttons, and power button Intel H110 Chipset						-		<ul> <li>purchase a product key to activate</li> <li>PowerDVD Create (DVD±RW)</li> </ul>					
Rear ports	Four USB 2.0, ethernet (RJ-45), DisplayPort, optional serial (9-pin),						-				<ul> <li>PowerDVD Create (DVD±RW)</li> <li>Lenovo ThinkVantage Tools</li> </ul>			
Side ports	Two USB 3.0 (one is Always On and fast charge), optional card reader, one headphone / microphone combo jack (3.5mm)								<ul> <li>Only for Window 10</li> <li>Lenovo Companion</li> </ul>					
M.2 card slot	One M.2 Card slot (for WLAN)						-	<ul> <li>Cyberlink PowerDVD (DVD, DVD±F</li> <li>Lenovo QuickOptimizer</li> </ul>						
Audio support	High Definition (HD) Audio, Realtek ALC233 / two internal stereo speakers (2W x 2), Dolby <sup>®</sup> Audio™ certified						,	- Only for Window 7						
							_		Rescue and Recovery					
WLAN <sup>13</sup>	Some: 11ac wireless, M.2 Card, Qualcomm Atheros QCA9377 (dual band), Wi-Fi + Bluetooth 4.1 combo adapter, 1x1										<ul> <li>Password Manager</li> <li>ThinkVantage System</li> </ul>	Undate		
	Some: 11ac wir				os OCA6174 (dua	al band)					<ul> <li>Lenovo Message Cent</li> </ul>			
	Wi-Fi + E	Bluetooth	4.1 combo adap	ter, 2x2	,	,.					<ul> <li>Adobe<sup>®</sup> Reader<sup>®</sup></li> </ul>			
	<ul> <li>Some: 11ac wireless, M.2 Card, Intel Dual Band Wireless-AC 3165, Wi-Fi + Bluetooth 4.0 combo adapter, 1x1</li> <li>Some: 11ac wireless, M.2 Card, Intel Dual Band Wireless-AC 8260, Wi-Fi + Bluetooth 4.1 combo adapter, 2x2</li> </ul>						Environment	EPEAT™ Gold rating; ENERGY STAR <sup>®</sup> 6.1; TCO Certified; ErP Lot 3;						
									GREENGUARD® certified; RoHS-compliant For compatible accessories, please go to TC-AQP sheet					
							Accessories	For com	ipatible	accessories, please go to	DIG-AQP SNEET			
Bluetooth™ Ethernet	Some: Bluetooth Gigabit ethernet,					combo adapter								
Manageability	None	rieditek			N		-							
Security chip	Trusted Platform	Module (	TPM 1.2-complia	ant)										
	• Security slot (in rear for attachment of • Power-on, admin, hard disk password													
,	optional Kensir	ngton® Mi	croSaver® cable	<ul> <li>Boot s</li> </ul>	equence control									
	<ul> <li>Kensington loc</li> <li>Smart USB pro</li> </ul>				vithout keyboard lual USB port dis									
			torage devices		al Chassis intrus									
0 (	nore detailed inform	action										© Lenovo		

See footnotes for more detailed information