HP LaserJet Pro M12 Printer series



Small price. Big performance. Smart choice.

Depend on professional quality and trusted HP performance, using the lowest-priced and smallest laser printer from HP.¹ Easily save space and budget.



HP LaserJet Pro M12a Printer



HP LaserJet Pro M12w

Outstanding, reliable quality without compromises

- Time after time, count on documents with sharp black text from the industry leader in laser printing.²
- Help save energy with HP Auto-On/Auto-Off Technology.⁷
- Start printing right out of the box, using a preinstalled Original HP LaserJet toner cartridge.

Efficient printing for small workspaces

- Stay productive with print speeds up to 19 pages per minute.³
- Make the most of limited workspace with this compact HP LaserJet Pro—the smallest laser printer HP offers.
- Get high-quality pages and the performance you can count on with Original HP toner cartridges.

Well-connected printing to match the way you work⁹

- Easily access, print, and share resources with wireless networking.4
- Easily print from mobile devices with Android™ version 4.4 or later or Google Chrome™ operating systems.⁶
- Print directly from your mobile device—without accessing the network.⁵
- Print with the ease of sending an email, right from a smartphone, tablet, or notebook, using HP ePrint.^a

Product walkaround



HP LaserJet Pro M12w

- 1. LED control panel
- 2.100-sheet output bin
- 3. Hi-Speed USB 2.0 port
- 4. Top cover access to toner cartridges
- 5. Wireless Direct Printing
- 6. Built-in wireless networking (802.11b/g/n)
- 7.150-sheet multipurpose tray (shown open)

Series at a glance





Model	HP LaserJet Pro M12a Printer	HP LaserJet Pro M12w
Product number	T0L45A	TOL46A
Mobile printing capability	No	HP ePrint; Wireless direct printing

HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs.

Choose from

Optimized Care (optimum performance and stability)

4 hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configu ation Service

Standard Care (high level of uptime)

Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configu ation Service

Basic Care (minimum recommended support)

Next Business Day Onsite Support

4 hr Onsite Support

Onsite support within four hours after a service call received within the coverage window

Next Business Day Onsite Support

Onsite service the next business day after the service call is received

Maintenance Kit Replacement Service

Onsite replacement of your printer's maintenance kit including parts, materials, and labor

Installation with Network Configuration Service

Assembly, network configu ation, and basic administrator familiarization For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit hp.com/go/printservices









Top Features

Easily print high-quality documents, and get the reliability you count on from the industry leader in laser printing.² Print right out of the box with a preinstalled Original HP cartridge. Help save energy with HP Auto-On/Auto-Off Technology.⁷

Stay productive. Quickly and easily print documents and save space with the smallest laser printer from HP. Together with Original HP toner cartridges, this HP laser printer delivers high-quality performance.

Quickly and easily get consistent results with this HP laser printer. Tackle jobs from your mobile device, with or without a network.⁴⁵ Mobile printing options let you produce high-quality prints from virtually anywhere.⁶⁸

Product

TOL45AHP LaserJet Pro M12a PrinterTOL46AHP LaserJet Pro M12w

Replacement cartridges*

CF279A HP 79A Black Original Laser Jet Toner Cartridge(1,000 pages)

HP Care Packs

UG086EHP 3 year Care Pack w/Next Day Exchange for LaserJet PrintersUG481EHP 3 year Care Pack w/Onsite Exchange for LaserJet PrintersUG361EHP 3 year Care Pack w/Pickup and Return Support for LaserJet PrintersUG289EHP 3 year Care Pack w/Return to Depot Support for LaserJet Printers

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to hp.com/go/cpc

Paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

HP Web Jetadmin: hp.com/go/wja

HP Universal Print Driver: hp.com/go/upd

HP Imaging and Printing Security Center: hp.com/go/ipsc

HP LaserJet Pro M12 Printer series

Print Number Print Only Print Sprint options Manual Duplex print options Black (normal, A4) Up to 18 ppm; Black (normal, letter) Up to 19 ppm First spage out Black (A4, ready) Up to 9.2 sec; Black (A4, sleep) Up to 9.3 sec E Print resolution Black (b4) Up to 600 x 600 x 2 dpi; Black (normal) Up to 400 x 600 x 2 dpi (600 dp Print resolution HP FastRes 600, HP FastRes 1200 Print resolution Standard print languages Host-based printing T Standard print languages Host-based printing T Connectivity 1 Hi-Speed USB 2.0 N Standard print languages Mobile print capability No Network ready No N Network ready No N Duty cycle (monbly) ⁸ Up to 5000 pages; Recommended monthly page volume ⁸ 100 to 1,000 Paper handling Ipp S Input 150-sheet input tray; Output Output 100-sheet output bin S Media sizes custom 150-sheet input tray; 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm S <th>HP LaserJet Pro M12w</th>	HP LaserJet Pro M12w		
Print Manual Duplex print options Manual Print speed Black (normal, A4) Up to 18 ppm: Black (normal, letter) Up to 19 ppm First page out Black (A4, ready) Up to 9.2 sec; Black (A4, sleep) Up to 9.3 sec; E Print technology Laser Print resolution Black (DeSt Up to 600 x 600 x 2 dpi; Black (normal) Up to 400 x 600 x 2 dpi (600 dp Print resolution technology HP FastRes 600, HP FastRes 1200 Print and the fast fast of the fast fast fast fast fast fast fast fast	TOL46A		
Duplex print options Manual Print speed Black (normal, A4) Up to 18 ppm; Black (normal, letter) Up to 19 ppm First page out Black (A4, ready) Up to 9.2 sec; Black (A4, sleep) Up to 9.3 sec B Print resolution Black (Best) Up to 600 x 600 x 2 dpi; Black (normal) Up to 400 x 600 x 2 dpi (600 dp Print resolution technology HP FastRes 600, HP FastRes 1200 Print resolution technology Print resolution technology HOS-based printing Connectivity Standard print languages Host-based printing Connectivity Standard print capability Mobile Print Capability not supported H Network ready No S Wireless capability No S Processor speed 266 MHz S Duty cycle (monthly)* Up to 5000 pages; Recommended monthly page volume* 100 to 1,000 Paper handling Iso-sheet input tray; Output Iop-sheet input tray; 147 x 211 to 216 x 356 mm D Dimensions (W x D x H)* 349 x 238 x 196 mm Weight Weight 5.2 kg Wind ws* 7, 8, 8, 1, 10 (32-bit/64-bit), Windows Vsta* (32-bit/64-bit), Windows* XP1 2003 (32-bit/64-bit), Windows* XP1 2003 (32-bit/64-bit), Win			
Display System Display System Display System Black (normal, A4) Up to 18 ppm; Black (normal, letter) Up to 19 ppm First speed Black (A4, ready) Up to 9.2 sec; Black (A4, sleep) Up to 9.3 sec E Print resolution Black (best) Up to 600 × 600 × 2 dpi; Black (normal) Up to 400 × 600 × 2 dpi (600 dp Print resolution He FastRes 600, HP FastRes 1200 Print resolution technology Print resolution technology HP FastRes 600, HP FastRes 1200 1 Mobile print anguages Host-based printing 1 Connectivity 1 H-Speed USB 2.0 1 Mobile print capability Mobile Print Capability not supported I Mobile print capability No N Y Wireless capability No Y Y Processor speed 266 MHz S S Processor speed 266 MHz S Duty cycle (monthyl)* Up to 5000 pages; Recommended monthly page volume* 100 to 1,000 Paper nandling Input 150-sheet input tray; Duty cycle (monthyl)* Got to 163 g/m² Media sizes custom 150-sheet input tray; Duty cycle (monthyl)*			
First page out Black (A4, ready) Up to 9.2 sec; Black (A4, sleep) Up to 9.3 sec. B Print technology Laser Print resolution Black (best) Up to 600 × 600 × 2 dp; Black (normal) Up to 400 × 600 × 2 dp; (600 dp Print resolution technology HP FastRes 600, HP FastRes 1200 Print resolution technology HD FastRes 600, HP FastRes 1200 Print resolution technology HD FastRes 600, HP FastRes 1200 Print resolution technology HD FastRes 20, HD FastRes 1200 Standard connectivity 1 HE-Speed USB 2.0 Mobile print capability Mobile Print Capability not supported No No Wireless capability No Memory Standard 2 MB Processor speed 266 MHz Duty cycle (monthy)* Up to 5000 pages; Recommended monthly page volume* 100 to 1,000 Paper handling Input Input 150-sheet input tray; Output 100-sheet output bin Media vight 60 to 163 g/m² Media sizes custom 150-sheet input tray; 147 x 211 to 216 x 356 mm Dimensions (W x D x H)2 349 x 238 x 196 mm Weight 5.2 kg What's in the box HP			
Print technology Laser Print resolution Black (best) Up to 600 x 600 x 2 dpi; Black (normal) Up to 400 x 600 x 2 dpi (600 dp Print resolution HP FastRes 600, HP FastRes 1200 Print cartridges number 1 Black Standard print languages Host-based printing Connectivity Standard connectivity Standard connectivity Mobile Print Capability not supported Network ready No Wireless capabilities None Metwork ready No Memory Standard 2 MB Processor speed 266 MHz Duty cycle (monthy) ⁴ Up to 5000 pages; Recommended monthly page volume ⁹ 100 to 1,000 Paper handling Input Input 150-sheet input tray; Output 100-sheet output bin Media sizes custom 150-sheet input tray; 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Ye Nindows [®] 7, 8, 8, 1, 10 (32-bit/64-bit), Windows Vista [®] (32-bit/64-bit), Windows [®] XP i 2003 (32-bit/64-bit), Windows [®] 7, 9, 8, 1, 10 (32-bit/64-bit), Windows [®] XP i 2003 (32-bit/64-bit), Windows [®] 7, 9, 8, 1,	Black (normal, A4) Up to 18 ppm; Black (normal, letter) Up to 19 ppm		
Print resolution Black (best) Up to 600 × 600 × 2 dpi; Black (normal) Up to 400 × 600 × 2 dpi (600 dp Print resolution technology HP FastRes 600, HP FastRes 1200 Print cartidges number 1 Black Standard print languages Host-based printing Connectivity 1 Hi-Speed USB 2.0 1 Mobile print capability Mobile Print Capability not supported 1 Metwork ready No No No Wireless capability No No No Memory Standard 2 MB S S Processor speed 266 MHz S Duty cycle (monthly) ^B Up to 5000 pages; Recommended monthly page volume ⁹ 100 to 1,000 Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media sizes custom 150-sheet input tray; 214 × 211 to 216 × 356 mm Dimensions (W x D x H) ² 349 × 238 × 196 mm Weight 5.2 kg What's in the box HP Laser let Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Inder Struge Contrast and graves and documentation on CD-R0M, Power cond; USB V Warranty features Oneyear limited warranty Systems	Black (A4, ready) Up to 9.2 sec; Black (A4, sleep) Up to 9.4 sec		
Print resolution technology HP FastRes 600, HP FastRes 1200 Print cartridges number 1 Black Standard print languages Host-based printing Connectivity 1 Hi-Speed USB 2.0 Mobile print capability Mobile Print Capability not supported Network ready No Wireless capability No Processor speed 266 MHz Duty cycle (monthly) ^a Up to 5000 pages; Recommended monthly page volume ^a 100 to 1,000 Paper flaser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media type Paper flaser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media type Paper flaser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media type Paper flaser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray; 147 x 211 to 216 x 356 mm Dimensions (W X D x H) ² 349 x 238 x 196 mm What's in the box HP Laser.Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser.Jet IT for Cartridge (-500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-R0M; Power cord; USB V indows ^b XPi (2003 (32-bit/64-bit); Mindows Vista ^b (32-bit/64-bit), Windows ^b XPi (2003 (32-bit/64-bit); Mac 05 X v 10.9, v 10.	,		
Print cartridges number 1 Black Standard print languages Host-based printing Connectivity Standard connectivity Standard connectivity No Mobile print capability Mobile Print Capability not supported I Network ready No S Wireless capabilities Non S Memory Standard 2 MB S Paper handling Ipt o 5000 pages; Recommended monthly page volume® 100 to 1,000 Paper handling Ipt o 5000 pages; Recommended monthly page volume® 100 to 1,000 Paper handling Ipt o 5000 pages; Recommended monthly page volume® 100 to 1,000 Paper handling Ipt o 5000 pages; Recommended monthly page volume® 100 to 1,000 Media type Paper laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray; 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet IP Tomer Cartridge (-500 pages); Installation guide, Sottware drivers and documentation on CD-R0M; Power cord; USB Vindows ⁶ XP i 2003 (32-bit/64-bit); Mac OS X 10.9, vol.0, vol.0.1 Warranty features) dpi effective output); Black (fine lines) Up to 600 × 600 × 2 dpi		
Standard print languages Host-based printing Connectivity 1 Standard connectivity 1 Mobile print capability Mobile Print Capability not supported 1 Mobile print capability No 2 Wireless capability No 1 Network Capabilities None 1 Memory Standard 2 MB 7 Processor speed 266 MHz 100 Duty cycle (monthy) ^a Up to 5000 pages; Recommended monthly page volume ^a 100 to 1,000 Paper handling 100-sheet output bin 100-sheet output bin Media stype Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What's in the box HP Laser.Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser.Jet I for Oner Cartridge (-500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V cable (AP only) Warranty features One-year limited warranty Systems <	HP FastRes 600, HP FastRes 1200		
Connectivity 1 Hi-Speed USB 2.0 Mobile print capability Mobile Print Capability not supported 1 Network ready No S Wireless capability No N Network Capabilities None S Memory Standard 2 MB S Processor speed 266 MHz S Duty cycle (monthly) ^B Up to 5000 pages; Recommended monthly page volume ⁹ 100 to 1,000 Paper handling 150-sheet input tray; O Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight S 2.48 What 's in the box HP Laser/let Pro M12a Printer; Preinstalled HP Original Introductory Black Laser/let I Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Waranty guide; Software drivers and documentation on CD-ROM; Power cord; USB U cable (AP only) V Warranty features One-year limited warranty S2 -bit/64-bit); C6 RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows [®] 7, 8, 8, 1, 10 (32-bit/64-bit); C6 RAM for 64-bit, 1, Windows Vista [®] (32-bit/64-bit), Windows [®] XP 12 003 (32-bit/64-bit); C6 RAM for 64-bit); C4 B RAM for 32-bit, 4 <t< td=""><td colspan="2">1 Black</td></t<>	1 Black		
Standard connectivity 1 Hi-Speed USB 2.0 1 Mobile print capability Mobile Print Capability not supported 1 Network ready No 2 Wireless capabilities None 1 Metwork Capabilities None 1 Memory Standard 2 MB S Processor speed 266 MHz 2 Duty cycle (monthly) ^a Up to 5000 pages; Recommended monthly page volume ^a 100 to 1,000 Paper handling Input 150-sheet input tray; 0 0 Output 100-sheet output bin 100-sheet output bin 100-sheet adapted	Host-based printing		
Mobile print capability Mobile Print Capability not supported I Network ready No S Wireless capability No No Network Capabilities None Nemory Standard 2 MB Y Processor speed 266 MHz S S Duty cycle (monthly) [®] Up to 5000 pages; Recommended monthly page volume [®] 100 to 1,000 Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media weight 60 to 163 g/m ² Media sizes custom Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg Mohle Software drivers and documentation on CD-ROM; Power cord; USB varranty guide; Software drivers and documentation on CD-ROM; Power cord; USB varranty guide; Software drivers and documentation on CD-ROM; Power cord; USB varranty features One-year limited warranty Systems One-year limited warranty 2003 (32-bit/64-bit); Mindows Vista® (32-bit/64-bit), Windows® XP 12003 (32-bit/64-bit); AGB RAM for 32-bit, 4 You Mindows® XP 12, 60 ang; Power consumption*: 375 watts (active printing), 1.2 watts (reactive rows of XP 10, 0, 0, 10, 11; 1 GB available processor, 750 MB F 512 MB RAM, 400 MB free HD 5pace; all systems: CO-ROM/DVD drive or Internet conn S12 MAM, 40			
Network ready No Standard 2 MB None Memory Standard 2 MB Y No Processor speed 266 MHz Duty cycle (monthly) [®] Up to 5000 pages; Recommended monthly page volume [®] 100 to 1,000 Paper handling Input 150-sheet input tray; Dutput Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet Inore Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V V What's in the box Windows [®] 7, 8, 8, 1, 10 (32-bit/64-bit), Windows Vista [®] (32-bit/64-bit), Windows [®] XP intel Pentium [®] II, Celeron [®] or 233 MHz compatible processor, 750 MB for 2-bit, 4 Nindows [®] XP. Intel Pentium [®] II, Celeron [®] or 233 MHz compatible processor, 750 MB for 2412, MB RAM, 400 MB free HD Space; all systems: CD-ROM/IVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 11.1 Minimum system requirements PC windows [®] XP. Intel Pentium [®] II, Celeron [®] or 233 MHz compatible processor, 750 MB for 2412, Ha RAM, 400 MB free HD Space; all syste	1 Hi-Speed USB 2.0; 1 WiFi 802.11b/g/n		
Wireless capability No N Network Capabilities None S Memory Standard 2 MB S Processor speed 266 MHz S Duty cycle (monthly) [®] Up to 5000 pages; Recommended monthly page volume [®] 100 to 1,000 Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media sizes custom 60 to 163 g/m ² Media sizes custom Media sizes custom Dimensions (W x D x H) ² 349 x 238 x 196 mm Media sizes custom Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V Compatible operating systems Compatible operating systems Windows [®] 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista [®] (32-bit/64-bit), Windows [®] XP i 2003 (32-bit/64-bit), Mac OS X v 10.9, v 10.1, 1 Mac Mac OS X v 10.9, v 10.1, 1 Minimum system requirements PC Windows [®] XP, ittel Pentium [®] II, Celeron [®] or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.1, 1 Gavailable hard disk space; CD-ROM drive; USB V 10.9, V10.1, 1 EV Power Power supply type Built-in power s	HP ePrint; Mopria™-certified; Mobile Apps		
None Metwork Capabilities None Memory Standard 2 MB S Processor speed 266 MHz Duty cycle (monthly) [®] Up to 5000 pages; Recommended monthly page volume [®] 100 to 1,000 Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media weight 60 to 163 g/m ² Media sizes custom 150-sheet input tray; 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet To ore Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V cable (AP only) Warranty features One-year limited warranty Systems Windows [®] 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista [®] (32-bit/64-bit), Windows [®] XP it 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows [®] 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista [®] (32-bit/64-bit), 1 GB RAM for 32-bit, 4 Windows [®] XP it Be Huitu [®] HU Caron [®] or 23 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB I 2 MB RAM, 400 MB free HD spa	Standard (built-in WiFi 802.11b/g/n)		
Memory Standard 2 MB S Processor speed 266 MHz Duty cycle (monthly)® Up to 5000 pages; Recommended monthly page volume® 100 to 1,000 Paper handling Input Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H)2 349 x 238 x 196 mm Weight 5.2 kg What's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V cable (AP only) Warranty features One-year limited warranty Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP i 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements Windows® 7, 8, 8.1,10 (32-bit/64-bit), S GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XD i 10.10, 0.11; 1 GB available hard disk space; CD-ROM drive; USB i 12 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac AG OS X 10.9, 10.10, 1.1; 1 GB available hard disk space; CD-ROM drive; USB i 12 MB RAM, 400 MB free HD space; all system	Yes		
Processor speed 266 MHz Duty cycle (monthly) ^a Up to 5000 pages; Recommended monthly page volume ⁹ 100 to 1,000 Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet [1 Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB [2 Cable (AP only) Warranty features One-year limited warranty Systems 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP in 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP in 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP in 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10,			
Duty cycle (monthly) ^e Up to 5000 pages; Recommended monthly page volume ^a 100 to 1,000 Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media weight 60 to 163 g/m ² Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Media sizes custom 5.2 kg What 's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V cable (AP only) Warranty features One-year limited warranty Systems Compatible operating systems Windows® 7, 8, 8.1,10 (32-bit/64-bit); Windows Vista® (32-bit/64-bit), Windows® XP i 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 11.1 1 GB available hard disk space; CD-ROM drive; USB I Power Power supply type Built-in power supply; Power supply required Input voltage 115 t/-2 L2), 6.0 amp;	Standard 8 MB		
Paper handling Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies. Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V cable (AP only) Warranty features One-year limited warranty Systems 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F S12 MB RAM, 400 MB free HD space; all systems: CD-ROM/IVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB I Control panel Power supply type Built-in power supply; Power supply required Input voltage 115 (+/- 2 Hz), 6,0 amp; Power consumption*, 375 wats (active printing), 1.2 watts (read wats (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption and watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption and watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption and watts (Auto-off/Ma			
Input 150-sheet input tray; Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H) ² 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet IT Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB I cable (AP only) Warranty features One-year limited warranty Systems Compatible operating systems Compatible operating systems Windows® 7, 8, 8.1,10 (32-bit/64-bit); Windows Vista® (32-bit/64-bit), Windows® XP i 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows WP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB I Control panel Power upply type Built-in power supply; Power supply required Input voltage 115 (+/- 2 Hz), 6.0 a mp; Power consumption 375 watts (active printing), 1.2 watts (read watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur watts (Auto-off/Manual-on), 0.45 (Man			
Output 100-sheet output bin Media type Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies Media weight 60 to 163 g/m² Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H)² 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB (able (AP only)) Warranty features One-year limited warranty Systems Compatible operating systems Windows [®] 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista [®] (32-bit/64-bit), Windows [®] XP (2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows [®] 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows [®] XP: Intel Pentium [®] II, Celeron [®] or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems; CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB J Control panel 2 LED indicator lights (Attention, Ready) 3 Power Power supply type Built-in power supply; Power supply required Input voltage 115 (+/- 2 H2), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manu			
Media veight Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies. Media veight 60 to 163 g/m² Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H)2 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB (cable (AP only)) Warranty features One-year limited warranty Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.1,0, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows % XP 1000 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11,1 GB available hard disk space; CD-ROM drive; USB J 10 (actor lights (Attention, Ready) Power Power supply type Built-in power supply; Power supply required Input voltage 113 Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustics Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (act Environmental ranges Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperature Humidity	150-sheet input tray;		
Media weight 60 to 163 g/m² Media sizes custom 150-sheet input tray: 147 x 211 to 216 x 356 mm Dimensions (W x D x H)² 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (-500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB (cable (AP only) Warranty features One-year limited warranty Systems 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB I (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included Al HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Accustic Pressure Emissions Bystander (act Environmental ranges Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperatu Humidity Range: 10 to 80% RH; Recommended Operating Temperatu Humidity Range: 10 to 80% RH; Recommended Operating Temperatu Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to Safety appr	100-sheet output bin		
Media sizes custom 150-sheet input tray: 147 × 211 to 216 × 356 mm Dimensions (W x D x H)2 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet IT Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB V cable (AP only) Warranty features One-year limited warranty Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP 12003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB I (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Accustic Pressure Emissions Bystander (act thumidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 30 to 186 (4000 Prover 2012/01 / EN 62479:2010	Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies, postcards		
Dimensions (W x D x H)2 349 x 238 x 196 mm Weight 5.2 kg What 's in the box HP Laser Jet Pro M12a Printer; Preinstalled HP Original Introductory Black Laser Jet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB (cable (AP only)) Warranty features One-year limited warranty Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP (2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11) Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB for 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB for the Amax Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB for the Amax Mac OS X 10.9, 0.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB for the Amax (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption num Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Accustic Pressure Emissions Bystander (actt Humidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 30 to 10 80% RH; Recommended Operating Temperatt Humidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 30 to 10 80%	60 to 163 g/m ²		
Weight 5.2 kg What 's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB cable (AP only) Warranty features One-year limited warranty Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP (2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB for 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 11; 1 GB available hard disk space; CD-ROM drive; USB for the Control panel Power Power supply type Built-in power supply Power supply required Input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (act Humidity Range: 10 to 80% RH; Recommended Operating Temperatur Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 t	•		
What 's in the box HP LaserJet Pro M12a Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB cable (AP only) Warranty features One-year limited warranty Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP I 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB f 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 11; 1 GB available hard disk space; CD-ROM drive; USB J Control panel Power Power supply type Built-in power supply: Power supply required Input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (act Humidity Range: 10 to 80% RH; Recommended Operating Temperature Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 7 Safety approvals and requirements			
Toner Cartridge (~500 pages): Installation guide, Setup Poster, Support flyer, 1 Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB cable (AP only) 1 Warranty features One-year limited warranty Systems 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit); 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet com Mac Mac OS X 10.9, 10.10, 11; 1 GB available hard disk space; CD-ROM drive; USB J Control panel 2 LED indicator lights (Attention, Ready) Power Power supply type Built-in power supply: Power supply required input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 1.5 to 32.5°C; Recommended Operating Temperature Humidity Range: 10 to 80% RH; Recommended Operating Temperature Product); IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12	5.2 kg		
Systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP I 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F S12 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.1; 1: GB available hard disk space; CD-ROM drive; USB J Control panel 2 LED indicator lights (Attention, Ready) 3 Power Power supply type Built-in power supply; Power supply required Input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Accustic Pressure Emissions Bystander (act Humidity Range: 10 to 80% RH; Recommended Operating Temperatt Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 3 Safety approvals and requirements	HP LaserJet Pro M12w Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB cable		
Compatible operating systems Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP I 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB J Control panel Power supply type Built-in power supply; Power supply required Input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Operating Temperature Range: 15 to 32.5%; Recommended Operating Temperature Humidity Range: 10 to 80% RH; Recommended Operating Temperature Humidity Range: 10 to 80% RH; Recommended Operating Temperating Humidity Range: 30 to 32.5%; Recommended Operating Temperature Humidity Range: 30 to 30.5%; Recommended Operating Humidity Range: 30 to 30.5%; Recommended Operating Humidity Range: 30 to 30.5%; Recommended Operating Humidity Range: 30 to 30.5%; Recommended Operating H	One-year limited warranty		
2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11 Minimum system requirements PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 4 Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB J Control panel 2 LED indicator lights (Attention, Ready) 3 Power Power supply type Built-in power supply; Power supply required input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustic Power Emissions: 6.4 B(A); Accustic Pressure Emissions Bystander (act Humidity Range: 10 to 80% RH; Recommended Operating Temperature Humidity Range: 30 to 3 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12			
Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB F S12 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet conn Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB J Control panel 2 LED indicator lights (Attention, Ready) Power Power supply type Built-in power supply; Power supply required Input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (read watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustics Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (acti Humidity Range: 10 to 80% RH; Recommended Operating Temperature Humidity Range: 10 to 80% RH; Recommended Operating Temperating Temperature Range: 15 to 32.5%; Recommended Operating Temperature Humidity Range: 20 to 7 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12	Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP (32-bit/64-bit), Windows® Server 2008 (32-bit/64-bit), Windows® Server 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11		
Power Power supply type Built-in power supply: Power supply required input voltage 115 (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reac watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption nur Software included MP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustics Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (acti Humidity Range: 10 to 80% RH; Recommended Operating Temperatur Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 3 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12 Product); IEC 62479:2010 / EN 62479:2010	PC Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 400 MB Free HD space; Windows Vista® (32-bit/64-bit): 1 GB RAM (32-bit); Windows® XP: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB Free HD space; Windows® Server 2008 (32-bit/64-bit), Windows® Server 2003: 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet connection, USB port Mac Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB port; Internet		
(+/- 2 H2), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (reactive vatts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption num Software included HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller Accoustics Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (active printing Temperature Range: 15 to 32.5%; Recommended Operating Temperature Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 3 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009+A1:2010+A12	3 LED indicator lights (Wireless, Attention, Ready); 2 buttons (Wireless, Cancel)		
Acoustics Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (acti Environmental ranges Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperatur Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 3 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12 Product); IEC 62479:2010 / EN 62479:2010	Power supply type Built-in power supply; Power supply required Input voltage 115 to 127 VAC (+/- 10%), 60 Hz (+/- 2 Hz), 12 amp; 220 to 240 VAC (+/- 10%), 50 Hz (+/- 2 Hz), 6.0 amp; Power consumption ⁴ : 375 watts (active printing), 1.2 watts (ready), 0.8 watts (sleep), 0.8 watts (Auto Off/Wake on USB, enabled at shipment), 0.4 watts (Auto-off/Manual-on), 0.45 (Manual Off); Typical Electricity Consumption number ⁵ BA: 0.509 kWh/Week; ES: 0.494 kWh/wk		
Environmental ranges Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperatur Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 3 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12 Product); IEC 62479:2010 / EN 62479:2010	HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller		
Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 7 Safety approvals and requirements IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12	Accoustic Power Emissions: 6.4 B(A); Acoustic Pressure Emissions Bystander (active, printing): 50 dB(A)		
requirements Product); IEC 62479:2010 / EN 62479:2010	Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperature: 17.5 to 25°C; Non-operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 30 to 70% RH		
Supported network protocols Via built-in Wi-Fi 802.11b/g/n wireless network: IPv4, IPv6; HP ePrint	Via built-in Wi-Fi 802.11b/g/n wireless network: IPv4, IPv6; HP ePrint		

Footnotes

¹ Lowest-priced claim based on manufacturer's suggested retail price (MSRP). Actual prices may vary.

² Based on WW market share of units shipped CY-1996 through CY-2015, WW color and monochrome laser categories. Source: IDC 2015Q4 Quarterly Hardcopy Peripheral Tracker. ³ Measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz routers only.

Sector works with devices running Android[®] 4.4 or later. Mobile device needs to be connected directly to the Wi-Fi[®] network of a witzet solic contents solid. FP or printer prior to printing. Depending on mobile device, each app or driver may also be required. Learn more at hp.com/go/mobileprinting. Wi-Fi is a registered trademark of Wi-Fi Alliance[®].

⁶ Feature does not work with an iPhone[®], an iPad[®], or mobile devices running Windows[®]. Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Learn more at h.c.com/ao/mobileorintina.

⁷ HP Auto-On/Auto-Off Technology capabilities are subject to printer and settings.

⁸ Printer requires ePrint account registration. App or software may be required. Wireless operations are compatible with 2.4 GHz operations only. Learn more at hp.com/go/mobileprinting.

⁹ Features are all applicable to M12w only.

Technical specification disclaimers

² Without input or output trays extended ³ With print cartridges

⁴ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typicallty based on measurement of 115V device

Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device

⁶ Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled.

⁷ Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see

http://www.hp.com/go/learnaboutsupplies

⁸ Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP Laser Jet or HP Color Laser Jet devices, and ⁹ HP recommends that the number of printers and MPPs to satisfy the demands of connected individuals or groups.

extended warranty period. ¹⁰ HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit http://www.hp.com/go/SureSupply

To learn more, visit hp.com

© Copyright 2016 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained hereir



ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Microsoft and Windows are registered trademarks of Microsoft Corporation. AirPrint and the AirPrint logo are trademarks of Apple Inc., registered in the U.S. and other countries. Linux is a U.S. registered trademark of Linux Torvalds. UNIX is a registered trademark of The Open Group.