

# ASR1102A ASR1102A-D

## Fingerprint RFID Reader



### Features

- RS-485 protocol
- Default IC (Mifare) card (“-D” means ID EM card)
- Support card, fingerprint
- Up to 3000 fingerprints capacity
- Blue backlight
- Watch dog function ensure device free from halting
- Beep and indicator
- Surface mounted installation



### Technical Specification

Mode	ASR1102A	ASR1102A-D
------	----------	------------

#### System

Main Processor	8 Bit
----------------	-------

#### Read

Read Format	13.56MHz	125KHz
-------------	----------	--------

Read Range	6-8cm (max.)
------------	--------------

Reading time	<0.1s
--------------	-------

#### Fingerprint

Capacity	3000
----------	------

Response Time	≤0.5s
---------------	-------

Recognition Time	≤1.5s
------------------	-------

FAR	≤0.00004%
-----	-----------

FRR	≤0.15%
-----	--------

#### Function

Tamper Alarm	Yes
--------------	-----

#### Interface

To Controller	RS485
---------------	-------

#### General

LCD Display	Blue backlight
-------------	----------------

Beep Tone	Buzzer
-----------	--------

Ingress protection	IP55
--------------------	------

Power Supply	9-15VDC/100mA
--------------	---------------

Working Environment	-5°C~+55°C
---------------------	------------

Working Humidity	5%~95%
------------------	--------

Dimension(W×D×H)	125mm*56mm*47mm
------------------	-----------------

Weight	0.25kg
--------	--------

### Dimensions

