

Xerox[®] VersaLink[®] B605 Multifunction Printer

VersaLink B605 Multifunction Printers are built on Xerox[®] ConnectKey[®] Technology.
For more information, go to www.ConnectKey.com.



SYSTEM SPECIFICATIONS	B605/S	B605/X	B605/XL
One-sided Speed¹ A4 / 210 x 297 mm 216 x 356 mm	Up to 55.5 ppm black and white Up to 48.5 ppm black and white		
Two-sided Speed¹ A4 / 210 x 297 mm 216 x 356 mm	Up to 49.3 ppm black and white Up to 27 ppm black and white		
Monthly Duty Cycle²	Up to 300,000 pages / month		
Recommended Average Monthly Print Volume³	Up to 25,000 pages		
Hard Drive	320 GB HDD		
Processor	1.05 GHz ARM Dual Core		
Memory	2 GB		
Connectivity	Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair		
Controller Features	Unified Address Book, Configuration Cloning, Scan Preview, Xerox Extensible Interface Platform [®] , Xerox [®] App Gallery App, Xerox [®] Standard Accounting Tool, Network Accounting Enabled, Role Based Permissions, Convenience Authentication Enabled, Online Support		
User Interface Languages	English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan, Ukrainian, Croatian		

Xerox® VersaLink® B605 Multifunction Printer

DEVICE SPECIFICATIONS				
ELECTRICAL REQUIREMENTS				
North America	Voltage: 110-127 VAC +/- 10% Frequency: 50/60 Hz +/- 3% Hz, 12 A			
Europe and Other Geographies	Voltage: 220-240 VAC +/- 10% Frequency: 50/60 Hz +/- 3% Hz, 8 A			
POWER CONSUMPTION				
Continuous Print ⁴	950 watts or less			
Ready (Standby) ⁴	79 watts or less			
Energy Saver (Sleep Mode) ⁴	1.1 watts or less			
Power Off Mode ⁴	0.3 watts or less			
OPERATING ENVIRONMENT				
Required Temperature Range (Storage)	0° to 35° C			
Required Temperature Range (Operating)	10 to 32° C			
Required Relative Humidity	15% to 85%			
Sound Power Levels Running Standby	70 dB(A) or less 43 dB(A) or less			
Sound Pressure Levels Running Standby	58.3 dB(A) or less 29 dB(A) or less			
Boot Time (from Off to UI Ready)	Less than 79 seconds			
Warm-up Time (from Sleep to UI Ready)	Less than 47 seconds			
DIMENSIONS AND WEIGHT (UNPACKAGED)	WIDTH	DEPTH	HEIGHT	WEIGHT
B605/XL	470 mm	502.8 mm	843.7 mm	32.5 kg
B605/S and B605/X	470 mm	502.8 mm	643.7 mm	30.5 kg
B605/XL with Finisher	470 mm	502.8 mm	843.7 mm	39.3 kg
B605/XL with Mailbox	470 mm	502.8 mm	843.7 mm	37.8 kg
B605/S and B605/X with High Capacity Feeder	470 mm	502.8 mm	1425.7mm	65.6 kg
550-sheet Tray	420 mm	464.5 mm	123 mm	6.6 kg
High Capacity Feeder (includes Caster Base)	724.2 mm	772.1 mm	459 mm	19.7 kg
Stand (includes Caster Base)	724.2 mm	772.1 mm	336 mm	16.6 kg
Caster Base	724.2 mm	772.1 mm	90 mm	8.5 kg
Mailbox	450.8 mm	477.6 mm	248.0 mm	5.3 kg
Finisher	450.8 mm	411.0 mm	248.0 mm	6.8 kg
DIMENSIONS AND WEIGHT (PACKAGED)	WIDTH	DEPTH	HEIGHT	WEIGHT
B605/S and B605/X	594 mm	655 mm	789 mm	38 kg
B605/XL	594 mm	655 mm	996 mm	43 kg

Xerox® VersaLink® B605 Multifunction Printer

550-sheet Tray	535 mm	584 mm	248 mm	8.5 kg
High Capacity Feeder	568 mm	663 mm	711 mm	38 kg
Stand (includes Caster Base)	584 mm	629 mm	597 mm	28 kg
Caster Base	585 mm	619 mm	330 mm	18 kg
Mailbox	573 mm	518 mm	386 mm	7.8 kg
Finisher	573 mm	398 mm	386 mm	8.8 kg
Wireless Network Adapter (Wi-Fi Kit)	188 mm	136 mm	55 mm	0.1 kg
CERTIFICATIONS				
To view the latest list of certifications, go to www.xerox.com/OfficeCertifications .				
PRINT				
First-print-out Time	As fast as 7.5 seconds			
Print Resolution	Up to 1200 x 1200 dpi			
Page Description Languages	PCL® 5e, 6 PDF XPS TIFF JPEG HP-GL Adobe® PostScript® 3™			
Maximum Print Area	4 mm from lead edge of paper, 2 mm from Side and Trail edges of paper			
Print Features	<ul style="list-style-type: none"> Application Defaults Banner Pages Enable / Disable Bi-directional Real-time Status Booklet Layout Draft Mode Fit to new paper size Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages) Job Monitoring (Client or Local User Interface) LAN Fax (requires Fax Kit) N-up Page Layout (up to 16 pages per sheet) Paper Selection by Attribute Personal Print Print Around Enable / Disable Print from USB Sample Set Saved Job Scaling Secure Print Skip Blank Pages Special Pages (exception page programming: covers, inserts, exceptions pages) Store and Recall Driver Settings Stored Jobs Deletion Two-sided Printing (as default) Watermark (predefined and custom) Earth Smart Driver Settings 			
Print from USB	<ul style="list-style-type: none"> Allows walk-up printing from Type A USB port Supports direct printing from computer via Type B USB port Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A 			

Xerox® VersaLink® B605 Multifunction Printer

Operating Systems	<p>Windows® 7, 8, 8.1, 10 Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016 macOS® 10.11, 10.12, 10.13 Citrix® Redhat® Enterprise Linux® Fedora Core IBM® AIX® HP-UX® Oracle® Solaris SUSE® SAP®</p> <p>Note: For information about supported versions for the above operating systems, please visit our Drivers & Downloads page and specify your device at www.support.xerox.com</p>
Fonts	<p>PostScript fonts: 136 PCL fonts: 83</p>
Xerox® Global Print Driver®	A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.
Xerox® Pull Print Driver	Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others.
COPY	
Document Scanner	100-sheet Single-pass Duplex Automatic Document Feeder (DADF)
Maximum Scan Area	Platen: Up to 215.9 mm x 355.6 mm DADF: Up to 215.9 mm x 355.6 mm
Simplex Copy Speed	Up to 58 cpm (copies per minute) A4 black and white
Duplex Copy Speed	Up to 52.2 cpm A4 black and white
First-copy-out Time	As fast as 5.8 seconds
Sides (input:output)	1:1, 1:2, 2:2 and 2:1
Quantity	1 to 999
Resolution (max.)	Up to 600 x 600 dpi
Reduction / Enlargement	Variable zoom from 25% to 400% in 1% increments
Concurrency	Concurrent scanning and printing
Copy Features	<p>Annotation (Page Numbers, Comments, Date Stamp, Bates Stamping) Automatic Background Suppression Book Copying with Center Erase Booklet Copying Collation Darkness Control Edge Erase Front Cover ID Card Copy Image Enhancement Lighten/Darken N-up Reduce / Enlarge 25% to 400% Image Shift Original Orientation Original Size Original Type Page Layout Sample Copy Saturation Sharpness</p>

Xerox® VersaLink® B605 Multifunction Printer

SCAN	
Capability	Black-and-white and colour scanning
Concurrency	Scan while the system is printing copy or network print jobs, or while it is transferring scan to network or fax jobs
Simplex Input Speed	Black-and-white: Scan up to 55 ipm A4 Colour: Scan up to 55 ipm A4
Duplex Input Speed	Black-and-white: Scan up to 55 ipm A4 Colour: Scan up to 55 ipm A4
Resolution	600 x 600 dpi
Bit Depth	24-bit colour / 8-bit grayscale
Maximum Scan Area	Platen: Up to 215.9 x 355.6 mm Document Feeder: Up to 215.9 x 355.6 mm
Network Filing Protocols	FTP SMTP SMB sFTP
File Formats	JPG TIFF (single and multi-page) XPS (single and multi-page) PDF (single and multi-page) Searchable PDF via Optical Character Recognition (OCR) Password-protected PDF Linearised PDF (set via embedded web server) and PDF/A
Scan Driver Compatibility (Network Only)	WIA TWAIN
Supported Scan Destinations	Scan to Home Scan to USB Scan to Email Scan to Network (FTP or Browse SMB)
NETWORK SCANNING – SOFTWARE SOLUTIONS	
Xerox® ConnectKey Apps (Found at the Xerox App Gallery)	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, serverless ConnectKey Apps to the ConnectKey-enabled device.
FAX (AVAILABLE ON B605/X ONLY)	
FAX⁵	
Fax Speed	33.6 Kbps
Memory	4 MB
Resolution	Standard 200x100 dpi, Fine 200x200 dpi, Super Fine 300x300, 400x400, 600x600 dpi
Compression	MH/MR/MMR/JBIG
Fax Features	Walk-up Fax, LAN Fax, Direct Fax, Fax Forward to Email Fax dialing via Unified Address Book (up to 2,000 contacts)

Xerox® VersaLink® B605 Multifunction Printer

MOBILE SOLUTIONS AND MOBILE DEVICE APPS	
Apple® AirPrint®	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.
Google Cloud Print™	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.
Mopria® Certified	ConnectKey Technology-enabled print devices are Mopria® certified. Mopria® certification ensures you can print wirelessly from your Mopria® supported (Android) smart phone, tablet and other mobile devices instantly and easily.
Xerox® @printbyXerox App	@printbyXerox App is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address, and release them at the MFP panel.
Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.
Xerox® Mobile Link App (Free at Google Play™ Store and Apple® App Store)	The Xerox® Mobile Link App allows you to scan, email and fax from your phone or tablet by connecting with our multifunction printers and send data to and print data from cloud storage. It is easy to create Mobile Link One-Touch Workflows between a mobile device and a multifunction printer. Using a manual address or QR code identification for pairing, automatic device discovery makes it easy to find and pair a mobile device with a nearby Xerox® multifunction printer.
Xerox® Workplace Suite and Xerox® Workplace Cloud	Xerox® Workplace Suite is a modular set of workflows designed to save customers time and money by providing effective control over their print fleet, while enabling worker productivity and mobility through a set of robust workflows. Xerox enables ultimate customer flexibility by offering these capabilities in both an on-premises server version (Workplace Suite) and with a cloud based-version (Workplace Cloud) of this solution.
SECURITY	
Security Features	<ul style="list-style-type: none"> Access Controls AES 256-bit Encryption Audit Log Certificate Path Validation Certificate Revocation List (CRL)/Status Protocol (OCSP) Detection of External Program Falsification (XCP Plug-in) Cisco® Identity Services Engine (ISE) Integration Domain Filtering FIPS 140-2 Firmware Verification Immediate Disk Overwrite IP Address Filtering IPsec Network Authentication Port Filtering Pre-installed Self-Signed Certificates Role Based Permissions Secure Email Secure Fax Secure Print Secure Scanning via SFTP Security Certificate Management Smart Card Enablement (CAC/PIV/.NET) SNMPv3 Status Protocol (OCSP) TLS/SSL Trusted Platform Module (TPM)

Xerox® VersaLink® B605 Multifunction Printer

ACCOUNTING			
XEROX® STANDARD ACCOUNTING / NETWORK ACCOUNTING (STANDARD)			
Tracking	Copy, Print, Fax, Scan and Email usage		
Accounting	Xerox® Standard Accounting Tool Up to 9,999 User Accounts Up to 500 General Accounts Network Accounting (Job Based Accounting) Up to 60,000 User IDs; Up to 60,000 Account IDs Up to 14,000 Accounting Records (transactions)		
Features	Administrator can manage the feature via the Embedded Web Server.		
ACCOUNTING OPTIONS – NETWORK ACCOUNTING (ALLOWS CENTRAL SERVER TO MANAGE ALL ACCOUNTING)			
	<ul style="list-style-type: none"> Enhanced network accounting with up-to-the-minute data on how the system is being used Comprehensive management and enterprise scale tracking and reporting of device usage of copy, print, scan and server fax Numerous solutions are available through Xerox Alliance Partners. For details visit www.xerox.com Security enhancements include simultaneous support for HTTP/HTTPS protocols Device requests account authentication from third party server enabling larger databases of users and accounts Accept Authentication Login at control panel and pass to third party Networking Account Interface with third party accounting terminal for accounting user interface 		
PAPER HANDLING			
DOCUMENT FEEDER			
Capacity⁶	Single-pass Duplex Automatic Document Feeder (DADF): 100 sheets		
Sizes	Custom sizes: 140 x 140 mm to 216 x 356 mm		
Weights One-sided: Two-sided:	60 to 128 gsm 60 to 128 gsm		
BYPASS TRAY			
Capacity⁶	150 sheets		
Sizes	Custom sizes: 76 x 127 mm to 216 x 356 mm		
Weights One-sided: Two-sided:	60 to 220 gsm 60 to 176 gsm		
Media Types	Plain Paper Bond Punched Pre-Printed	Recycled Envelopes Labels Lightweight Card Stock	Card Stock Letterhead Custom 1-5
TRAY 1			
Capacity⁶	550 sheets		
Sizes	Custom sizes: 76.2 x 190 mm to 216 x 356 mm		
Weights One-sided: Two-sided:	60 to 220 gsm 60 to 176 gsm		
Media Types	Pre-Printed Recycled Envelopes (Tray 1 only)	Labels Lightweight Card Stock Card Stock	Letterhead Custom 1-5

Xerox® VersaLink® B605 Multifunction Printer

UP TO 4 ADDITIONAL TRAYS (OPTIONAL)			
Capacity⁶	550 sheets		
Sizes	Custom sizes: 76.2 x 190 mm to 216 x 356 mm		
Weights One-sided: Two-sided:	60 to 220 gsm 60 to 176 gsm		
Media Types	Pre-Printed Recycled Envelopes (Tray 1 only)	Labels Lightweight Card Stock Card Stock	Letterhead Custom 1-5
HIGH CAPACITY FEEDER (OPTIONAL – CAN BE COMBINED WITH 1 ADDITIONAL TRAY)			
Capacity⁶	2000 sheets		
Sizes	Standard sizes: A4 SEF		
Weights One-sided: Two-sided:	60 to 176 gsm 60 to 176 gsm		
Types	Plain Paper Bond Punched	Pre-Printed Recycled Lightweight Card Stock	Letterhead Custom 1-5
TOTAL PAPER CAPACITY⁶			
Standard Paper Capacity	700 sheets		
Maximum Paper Capacity	3,250 sheets		
PAPER OUTPUT			
OUTPUT TRAY			
Capacity⁶	400 sheets with tray full sensor (without Finisher or Mailbox)		
Automatic Two-sided Printing	Standard		
FINISHER (OPTIONAL)			
Capacity⁶	500-sheet tray, 50-sheet stapling		
MAILBOX (OPTIONAL)			
Capacity⁶	Four 100-sheet bins		

Xerox® VersaLink® B605 Multifunction Printer

DEVICE MANAGEMENT	
Network Protocols	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD LDAP Bonjour® / AirPrint® FTP Most protocols not in use can be disabled
Administrative Protocols	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS
REMOTE CONTROL PANEL	
	<ul style="list-style-type: none"> • Enables faster, more convenient technical support and user training • IT administrators and other authorized users can control the device remotely from a web page on any device • Remote user experience is identical to performing tasks directly at the device
XEROX® CENTREWARE® WEB	
	<ul style="list-style-type: none"> • A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system • Works with any SNMP-managed printer from any manufacturer • Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management
EMBEDDED WEB SERVER – INTEGRATED DEVICE WEB PAGE	
Device Status	<ul style="list-style-type: none"> • Tray status/contents • Consumables status • Billing/Usage • Quick Links • Online Support
Print Queue Viewing	Job print queue management—view and delete
Job Submission	Print-ready files (PS, PCL, PDF, XPS, JPEG)
Device Administration	Allows simple, remote installation setting of configuration options and management of the device
Browsers	Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™
REMOTE SERVICES	
Automated Meter Readings (AMR)	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.
Automatic Supplies Replenishment (ASR)	Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory.
Maintenance Assistant	Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox, allowing for problems to be solved faster with increased uptime.

Xerox® VersaLink® B605 Multifunction Printer

WHAT COMES IN THE BOX		
	VersaLink B605 Multifunction Printer Standard Capacity Print Cartridge –Black: 10,300 print capacity ⁷ Software and Documentation CD (with User Manual, Quick Install Guide, Safety, Regulatory, Recycling and Disposal Guides, Print Drivers, and Warranty Statement) Installation Guide Quick Use Guides Power cord Fax cord	
SUPPLIES AND ACCESSORIES	QUANTITY	PART NUMBER
SUPPLIES		
Extra-High Capacity Toner Cartridge	Black: 46,700 standard pages ⁷	106R03944
High Capacity Toner Cartridge	Black: 25,900 standard pages ⁷	106R03942
Standard Capacity Toner Cartridge	Black: 10,300 standard pages ⁷	106R03940
Drum Cartridge	Black: 60,000 pages ⁸	101R00582
ACCESSORIES / OPTIONS		
2,000-sheet High Capacity Feeder (includes Stand/Caster Base)		097S04948
550-sheet Feeder		097S04949
Finisher (500 sheets, 50-sheet stapler)		097S04952
4-Bin Mailbox (100 sheets per bin)		097S04953
Caster Base		097S04954
Stand (includes Caster Base)		097S04994
Wireless Network Adapter (Wi-Fi Kit)		497K16750

¹ Declared print speed in accordance with ISO/IEC 24734.

² Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

³ Recommended average throughput is not a minimum, but is intended to cover a range of volumes for different environments.

⁴ Power states defined per ENERGY STAR® Program requirements for Imaging Equipment.

⁵ Requires analog phone line.

⁶ Paper capacities are based on 20 lb. / 75 gsm stock; capacities will vary with different weight stocks.

⁷ Average standard pages. Declared Yield in accordance with ISO/IEC19752. Yield will vary based on image, area coverage and print mode.

⁸ Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: <https://www.office.xerox.com/latest/SUPGL-01.pdf>.

For more information, visit us at www.xerox.com/Office

Configurations vary by geography.

©2019 Xerox Corporation. All rights reserved. Xerox®, CentreWare®, ConnectKey®, Global Print Driver®, Mobile Express Driver®, VersaLink® and Xerox Extensible Interface Platform® are trademarks of Xerox Corporation in the United States and/or other countries. The information in this brochure is subject to change without notice. 7/19 PN03335_T121 BR26781 VB6SS-02EF

