



Analog Box Camera

Taurus ECB 3rd Generation

- True WDR 120dB
- 2 Megapixel 1/3" CMOS sensor
- 700 TVL Compatible output
- On Screen Display
- Privacy Masking
- Motion Detection
- 2 X BNC outputs
- True Day/Night
- 2 year Warranty

New 2MP CMOS Sensor

The 3rd generation Taurus box camera incorporates a new CMOS image sensor offering a 700TVL output for legacy systems while offering excellent colour reproduction and low light sensitivity.

WDR

The Taurus range also offers the latest Wide Dynamic Range (120dB) feature making this range ideal for surveillance in areas with strong variations in light, for instance close to large windows and entrances or where the sunlight creates both very bright zones and dark shadows.

Masking

Up to 8 privacy masking zones can be set using the on screen display (OSD) Other features include motion detection and Defog settings in the camera.

Legacy Support

The new range of CMOS analog cameras have a 700TV Line BNC output which will work on any analog DVR, Matrix System, Twisted Pair Video Transmission and any other Analog systems you may have installed over the years making them ideal for existing legacy project maintenance.

Motion Detection


Up to 4 motion detection zones can be set using the on screen display (OSD) , these zones can be used to trigger the alarm output.

On Screen Display

The in screen display makes simple work of setting up privacy masking and other camera settings like camera text and wide dynamic range settings.

Technical Specification Taurus ECB 245

Camera		
Image Sensor	2MP CMOS Image Sensor	
Signal System	PAL/NTSC	
Effective Pixels	1944(H)*1092(V)	
Min. illumination	Colour : 0.01 Lux @(F1.2,AGC ON); B/W : 0.001 Lux @(F1.2,AGC ON)	
Shutter Time	1/25(1/30)s to 1/50,000s	
Lens Mount	C/CS mount	
Auto-iris	DC drive	
Day & Night	ICR	
Synchronization	Internal synchronization	
WDR	120dB	
Video Frame Rate	1080p@25fps/1080p@30fps	
HD Video Output	1 BNC HD output	
Analog Output	1Vp-p 700TVL Composite Output(75Ω/BNC)	
Alarm	-A: 1 Alarm input; 1 Alarm output	
S/N Ratio	>62dB	
Menu		
Scene	Indoor, Outdoor, Indoor1, Low-Light	
Camera ID	On/off (15 characters, position programmable)	
AGC	Support	
D/N Mode	Colour/BW/EXT	
White Balance	ATW, AWC-SET, Manual	
Privacy Mask	On/Off, maximum 8 zones	
Motion Detection	On/Off, maximum 4 zones	
BLC	Support	
Anti-flicker	On/Off	
Language	English, Japanese, CHN1, CHN2, Korean, German, French, Italian, Spanish, Polish, Russian, Portuguese, Dutch, Turkish, Hebrew and Arabic	
Functions	HSBLC, Digital noise reduction, Digital zoom(62x), Slow shutter, Mirror, Defog, Defect pixel correction, SMART D-ZOOM	
General		
Operating Conditions	-30 ° C – 60 ° C (-22 ° F – 140 ° F), Humidity 90% or less (non-condensing)	
Power	12 VDC±15%, -A: 24V±15% AC, 12V±15% DC	
Power Consumption	Max. 4W, -A: Max. 6W	
Communication	Up the coax, (HD output)	
Dimensions	69.2×57.3×148.7mm(2.7" × 2.3" × 5.85")	
Weight	520 g	
Operating Conditions	-30 ° C – 60 ° C (-22 ° F – 140 ° F), Humidity 90% or less (non-condensing)	
Part Number		
Part Number	Type	Voltage
0017-06400	Taurus ECB 245 D	12VDC / 24VAC
0017-06401	Taurus ECB 245 M	12VDC / 24VAC / 240V AC PSU included



DISTRIBUTED BY

CE FC

We reserve the right to introduce product modifications without notice

Follow us on



© 2015 Ernitec. All rights reserved
www.ernitec.com

Ernitec
Tempovej 41
2750 Ballerup
Denmark

R01 FN0717