

Product Line
PA-RACK

Type
RM-PA-T3

Supported Models **PALO ALTO PA-220 (2UP)**

DIMENSIONS 1.3/U
COLOR RAL 5009 Azure Blue
PACKING DIMENSIONS 80 x 520 x 270 mm
3.14 x 20.47 x 10.63 in
PRODUCT DIMENSIONS 57 x 482 x 217 mm
(height x width x depth) 2.24 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Slide the extension part into the rack as shown on the picture and fix the two parts with two washers and M3x4mm bolts.
2. Place up to two Palo Alto PA-220 on the rack with the connectors facing the front.
3. Use two K40x6,4mm bolts and washers per Palo Alto PA-220 to fix the appliances on the sides.
4. Place up to four power supplies on the rack and tie them down with two zip ties each.
5. Tie the excess length of the power cable down with one zip tie each.
6. Place your PA-Rack in your 19 inch rack.
7. Place the Rackmount.IT front plate **BELOW** the rack mount kit. Together they are 2U high.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	PA-Rack + front plate
1	PA-Rack extension part
12	Zip ties
2	Bolts M3x4mm
4	Bolts K40x6,4mm
6	Washers



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 5 - 20-08-2020

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT