HP LaserJet Pro M1213nf Multifunction Printer



Tackle your everyday office tasks with an affordable, full-featured MFP. Easily print, copy, scan and fax from one compact machine. Share resources with Ethernet networking or work anywhere in the office with wireless connectivity.¹²





Get more done—affordably—with a full-featured MFP.

- Share on a network and work from anywhere in the office, using built-in Ethernet and wireless.¹²
- Print high-quality documents with bold text and sharp images, using Original HP print cartridges.
- Send and receive faxes from your PC, using the 33.6 kbps fax. Use the built-in handset for phone calls.3
- Print documents at up to 19 ppm letter/18 ppm A4. Start printing fast with Instant-on Technology.

Get up and running quickly and easily.



- Connect the MFP directly to a PC or Netbook via the included Hi-speed USB 2.0 port.
- Ensure reliable printing with an HP all-in-one print cartridge. Easily replace it with HP SureSupply.

Reduce your impact and protect your bottom line.

- Conserve energy with HP Auto-On/Auto-Off Technology, Instant-on Technology and Instant-on Copy.
- Reduce your impact—pre-installed cartridges decrease packaging. Recycle easily with HP Planet Partners.⁷
- Get the services, solutions, software and support of HP Total Care.
- Save energy with an ENERGY STAR® qualified MFP.





Technical specifications

Functions	Print, copy, scan, fax
Print	
Duplex print options	Manual (driver support provided)
Print speed	Black (A4, normal) Up to 18 ppm; Black (letter, normal) Up to 19 ppm
First page out	Black (A4, ready) As fast as 8.5 sec
Print resolution	Black (best) Up to 600 x 600 dpi (1200 dpi effective); Black (normal) Up to 600 x 600 dpi (1200 dpi effective)
Print technology	Läser
Print resolution technology	HP FastRes 1200, HP FastRes 600
Print cartridges number	1 (black)
	Host-haspf
Standard print languages	HP Trollhox
Printer management	TIE TOURDA
Scan	Type Flatbed, ADF;
Scan technology	Normal (A4) Up to 7.4 ppm (b&w), up to 3 ppm (color)
Scan speed	
Scan resolution	Enhanced Up to 19,200 dpi; Hardware Up to 1200 x 1200 dpi; Optical Up to 1200 dpi
Scan size	ADF 216 x 356 mm Flatbed 216 x 297 mm
Scan input modes	Scanning via HP LaserJet scan application or TWAIN—or WIA-compliant application software
Сору	
Copy speed	Black (A4, normal) Up to 18 cpm
Copy resolution	Black (text and graphics) Up to 600 × 400 dpi; Color (text and graphics) Up to 600 × 400 dpi
Max. number of copies	Up to 99 copies
Copier resize	25 to 400%
Copier settings	Number of copies; Lighter/Darker; Reduce/Enlarge; Copy quality (draft, text, mixed, picture, photo)
Fax	
Fax speed	Black (best) Up to 300 x 300 dpi; Black (standard) 203 x 98 dpi; Black and white (fine) 203 x 196 dpi, 256 levels of gray; Black and white (superfine) 300 x 30
	dpi or 203 x 392 dpi, 256 levels of gray: Black photo grayscale 300 x 300 dpi (halftone)
Fax resolution	Up to 300 x 300 dpi
Fax features	Auto fax reduction supported Yes; Auto-redialing Yes; Fax delayed sending Yes; Distinctive ring detection supported Yes; Fax forwarding supported Yes;
	Junk barrier supported Yes; Maximum speed dialing numbers Up to 100 numbers; PC interface supported Yes; Fax polling supported Yes
Fax smart software features	Auto fax reduction; auto redialing; delayed sending; fax forwarding; TAM interface; save and load speed dials; poll receive; fax activity reports; dial prefix setting;
	receive to PC; print fax log
Connectivity	
Standard connectivity	Hi-Speed USB 2.0 port; 10/100Base-T Ethernet network port; RJ-11 Telephone port
Mobile printing capability	HP ePrint, Apple AirPrint™
Network ready	Standard (built-in Ethernet)
Wireless capability	No
Network Capabilities	Via built-in 10/100Base-T TCP/IP networking
HP ePrint capability	No
Memory	Standard 64 MB; Maximum 64 MB
Processor speed	400 MHz
Duty cycle (monthly)	Up to 8000 pages; Recommended monthly page volume: 250 to 2000
Paper handling	
Input	150-sheet input tray;
Output	100-sheet face-down bin
Media type	Paper (plain, laser), envelopes, transparencies, labels, cardstock, postcards
	60 to 163 g/m²
Media weight	76 x 127 to 216 x 356 mm
Media sizes custom	435 x 265 x 306 mm
Dimensions (W x D x H)	
Weight	8.3 kg
What's in the box	HP Laser let Pro M1213nf MFP, power cord(s), phone cord(s), 150-sheet input tray, output tray, introductory HP Laser let Black print cartridge, Readris PRO text recognition software, CD(s) with software and documentation, Installation Guide, support flyer, Errata sheet, Discovery Sheet, Ferrite with flyer, Warranty Guide (where applicable), USB cable:
Warranty features	One-year limited warranty.
Systems	
Compatible operating systems	Windows 8, Windows 7, Windows Vista, Windows XP, Windows Server 2008, Windows Server 2003; Mac OS X v10.4, v10.5, v10.6; Linux (see hplip.net)
Minimum system requirements	PC Microsoft® Windows® 7, Windows Vista®, Windows® XP, Windows® Server 2003: 1 GHz processor, 1 GB RAM, 700 MB free hard disk space, SVGA 800 x 600 with 16-bit colour display, Internet Explorer 5.5 or higher, USB or Ethernet port Mac Mac OS X, 10.4, v. 10.5, v. 10.6, PowerPC G3, 64, 65, or Intel processors; 1 GB RAM; 200 MB available hard disk space; CD-ROM drive; USB or network port
Fonts and Typefaces	None (Host-based)
ronts and ryperaces	2 Part 22 days and the state of
Control panel	2-line, 13-character graphic display; menu and navigation buttons (Setup/Enter, Left, Right, Cancel); copy control buttons (Number buttons, Lighter/Darker, More copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low)
	2-line, 13-character graphic display; menu and navigation buttons (Setup/Enter, Left, Right, Cancel); copy control buttons (Number buttons, Lighter/Darker, More copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low) 2-line LCD
Display	copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low) 2-line LCD Power supply type Built-in power supply; Power supply required input voltage 110 to 127 VAC (+/- 10%), 60 Hz (+/- 2 Hz); 220 to 240 VAC (+/- 10%), 50/60 Hz
Display Power	copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low) 2-line LCD Power supply type Built-in power supply; Power supply required input voltage 110 to 127 VAC (+/-10%), 60 Hz (+/-2 Hz); 220 to 240 VAC (+/-10%), 50/60 Hz (+/-2 Hz); Power consumption: 375 watts (printing), 245 watts (copying), 4.7 watts (ready), 2 watts (sleep), 0.3 watts (off); Typical electricity consumption (TEC)
Display Power Software included	copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low) 2-line LCD Power supply type Built-in power supply, Power supply required Input voltage 110 to 127 VAC (+/- 10%), 60 Hz (+/- 2 Hz); 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); Power consumption: 375 watts (printing), 245 watts (copying), 4.7 watts (ready), 2 watts (sleep), 0.3 watts (off); Typical electricity consumption (TEC numbers: 0.711 Whl/Week Host-based print drivers, TWAIN, WIA, Scan to application, XPS driver, Mac driver, Send Fax, Toolbox.
Display Power Software included Acoustics Environmental ranges	copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low) 2-line LCD Power supply type Bull:-in power supply: Power supply required input voltage 110 to 127 VAC (+/- 10%), 60 Hz (+/- 2 Hz); 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); Power consumption: 375 watts (printing), 245 watts (copying), 4.7 watts (ready), 2 watts (sleep), 0.3 watts (off); Typical electricity consumption (TEC number: 0.771 kWh/Week Host-based print drivers; TWAIN, WIA, Scan to application, XPS driver, Mac driver, Send Fax, Toolbox. Acoustic power emissions: 6.3 B(A); Acoustic power emissions (ready) inaudible; Acoustic pressure emissions bystander (ready) inaudible pressure emissions bystander (ready) inaudible and pr
Display Power Software included Acoustics	copy settings, Start Copy); Fax control buttons (Redial, Start Fax); 3 LED indicator lights (Attention, Ready, Toner low) 2-line LCD Power supply type Built-in power supply: Power supply required input voltage 110 to 127 VAC (+/- 10%), 60 Hz (+/- 2 Hz); 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); Power consumption: 375 watts (printing), 245 watts (copying), 4.7 watts (ready), 2 watts (sleep), 0.3 watts (off); Typical electricity consumption (TEC number: 0.771 kWh/Week Host-based print drivers, TWAIN, WIA, Scan to application, XPS driver, Mac driver, Send Fax, Toolbox. Acoustic power emissions: 6.3 B(A); Acoustic power emissions (ready) inaudible: Acoustic pressure emissions bystander (active, printing) 50 dB(A); Acoustic pressure emissions bystander (active, printing) 50 dB(A); Acoustic pressure emissions bystander (ready) inaudible: Acoustic pressure emissions bystander (active, printing) 50 dB(A); Acoustic pressure emissions bystander (active, printi

Ordering Information

Number Description

HP LaserJet Pro M1213nf Multifunction Printer CE845A

Supplies and Maintenance Kits

Number Description

CC388A HP 88A Black Original LaserJet Toner Cartridge

Accessories

Number Description

Q6264A HP Hi-Speed USB Cable (6 ft./1.8 m)

HP Care Packs

Number	Description
UH774PE	HP 1 year Post Warranty Care Pack w/Onsite
	Exchange for LaserJet Printers
UH772E	HP 2 year Care Pack w/Onsite Exchange for
	LaserJet Printers
UH773E	HP 3 year Care Pack w/Onsite Exchange for
	Laser let Printers

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to hp.com/go/cpc

HP Inc. offices

Australia	(613) 8833 5000	hp.com.au
China	(010) 6564 3888	hp.com.cn
Hong Kong	(852) 3559 7777	hp.com.hk
India	(80) 2612 9000	hp.com/in
Indonesia	(62-21) 5799 1088	hp.com/id
Korea	(02) 2199 0114	hp.co.kr
Malaysia	(603) 2332 3333	hp.com.my
New Zealand	(09) 918 9555	hp.co.nz
Philippines	(632) 888 5900	hp.com/ph
Singapore	(65) 6275 3888	hp.com.sg
Taiwan	(02) 8722 9000	hp.com.tw
Thailand	(662) 353 9500	hp.com/th
Vietnam	(848) 3823 4151	hp.com/vn

For the following countries, please fax your queries to(65) 6275 6707 Bangladesh, Bhutan, Brunei, Cambodia, Maldives, Nepal, Pakistan, Sri Lanka

Supported paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

For more solutions information, please visit



Windows 8









Footnotes

- 1 Wireless performance is dependent upon physical environment and distance from access point. 2 Built-in wireless is available on the HP LaserJet Pro M1210nfw MFP only.
- $^{\rm 3}$ The handset is available on the HP LaserJet Pro M1214nfh MFP and M1216nfh MFP.

- HP Auto-On and Auto-Off capabilities subject to printer and settings.

 Program features and availability may vary by country. For more information, visit www.hp.com/learn/suresupply.

 HP Auto-On and Auto-Off capabilities subject to printer and settings.

 HP toner cartridge return and recycling is available in 49 countries and territories around the world, covering 88% of the addressable market; see www.hp.com/recycle for details.

To learn more, visit hp.com

© Copyright 2016 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.



