

ThinkCentre M715 Tiny Platform Specifications

Product Specifications Reference (PSREF)

Processor	AMD A6, A10, or A12 series APUs						<p>Keyboard Some: Fullsize USB Keyboard (USB connector), Lenovo logo Some: Lenovo New Slim USB Keyboard (USB connector), black, Lenovo logo Some: USB Optical Wheel Mouse, black, Lenovo logo</p> <p>Mouse</p> <p>Mechanical</p> <p>Tiny (1L), black color; metal case M715 Tiny only: 7.05" W X 7.20" D X 1.36" H 179mm W X 182.9mm D X 34.5mm H 2.9 lb (1.3 kg), weight may vary by configuration With VESA mount & ODD box: 7.42" W X 7.30" D X 2.48" H 188.4mm W X 185.38mm D X 63mm H 4.12 lb (1.87 kg), weight may vary by configuration With VESA mount & I/O box: 7.42" W X 7.30" D X 2.62" H 188.4mm W X 185.38mm D X 66.6mm H 3.53 lb (1.6 kg), weight may vary by configuration Optional VESA mount bracket kit, supports VESA 75mm and 100mm Optional system floor stand for vertical orientation</p> <p>VESA mount Floor Stand</p> <p>Power supply</p> <p>65 watts AC/DC adapter, autosensing, 88% PSU (not included for T10 models) 90 watts AC/DC adapter, autosensing, 88% PSU (only for models with I/O box)</p> <p>Limited warranty³</p> <p>Some: 1-year or 3-year, depot service / service upgrades available Some: 1-year or 3-year, limited onsite service / service upgrades available</p> <p>Preload</p> <p>Preloaded operating system Some: Windows 10 Pro 64-bit Some: Windows 10 Home 64-bit Some: Windows® 7 Professional 64 preinstalled through downgrade rights in Windows 10 Pro 64-bit</p> <p>Preloaded applications (only some listed) - Windows 10 only • Lenovo Companion • Microsoft Office preloaded; purchase a product key to activate - Windows 7 only • Lenovo Solution Center • ThinkVantage System Update • Create Recovery Media • Lenovo ThinkVantage Tools • CyberlinkPowerDVD Create(DVD±RW) • Microsoft Office preloaded; purchase a product key to activate • Adobe® Reader®</p> <p>Environment</p> <p>ENERGY STAR® 6.1*, EPEAT™ Gold rating* (*Not for non-OS models); ErP Lot 3; GREENGUARD®; RoHS-compliant</p> <p>Accessories</p> <p>For compatible accessories, please go to http://www.lenovoquickpick.com</p>	
	APU	Cores	Frequency Base/Max	L2 Cache	Memory Types	Integrated Graphics		
	PRO A6-9500E	2	3.0 / 3.4 GHz	1 MB	DDR4-2400	Radeon R5 Series		
	PRO A10-9700E	4	3.0 / 3.5 GHz	2 MB	DDR4-2400	Radeon R7 Series		
	PRO A12-9800E	4	3.1 / 3.8 GHz	2 MB	DDR4-2400	Radeon R7 Series		
	PRO A6-8570E	2	3.0 / 3.4 GHz	1 MB	DDR4-2400	Radeon R5 Series		
	PRO A10-8770E	4	2.8 / 3.5 GHz	2 MB	DDR4-2400	Radeon R7 Series		
	PRO A12-8870E	4	2.9 / 3.8 GHz	2 MB	DDR4-2400	Radeon R7 Series		
Memory	32GB max, DDR4 2400, two 260-pin SO-DIMM sockets, dual-channel capable *16GB single SO-DIMM memory is only available via special bid models							
Disk	<p>Some: SATA 6.0Gb/s, 2.5" Wide, 5400 rpm or 7200 rpm</p> <p>Some: Solid State Drive (SSD) / SATA 6.0Gb/s, 2.5"</p>							
Optical	<p>Some: M.2 Solid State Drive (SSD) / SATA interface or PCIe NVMe interface</p> <p>Some: DVD-ROM, 9.0mm high, via USB external ODD box</p> <p>Some: DVD±RW, 9.0mm high, via USB external ODD box</p>							
Onboard SATA Media reader	<p>One SATA cable (1-drop to device), one SATA 6.0Gb/s connector on planar</p> <p>None</p>							
Graphics	<p>AMD Radeon™ Graphics in processor, uses main memory, DirectX® 12, two DisplayPort™, one optional port (HDMI, VGA, or 3rd DP), supports 3 independent displays (supports maximum of 2 concurrent HDMI/DVI displays when using HDMI port or DP to DVI/HDMI dongles);</p> <p>Max resolution: 4096x2160 (DP) @ 60Hz; 4096x2160 (HDMI) @ 60Hz; 1920x1200 (VGA) @ 60Hz</p>							
DP cable	Optional DP to VGA, DP to DVI-D (single link), or DP to HDMI 1.4 dongle							
Chipset	AMD B300 Chipset							
Front ports	Two USB 3.0 (one is Always On and fast charge), one microphone (stereo, 3.5mm), one headphone / microphone combo jack (stereo, 3.5mm)							
Rear ports	One USB 3.0 and three USB 2.0 (optional external optical box or I/O box occupies one specific USB 2.0 on some models), ethernet (RJ-45), two DisplayPort, one optional port (VGA, 3rd DP, HDMI, or serial on some models), one headphone							
I/O box	Optional external I/O box, extends four USB 2.0 (two on front and two on rear), one serial, and two PS/2, via USB port (occupy one specific USB 2.0 of M715q Tiny)							
Audio support	High Definition (HD) Audio, Realtek ALC233-CG / internal speaker (1.5 watt)							
WLAN ¹³	<p>Some: 11ac wireless, M.2 Card, Realtek RTL8821AE (dual band), Wi-Fi + Bluetooth 4.0 combo adapter, 1x1</p> <p>Some: 11ac wireless, M.2 Card, Realtek RTL8822BE (dual band), Wi-Fi + Bluetooth 4.1 combo adapter, 2x2</p> <p>Some: 11ac wireless, M.2 Card, Qualcomm Atheros QCA9377 (dual band), Wi-Fi + Bluetooth 4.1 combo adapter, 1x1</p>							
Bluetooth™	Some: Bluetooth 4.0 or 4.1 wireless, integrated in Wi-Fi + BT combo adapter							
Ethernet Modem	Gigabit ethernet, Realtek RTL8111EPV, Wake on LAN® None							
Manageability	DASH 1.0/1.1							
Security chip	Discrete TPM 2.0, TCG Certified							
Security features	<ul style="list-style-type: none"> • Security slot (in rear for optional Kensington® MicroSaver® cable) • Padlock loop • Smart USB protection, allows keyboard/mouse only, blocks all storage devices • Power-on password <ul style="list-style-type: none"> • Administrator password • Hard disk password • Boot sequence control • Boot without keyboard and mouse • Individual USB port disablement • Chassis intrusion switch 							