

SPS ADVANCE RT²

Line-interactive sine-wave UPS
800 VA to 3000 VA

BACKUP CHART: SPS ADVANCE RT2 800 VA to 3000 VA



PRODUCT	P/N	Stand alone	6A0BU000001			6A0BU000002		
			2 x	3 x	2 x	3 x		
SPS 800 ADV RT2 B1	6A0CA000006	0	18	49	85	22	56	87
SPS 800 ADV RT2	6A0CA000001	5	30	-	-	34	-	-
SPS 1100 ADV RT2 B1	6A0CA000007	0	10	30	54	14	38	59
SPS 1100 ADV RT2	6A0CA000002	5	20	-	-	25	-	-

PRODUCT	P/N	Stand alone	6A0BU000003			6A0BU000004			6A0BU000005		
			2 x	3 x	2 x	3 x	2 x	3 x			
SPS 1500 ADV RT2 B1	6A0CA000008	0	21	54	95	25	60	99	-	-	-
SPS 1500 ADV RT2	6A0CA000003	7	37	-	-	41	-	-	-	-	-
SPS 2000 ADV RT2 B1	6A0CA000009	0	13	37	60	17	45	70	-	-	-
SPS 2000 ADV RT2	6A0CA000004	6	23	-	-	29	-	-	-	-	-
SPS 3000 ADV RT2 B1	6A0CA000010	0	-	-	-	-	-	-	17	46	71
SPS 3000 ADV RT2	6A0CA000005	6	-	-	-	-	-	-	29	57	-

Important: B1 Models NO internal batteries (0 min. back-up time). At least 1xBEM (Battery Extension Module) is required.