

# **H310-F PRO** BUSINESS ELEGANCE





# **SPECIFICATIONS**

Model Name	H310-F PRO
CPU Support	Supports 8th Gen Intel® Core™ / Pentium® Gold / Celeron®
	processors
CPU Socket	LGA 1151
Chipset	Intel® H310 Chipset
Graphics Interface	1 x PCI-E 3.0 x16 slot
Display Interface	HDMI, DVI-D - Requires Processor Graphics
Memory Support	2 DIMMs, Dual Channel DDR4 up to 2666MHz
Expansion Slots	12 x PCI-E x1 slots
Storage	4 x SATA 6Gb/s ports
USB ports	4 x USB 3.1 (Gen1) + 6 x USB 2.0
LAN	Intel® I219-V Gigabit LAN
Audio	8-Channel(7.1) HD Audio with Audio Boost

# **FEATURES**



#### EZ Debug LED

Easiest way to troubleshoot.



#### Mining Guard

Power/Reset/Clear CMOS Buttons on Board for managing your mining board without screen on



#### Intel LAN

Premium network solution from Intel® for professional and multimedia use. Delivers a secure, stable and fast network connection.



#### Mining Management

MSI mining motherboard featuring customized Mining BIOS and built-in slot detection. Auto detect your PCIE slot status and manage your mining rig with just one glance



#### **Diskless Boot Supports**

With diskless boot environment, miners don't need maintain the operation system for each mining machines and save the money from the hard drives.



#### Mining LED

Featuring mining LED for each PCIE slot on the mining motherboard, you can check the status for each GPU by only spot the motherboard.



### **Super Mining Machine**

Support 13X graphic cards for more hash. Give you the easiest and the most convenient solution for your mining rig.



## **Independent Slot Power**

The 13 PCle slots are grouped into two distinct zones; each slot can be enhanced for better signal and more stable voltage.

### **CONNECTIONS**



- 1. Ez Debug LED
- 2. PS/2 Combo Port
- 3. DVI-D Port
- 4. HDMI Port
- 5. USB 3.1 Gen1
- 6. LAN Port
- 7. USB 2.0 Port 8. USB 2.0 Port
- 9. HD Audio Connectors