

MOTHERBOARD

#### **B360M MORTAR** BLAST AWAY THE COMPETITION





# **SPECIFICATIONS**

Model Name	B360M MORTAR
CPU Support	Supports 8th Gen Intel <sup>®</sup> Core <sup>TM</sup> / Pentium <sup>®</sup> Gold / Celeron <sup>®</sup> processors
CPU Socket	LGA 1151
Chipset	Intel <sup>®</sup> B360 Chipset
Graphics Interface	2 x PCI-E 3.0 x16 slot, Supports 2-way CrossFire
Display Interface	DisplayPort, HDMI, DVI-D - Requires Processor Graphics
Memory Support	4 DIMMs, Dual Channel DDR4 up to 2666MHz
Expansion Slots	2 x PCI-E x1 slots
Storage	2 x Turbo M.2 slots, supports Intel <sup>®</sup> Optane <sup>™</sup> Technology 4 x SATA 6Gb/s
USB ports	3 x USB 3.1(Gen2, A+C) + 2 x USB 3.1 (Gen1) + 6 x USB 2.0
LAN	Intel <sup>®</sup> I219-V Gigabit LAN
Audio	8-Channel(7.1) HD Audio with Audio Boost

## **CONNECTIONS**



- 2. DisplayPort
- 3. LAN Port
- 4. USB 3.1 Gen2 Type A
- 5. HD Audio Connectors

1. PS/2 Combo Port

- 6. USB 2.0 Port
- 7. DVI-D Port 8. HDMI Port
- 9. USB 2.0 Port 10. USB 3.1 Gen2 Type C
- 11. Optical S/PDIF OUT

CORE AUUZ

**FEATURES** 

ТШІМ

URBC

INTEL TURBL

J58 3.1 G



### **DDR4 Boost**

Core Boost

Twin Turbo M.2

Advanced technology to deliver pure data signals for the best gaming performance and stability.

With 2 x M.2 slots. Running at PCI-E Gen3 x4 maximizes

Powered by Intel, ensure an uninterrupted connection with

MSI extended PWM and enhanced circuit design ensures

With premium layout and optimized power design to support

performance for NVMe based SSDs

more stability and fastest USB speeds.

even high-end processors to run in full speed.

more cores and provide better performance.

Intel Turbo USB 3.1 Gen2

**Extended Heatsink Design** 



AUDIO 8005T

### GAMING LAN

Experience smooth wired gaming experience by reducing CPU overhead and offer long-term network usage.



Reward your ears with studio grade sound quality for the

most immersive audio experience

#### MULTI-GPU

With Steel Armor PCI-E slot. Supports 2-Way AMD Crossfire™

Benerated 2018-04-10, check for the latest version www.msi.com/datasheet. The information provided in this document is intended for informational purposes only and is subject to change without notice









