



## LD5400T Multi-User Thunderbolt 3 40Gbps Dual 4K Dock w/ K-Fob™ Smart Lock - 85W PD - Windows/macOS

Best-in-class docking with next gen locking for shared workspaces

### K39470M

#### Product Description

Combining a best-in-class Thunderbolt 3 docking experience with next generation laptop locking technology, Kensington delivers a game-changing 2-in-1 docking and locking solution for both Windows and Mac users. The LD5400T multi-user dock combines the productivity benefits of Thunderbolt 3 connectivity with K-Fob™ Smart Lock technology. Get more speed, more pixels, more power and more possibilities while reducing laptop theft and improving compliance with corporate security protocols. Secures thin and light laptops 11-15" in size, including models from Apple, Dell, HP, Lenovo and other manufacturers.

#### Shipping Information

Warranty Period 24

#### General information

Recycled % 0

#### Features

- Best for: Thunderbolt 3 or Thunderbolt 4 Laptops, Ultrabooks and Monitors that support up to 4K. Ideal for customers that require Integrated Physical Security
- Connection technology: Thunderbolt 3 (Thunderbolt 4 laptops supported at Thunderbolt 3 features)
- USB-C power delivery: Supports USB-C PD 2.0 (85W of laptop charging)
- Compatibility: macOS 10.13 or above, Windows 10
- No. of monitors supported: 2
- Video output: 1 x DisplayPort v1.2 and optional secondary monitor via USB-C video adapter
- Maximum resolution supported: Single monitor: 5K (5120 x 2880 @ 60Hz) and Dual monitors: 4K (4096 x 2160 @ 60 Hz)
- Plug & play installation without need for drivers or downloads
- System requirements: Only compatible with laptops equipped with Thunderbolt 3 or Thunderbolt 4 ports; not backwards compatible with Thunderbolt 1 or Thunderbolt 2. For Windows based devices, ensure your laptop supports Power Delivery.
- Warranty: 3 Years
- Register & Retrieve™ program provides free and secure cloud-based key fob replacement.
- Compatible with the new MacBook Pro 16-inch.
- Apple M1 - While this docking station will work with the M1 MacBook, only a single video output is supported. For multi-monitor support on your M1 MacBook, see our Hybrid USB-C DisplayLink docking stations (e.g.: SD4700P, SD4750P, SD4780P or SD4900P) or USB-A DisplayLink adapters (DisplayPort K33989, HDMI K33988, DVI-I K33974).

#### Specifications

• <b>Connection technology</b> Thunderbolt 3 (Thunderbolt 4 laptops supported at Thunderbolt 3 features)	• <b>Maximum resolution</b> 4K
• <b>Driverless</b> Yes	• <b>Power delivery</b> 85W
• <b>Number of Screen Outputs</b> 2	• <b>Operating system(s)</b> macOS, Windows
• <b>Video ports</b> DisplayPort, USB-C	• <b>Number of USB ports</b> 4