



msi

MOTHERBOARDS X299 GAMING PRO CARBON AC PERFORM IN STYLE



SPECIFICATIONS

| | |
|--------------------|--|
| Model Name | X299 GAMING PRO CARBON AC |
| Segment | Performance GAMING |
| CPU support | Supports New Intel® Core™ X-series Processor Family |
| CPU socket | LGA 2066 |
| Chipset | Intel® X299 Chipset |
| Graphics Interface | 4 x PCI-E 3.0 x16 slot 3-way SLI / CrossFire |
| Memory support | 8 DIMMs, Quad Channel DDR4-4133(OC)+, Dual Channel DDR4-4500(OC)+ |
| Expansion slots | 2 x PCI-E 3.0 x1 slots |
| SATA / M.2 / U.2 | 8x SATA 6Gb.s ports, 2x Turbo M.2 slots, 1x Turbo U.2 connector |
| Intel® Optane™ | Intel® Optane™ Memory Ready |
| USB 3.1 Gen2 | 3 x USB 3.1 Gen2 (Type A+C) |
| USB 3.1 Gen1 | 8 x USB 3.1 Gen1 |
| USB 2.0 | 7 x USB 2.0 |
| LAN | Intel® I219-V Gigabit LAN |
| Wireless / BT | Intel® Wireless-AC 8265, Bluetooth 4.2 |
| Audio | 7.1 Channel High Definition Audio with S/PDIF |
| Form Factor | ATX |

FEATURES

1. MYSTIC LIGHT: 16.8 million colors / 17 effects controlled in one click with MYSTIC LIGHT APP or mobile devices.
2. 3D Printing Support: exchangeable cover and 3D X-MOUNTING screws.
3. Designed for Extreme Performance: TURBO SOCKET with GAME BOOST, DIGITAL POWER Design
4. Lightning Fast Game experience: TWIN TURBO M.2 with M.2 Shield and Intel Optane Memory Ready, Turbo U.2, LIGHTNING USB 3.1 GEN2
5. VR READY and VR BOOST: Best virtual reality game experience without latency, reduces motion sickness. Supports Nahimic VR & TriDef VR.
6. AUDIO BOOST 4 with NAHIMIC 2+: Reward your ears with studio grade sound quality for the most immersive gaming experience
7. DDR4 BOOST with STEEL ARMOR: Give your DDR4 memory a performance boost
8. GAMING LAN and Wireless support, powered by Intel®: The best online gaming experience with lowest latency and bandwidth management.

REAR CONNECTORS

- | | |
|----------------------------|------------------------------|
| 1. Clear CMOS Button | 8. USB 2.0 / BIOS Flashback+ |
| 2. Keyboard / Mouse | 9. USB 3.1 Gen1 |
| 3. Intel Wi-Fi & Bluetooth | 10. USB 3.1 Gen2 Type-A/C |
| 4. Intel® Gigabit LAN | 11. Optical S/PDIF-Out |
| 5. Golden Audio Connectors | |
| 6. BIOS Flashback Button | |
| 7. USB 2.0 | |

