

# 1000W Light-Duty Compact Power Inverter with 2 AC/1 USB - 2.0A/Battery Cables, Mobile

MODEL NUMBER: PINV1000



Converts 12V DC power from your vehicle's battery into 120V AC power to operate electronics while on the road or at a remote site.

## Features

**Mobile Power Inverter Charges and Powers Multiple Electronic Devices in Your Vehicle** You don't have to be near your computer or an AC power source to keep your mobile devices fully charged and your power tools and small appliances operating. This 1000W mobile inverter converts 12V DC power from your car, truck, fleet vehicle, boat or RV's battery into standard 120V AC power. Just connect the included battery cables between the inverter's DC input terminals and the positive and negative terminals on your vehicle's battery.

**Dual AC Outlets Provide Portable Power for Your Mobile Applications** This compact power inverter is ideal for use at remote locations, such as campgrounds, construction sites and mobile offices. Two NEMA 5-15R outlets provide a continuous output of 1000 watts and a peak output of 2,000 watts. That's plenty to operate a variety of appliances and power tools, such as low-power lights, camping accessories, battery rechargers for small battery-operated power tools, and mobile office equipment.

**USB Charging Port Keeps Your Devices at Full Strength** The 2.0A USB charging port remains active even when the inverter's on/off switch is set to Off. This allows you to charge your smartphone, tablet, laptop, MP3 player or GPS unit without draining too much power from the vehicle's battery.

**Includes the Latest Safety Features to Protect Your Equipment and Battery** An on/off switch offers one-touch control over both AC outlets. If the power input from the vehicle's battery drops below 10 volts or exceeds 16 volts, the mobile power inverter will automatically shut down. Green and red LEDs indicate normal and improper operation. A load-controlled fan begins cooling automatically when the internal temperature rises to a certain level during extended use. An audible alarm sounds during excessively high or low voltage conditions.

**Brackets Included for Permanent Mounting** The compact power inverter's durable aluminum housing is designed to withstand the rigors of road trips, campouts, business trips and family vacations. Use the built-in front and rear mounting brackets and your own hardware to permanently install the inverter in a horizontal position.

## Highlights

- Provides portable power for mobile applications, including phones and laptops
- Ideal for areas without regular power outlets, such as campsites or construction sites
- Dual NEMA 5-15R outlets deliver continuous output of 1000W for powering devices
- 2A USB charging port keeps smartphones, tablets and laptops at full capacity
- Rugged aluminum housing built to withstand rigors of travel and outdoor use

## Applications

- Charge your smartphone and laptop to 100% battery capacity while camping
- Plug in a power drill or other power tool on a construction site
- Keep a radio and emergency lighting operating during severe weather or blackout conditions

## Package Includes

- PINV1000 1000W Light-Duty Compact Car Inverter
- Battery cable, red/black, 3 ft.
- Grounding cable, 3 ft.
- Owner's manual

## Specifications

| OVERVIEW |             |
|----------|-------------|
| UPC Code | 03733225160 |



| <b>OUTPUT</b>                                |  |
|--|--|
| Charging Ports / Amps                        | (1) 2A   |
| Frequency Compatibility                      | 60 Hz  |
| Pure Sine Wave Output                        | No   |
| Output (Watts)                               | 1000   |
| Nominal Output Voltage(s) Supported          | 120V   |
| Output Receptacles                           | (2) 5-15R  |
| Continuous Output Capacity (Watts)           | 1000   |
| Peak Output Capacity (Watts)                 | 2000   |
| Output Voltage Regulation                    | Maintains PWM sine wave output voltage of 120VAC (+/- 10%)                         |
| Output Frequency Regulation                  | 60 Hz (+/- 3 Hz)   |
| Overload Protection                          | Yes  |
| <b>INPUT</b>                                 |  |
| Recommended Electrical Service               | 12VDC  |
| Input Connection Type                        | DC terminal post for battery cables with ring terminals                            |
| Voltage Compatibility (VDC)                  | 12   |
| Input Cord Length (ft.)                      | 3  |
| Input Cord Length (m)                        | 0.91   |
| <b>BATTERY</b>                               |  |
| DC System Voltage (VDC)                      | 12   |
| <b>USER INTERFACE, ALERTS &amp; CONTROLS</b> |  |
| Front Panel LEDs                             | Single multi-color status LED for operation (Green) and fault conditions (RED)     |
| Switches                                     | ON/OFF Rocker Switch   |
| Audible Alarm                                | Low Battery, Short Circuit, Over-temperature, High DC Voltage, Overload protection |
| <b>PHYSICAL</b>                              |  |
| Form Factors Supported                       | Horizontal Floor, Wall-Mount   |
| Material of Construction                     | Aluminum/sheet metal   |
| Receptacle Color                             | Black  |
| Shipping Dimensions (hwd / in.)              | 6.89 x 5.70 x 2.55   |
| Shipping Weight (kg)                         | 0.69   |
| Unit Dimensions (hwd / cm)                   | 15/14 x 10.59 x 5.99   |
| Unit Dimensions (hwd / in.)                  | 3.00 x 5.04 x 7.28   |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

|                                     |  |
|-------------------------------------|--|
| Unit Weight (kg)                    | 1.22   |
| Unit Weight (lbs.)                  | 2.69   |
| <b>ENVIRONMENTAL</b>                |  |
| Relative Humidity                   | 0-95% non-condensing   |
| Operating Temperature               | 0C-40C (32F~104F)  |
| <b>SPECIAL FEATURES</b>             |  |
| TVSS Grounding                      | Grounding lug grounds the inverter to vehicle or earth ground; ground cable included |
| <b>WARRANTY</b>                     |  |
| Product Warranty Period (Worldwide) | 2-year limited warranty  |

© 2019 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

<https://www.tripplite.com/products/product-certification-agencies>