





# GeForce RTX 2060 GAMING Z 6G







## **SPECIFICATION**

Model Name	GeForce RTX™ 2060 GAMING Z 6G
Graphics Processing Unit	NVIDIA <sup>®</sup> GeForce RTX™ 2060
Interface	PCI Express x16 3.0
Cores	1920 Units
Core Clocks	Boost: 1830 MHz
Memory Speed	14 Gbps
Memory	6GB GDDR6
Memory Bus	192-bit
Output	DisplayPort x 3 (v1.4) / HDMI 2.0b x 1
HDCP Support	2.2
Power consumption	190 W
Power connectors	8-pin x 1
Recommended PSU	500W
Card Dimension(mm)	247 x 129 x 52 mm
Weight (Card / Package)	957 g / 1525 g
Afterburner OC	Υ
DirectX Version Support	12 API
OpenGL Version Support	4.5
Maximum Displays	4
VR Ready	Y
G-SYNC <sup>™</sup> technology	Y
Adaptive Vertical Sync	Υ


## **FEATURE**



### **TORX FAN 3.0**


Award-winning fan design combining two different fin designs for cool & quiet gaming.

#### Mastery of Aerodynamics



Using groundbreaking aerodynamic techniques, the heatsink is optimized for efficient heat dissipation.

### **ZERO FROZR**



#### **CUSTOM PCB**





SOLID BACKPLATE

An optimized PCB design with enhanced power delivery provides a solid base for high performance gaming.

Increases toughness of the card to prevent bending while complementing the design.

only and is subject to change without notice

1 for



TRUE GAMING © 2018 Micro-Star Int'l Co.Ltd. MSI is a registered trademark of Micro-Star Int'l Co.Ltd. All rights reserved. © 2016 NVIDIA, the NVIDIA logo, GeForce, SHIELD, and NVIDIA G-SYNC are trademarks and/or registered trademarks of NVIDIA Corporation in the U.S. and other countries.





# **GeForce RTX 2060 GAMING Z 6G**

**Digital Maximum** Resolution

7680 x 4320



#### **RGB Mystic Light**

Customize colors and LED effects with exclusive MSI software and synchronize the look & feel with other components.

#### **MSI Afterburner**



The ultimate overclocking software with advanced control options and real-time hardware monitor.

#### **OC PERFORMANCE**



MSI OC graphics cards are equipped with higher clock speeds out of the box for increased performance.

## **CONNECTIONS**

×

1. DisplayPort 2. HDMI