



Dynalite Leading Edge Dimmers

DTE1210

12 channel Trailing Edge Dimmer Controller with a maximum load per channel of 10 A.

The Philips Dynalite DTE1210 trailing-edge dimmer controller features 12 channels, with a maximum load per channel of 10 A and a total box load of 120 A. The trailing-edge output makes the device suitable for control of both trailing- and leading-edge electronic transformers, as well as incandescent lamps and track lighting. Operates from a three-phase supplyVoltage regulation and soft start technologiesNaturally ventilatedInterface to other devicesInternal controlsOptions available

Product data


General Information	
CE mark	CE mark
Remarks	Please download the Lighting - Product Data Sheet
	for more information and ordering options
RoHS mark	RoHS mark
Application Conditions	
Ambient temperature range	0 to +40 °C
Product Data	
Full product code	871016350586200
	-

Order product name	DTE1210
EAN/UPC – product	8710163505862
Order code	50586200
Numerator – quantity per pack	1
Numerator – packs per outer box 1	
Material no. (12NC)	913703022009
Net weight (piece)	16.000 kg


Datasheet, 2019, April 2 data subject to change

Dynalite Leading Edge Dimmers

Dimensional drawing



Dynalite Trailing Edge Dimmers



Dynalite Trailing Edge Dimmers



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.