



# HP Neverstop Laser MFP 1202nw

Neverstop printing. Never stop saving – with wireless MFP versatility.<sup>1</sup>

Exceptional value out of the box – up to 60% savings on toner<sup>2</sup> with 5000 pages of toner included.<sup>3</sup> Get up to 7x more pages in box.<sup>4</sup> Print, scan, and copy, and restore toner levels for less.<sup>2</sup> Print and scan anywhere with HP Smart app.<sup>5</sup>



## Highlights

- Print, Scan, Copy
- Up to 20ppm mono printing
- 5,000 pages of toner inbox
- Self Re-loadable toner
- Wireless printing with WiFi direct (w model only)
- HP Smart App compatible
- Ethernet and WiFi direct Connectivity
- 150 sheet input capacity
- Ethernet connectivity (n model only)

### Up to 60% savings on toner<sup>2</sup>

- Count on toner savings right out of the box.<sup>2</sup> Get up to 60% savings on toner every time you reload.<sup>2</sup>
- Help save on laser quality. Get the lowest toner cost compared to traditional HP toner cartridges.<sup>2</sup>
- Breeze through tasks with versatile MFP performance – print, scan, and copy.
- Business doesn't need to wait for your printer. Help maximise your uptime with fast print speeds.

### Up to 7x more pages than in-class laser<sup>4</sup>

- Get more toner in-box delivering up to 7x more pages than in-class laser.<sup>4</sup>
- Count on thousands of pages right out of the box – 5,000 pages of toner included.<sup>3</sup>
- Handle large print jobs and reload paper less often with a 150 sheet capacity paper tray.

### Save every time you reload<sup>2</sup>

- HP's reloadable toner system gives you easy, convenient, mess-free toner reloads.<sup>6</sup>
- Reload toner with confidence. Quickly restore toner levels with the toner reload kit.<sup>7</sup>
- This innovative laser printer delivers exceptional quality, page after page.
- Produce sharp text and bold blacks for all your documents.

### Stay productive from anywhere

- Print, scan, and send a secure fax from anywhere, with HP Smart app.<sup>5</sup>
- Easily share resources – access and print with wireless and Ethernet networking.<sup>1</sup>
- Connect your mobile device directly to your printer – and easily print without accessing a network.<sup>8</sup>
- Save time and eliminate steps in repetitive tasks with customisable shortcuts.<sup>5</sup>

## Product walkaround

### HP Neverstop Laser MFP 1202nw

1. Iconic LCD display
2. HP Smart - mobile print app
3. 100 sheet output bin
4. Flatbed scanner
5. Hi-Speed USB 2.0 port
6. 20 ppm (A4)
7. Built-in wireless networking, Wi-Fi Direct printing. Built-in Ethernet.
8. 150 sheet input tray
9. Pre-installed Original HP Toner delivers up to 5,000 pages



## Accessories, Supplies and Support

<b>Supplies</b>	<b>W1143A</b> HP 143A Black Original Neverstop Toner Reload Kit (2,500 pages)
	<b>W1143AD</b> HP 143AD Dual Pack Black Original Neverstop Toner Reload Kit (Per kit: 2,500 pages)
	<b>W1144A</b> HP 144A Black Original Laser Imaging Drum (20,000 pages)
<b>Service and Support</b>	<b>UB4Y5E</b> HP 3 year Standard Exchange Service for Neverstop Laser 1200
	<b>UB4Y2E</b> HP 3 year Next Business Day Exchange Service for Neverstop Laser 1200 (UB4Y5E - available in All EMEA countries except Middle East, Adriatic, Africa, South Africa, Israel, Slovenia, Turkey. UB4Y2E - available in Austria, Belgium, Czech Rep, Denmark, Finland, France, Germany, Greece, Ireland, Italy, Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Spain, Sweden, Switzerland, UK)

## Technical specifications

<b>Model</b>	HP Neverstop Laser MFP 1202nw
<b>Product number</b>	5HG93A
<b>Functions</b>	Print, copy, scan
<b>Control panel</b>	ICON LCD
<b>Print</b>	
Print technology	Laser
Print speed	<b>Black (A4, normal):</b> Up to 20 ppm;
First page out	<b>Black (A4, ready):</b> As fast as 8.5 sec; <b>Black (A4, sleep):</b> As fast as 15 sec;
Print resolution	<b>Black (best):</b> Up to 600 x 600 x 2 dpi; <b>Technology:</b> HP FastRes 1200 (600 x 600 x 2 dpi);
Monthly duty cycle	Up to 20,000 pages A4; <b>Recommended monthly page volume:</b> 250 to 2,500 pages
Printer smart software features	Apple AirPrint™, Mopria Certified, HP Auto-On/Auto-Off, Wi-Fi Direct, HP Smart App, HP Smart Task
Standard print languages	PCLm5; URF; PWG
Print area	<b>Print margins</b> Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area : 216 x 356 mm
Duplex printing	Manual (driver support provided)
<b>Copy</b>	
Copy speed	<b>Black (A4):</b> Up to 14 cpm
Copier specifications	Number of Copies; Lighter/Darker; Optimise; Paper; <b>Maximum number of copies:</b> Up to 99 copies; <b>Reduce/Enlarge:</b> 25 to 400%
<b>Scan</b>	
Scan file format	JPG, RAW (BMP), PNG, TIFF, PDF
Scanner specifications	<b>Scanner type</b> Flatbed; <b>Scan technology:</b> D-CIS; <b>Twain version:</b> Version 2.1 (Windows 7 or higher); <b>Scan size maximum (flatbed, ADF):</b> 216 x 297 mm; <b>Optical scan resolution:</b> Up to 600 ppi
Scanner advanced features	No
Scannable area	<b>Maximum media size (flatbed):</b> 216 x 297 mm
Bit depth/ Grey scale levels	24-bit / 256
<b>Processor speed</b>	500 MHz
<b>Connectivity</b>	
Standard	Hi-Speed USB 2.0 port; Built-in WiFi 802.11b/n/g; Fast Ethernet 10/100 Base
Wireless	Yes
Mobile printing capability <sup>1</sup>	Apple AirPrint™; Google Cloud Print™; HP Smart App; Mopria™ Certified; Wi-Fi® Direct Printing
Supported network protocols	TCP/IP; IPv4; IPv6; IP Direct Mode; LPD; SLP; Bonjour; WS-Discovery; BOOTP/DHCP/IPv4; SNMP v 1/2/3; HTTP/HTTPS
Network capabilities	Fast Ethernet 10/100 Base
<b>Hard disk</b>	None
<b>Memory</b>	<b>Standard:</b> 64 MB ; <b>Maximum:</b> 64 MB
<b>Media handling</b>	
Number of paper trays	<b>Standard:</b> 1 input tray ; <b>Maximum:</b> 1 input tray
Media types	Plain paper; Heavy paper; Bond paper; Label; Light paper; Envelope
Media size	<b>Custom (metric):</b> 105 x 148.5 mm to 216 x 356 mm <b>Supported (metric):</b> A6; A5; A4; No.10 Env; C5 Env; DL Env; B5(UIS); Oficio 216 x 340; 105 x 148.5 mm to 216 x 356 mm

<b>Model</b>	HP Neverstop Laser MFP 1202nw
<b>Product number</b>	5HG93A
<b>Media handling</b>	<b>Standard input:</b> 150 sheet input tray <b>Standard output:</b> 100 sheet output bin
<b>Media weight</b>	60 to 120 g/m <sup>2</sup>
<b>Input capacity</b>	<b>Tray 1:</b> Sheets: 150; Envelopes: 1 <b>Maximum:</b> Up to 150 sheets
<b>Output capacity</b>	<b>Standard:</b> Up to 100 sheets <b>Maximum:</b> Up to 100 sheets
<b>Compatible operating systems</b>	Windows® 10, 8.1, 8, 7: 32/64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Apple®OS X El Capitan (v10.11), macOS Sierra (v10.12), macOS High Sierra (v10.13), 1.5 GB available hard disk space, Internet required; USB Linux (for more information, see <a href="https://www.developers.hp.com/hp-linux-imaging-and-printing">https://www.developers.hp.com/hp-linux-imaging-and-printing</a> )
<b>Compatible network operating systems</b>	Windows® 10, 8.1, 8, 7: 32/64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Apple®OS X El Capitan (v10.11), macOS Sierra (v10.12), macOS High Sierra (v10.13), 1.5 GB available hard disk space, Internet required; USB Linux (for more information, see <a href="https://www.developers.hp.com/hp-linux-imaging-and-printing">https://www.developers.hp.com/hp-linux-imaging-and-printing</a> )
<b>Minimum system requirements</b>	<b>Windows:</b> Windows® 10, 8.1, 8, 7: 32/64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer <b>Mac:</b> Apple®OS X El Capitan (v10.11), macOS Sierra (v10.12), macOS High Sierra (v10.13), 1.5 GB available hard disk space, Internet required, USB
<b>Software included</b>	For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, online user manuals, HP Printer Assistant, HP Scan Driver, HP Scan Application, HP Product Improvement Study; For Mac OS: welcome Screen (directs users to <a href="http://www.hp.com">http://www.hp.com</a> or OS App Source for LaserJet Software)
<b>Printer management</b>	HP Printer Assistant (UDC); HP Device Toolbox; HP Utility (Mac)
<b>Dimensions and weight</b>	
<b>Printer dimensions (W x D x H)</b>	<b>Minimum:</b> 380.5 x 293.4 x 287 mm; <b>Maximum:</b> 380.5 x 385 x 521 mm
<b>Package dimensions (W x D x H)</b>	481 x 390 x 421 mm
<b>Printer weight</b>	8.78 kg
<b>Package weight</b>	11.2 kg
<b>Operating environment</b>	<b>Temperature:</b> 15 to 32.5°C <b>Humidity:</b> 30 to 70% RH
<b>Storage conditions</b>	<b>Temperature:</b> -20 to 50°C
<b>Acoustics</b>	<b>Acoustic power emissions:</b> 6.5 B(A) <b>Acoustic pressure emissions:</b> 51 dB(A)
<b>Power<sup>2</sup></b>	<b>Requirements:</b> 220V - 240V nominal at +/-10% (min 198V, Max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); <b>Consumption:</b> 338 watts (active printing), 3.3 watts (ready), 0.95 watts (sleep), 0.1 watts (manual off); <b>Typical Electricity Consumption (TEC):</b> Energy Star version 3.0 : 0.305 kWh/Week; Blue Angel : 0.677 kWh/Week; <b>Power supply type:</b> Internal (Built-in) power supply;
<b>Energy savings feature technology</b>	HP Auto-On/Auto-Off Technology
<b>Certifications</b>	EN 61000-3-2:2014, EN 61000-3-3:2013, EN 55024:2010, EN 55032:2012/AC:2013, ICES-003 Issue 5, CISPR 22:2008, CISPR 32:2012, other EMC approvals as required by individual countries. ENERGY STAR® qualified <b>Blue Angel compliant</b> Yes, Blue Angel DE-UZ 205—only ensured when using Original HP supplies
<b>Country of origin</b>	Made in China
<b>What's in the box<sup>4</sup></b>	HP Neverstop Laser 1202nw Printer; Preinstalled HP Black Original Imaging Drum (5,000 pages yield, 20,000 pages useful life); Reference guide; Setup guide; Regulatory flyer; Support flyer; Warranty guide; Power cord; USB cable
<b>Warranty</b>	One year standard limited hardware warranty and get up to 3 years extended warranty upon registration at <a href="http://www.hp.com/eu/3yearwarranty">http://www.hp.com/eu/3yearwarranty</a>

## Footnotes

- <sup>1</sup> Wireless operations are compatible with 2.4 GHz operations only. Learn more at <http://www.hp.com/go/mobileprinting>.
- <sup>2</sup> Based on internal HP comparison of MRSP and cost-per-page of in-class HP LaserJet Pro M15 and HP LaserJet Pro MFP M28 with standard-fill HP 44A/48A Black Original LaserJet Toner Cartridge, as of March 2020. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>3</sup> Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>4</sup> Based on HP LaserJet Pro M15 and HP LaserJet Pro MFP M28 with standard-fill HP 44A/48A Black Original LaserJet Toner Cartridge with ISO yield of 500 pages. Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>5</sup> Requires the HP Smart app download. For details on local printing requirements see <http://www.hp.com/go/mobileprinting>. Certain features/software are available in English language only.
- <sup>6</sup> When used in accordance with setup instructions.
- <sup>7</sup> Toner reload kit is not included with the printer; please purchase separately.
- <sup>8</sup> Mobile device needs to be connected to Wi-Fi Direct® signal of a Wi-Fi Direct-supported AiO or printer prior to printing. Details at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting). Wi-Fi Direct® is a registered trademark of Wi-Fi Alliance®.

## Technical specifications disclaimers

- <sup>1</sup> Apple AirPrint - mobile device must have AirPrint®. Wireless operations are compatible with 2.4 GHz operations only. Learn more at <http://www.hp.com/go/mobileprinting>. Google Cloud Print™ 2.0 - requires Google Cloud Print™ registration and Google account. Wireless operations are compatible with 2.4 GHz operations only. Learn more at <http://www.hp.com/go/mobileprinting>.
- <sup>2</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device.
- <sup>3</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device.
- <sup>4</sup> HP Black Original Laser Imaging Drum (introductory 5,000 page black toner yield provided, with 20,000 page Imaging Drum useful life). Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>.

<http://www.hp.com/uk>

© Copyright 2021 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

Published in EMEA April 2021

---

