MOTHERBOARD

MEG Z490 ACE ACE YOUR ENEMY



SPECIFICATION

Model Name	MEG Z490 ACE
CPU Support	Supports 10 th Gen Intel [®] Core TM and Pentium [®] Gold / Celeron [®] processors
CPU Socket	LGA 1200
Chipset	Intel® Z490 Chipset
Graphics Interface	3x PCI-E 3.0 x16 slots Support 2-way NVIDIA® SLI™ Technology / 3-way AMD® CrossFire™ Technology
Memory Support	4 DIMMs, Dual Channel DDR4-4800MHz(OC)
Expansion Slots	2x PCle 3.0 x1 slots
Storage	3 x Turbo M.2 32Gb/s slots, supports Intel® Optane™ technology 6x SATA 6Gb/s
USB ports	1 x USB 3.2 Gen 2x2 20Gbps (Type-C) + 4 x USB 3.2 Gen 2 10Gbps (3 Type-A + 1 Type-C) + 4 x USB 3.2 Gen 1 5Gbps (Type-A) + 6 x USB 2.0
LAN	Realtek® 8125B 2.5G LAN + Intel® I219V Gigabit LAN
WiFi / BT	Intel® Wi-Fi 6 AX201, Bluetooth 5.1
Audio	8-Channel(7.1) HD Audio with Audio Boost HD
Form Factor	ATX

FEATURE



Mystic Light RGB LED

Personalize your PC with 16.8 million colors / 29 effects, controlled in one click!



Extreme Power Design

ISL digital PWM, 16+1 phases with 90A SPS and dual CPU power connectors to unleash your true power.



Frozr Heatsink Design

Designed with double ball bearings to provide best performance for enthusiast gamers and prosumers.



M.2 SHIELD FROZR

Onboard M.2 thermal solution to keep M.2 SSDs safe while preventing throttling, making them run cooler & faster.



2.5G LAN

Onboard 2.5G LAN with LAN manager, delivering the best online gaming experience.



WIFI 6

The latest wireless solution supports MU-MIMO and BSS color technology, delivering speeds up to 2400Mbps.



Triple Turbo M.2

Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.



Smart Button

Reset Computer, Safe Boot, Turbo Fan and EZ LED control functions with just one click.

CONNECTIONS



- 1. Clear CMOS Button
- 2. PS/2 Keyboard / Mouse Port
- 3. 1G LAN
- 4. 2.5G LAN
- 6. HD Audio Connectors
- 7. Flash BIOS Button
- 8. USB 2.0 Ports
- 9. USB 3.2 Gen 2 10Gbps (Type-A)
- **10.** USB 3.2 Gen 1 5Gbps (Type-A)
- 5. Wi-Fi /Bluetooth Antenna Connectors 11. USB 3.2 Gen 2x2 20Gbps (Type-C)
 - 12. Optical S/PDIF-Out