

TECHNICAL DATASHEET 65W Adapter FSP065-RBBN3



# FSP065-RBBN3

## **FEATURES**

- · Certified IEC 62368-1 & CB 60950-1
- · Peak current function
- Meet Energy Efficiency DOE Level VI
- Meet Code of Conduct Version 5 Tier 2
- · High Reliability
- · Low Profile
- Over Current Protection
- · Over Temperature Protection
- · Over Voltage Protection
- With PFC Circuit

INPUT SPECIFICATIONS

## SAFETY STANDARD APPROVAL



115Vac, 230Vac / full load  $\geq$  0.9

surge and current limiting device)

Power turn-on time At 100Vac / full load, output voltage shall remain

remain regulation  $\geq$  5ms

regulation  $\leq$  3Sec

DOE level 6 : 88% ; CoC v5 Tier 2 : 89%

At 100Vac or 240Vac / full load, output voltage shall

100Vac, 240Vac / full load , Shall be less than the rating of adapter critical component (including rectifiers, fuse

#### DESCRIPTION

This product is a 65 watts AC to DC adapter intended for use in IPC systems, embedded systems, printers, monitors, POS systems and PoE application, that have a mid-range wattage demands. This adapter operates at 90 to 264 VAC input voltage. The unit meets CISPR32 EN55032 CLASS B, EN55024 and FCC PART 15B Class B emission limits and is designed for ITE application.

Power factor:

Hold-up time:

Inrush current:

Efficiency:

#### **INPUT SPECIFICATIONS**

Input voltage: Input frequency: Input current: No load power consumption Touch current:

90-264 VAC 47-63 Hz 100Vac, 240Vac / full load  $\leq 1.5$ A 115Vac , 230Vac  $\leq 0.15$ W 264Vac / 50Hz  $\leq 0.25$ mA

## **OUTPUT SPECIFICATIONS**

OUTPUT SPECIFICATIONS			
Output voltage/current: Total output power:	19V/ 3.42A 65W	Operating altitude: Withstand voltage:	5000 meters above sea level Between AC input and secondary applied DC 4000V, test time 1 minute, cut off current shall be less than 10mA
Protection: Over voltage:	The adapter will enter into shut down	MTBF:	100Vac, 240Vac / full load, 300,000 hours at 25°C, standard SR332
Short circuit &	that means no output while over voltage happened at output terminal that caused by internal fault, the output trip voltage shall not exceed 25 vlots. That will be return to normal state by AC reset. When an internal fault occurs, or an	EMC Performance: EN55032 FCC VCCI EN61000-4-2	Class B conducted, class B radiated Class B conducted, class B radiated Class B conducted, class B radiated Air discharge: ±15KV, contact discharge: ±8KV, meet
Over current:	external fault is applied to the output, the power supply shall shut down and enter auto-recovery mode.	EN61000-4-3 EN61000-4-4	criterion A 80 ~1000 MHz, 3V/m, 80% AM(1kHz), meet criterion A Impulse: ±1kV applied to L,N,meet criterion A
Over temperature:	The power supply will enter into shut down while the abnormal thermal rise occurs. That will be return to normal state by AC reset.	EN61000-4-5 EN61000-4-6 EN61000-4-8 EN61000-4-11	±1kV applied differential mode, ±2kV applied common mode,meet criterion A 0.15 ~ 80 MHz,3Vrms,80% AM(1kHz),meet criterion A 50 Hz or 60Hz,1A/m,meet criterion A Voltage Dips :
Brown-out	Shutdown and no damage		>95% reduction for 0.5 period, meet criterion B 30% reduction for 25 period, meet criterion C
Environment Working TEMP. Storage TEMP. Working Humidity Storage Humidity	0~70°C (> 40°C de-rating ) -20~+80°C 20~80% RH non-condensing 10~90% RH non-condensing	Power de-rating:	Voltage Interruptions : >95% reduction for 250 period,meet criterion C 100Vac or 240Vac,0°C to 40°C,100% load,50°C,85% load,60°C,70% load,70°C,55% load (Shall be less than the rating of adapter critical component, follow FSP specification (adapter))



TECHNICAL DATASHEET 65W Adapter FSP065-RBBN3

# INPUT VOLTAGE DERATING CURVE



## **OUTPUT POWER DERATING CURVE**





TECHNICAL DATASHEET 65W Adapter FSP065-RBBN3

## **MECHANICAL SPECIFICATIONS**



**CONNECTOR SPECIFICATIONS** 

